

Lab 1 Worksheet — Laptop Teardown and Field-Replaceable Unit Identification

Name: ____ Date: ____

Exam objective: Identify and safely replace laptop field-replaceable units — battery, RAM, storage, keyboard and wireless card — with correct ESD precautions (Core 1 objective 1.1).

Record as you go

Step	What you did	What you observed
1	Put on the anti-static strap and clip it to an unpainted metal point on the chassis. Confirm the mat is earthed before you touch any component.	
2	Shut the laptop down completely — not sleep or hibernate — then disconnect the AC adapter and remove the external battery if the model has one.	
3	Press and hold the power button for 15 seconds to drain residual charge from the capacitors before opening the case.	
4	Remove the bottom cover screws into a parts tray, laying them out in the same pattern as the chassis so each screw returns to its own hole.	
5	Locate and photograph each field-replaceable unit: battery, SODIMM slots, M.2 or 2.5-inch storage, wireless card, cooling fan and keyboard ribbon connector.	
6	Disconnect the internal battery connector FIRST — before any other component — so the board is fully de-energised for the rest of the work.	
7	Record for each FRU in your inventory table: component name, form factor, connector or socket type, removal order position, and the	

Step	What you did	What you observed
	specific ESD or safety risk.	
8	Note the two antenna leads on the wireless card and which is main and which is auxiliary, then photograph their routing before disturbing them.	
9	Reassemble in exact reverse order, reconnecting the internal battery connector LAST, and confirm every screw is returned to its original hole.	
10	Write a replacement runbook for one FRU of your choice with numbered steps, required tools, ESD precautions and a post-replacement verification test.	

Verification

Success criterion: Your FRU inventory lists at least six components with form factor and socket type; the runbook states the internal battery is disconnected first and reconnected last; and the laptop powers on and completes POST after reassembly.

- I completed every step in the lab.
- My result meets the success criterion above.
- I recorded my evidence (screenshots, output, completed tables).

Reflection

What surprised you in this lab?

Where would you apply this on the job?

What do you still need to revise before the exam?
