/provider

Change provider, show config, or configure model router: /provider [show|router|help]

Overview

`/provider` is the entry point for provider configuration in the TUI. The bare form opens the interactive provider setup dialog, `/provider show` opens a viewer over the configured providers, and `/provider router` opens the model-router setup dialog seeded from the providers you have already configured. Provider setup covers API key entry, model selection, and provider-specific options; `/model` then picks a model from the configured provider.

Syntax

```
/provider               Open the interactive provider setup dialog
/provider show          Show configured providers
/provider router        Open the model-router setup dialog
/provider help          Show the help table
```

Options / Subcommands

Form	Description
`/provider`	Open the interactive provider setup dialog
`/provider show`	Show configured providers (and the router virtual provider when configured)
`/provider router`	Open the model-router setup dialog seeded from configured providers
`/provider help`	Show the help table

Any other argument prints a one-line usage reminder in the chat: `/provider` | `/provider show` | `/provider router` | `/provider help`.

Behaviour

- **Bare form.** Opens the provider selection step with API key entry forced (`force_key_entry: true`), so it can be used both for first setup and for adding another provider.
- **`show`.** Lists all configured providers from storage in a selection dialog. When a saved router configuration exists, a virtual `router` provider ("Model Router") is appended to the list so the cluster can be viewed inline. With no configured providers it reports `[warn] No configured providers`.
- **`router`.** Requires at least one concrete provider; without one it reports `[warn] No concrete providers - configure one first`. The router setup dialog is seeded with the concrete providers so tiers can be assigned to them.
- `/provider help` prints a four-row subcommand table into the chat.

Examples

```
/provider
```

Opens the provider setup dialog to add or reconfigure a provider.

`/provider show`

Opens the provider-config viewer listing every configured provider, including the Model Router virtual entry when router config has been saved.

`/provider router`

Opens the router setup dialog seeded from the configured providers for tier assignment.

`/provider help`

Prints the subcommand table with status line `provider: help`.

`/provider models`

Unknown subcommand - prints the usage reminder line.

Output

- Bare and `show` forms: no chat text; a dialog state is set and the TUI renders the interactive provider UI.
- `router` form: dialog state when providers exist; otherwise the `[warn] No concrete providers - configure one first` status line plus a log entry.
- `help` form: help table in the message window with status `provider: help`.
- Unknown form: usage line in chat with status `provider: usage`.

Related

- `/model` - pick a model from the configured provider
- `/provider_reset` - remove the current provider and its stored credentials
- `/router` - manage router runtime state (enable/disable, test, reload)
- `ragent config` - CLI view of the resolved configuration
- `ragent auth` - CLI provider authentication setup