

/memory

Memory panel (Alt+M): `/memory` | `/memory show` | `/memory init` | `/memory read` | `/memory search`

Overview

`/memory` toggles the memory side panel and prints a structured-memory summary into the transcript. The panel view and the transcript summary are the only implemented behaviours: the bare form and `/memory show` do the same thing, and `/memory help` prints the usage line.

The command description in the slash-command registry also advertises `init`, `read <label>`, and `search <query>`, but the dispatcher does not implement them. Any argument other than `show` (including `help` and those advertised forms) prints the usage line. This documentation records the code truth so readers do not hunt for behaviour that does not exist.

For real memory operations use the `memory_*` tools (`memory_store`, `memory_recall`, `memory_forget`) in chat, or Alt+M to toggle the panel.

Syntax

```
/memory          # toggle panel + transcript summary (same as show)
/memory show     # same as bare form
/memory help     # prints the usage line
```

Options / Subcommands

Form	Description
<code>/memory</code>	Toggle the memory side panel; print the structured-memory summary
<code>/memory show</code>	Identical to the bare form
<code>/memory help</code>	Prints Usage: <code>/memory show</code> <code>/memory help</code>

Documented-but-unimplemented forms (the registry lists them, the dispatcher prints the usage line for all of them):

Form	Status
<code>/memory init</code>	Not implemented - prints usage
<code>/memory read <label></code>	Not implemented - prints usage
<code>/memory search <query></code>	Not implemented - prints usage

Examples

Toggle the panel and show the summary:

```
/memory
```

Same effect via the explicit form:

```
/memory show
```

Check the usage line:

```
/memory help
```

Attempt a documented-but-unimplemented subcommand; you get the usage line:

```
/memory search permissions
```

Manage memories through tools instead of slash commands:

```
memory_recall(query: "tool repeat guard")  
memory_store(content: "...", category: "workflow")
```

Toggle the panel with the keyboard shortcut:

```
Alt+M
```

Output

Panel behaviour:

- Opens or closes the memory side panel.
- Opening the panel closes the log, profile, tasks, and telemetry panels (side panels are mutually exclusive).
- The status line reports `memory panel visible` or `memory panel hidden`.

Transcript summary (printed alongside the panel toggle):

- **Structured memories:** N - the count of memories stored for this project directory.
- Up to 50 memory rows grouped by category, each group headed `### <category> (N entries)`.
- Each row: - `##id## \confidence' preview'` with the preview truncated to 120 characters.

Non-show forms print exactly:

Usage: `/memory show` | `/memory help`

Related

- `memory_store` / `memory_recall` / `memory_forget` - the actual memory tools
- `Alt+M` - keyboard shortcut for the same panel toggle
- `/reload` - refresh configuration and skills after editing memory config
- Structured memory store (SQLite) configured under `memory` in `ragent.json`