

Compatibility List		i-Control										
		(and related software packages)										
		(and related instrument support with corresponding firmware versions)										
Product		<b>i-Control</b>	<b>Magellan</b>	<b>EVOware</b>	<b>EVOware Reader-Driver</b>	infinite F 200	infinite M 200	infinite F 500	infinite M1000	infinite F50	infinite F200PRO	infinite M200PRO
Version		V 1.0	V 6.0	V 1.20	V 1.0	V 1.10	V 1.10	-				
	Build	1.0.9	6.0.0.75		1.0.10							
SAP code						30024258	30024259					
Version		V 1.1	V 6.1	V 1.21 (SP1)	V 1.1 (Infinite 200)	V 2.01	V 2.01	-				
	Build	1.1.9	6.1.0.18		1.1.5							
SAP code						30024565	30024566					
Version		V 1.2	V 6.2	V 1.3 (SP1)	V 1.2 (Infinite 200 + 500)	V 2.01	V 2.01	V 1.00				
	Build	1.2.6	6.2.0.8		1.2.1							
SAP code						30024565	30024566	30023683				
Version		V 1.3	V 6.3	V 1.3 (SP1)	V 1.2 (Infinite 200 + 500)	V 2.01	V 2.01	V 1.00				
	Build	1.3.3	6.3.0.8		1.2.1							
SAP code						30024565	30024566	30023683				
Version		V 1.4	V 6.4	V 1.3 (SP1)	V 1.3 (Infinite 200 + 500)	V 2.02	V 2.02	V 1.30				
	Build	1.4.5	6.4.0.21		1.3.2							
SAP code						30028170	30028171	30032151				
Version		V 1.4 SP1	V 6.4	V 1.3 (SP1)	V 1.3 (Infinite 200 + 500)	V 2.10	V 2.10	V 1.30				
	Build	1.4.7	6.4.0.21		1.3.2							
SAP code						30034943	30034944	30032151				
Version		V 1.5	V 6.5	V 2.1 SP2	V 1.5 (Infinite 200, 500, 1000)	V 2.11	V 2.11	V 1.30	V 1.10			
	Build	1.5.14	6.5.0.17		1.5.2							
SAP code						30037201	30037200	30032151	30034544			
Version		V 1.6	V 6.5.5	V 2.1 SP2	V 1.5 (Infinite 200, 500, 1000)	V 2.11	V 2.11	V 1.30	V 1.20			
	Build	1.6.17	6.5.5.3		1.5.2				MAI 1.28			
SAP code						30037201	30037200	30032151	30046298			
Version		V 1.6 SP1	V 6.5.5	V 2.1 SP2	V 1.5 (Infinite 200, 500, 1000)	V 2.11	V 2.11	V 1.30	V 1.20			
	Build	1.6.19	6.5.5.3		1.5.2				MAI 1.28			
SAP code						30037201	30037200	30032151	30046298			
Version		V 1.6 SP2	V 6.5.5	V 2.1 SP2	V 1.6 (Infinite 200, 500, 1000)	V 2.11	V 2.11	V 1.30	V 1.21			
	Build	1.6.19.2	6.5.5.3		1.6.1				MAI 1.29			
SAP code						30037201	30037200	30032151	30049109			

Version		V 1.7	V 6.6	V 2.3 SP3	V 1.7 (all infinite readers)	V 2.11	V 2.11	V 1.30	V 1.21	V2.0	MAI(3.12)	MAI(3.12)
	Build	1.7.1.9 (1.7.1.7)	6.6.0.12		1.7.0				MAI 1.29	MAI(2.0)		
SAP code						30037201	30037200	30032151	30049109	30052171		
Version		V 1.7 SP-1	V 6.6	V 2.3 SP4	V 1.7 (all infinite readers)	V 2.70	V 2.60	V 1.50	V 1.23	V2.01	V1.2	V1.2
	Build	1.7.1.12	6.6.0.12		1.7.2							
SAP code						30055112	30055111	30046310	30055719	30053739	30054978	30054977
Attention:												
x Do not mix i-Control V 1.1 and Magellan V 6.0 (or i-Control V 1.0 and Magellan V 6.1)												
x If using i-Control V 1.0 and / or Magellan V 6.0, Infinite 200 Firmware V 1.10 is required! (SAP code: 30024258 or 30024259)												
x If using i-Control V 1.1 and / or Magellan V 6.1, Infinite 200 Firmware V 2.01 is required! (SAP code 30024565 or 30024566)												
x If using Infinite 200 Firmware V 1.10, EVOware reader driver V 1.0 and minimum EVOware V 1.20 is required!												
x If using Infinite 200 Firmware V 2.01, EVOware reader driver V 1.1 and minimum EVOware V 1.21 is required!												
x EVOware Reader-Driver V 1.1 does not support Infinite 500 (V 1.2 is required)												