











Bench reader. Firmware: reader/src/main.cpp (filament-kit).
Power: the C3's USB 5 V; every module on the C3's 3V3 pin.
I2C: PN532 (0x24, mode switches set to I2C) and OLED (0x3C) share SDA/SCL.
PN532 IRQ and RSTO stay unconnected (firmware polls over I2C).
Encoder: A/B to GPIO 3/4 with internal pull-ups, common C to GND;
push switch S1-S2 between GPIO 1 and 3V3, internal pull-down.
Buzzer module is active-low: firmware idles GPIO 0 high.
UNCONFIRMED: PN532 and encoder module pin orders, PN532 supply pin, encoder type.

Sheet: /		
File: bench-reader.kicad_sch		
Title: Bench reader		
Size: A4	Date:	**Rev:**
KiCad E.D.A. 10.0.5		Id: 1/1