

GENERIC REFINERY - GULF COAST

100 kBPSD Crude & Vacuum Distillation Unit

Electrical System Sizing Calculations

Document No.	CFU-000-EL-CAL-001
Revision	A
Status	Issued for review (FEED)
Date	2026-10-02
Prepared	Claude Code
Checked / Approved	- / -

CFU-000-EL-CAL-001 - Electrical System Sizing Calculations

Rev A - Issued for review (FEED). Unit: 100 kbpsd Crude & Vacuum Distillation Unit (100,000 BPSD). Generated from cfu/elec (load list, studies and cable schedule are computed from data/equipment.json; no hand-typed process data).

1. Purpose and scope

FEED-level sizing of the unit electrical distribution in substation SS-100: maximum demand, transformer ratings, short-circuit levels and switchgear ratings, largest-motor starting voltage dip, cable sizing method and results, UPS and DC battery sizing, and the basis for not providing an emergency diesel generator. Hazardous-area classification is deferred until the plot plan is final.

2. Basis and references

Item	Value
Utility supply	2 x 13.8 kV feeders from refinery main substation, 3-ph, 60 Hz
Utility fault level	31.5 kA at 13.8 kV (753 MVA), X/R 15 (assumed)
Distribution voltages	4.16 kV MV motors >= 200 kW; 480 V LV; 208Y/120 V lighting; 120 V UPS
System grounding	13.8 kV per utility; 4.16 kV low-resistance 400 A / 10 s; 480 V high-resistance 5 A (alarm, continued operation); 208Y/120 V solidly grounded
Codes	NFPA 70 (NEC), IEEE 141, 242, 399, 485, 1100, IEEE C57.12.00/10, C37.20.1/2/7, C37.2, IEC 60364-5-52, IEC 60502-2, IEC 60909 (peak factor), API RP 540
Ambient	35.0 C design, -5.0 C min, elevation 5 m

3. System configuration

Secondary-selective (double-ended) arrangement at every level: two 13.8 kV incomers to SWG-101A/B with a normally-open tie; two 13.8/4.16 kV transformers TR-101/102 feeding SWG-102A/B (N.O. tie); two 4.16/0.48 kV transformers TR-103/104 feeding the 480 V switchgear/MCC-101A/B (N.O. tie). Ties are interlocked 2-out-of-3 so transformers are never paralleled; on loss of one source the incomer opens and the tie closes automatically (open transition). Every transformer therefore carries the full demand of both bus sections in the contingency case. Pump pairs (2 x 100 %) are split across the two bus sections. See CFU-000-EL-SLD-001..004.

4. Electrical load and maximum demand

Maximum demand MD = $1.0 \times C + 0.3 \times I + 0.1 \times S$ (continuous / intermittent / standby), applied separately to kW and kvar (IEEE 141 practice). Motor input = absorbed kW / efficiency (/ 0.97 for VFDs). Detailed list: CFU-000-EL-LDL-001.

Bus	Connected kW	C kW	I kW	S kW	MD kW	MD kvar	MD kVA	PF
MCC-101A	1,768	1,082	127	559	1,176	641	1,340	0.88
MCC-101B	1,778	1,079	124	575	1,173	632	1,333	0.88
SWG-102A	1,821	985	0	836	1,068	524	1,190	0.90
SWG-102B	1,821	836	0	985	934	487	1,054	0.89
SWG-102A incl. LV					2,257	1,190	2,551	0.88
SWG-102B incl. LV					2,120	1,145	2,409	0.88
Unit total at 13.8 kV					4,411	2,475	5,058	0.87

LV transformer through-load includes 1 % active / 4 % reactive transformer losses; MV transformer 0.8 % / 6 %.

5. Transformer sizing

Criteria: (a) ONAN rating $\geq$ contingency maximum demand (both bus sections on one transformer, tie closed), with ONAN loading $\leq 95\%$; (b) ONAF (fan-cooled, +25 % for ≤ 10 MVA per IEEE C57.12.10) $\geq 1.25 \times MD$, i.e. the 25 % future margin is available with forced cooling. Off-circuit taps $\pm 2.5\%$.

Transformer	Ratio	MD kVA	1.25 x MD	Selected ONAN/ONAF kVA	ONAN load %	Z %	Secondary FLC (ONAF) A
TR-101 / TR-102	13.8/4.16 kV	4,960	6,200	7,500 / 9,375	66	7.0	1,301
TR-103 / TR-104	4.16/0.48 kV	2,673	3,341	3,000 / 3,750	89	5.75	4,511
LTR-101A	480-208Y/120 V	41	51	75 (dry, AN)	54	4.0	
LTR-101B	480-208Y/120 V	41	51	75 (dry, AN)	54	4.0	

The 13.8/4.16 kV unit rating (7.5 MVA) is governed by the 95 % ONAN loading limit: the next smaller standard size (5 MVA) would be loaded to 99 % with no ONAN margin. The 480 V transformers are at the practical upper limit for 480 V unit substations (5000 A bus); see Section 11.

6. Short-circuit levels

Method: IEEE 141 / ANSI E/X hand calculation on a 100 MVA base, prefault voltage 1.0 pu. Sources: utility (753 MVA, X/R 15); running motors as subtransient sources - MV motors $X'' = 0.17$ pu on motor kVA, LV motors grouped at $4 \times FLC$ ($X'' = 0.25$ pu); VFD-fed motors excluded. Peak ip = $\kappa \times \sqrt{2} \times I_k''$, $\kappa = 1.02 + 0.98 e^{(-3R/X)}$ (IEC 60909).

Element	Z (pu, 100 MVA)	X/R
Utility 13.8 kV	0.1328	15
TR-101/102 (7.5 MVA, 7.0 %)	0.9333	14
TR-103/104 (3 MVA, 5.75 %)	1.9167	6

Case	Bus	I_k'' kA sym	X/R	ip kA peak
normal (tie open) - section A	13.8 kV	31.9	14.9	82.1
normal (tie open) - section A	4.16 kV	14.4	13.7	36.8
normal (tie open) - section A	0.48 kV	46.2	7.3	109.2
normal (tie open) - section B	13.8 kV	31.9	14.9	82.2
normal (tie open) - section B	4.16 kV	14.5	13.7	37.0
normal (tie open) - section B	0.48 kV	46.4	7.3	109.5
one transformer, tie closed	13.8 kV	32.2	14.9	82.9
one transformer, tie closed	4.16 kV	15.8	13.4	40.3
one transformer, tie closed	0.48 kV	52.2	7.1	122.7

Equipment	Max. calculated I_k'' kA	Selected rating (kA sym, $\geq 1.1 \times \text{calc.}$)	Bus continuous A
SWG-101 13.8 kV	32.2	40	1200
SWG-102 4.16 kV	15.8	31.5	2000
MCC-101 480 V	52.2	65	5000

The 13.8 kV rating is set by the utility (31.5 kA) plus motor contribution; 40 kA switchgear is specified. Ratings assume the tie is never closed with both incomers in service (2-out-of-3 interlock).

7. Motor starting voltage dip

Largest DOL motor: P-101A (710 kW, 4.16 kV; P-101A/B and P-102A/B are identical 710 kW units). Locked-rotor 6.5 x FLC at PF 0.2 -> 5,373 kVA. Network: utility + one 13.8/4.16 kV transformer (ONAN impedance); pre-start bus load modelled as constant impedance with pre-start bus voltage 1.00 pu (tap setting); motor cable impedance included for the terminal voltage. Limits: 10 % at the 4.16 kV bus, 15 % at the motor terminals.

Case	Pre-start load kVA	Bus dip %	Terminal dip %	Result
Normal: tie open, motor bus section on its own transformer	1,833	5.3	5.8	OK
Contingency: one 13.8/4.16 kV transformer feeding both sections, largest motor started last	4,242	5.2	5.8	OK
Contingency + one 13.8 kV incomer (utility fault level reduced to 20 kA assumed)	4,242	5.6	6.1	OK

DOL starting of the 710 kW pumps is therefore acceptable; no soft-starter / autotransformer is required.

Motor-acceleration time and pump torque margin to be confirmed with vendor curves (IEEE 399 dynamic study at detailed design). LV motors: bus dip on MCC-101A/B for each DOL start is computed in the cable schedule (largest 3.5 %).

8. Cable sizing

- Conductors: copper, XLPE 90 C, IEC 60228 metric sizes (mm²). LV 0.6/1 kV Cu/XLPE/SWA/PVC multicore with separate earth core (IEC 60364-5-54 sizing); 4.16 kV: 3.6/6 kV screened 3-core Cu/XLPE/CWS/SWA/PVC; 13.8 kV: 8.7/15 kV single-core in trefoil. Equivalent UL/NEC types (MC-HL / TC-ER) acceptable; NEC 310 ampacity check at detailed design.
- Ampacity: base values IEC 60364-5-52 Table B.52.12 method E (LV) / IEC 60502-2 Annex B (MV) at 30 C in air on ladder tray; derating 0.91 (40 C ambient incl. solar) x 0.8 (grouping) = 0.73. Required ampacity $\geq 1.25 \times$ FLC for motors (NEC 430.22) and $\geq 1.25 \times$ rated current for feeders (continuous load).
- Voltage drop: $dV\% = \sqrt{3} I L (R \cos(\phi) + X \sin(\phi)) / V \times 100$ with R at 90 C. Running $\leq 5\%$. Starting (DOL, 6.5 x FLC at PF 0.35 LV / 0.2 MV): bus dip + cable drop $\leq 15\%$ at motor terminals; bus dip $\leq 10\%$.
- Short-circuit withstand: $S \geq \sqrt{I^2 t} / k$, $k = 143$ (Cu/XLPE 90->250 C). MV: prospective bus fault current with $t = 0.25$ s (motor feeders, instantaneous 50 element) / 0.5 s (incomers, transformer feeders). LV: let-through $I^2 t$ of current-limiting MCCB by rating (manufacturer typical, 65 kA class).
- Minimum sizes: LV power 4 mm²; 4.16 kV 35 mm². Parallel LV runs ≥ 95 mm².
- Route length = Manhattan distance from SS-100 reference point (25, 12.5) m to the consumer + 15 m riser/termination allowance (+10 m for air-cooler fan motors on top of the pipe rack), rounded up to 5 m. Coordinates source: data/layout.json (137 tagged items).
- 13.8 kV incomer route from the refinery main substation assumed 600 m (OSBL, to be confirmed by refinery electrical master plan).

Worked example CBL-P-101A: Crude charge pump A; design FLC 115 A; route 100 m (layout); required ampacity 143 A; selected 3C x 70 mm² Cu/XLPE/CWS/SWA/PVC 3.6/6 kV; derated ampacity 186 A; VD running 0.17 %; VD starting (cable) 0.5 %; bus dip 5.3 % -> terminal 5.9 %; SC minimum 55 mm².

Worked example CBL-P-104A: Unstabilised naphtha pump A; design FLC 233 A; route 140 m (layout); required ampacity 291 A; selected 3C x 185 + E95 mm² Cu/XLPE/SWA/PVC 0.6/1 kV; derated ampacity 332 A; VD running 1.75 %; VD starting (cable) 9.0 %; bus dip 3.5 % -> terminal 12.5 %; SC minimum 17 mm².

Summary	Value
Number of cables	113
Total route length (m)	16,435
Max running VD %	4.94
Max terminal dip at start %	15.0

9. UPS and battery sizing

Step	Value
UPS consumers (DCS 22, SIS/BMS 14, F&G 6, telecom 8, analysers 6, misc. 4 kVA)	60 kVA
Design load incl. 20 % future	72 kVA
Rating (design load <= 80 % of rating)	100 kVA each, 2 x 100 % dual-bus (UPS-101A -> UDB-101A, UPS-101B -> UDB-101B), each with own battery, static bypass and external maintenance bypass
Battery power = 72 kVA x 0.9 / 0.94	68.9 kW
Cells / nominal / float / end voltage	192 x 2 V / 384 / 432 / 336 V (1.75 V/cell)
Max discharge current at end voltage	205 A
Kt for 30 min to 1.75 V/cell (VRLA, 25 C)	1.1 Ah/A
Capacity = I x Kt x aging 1.25 x design margin 1.10 x temperature 1.00	310 Ah
Selected battery (per UPS)	350 Ah, 30 min

UPS input (rectifier) load on each MCC section includes 50 % share of the consumers plus 5 kW battery recharge. 125 V DC switchgear control supply (IEEE 485 duty cycle):

Section	Value
Duty cycle	L1 60 A 1 min (trip) / L2 15 A 120 min standing / L3 40 A 1 min (close)
Section 1 / 2 / 3 capacity (Ah)	33.0 / 35.7 / 49.6
Required = max x aging 1.25 x margin 1.10	68 Ah -> 75 Ah, 60 cells VRLA
Chargers	2 x 100 %, 30 A each (standing load + recharge in 8 h)

10. Emergency diesel generator - basis for omission

No emergency generator is provided. The unit is supplied by two independent 13.8 kV feeders, each able to carry the whole unit load, from the refinery main substation. On a total power failure the unit is designed to fail safe: the SIS is de-energise-to-trip, emergency isolation valves fail closed, the fired-heater BMS trips H-101/H-201 and snuffing steam is manual; there is no rotating equipment requiring post-trip power (no lube/seal-oil consoles - API 682 seals, ring-oil or rolling-bearing pumps; vacuum by steam ejectors). The essential loads (DCS, SIS/BMS, F&G, PAGA/telecom) are on the 2 x 100 % UPS with 30 min autonomy, which covers safe shutdown and operator response; escape lighting uses self-contained 90-min fittings. If the HAZOP identifies an essential motor load (e.g. an emergency cooling or flushing pump), it will be supplied from the refinery emergency power network rather than a dedicated unit generator.

11. Assumptions, holds and issues

- HOLD: utility X/R (15) and minimum fault level at 13.8 kV to be confirmed by the refinery power study; motor-start case 3 assumes 20 kA minimum.
- HOLD: 13.8 kV feeder route length from the refinery main substation assumed 600 m.
- The 480 V double-ended substation needs 3,000/3,750 kVA transformers and a 5000 A bus (52 kA calculated, 65 kA rated). This is at the practical limit for 480 V; recommended at detailed design to split LV into two double-ended substations (e.g. CDU / VDU+air coolers) of ~2000 kVA each, or to move the 160 kW pumps to 4.16 kV. Kept as one board here per the FEED key SLD.
- Long 480 V motor feeders: SS-100 is in the SW corner while the VDU pumps are ~170 m east, so the 15 % terminal-dip criterion governs (e.g. P-201B 150 mm² at 260 m, P-107B 240 mm² at 195 m, P-107A 240 mm² at 195 m, P-201A 150 mm² at 255 m). Moving the >= 110 kW LV pumps to 4.16 kV, or a satellite LV substation near the VDU, would reduce copper; to be reviewed with the plot plan.
- Allowance loads (lighting, HVAC, heat tracing, MOVs, welding, UPS, CP, analyser house) are FEED estimates and must be replaced by vendor / discipline data.

- Desalter transformer load factor (0.35) assumed; desalter vendor to confirm grid power.
- Cable lengths use equipment coordinates from data/layout.json (137 tagged items) with Manhattan routing from SS-100 plus allowances; actual tray/trench routes to be confirmed at detailed design (lengths regenerate automatically when the layout changes).
- Hazardous-area classification: CFU-000-EL-HAC-001/002/003 (Section 12); motor Ex protection per location in data/electrical.json (loads[].area_class).

12. Hazardous area classification and equipment protection

Classification CFU-000-EL-HAC-001/002 (schedule HAC-003) per API RP 505 / NFPA 70 Art. 505, point-source method, fluid categories per EI 15. Gas group IIA T3 generally, IIB in H₂S / fuel-gas / off-gas services. 144 release sources: Atmospheric vent 1, Control-valve station 32, Ejector / condenser flanges 1, Exchanger flanges 25, Header box plugs / flanges 10, Pump seal 42, Sample point 14, Vessel flanges / instruments 19.

Unclassified item	Clearance to nearest classified area (m)	Nearest source
H-101	16.6	RS-130 Control valves FV-1011, FV-1012, FV-1013, FV-1014,
H-201	12.5	RS-124 Control valves LV-9002 (D-103)
E-120	34.1	RS-130 Control valves FV-1011, FV-1012, FV-1013, FV-1014,
SS-100	17.1	RS-076 D-101B Electrostatic desalter, 2nd stage
FAR-100	20.1	RS-076 D-101B Electrostatic desalter, 2nd stage

Equipment	Zone 1	Zone 2
LV motors (480 V)	Ex db or Ex eb (tE, stall relay), IIB T3 (Gb)	Ex ec (non-sparking), IIA/IIB T3 (Gc); AEx ec per NEC 505
MV motors (4.16 kV)	Not located in Zone 1 (relocate) / Ex pxb	Ex ec with stator discharge risk assessment / pre-start purge, IIA T3
VFD-fed motors	Ex db certified with the drive (converter duty)	Ex ec certified for converter duty; T-class verified with VFD
Instruments	Ex ia / ib (intrinsic safety), Ex db	Ex ia / ic, Ex db, Ex ec
Lighting fittings	Ex db / eb, IIB T3	Ex ec / nR, IIA T3 (IIB in H ₂ S areas)
Junction boxes / glands	Ex eb boxes; Ex db barrier glands for Ex d	Ex eb / ec boxes and glands
Heat tracing	Ex 60079-30-1, stabilised design <= T3	Ex 60079-30-1, self-regulating, T3
Desalter transformers	n/a (Zone 2 only)	Vendor package certified for Zone 2 (Ex o / ec), HV entry to vessel via Ex bushings
Welding / receptacles	Not permitted	Ex de interlocked receptacles; hot-work permit
Buildings SS-100 / FAR-100	-	Non-classified; pressurised (NFPA 496 / IEC 60079-13), intakes in unclassified area, gas detection