

As System 6 loads, it displays small pictures—icons—across the bottom of the screen. These small pictures tell you which startup items are loading—for example, the “boot” icon tells you that the SetStart control panel has just loaded.

### ▲ **By The Way...**

You can keep your startup items (called “inits” in IIGS parlance) and desk accessories from loading by holding down the Shift key as you start up the computer. When the message “No Inits/DAs” appears under the “Welcome to the IIGS” banner, you can release the Shift key.

When the thermometer fills and the System 6 splash screen disappears, a program called the Finder usually appears. (You can change your startup program with the SetStart control panel). The Finder is “home base” for IIGS users—you’ll use the Finder to back up and maintain your disks, as a “launch pad” for running your programs. If you’re unfamiliar with the Finder (or wish to learn more), be sure to read Chapter 5.

## ***Switching Between System 5 & System 6***

---

Once System 6 has been installed, you can switch back to System 5 without removing System 6 by doing the following things (assuming you took our suggestion about renaming your existing Icons and System folders):

- Open your startup drive’s icon.
- Click the System folder, type “System6” and press Return.
- Click the Icons folder, type “Icons6” and press Return.
- Click the System5 folder, type “System” and press Return.
- Click the Icons5 folder, type “Icons” and press Return.
- Restart your IIGS by holding down the ⌘ and Control keys while pressing and releasing the Reset key.

You can switch back to System 6 from System 5 (assuming you’ve followed the above procedure) by performing these steps:

- Open your startup drive’s icon.
- Click the System folder, type “System5” and press Return.
- Click the Icons folder, type “Icons5” and press Return.
- Click the System6 folder, type “System” and press Return.
- Click the Icons6 folder, type “Icons” and press Return.
- Restart your IIGS by holding down the ⌘ and Control keys while pressing and releasing the Reset key.