

ECIFICATIONS

Product ID

High Frequency (HF) Driver

Mid Frequency (MF) Driver

Low Frequency (LF) Driver

Frequency Response

Power Capacity (per pair)

Sensitivity (1 watt / 1 meter)

Crossover Frequency

Protection

SPECIFICATIONS

Source Input

Included Accessories

Polar Dispersion

Single Panel Impedance

2-PANEL BASS-EXTENSION SYSTEM

BLENDS800SUB

N/A

N/A

1.5" (38 mm) voice coil

8" (203 mm) cone

20 oz. (567 gr) ceramic magnet

30Hz - 150Hz

100 Watts MIN | 160 Watts RMS @

4ohm wired in parallel

86 dB

Requires amplifier,
with low pass filter.

80Hz with 18 dB slope
recommended.

N/A

ALL MODELS

Phoenix Connector

Mounting shims

Mounting screws

170 degrees

Horizontal & Vertical

8Ω nominal