



Tech Install Application

Technician Guide

Tech Install Form • Depot Inventory • Reports

Mercy Technology Service | September 2026
tia-mercy.com

Contents

What's New in This Edition	3
1. Introduction	4
2. Signing In and Getting Around	4
3. Scanning Barcodes	5
4. The Tech Install Form	6
5. Service Types.....	6
6. Device Information	6
7. Location Information	7
8. Additional Information	8
9. Removals: Where the Device Goes.....	8
10. Installing a Device from Depot Stock	10
11. Submitting and Clearing the Form.....	10
12. Required Fields at a Glance.....	11
13. The Depot Inventory Tab	12
14. Depot Statuses.....	12
15. Checking In a Device Shipped to You	13
16. If a Shipment Arrives Damaged	13
17. Adding Devices to Your Depot (Add Device).....	13
18. A Device Shipped to a Clinic Arrives Damaged	14
19. Changing a Device's Status (Edit)	14
20. Sending Devices Back: Ship Pallet or Ship to.....	15
21. Counting Your Depot: Audit Depot	16
22. Reports.....	18
23. Troubleshooting.....	18

What's New in This Edition

This edition (September 28, 2026) updates the September 16 guide. New in this edition:

Change	What it means for you	See
Find and sort on the Depot tab	Search your depot by serial, asset tag or MercyID, and sort any column A to Z or Z to A by tapping its header.	13.2
Leased devices are marked	An amber LEASED tag shows which devices at your depot are on a lease.	13.2
Ship just one device	Ship to... on a device's row sends that one device to CORD or another depot. No need to stage it as Pending Transfer or uncheck the rest of the pallet.	20
Leading "S" removed from scanned serials	Many labels print an "S" in front of the serial. TIA removes it for a Lexmark on the Install form as soon as it looks the serial up, and for any make in Add Device and Audit Depot. The notice says "(leading S removed)".	6.3, 17, 21.3
Audit Depot won't run empty	Serials left in the paste box are included when you tap Run Audit, and a full audit with no serials is refused instead of reporting every device missing.	21.1
Help page	Help in the menu has this guide and the Quick Reference, to view or download.	2.2

Also new in September (the September 16 edition, which replaced the TIA Field Technician Guide of April 2026 and the TIA Depot Inventory Tech Guide of September 4, 2026): Depot Status on a Removal at a depot (9.2); a Removal to CORD is recorded even when the warehouse already has the device (9.1); red warnings before you submit (9, 10); Removals to CORD tracked in IMS (9.1); the Depot Inventory tab (13–21); and the Queue Name field (8).

Important — Close and reopen TIA on your phone after an update

Phone browsers keep an open tab in memory and don't always load the newest version when you switch back to it. If something in this guide is missing on your phone, close the TIA tab completely and open **tia-mercy.com** again.

1. Introduction

TIA (Tech Install Application) is Mercy Health's web-based tool for recording printer service events. Every time you install, move, hot swap or remove a printer, you log it in TIA.

TIA works on your laptop, tablet and phone. There is nothing to install. Open a browser and go to **tia-mercy.com**.

Tip — Bookmark the site

Add tia-mercy.com to your browser bookmarks, or to your phone's home screen, so you can open it quickly in the field.

1.1 TIA and IMS work together

The warehouse team at CORD uses a separate app called **IMS** (Inventory Management System). IMS tracks every printer from receipt through shipping, repair, damaged claims and decommission. TIA and IMS share one inventory, so what you do in TIA shows up in IMS right away:

- A **Removal sent to CORD** marks the printer In Transit to CORD, so the warehouse knows it is coming.
- A **Removal at an EPDS depot** adds the printer to that depot's stock.
- An **Install, Move or Hot Swap** of a printer from depot stock takes it off the depot's count.
- Everything on the **Depot Inventory** tab (check-ins, damaged arrivals, pallets and audits) goes straight into the shared inventory.

You don't need an IMS login. The warehouse sees your work in IMS.

2. Signing In and Getting Around

2.1 Signing in

Open tia-mercy.com, enter your username and password, then tap **Sign In**.

- Your administrator gives you your username and password.
- Tap the eye icon next to the password field to show or hide your password.
- Forgot your password? Contact your administrator, who can reset it.
- You stay signed in for up to **12 hours**. After that, TIA asks you to sign in again. Your submitted records are always saved.
- The **Legal** link at the bottom of the sign-in page shows the legal notice for this internal system.

2.2 The menu

The menu is at the top of every page. On a phone, tap the menu icon (three lines) to open it. **Sign Out** is at the top right.

Menu item	What it's for	Who sees it
Tech Install	The form for logging installs, moves, hot swaps and removals (Part 2).	Everyone
Reports	Export and email install records (Part 4).	Full-access techs and admins

Menu item	What it's for	Who sees it
Depot Inventory	Your depot's stock: check-ins, damaged arrivals, pallets, audits (Part 3).	All techs, once an admin turns the tab on
Admin	Users, locations, the model catalog and settings.	Admins only
Help	The user guides (this guide and the Quick Reference), to view or download.	Everyone

3. Scanning Barcodes

Tap the camera button () next to a field to scan a barcode into it. Scanning is faster and more accurate than typing. Scan buttons appear on phones and tablets. On a laptop, use a USB scanner instead.

You can scan on the Tech Install form (Serial Number, Asset Tag, MercyID, MDM #), in the Depot tab's search box and Add Device window (Serial, Asset Tag, MercyID) and in Audit Depot.

Device	How scanning works
iPhone / iPad	A live camera view opens. Hold the barcode steady inside the frame; TIA reads it and closes the camera. Allow camera access if asked. Tap Enter Manually or Cancel to close without scanning.
Android	Your camera opens to take a photo. Take a clear, close, well-lit photo of the barcode. TIA reads the photo and fills in the field. If you see "No barcode detected", retake the photo closer or type the value.
Laptop	Click into the field and scan with a USB barcode scanner as normal.
Bluetooth scanner (best option)	A small Bluetooth scanner paired to your phone (for example, the Eyoyo Mini 1D Bluetooth Barcode Scanner, about \$40 on Amazon) types the value into whichever field you tap. It is the quickest way to scan in the field.

Tip — Vertical barcodes on iPhone

If the barcode is vertical (taller than it is wide), turn on rotation lock first: open Control Center, tap the rotation lock icon, then hold your phone upright and scan.

4. The Tech Install Form

After you sign in, TIA opens the Tech Install form. You record every printer service event here. The form has five sections:

- **Service Information:** the date (filled in automatically) and the service type.
- **Device Information:** serial number, asset tag, MercyID, manufacturer and model.
- **Location Information:** where the printer is being installed, or where it is going on a Removal.
- **Additional Information:** end user, phone, ATR, IP address and queue name.
- **Additional Fields:** MDM # and notes.

Note

Fields marked with a red asterisk (*) are required. Some requirements depend on the service type and the location. Section 12 lists them all.

5. Service Types

Start by choosing the **Service Type** that matches what you are doing:

Service Type	When to use it
Install-New	You are installing a printer at a location for the first time.
Move	You are moving an existing printer from one location to another.
Hot Swap	You are replacing a printer with a different one at the same location.
Removal	You are removing a printer and it is not being replaced. The Location tells TIA where the printer is going (Section 9).

6. Device Information

6.1 Serial number lookup

When you scan or type a serial number, TIA looks it up in the device database (CMDDB) and checks the shared inventory at the same time. A notice appears under the serial:

Notice	What it means
Green: Device found in CMDDB — fields auto-populated, update any if needed	Asset Tag, MercyID, Manufacturer and Model are filled in. The fields stay editable, so check them against the printer's label and correct anything that's wrong.
Yellow: Not found in CMDDB — enter details manually	Type or scan Asset Tag, MercyID, Manufacturer and Model yourself.
Red: starts with X	TIA can't accept this submission as filled in, and Submit is disabled. The notice says why and what to do. See Sections 9 and 10.

Note

When you submit, TIA adds a new device to the device database, or updates an existing one, so the next lookup finds it.

6.2 Manufacturer and Model

Manufacturer and Model are searchable lists. Tap the field and start typing to filter it. If the value isn't in the list, type it in. You aren't limited to the list.

- Choosing a Manufacturer filters the Model list to that manufacturer's models.

6.3 Automatic clean-up

- Serial Number, Asset Tag, MercyID, MDM # and Queue Name are converted to UPPERCASE as you type.
- Spaces are removed from MercyID automatically.
- For a Lexmark, a leading "S" on the serial is removed. If TIA already knows the device, this happens as soon as you scan it and the notice says "(leading S removed — Lexmark)". Otherwise it happens when you submit with Manufacturer = Lexmark. Other makes keep the S on this form.

7. Location Information

Location is required for every service type. There are two ways to find it.

7.1 Search by facility name

Tap **Location (Facility)** and start typing the facility name. Tap the correct match and the Address, City, State and Zip fill in automatically.

7.2 Search by address

Tap **Address** and start typing the street address. Choosing an address also fills in the Facility name, City, State and Zip.

Note

Location and Address work together: choosing one fills in the other. City, State and Zip are filled in automatically when you use these fields.

7.3 Location not in the list

If the location isn't in the system, type it in **Location (Manual)**. When you use this field:

- The Location and Address fields are cleared.
- City, State and Zip unlock so you can type them.

Important — Removals to CORD or a depot

Choose **Cord Moving and Storage** or the EPDS depot from the **Location (Facility)** list. A name typed into Location (Manual) is not recognized as CORD or a depot, so the inventory isn't updated.

7.4 Floor and Room

Floor and Room are required for Install-New, Move and Hot Swap, and optional for Removal.

- **Floor:** for example 1st, 2nd, 3rd, Basement.
- **Room:** for example Room 204, Reception, Main Pharmacy, ICU Nurses Station.

8. Additional Information

These fields are optional. Fill in what you know at the time of service.

Field	Description
End User	The person who mainly uses this printer.
Phone	The end user's phone number.
ATR	Automatic Toner Replenishment. Choose Yes if the location is enrolled, No if not.
IP Address	The printer's IP address. If it connects by USB cable only, type USB.
Queue Name	The print queue name, for example MERCY-PRN-001.
MDM #	The MDM tracking number. You can scan it from the shipping label.
Notes	Anything else about this service event.

9. Removals: Where the Device Goes

For a **Removal**, the Location tells TIA where the printer is going, and TIA updates the shared inventory to match:

Location	What happens	Also required
Cord Moving and Storage (the CORD warehouse)	The printer is marked In Transit to CORD in IMS. The warehouse checks it in when it arrives.	MercyID, Manufacturer, Model (Asset Tag optional)
An EPDS depot (for example EPDS - ADA)	The printer is added to that depot's inventory with the Depot Status you choose.	Asset Tag, MercyID, Manufacturer, Model
Any other location	The Removal is recorded. Inventory doesn't change.	Nothing extra

9.1 Removal to CORD

1. Set **Service Type** to **Removal**.
2. Scan the serial number.
3. In **Location (Facility)**, choose **Cord Moving and Storage**.
4. Read the notice under the serial (see the table below).
5. Make sure **MercyID**, **Manufacturer** and **Model** are filled in. Asset Tag is optional here.
6. Tap **Submit**. The confirmation says the device was marked In Transit to CORD.

Notice under the serial	What it means / what to do
Green: This Removal will mark the device In Transit to CORD	Normal. Finish the form and submit.
Green: The warehouse already has this device (IMS status: ...)	CORD received the printer before you filed the Removal. Submit as normal: your Removal is recorded and IMS inventory stays as it is.
Red: ... cannot be marked inbound to CORD	Submit is disabled. The notice gives the reason: • Already In Transit to CORD: a Removal was already filed, or it's on a depot pallet headed to CORD. Don't file it again. • At a depot: use Ship Pallet on the Depot tab (Section 20), not a Removal. • Decommissioned, open damaged claim or open lease return: contact the warehouse.

Note

Sending devices from your depot to CORD is different. Stage them as Pending Transfer and use Ship Pallet (Section 20).

9.2 Removal at a depot

1. Set **Service Type** to **Removal**.
2. Scan the serial number.
3. In **Location (Facility)**, choose the EPDS depot.
4. A **Depot Status** field appears under Location. Choose how the printer lands in the depot's stock (see below). It starts at In Maintenance.
5. Read the notice under the serial. For example: "This Removal will add the device to EPDS - ADA as In Maintenance."
6. Make sure **Asset Tag**, **MercyID**, **Manufacturer** and **Model** are filled in.
7. Tap **Submit**.

Depot Status	Choose it when
In Stock	The printer is good and ready to use again right away.
In Maintenance (default)	It needs work or a check before it can be used. If you leave the field alone, this is what you get.
Pending Transfer	It's going back to CORD (or another depot). It goes straight onto the depot's next Ship Pallet .

You can change the status later from the Depot tab with **Edit** (Section 19).

Important — Red notice: "... cannot be added to [depot] depot inventory"

The printer is already recorded somewhere it shouldn't be added from: in inventory at CORD or another depot, on an open damaged claim or lease return, or decommissioned. Submit is disabled. Check the serial. If it's right, contact the warehouse.

9.3 Removal to any other location

The Removal is recorded as always. No inventory is updated.

10. Installing a Device from Depot Stock

When you do an **Install-New**, **Move** or **Hot Swap** with a printer that is **In Stock** at a depot, TIA automatically takes it off that depot's inventory when you submit. The confirmation says "Device pulled from EPDS - ...". Your depot count stays accurate with no extra step.

If the printer is at a depot in any other status, a red notice appears under the serial and Submit is disabled until you resolve it:

Depot status	Why it's blocked	Do this first
In Transit	It hasn't arrived at the depot yet.	Wait until it arrives and is checked in (Section 15).
In Maintenance	It's being repaired.	When repair is done: Depot tab → Edit → In Stock .
Pending Transfer	It's staged on an outbound pallet.	Depot tab → Edit → In Stock to take it off the pallet.
Damaged In Transit	It has an open damaged claim.	Don't install it. The warehouse resolves the claim in IMS.

11. Submitting and Clearing the Form

1. Check the form: service type, serial number and location are the most important.
2. Tap **Submit**.
3. If a required field is missing, a message at the top of the page says which one. Fill it in and tap Submit again.
4. When the record is saved, a green confirmation appears at the top of the page. For a Removal or a depot pull, it also says what changed in inventory. The form then clears for the next entry.

Tip — Submit is grayed out?

Look for a red notice under the serial number. It says what is blocking the submission and how to fix it (Sections 9 and 10).

Note — If you see an error

If an error appears after you tap Submit, nothing was saved. Your entries stay on the form, so fix the problem and submit again.

11.1 Clearing the form

To start over without submitting, tap **Clear Form** next to Submit. It erases every field and resets the form.

Important

Clearing can't be undone. Everything you entered is lost.

12. Required Fields at a Glance

Field	Install-New, Move, Hot Swap	Removal to CORD	Removal at a depot	Other Removal
Service Type	Required	Required	Required	Required
Serial Number	Required	Required	Required	Required
Asset Tag	Required	Optional	Required	Optional
MercyID	Required	Required	Required	Optional
Manufacturer	Required	Required	Required	Optional
Model	Required	Required	Required	Optional
Location or Location (Manual)	Required	Required (from list)	Required (from list)	Required
Depot Status	—	—	Required (defaults to In Maintenance)	—
Floor	Required	Optional	Optional	Optional
Room	Required	Optional	Optional	Optional
End User, Phone, ATR, IP, Queue Name, MDM #, Notes	Optional	Optional	Optional	Optional

Note

On a Removal, the form doesn't put asterisks on the extra fields that CORD and depots require. If one is missing when you submit, the message at the top of the page names it.

13. The Depot Inventory Tab

The Depot Inventory tab shows your EPDS depot's stock. Use it for the things the Tech Install form doesn't cover:

- Checking in stock that CORD or another depot ships you.
- Reporting a shipment that arrived damaged, with photos.
- Adding devices you already have to your depot.
- Moving a device between In Stock, In Maintenance and Pending Transfer.
- Shipping one device, or a pallet of devices, back to CORD or to another depot.
- Checking your depot's list against what is on your shelves (Audit Depot).

13.1 Opening the tab

1. Sign in to TIA.
2. In the menu, tap **Depot Inventory**.
3. Choose your depot from the **Depot** list.

Your depot's devices appear in a table with Serial, Asset, MercyID, Manufacturer, Model, Status, Lease, Received and an Actions column. Use  **Refresh** to reload the list.

Note

All TIA techs can use the Depot tab. If the Depot Inventory link isn't in your menu, an admin hasn't turned the tab on. Ask your admin.

13.2 Finding and sorting devices

- **Search:** type or scan ( on a phone) a serial, asset tag or MercyID into the search box above the table. Part of a value is enough. The list narrows as you type and the count shows how many match, for example "(1 of 24 devices)". Tap **Clear** to see everything again.
- **Sort:** tap a column header to sort A to Z, and tap it again for Z to A. An arrow shows which column and direction. Received sorts oldest or newest first; the list starts newest first.
- **LEASED:** an amber LEASED tag marks a device on a lease, and the count at the top shows how many are leased. On a laptop, point at the tag to see the leasing company, lease number and expiry date. Sorting by Lease puts leased devices first, soonest expiry first.

Searching and sorting only change what you see. Ship Pallet still lists every Pending Transfer device, and Audit Depot still checks the whole depot.

14. Depot Statuses

Status	What it means	What you do
In Transit	CORD or another depot shipped it to you; it hasn't been checked in.	Check In when it arrives, or Damaged if it arrived broken.
In Stock	Good, available stock at your depot.	Ready to install. Edit to In Maintenance or Pending Transfer.
In Maintenance	At your depot but being worked on; not available.	Edit back to In Stock when it's ready, or to Pending Transfer if it's going back to CORD.

Status	What it means	What you do
Pending Transfer	Staged for the next outbound pallet (purple badge).	Nothing until ship day, then Ship Pallet . Edit back if staged by mistake.
Damaged In Transit	Arrived damaged; a damaged claim is open in IMS.	Nothing more on the tab. The warehouse resolves the claim in IMS.

15. Checking In a Device Shipped to You

When CORD ships you replenishment stock, or another depot ships you a pallet, each device appears in your list as **In Transit**.

1. Find the device by serial number (the search box helps on a long list).
2. In the Actions column, tap **Check In**.
3. Choose what to check it in as: **In Stock** (good, ready to use) or **In Maintenance** (needs work first).
4. Tap **Check In**.

The status changes to what you chose, and the device now counts toward your depot. CORD sees the check-in in IMS.

16. If a Shipment Arrives Damaged

If a device shipped to you (an **In Transit** row) arrives broken:

1. On that row, tap **Damaged** (the red button).
2. In the Mark Damaged In Transit window, describe the damage in Notes. This is optional but helpful.
3. Tap  **Add Photos** and take 1–2 photos of the damage. On a phone this opens the camera; you can also pick from your photo library. Thumbnails appear so you can remove any before you submit.
4. Tap **Mark Damaged**.

TIA then does the following automatically:

- The status becomes **Damaged In Transit**.
- A damaged claim opens in IMS, and the warehouse gets the damaged-device email.
- Your photos are attached to the claim for the vendor return (RMA).

From there the warehouse handles the claim in IMS. Ship the device back to CORD using your normal damaged-return process.

17. Adding Devices to Your Depot (Add Device)

You can add devices you already have at your location to your depot's inventory. You aren't limited to what CORD ships you.

1. Choose your depot, then tap  **Add Device**.
2. Fill in the fields (see below).
3. Tap **Add Device**.

Field	Notes
Serial (required)	Scan or type. TIA looks it up in CMDB and fills in Asset, MercyID, Manufacturer and Model when it recognizes the device. Check and correct them.
Asset Tag, MercyID (required)	Scan or type.
Manufacturer, Model (required)	Choose from the list. Picking a catalog model keeps par levels accurate. A ⚠ warning appears if the model isn't in the catalog; you can still keep it.
Status (required)	In Stock (normal), In Maintenance , or Damaged In Transit (see Section 18).
Notes	Optional.

- Serials are converted to UPPERCASE and spaces are removed from MercyID. A leading "S" on a scanned serial is removed, whatever the make, and the notice under the serial says "(leading S removed)". The S stays only if IMS already has the serial with its S.
- Duplicate protection:** if the serial is already recorded somewhere it can't be added from (in inventory, on an open damaged claim, on an open lease return, or decommissioned), TIA shows a red warning and blocks the save. This keeps a device from being counted twice.

18. A Device Shipped to a Clinic Arrives Damaged

CORD sometimes ships a device straight to a site, such as a clinic, for you to install. If it's damaged when you get there and you can't install it, record it on the Depot tab so it doesn't get lost:

- Go to **Depot Inventory** and choose your depot.
- Tap **+ Add Device**.
- Scan the serial. CMDB fills in what it can.
- Set **Status** to **Damaged In Transit**.
- A **Photos of the damage** section appears. Tap **Add Photos** and take 1–2 photos.
- Tap **Add Device**.

This works like marking a shipment damaged. The device is added to your depot as Damaged In Transit, a damaged claim opens in IMS, the warehouse is emailed, and your photos are attached to the claim. Then return the device to CORD using your normal damaged-return process.

Tip — Why photos matter

Photos go into the RMA package the warehouse sends the vendor. Taking them on site, with the broken device in front of you, avoids a return trip and gets the replacement moving sooner.

19. Changing a Device's Status (Edit)

For a device that is In Stock, In Maintenance or Pending Transfer, tap **Edit** on its row to switch between those three statuses:

- In Stock → In Maintenance** when you set it aside for repair.
- In Maintenance → In Stock** when it's ready again.
- Pending Transfer** when it's going back to CORD or to another depot on the next pallet (Section 20).

- **Pending Transfer → In Stock or In Maintenance** if you staged it by mistake or are keeping it.

Note

Edit can't set Damaged In Transit. To flag damage, use **Damaged** on an In Transit row (Section 16) or **Add Device** (Section 18). That way each damaged device gets exactly one claim.

To clear Damaged In Transit, the warehouse closes the damaged claim in IMS.

20. Sending Devices Back: Ship Pallet or Ship to...

Printers usually go back to CORD on a pallet once it's full. The Depot tab handles this in two steps: stage each device as you box it, then ship the whole pallet with one button on the day it leaves. To send just one device, use **Ship to...** on its row instead (see the end of this section).

Step 1: Stage devices (any time)

- As you put a device on the pallet, tap **Edit** on its row and choose **Pending Transfer**.
- It gets a purple Pending Transfer badge and stays at your depot. Keep staging over days or weeks while the pallet fills.
- Staged one by mistake? Edit it back to In Stock or In Maintenance.
- Removal at a depot with **Depot Status = Pending Transfer** (Section 9.2) stages the device in the same step.

Step 2: Ship the pallet (ship day)

1. Choose your depot and tap  **Ship Pallet**. The button is active whenever at least one device is Pending Transfer.
2. **Destination:** CORD Warehouse (usually) or another depot.
3. **MDM Tracking #:** the tracking number from the shipping label. One number covers the whole pallet.
4. **Devices on this pallet:** every Pending Transfer device is listed and checked. Uncheck any that aren't going; they stay Pending Transfer for the next pallet.
5. Tap **Ship Pallet** and confirm.

TIA then does the following automatically:

- Each shipped device leaves your depot's list and becomes **In Transit** to the destination.
- A shipment record is created in IMS for each device, all with your MDM number, and the warehouse team is emailed the pallet list.
- At CORD, the warehouse checks each device in from IMS. At another depot, the techs check them in on their own Depot tab (Section 15).

Note

Once the pallet ships, the receiving end checks the devices in. If something shipped by mistake, contact the warehouse. A Pending Transfer device can't be installed: the Install form blocks it until you edit it back to In Stock.

Shipping one device: Ship to...

Use Ship to... when a single device needs to go to CORD or another depot. It works from any row that is In Stock, In Maintenance or Pending Transfer; you don't need to stage it first.

1. On the device's row, tap **Ship to...** and check the window shows the right device.
2. **Destination:** CORD Warehouse or another depot.
3. **MDM Tracking #:** the tracking number from the shipping label (required).
4. Tap **Ship Device**.

The device leaves your depot's list and becomes In Transit to the destination, just like a one-device pallet: a shipment record is created in IMS with your MDM number, and the warehouse team is emailed. There's no extra confirm step, so check the destination before you tap Ship Device.

21. Counting Your Depot: Audit Depot

To confirm your depot's list is right, whether for a periodic count or a quick check after a busy week, use  **Audit Depot**. You collect the serials physically on your shelves, and TIA shows where they differ from IMS.

Important — The audit changes nothing

It never adds, moves, edits or removes a device. It only reports. The warehouse corrects anything that needs fixing in IMS, so you can run an audit as often as you like.

21.1 Running an audit

1. Choose your depot, then tap  **Audit Depot**.
2. Choose the audit type (see below). Read the difference before you pick.
3. Collect the serials: scan them one at a time ( on a phone), paste a list (one serial per line) and tap ↓ **Add these to the list**, or upload a CSV or Excel file. You can mix all three. A counter shows how many you have, and Clear list starts over.
4. Tap **Run Audit**. Anything still in the paste box is included automatically. A full audit with no serials is refused, because it would report every device at the depot as missing.

Audit type	Use it when	Devices you didn't scan
Full audit	You are counting the whole depot.	Reported as Missing .
Spot check	You are only checking part of the depot.	Not reported. Only the serials you scan are checked.

Tip — Use Spot check unless you count everything

A full audit of half a depot lists every device you didn't get to as missing. The real problems get buried and the report is easy to ignore.

21.2 What the results mean

Result	What it means	What to do
Matched	You scanned it, and IMS agrees it's at your depot.	Nothing. All good.
Needs attention	It's here, but its status calls for action: In Transit, Pending Transfer or Damaged In Transit.	Do what the row says: check in the pallet, ship or un-stage the device, or leave it for the open claim.
Missing	IMS says it's at your depot, but you didn't scan it. Full audit only.	Look for it. If it's really gone, tell the warehouse.
Expected inbound	It's In Transit to your depot and hasn't arrived yet, so not scanning it is normal.	Nothing. This isn't a problem.
Found elsewhere	The serial is real, but IMS has it somewhere else: another depot, CORD, decommissioned, or on an open claim or lease return.	Send it to the warehouse to correct in IMS.
Unknown to IMS	The serial isn't in IMS at all.	Check for a mis-scan first. If it's a real device that belongs to your depot, add it with + Add Device .

21.3 Saving and sending the report

- **↓ Download CSV** saves the full report: every result, not just the problems.
- **✉ Send Report** emails the same report, with the CSV attached, to your depot's Team Lead and the warehouse audit list. TIA shows who will receive it before you send.
- If no recipients are set up for your depot, TIA says so and hides the send button. You can still download the CSV. Ask an admin to set a Team Lead for your depot in IMS.

Note — Serials with a leading "S"

Many labels print an "S" in front of the serial, and a scan picks it up. The audit removes a leading S before matching, whatever the make, and says so in the result details ("Scanned as ...; leading S removed."), so you don't go looking for a device that's already in front of you.

22. Reports

The **Reports** page is available to full-access techs and admins. It exports install records to a CSV file you can open in Excel, or emails the file.

22.1 Export by date and service type

The top of this section shows when records were last exported and how many are still unreported.

1. Choose a **Start Date** and **End Date**.
2. Tick the **Service Types** to include (all are ticked to start).
3. Optional: tick **Unreported Only** to export only records that haven't been exported before.
4. Tap **↓ Export to CSV** to download, or ☒ **Email Report** and enter the recipients' email addresses.

Note — Unreported Only

An export with Unreported Only ticked marks those records as reported, so the next Unreported Only export picks up only newer records.

22.2 Device lookup report

Find every record for one device. Choose **Search By** (Serial Number, Asset Tag or MercyID), enter the value, then tap **↓ Export to CSV** or ☒ **Email Report**.

23. Troubleshooting

Problem	Solution
Something in this guide is missing on my phone	Close the TIA tab completely and open tia-mercy.com again. Phones keep an old version of an open tab in memory after TIA is updated.
Serial not found in CMDDB	Enter Asset Tag, MercyID, Manufacturer and Model by hand. TIA adds the device to the database when you submit.
Submit is grayed out	Read the red notice under the serial number. It says what is blocking the submission (Sections 9 and 10).
"Cannot Install / Move / Hot Swap" (device at a depot)	Follow the notice: wait for check-in (In Transit), Edit to In Stock (In Maintenance or Pending Transfer), or leave it for the warehouse (Damaged In Transit).
"Cannot be marked inbound to CORD"	Already In Transit to CORD: don't file it again. At a depot: use Ship Pallet. Decommissioned or on an open claim or lease return: contact the warehouse.
"Cannot be added to ... depot inventory"	The device is already recorded somewhere else. Check the serial. If it's right, contact the warehouse.
Depot Status field doesn't appear	Service Type must be Removal and the depot must be chosen from the Location (Facility) list, not typed into Location (Manual).
Location not in the list	Use Location (Manual). City, State and Zip unlock so you can type them. (Not for CORD or a depot; see Section 7.3.)
Android: "No barcode detected"	Retake the photo closer, in good light, with just the barcode in view, or type the value. A Bluetooth scanner avoids the problem.

Problem	Solution
iPhone: camera won't open or won't scan	Allow camera access for the site when asked. For a vertical barcode, turn on rotation lock and hold the phone upright.
Error message after Submit	Read the message at the top of the page. Nothing was saved. Fix the field it names and submit again.
Depot Inventory isn't in my menu	The tab is turned off. Ask your admin.
Add Device shows a red duplicate warning	The serial is already recorded somewhere. Check the serial. If IMS is wrong, contact the warehouse.
Can't find a device in my depot list	Tap Clear next to the search box, then search by serial, asset tag or MercyID. Sorting by Serial also helps.
The serial changed after I scanned it	TIA removed a leading "S" that the barcode added. That's expected, and the notice under the serial says so (Sections 6.3 and 17).
Audit: no Send Report button	No recipients are set up for your depot. Download the CSV and ask an admin to set a Team Lead for the depot.
Signed out / sent back to sign-in	Sessions last up to 12 hours. Sign in again. Your submitted records are saved.
Forgot password	Contact your administrator, who can reset it.
Where are the user guides?	Tap Help in the menu to view or download this guide and the Quick Reference.

Tip — Questions?

If something looks wrong in inventory, contact the CORD warehouse team (IMS admin). For TIA sign-in or access questions, contact your TIA administrator.