

Yee-Cell Finite-Difference Solver for 2D Electromagnetics

Formulation, Discretization, and Implementation Plan
with a Roadmap to GSTC Metasurfaces

Tom Smy

September 29, 2026

Abstract

This note is the specification for MaxwellFD, a Python finite-difference code on a uniform Cartesian Yee grid. One grid, one material sampling, and one pair of discrete curls serve both the leapfrog scheme (FDTD) and the time-harmonic sparse scheme (FDFD). Phasors use $e^{j\omega t}$, the same convention as the sibling surface code MaxwellMOM. The derivation below is two-dimensional, for TMz and TEz, in free space and in a uniform isotropic medium. PEC and periodic walls, the CFL limit, numerical dispersion, a stretched-coordinate PML, and a resistive sheet are written out so later slices can code them against equation numbers. The non-dispersive GSTC subcell is the symmetric Yee cell: the face unknowns and the local system are derived here. Spatially varying χ , Bloch cells, and dispersive χ are specified as checks, not as this slice's code.

Contents

1	Mathematical formulation	3
1.1	Maxwell's equations	3
1.2	Two-dimensional reductions	3
1.3	Constitutive law	3
1.4	Boundaries in the continuous problem	4
2	Discretization	4
2.1	Cells, axes, and shapes	4
2.2	Discrete curls	4
2.3	Leapfrog update	5
2.4	Material sampling and staircase geometry	5
2.5	Bulk Debye and Lorentz media	5
3	Stability, dispersion, and domain closure	6
3.1	CFL limit	6
3.2	Semi-discrete and fully discrete frequencies	6
3.3	Lossless invariant	6
3.4	PEC, PMC, and periodic walls	7
3.5	PML	7
4	Linear algebra and thin sheets	7
4.1	Driven FDFD system	7
4.2	Cavity eigenproblem	8
4.3	Resistive sheet	8
4.4	Complex permittivity and a Dirichlet trace	8

5	Validation	9
5.1	Normal-incidence Fresnel slab	9
5.2	Dielectric cylinder	10
6	GSTC metasurfaces	11
6.1	Jump conditions	11
6.2	Reflection and transmission	11
6.3	Symmetric cell	12
6.4	What waits until the uniform sheet matches	13
7	Software architecture	13
7.1	Modules	13
7.2	Relation to MaxwellMOM	14
7.3	Milestone map	14

1 Mathematical formulation

1.1 Maxwell's equations

Fields are in SI units. The time convention is $e^{j\omega t}$, so a wave $e^{-jk\hat{\mathbf{k}}\cdot\mathbf{r}}$ propagates in the direction $\hat{\mathbf{k}}$ and ∂_t becomes $j\omega$. With an impressed current $\mathbf{J}$,

$$\nabla \times \mathbf{E} = -j\omega\mu \mathbf{H}, \quad (1.1)$$

$$\nabla \times \mathbf{H} = j\omega\varepsilon \mathbf{E} + \mathbf{J}. \quad (1.2)$$

Conduction is not a second current on the right. It stays in a real conductivity σ that the time stepper absorbs into its coefficients, or, in a later frequency-domain material, in a complex permittivity. The constants c_0 , ε_0 , μ_0 , and η_0 are the SI values used by MaxwellMOM. In a uniform lossless medium $c = 1/\sqrt{\mu\varepsilon}$ and $\eta = \sqrt{\mu/\varepsilon}$.

The impressed current is the source. A plane wave, a dipole, and a Gaussian beam are later special cases of $\mathbf{J}$ or of a total-field/scattered-field boundary. Milestone 1 does not inject those sources. Its free-space check is a periodic eigenmode, and its cavity check is a source-free resonance.

1.2 Two-dimensional reductions

The grid lies in the xy -plane and nothing depends on z .

TMz. The unknowns are E_z , H_x , and H_y . Equations (1.1) and (1.2) reduce to

$$\partial_y E_z + j\omega\mu H_x = 0, \quad (1.3)$$

$$-\partial_x E_z + j\omega\mu H_y = 0, \quad (1.4)$$

$$\partial_x H_y - \partial_y H_x - j\omega\varepsilon E_z = J_z. \quad (1.5)$$

Eliminating $\mathbf{H}$ gives the Helmholtz equation used only as a check,

$$\partial_x^2 E_z + \partial_y^2 E_z + \omega^2 \mu \varepsilon E_z = j\omega\mu J_z. \quad (1.6)$$

The code never forms this scalar operator when μ varies from face to face. It keeps the curls.

TEz. The unknowns are H_z , E_x , and E_y :

$$\partial_x E_y - \partial_y E_x + j\omega\mu H_z = 0, \quad (1.7)$$

$$\partial_y H_z - j\omega\varepsilon E_x = J_x, \quad (1.8)$$

$$-\partial_x H_z - j\omega\varepsilon E_y = J_y. \quad (1.9)$$

1.3 Constitutive law

A volumetric law returns ε , μ , and σ at the Yee location of each component. The milestone-1 law is uniform and isotropic: one positive ε , one positive μ , and one $\sigma \geq 0$. The call also accepts a frequency and an external state (a temperature map, a stress map, or anything the caller has already computed). The uniform law ignores both. A later law may return a different value at every sample, or a complex $\varepsilon(\omega)$ for FDFD. The time stepper requires real ε and σ ; a dispersive time-domain medium will add auxiliary variables rather than a complex coefficient inside the leapfrog.

Surface models are not constitutive samples. PEC, a resistive sheet, and a GSTC sheet modify curls or replace rows. They are not encoded by setting ε to zero or to infinity.

1.4 Boundaries in the continuous problem

On a PEC wall the tangential electric field is zero. On a PMC wall the tangential magnetic field is zero. A periodic wall identifies the two opposite faces, optionally with a Bloch phase $e^{-j\mathbf{k}_B \cdot \mathbf{L}}$ in a later slice; milestone 1 uses a phase of one. An open boundary is a PML, written in Sec. 3.5 and not coded yet.

2 Discretization

2.1 Cells, axes, and shapes

The grid has n_x by n_y cells of size Δx and Δy . The domain is $[0, a] \times [0, b]$ with $a = n_x \Delta x$ and $b = n_y \Delta y$. Stored arrays use index $[i, j]$ with axis 0 along x .

Table 1 is the layout the drivers assume. PEC keeps the boundary electric samples in the array and sets them to zero. Periodic identification drops the duplicate far side, so every stored sample is an unknown and every difference wraps.

Table 1: Sample locations. A PEC count of $n+1$ includes both boundaries. A periodic count of n is one period.

Field	Location	PEC shape	Periodic shape
E_z	$(i\Delta x, j\Delta y)$	(n_x+1, n_y+1)	(n_x, n_y)
H_x	$(i\Delta x, (j + \frac{1}{2})\Delta y)$	(n_x+1, n_y)	(n_x, n_y)
H_y	$((i + \frac{1}{2})\Delta x, j\Delta y)$	(n_x, n_y+1)	(n_x, n_y)
H_z	$((i + \frac{1}{2})\Delta x, (j + \frac{1}{2})\Delta y)$	(n_x, n_y)	(n_x, n_y)
E_x	$((i + \frac{1}{2})\Delta x, j\Delta y)$	(n_x, n_y+1)	(n_x, n_y)
E_y	$(i\Delta x, (j + \frac{1}{2})\Delta y)$	(n_x+1, n_y)	(n_x, n_y)

Centered differences of a linear field are exact on this stencil. That is the sign test for the curls: if $E_z = \alpha x + \beta y$, then the discrete $\partial_y E_z$ equals β and $-\partial_x E_z$ equals $-\alpha$.

2.2 Discrete curls

Collect the free electric samples in a vector $\mathbf{e}$ and the magnetic samples that the curls touch in a vector $\mathbf{h}$. The two real sparse matrices are defined so that they match (1.1) and (1.2) term by term:

$$\text{curl}_E \mathbf{e} + j\omega \text{diag}(\mu_H) \mathbf{h} = 0, \quad (2.1)$$

$$\text{curl}_H \mathbf{h} - j\omega \text{diag}(\varepsilon_E) \mathbf{e} = \mathbf{j}. \quad (2.2)$$

For TMz, curl_E stacks $(\partial_y E_z, -\partial_x E_z)$ and curl_H is $\partial_x H_y - \partial_y H_x$. For TEz, curl_E is $\partial_x E_y - \partial_y E_x$ and curl_H stacks $(\partial_y H_z, -\partial_x H_z)$.

On every grid in Table 1 the two matrices are transposes,

$$\text{curl}_H = \text{curl}_E^T. \quad (2.3)$$

The boundary terms that integration by parts would leave are absent because PEC electric samples are not unknowns, and periodic faces cancel. The product $\text{curl}_H \text{diag}(\mu^{-1}) \text{curl}_E$ is therefore symmetric.

PEC degrees of freedom, TMz: E_z for $i = 1, \dots, n_x - 1$ and $j = 1, \dots, n_y - 1$; H_x for $i = 1, \dots, n_x - 1$ and $j = 0, \dots, n_y - 1$; H_y for $i = 0, \dots, n_x - 1$ and $j = 1, \dots, n_y - 1$. The magnetic samples on the outer PEC edges do not enter curl_H at a free E_z . TEz keeps every H_z , drops E_x on $y = 0$ and $y = b$, and drops E_y on $x = 0$ and $x = a$.

TEz curl-curl on tangential $\mathbf{E}$ has a kernel: any discrete gradient of a nodal potential that is constant on the PEC boundary has zero circulation. Those eigenvalues are zero. They are not cavity modes. The physical spectrum is the positive one.

2.3 Leapfrog update

Store $\mathbf{E}$ at integer steps and $\mathbf{H}$ at the half-step before it. One step produces $\mathbf{H}^{n+1/2}$ from $\mathbf{E}^n$, then $\mathbf{E}^{n+1}$ from $\mathbf{H}^{n+1/2}$. For TMz, with the curls of Sec. 2.2,

$$H_x \leftarrow H_x - \frac{\Delta t}{\mu_x} \partial_y E_z, \quad (2.4)$$

$$H_y \leftarrow H_y + \frac{\Delta t}{\mu_y} \partial_x E_z, \quad (2.5)$$

$$E_z \leftarrow C_a E_z + C_b (\partial_x H_y - \partial_y H_x). \quad (2.6)$$

The coefficients are evaluated at the E_z samples,

$$C_a = \frac{1 - \sigma \Delta t / (2\varepsilon)}{1 + \sigma \Delta t / (2\varepsilon)}, \quad C_b = \frac{\Delta t / \varepsilon}{1 + \sigma \Delta t / (2\varepsilon)}. \quad (2.7)$$

When $\sigma = 0$ they are $C_a = 1$ and $C_b = \Delta t / \varepsilon$. The same pair is used on E_x and E_y in TEz, and the magnetic update is

$$H_z \leftarrow H_z - \frac{\Delta t}{\mu_z} (\partial_x E_y - \partial_y E_x). \quad (2.8)$$

After the electric update, PEC edges are set back to zero.

No matrix is stored. The array curls are the same stencil as curl_E and curl_H , including the wrap on a periodic grid.

2.4 Material sampling and staircase geometry

ε and σ live on electric samples. μ lives on magnetic samples. A uniform law fills those arrays with constants. A staircase solid fills each sample from the coordinate of that sample, so an electric node and a magnetic node on the same cell can lie on opposite sides of a face. A slab $y_0 \leq y < y_1$ is half-open, and a disk $(x - x_c)^2 + (y - y_c)^2 \leq R^2$ is closed. Later regions overwrite earlier ones. There is no volume-fraction weight. The assignment is

$$(x, y) \in \mathcal{R} \implies (\varepsilon, \mu, \sigma)(x, y) = (\varepsilon, \mu, \sigma)_{\mathcal{R}}, \quad (2.9)$$

The stepper is unchanged, because it already reads one coefficient per sample. Conformal cuts and sub-cell dielectric smoothing are not part of this scheme.

Tensor $\bar{\varepsilon}$ is out of scope until the scalar isotropic tests match the analytic formulas. Off-diagonal samples would sit at locations the present curls do not read.

2.5 Bulk Debye and Lorentz media

A dispersive law returns a complex $\varepsilon(\omega)$ to FDFD and a real instantaneous permittivity ε_∞ to the leapfrog. One electric Debye pole and one electric Lorentz pole are enough for this slice. With the $e^{j\omega t}$ convention,

$$\varepsilon(\omega) = \varepsilon_\infty + \frac{\varepsilon_0 \Delta \varepsilon}{1 + j\omega \tau}, \quad (2.10)$$

$$\tau \partial_t P + P = \varepsilon_0 \Delta \varepsilon E, \quad (2.11)$$

$$\varepsilon(\omega) = \varepsilon_\infty + \frac{\varepsilon_0 \omega_p^2}{\omega_0^2 - \omega^2 + j\gamma \omega}, \quad (2.12)$$

$$\partial_t^2 P + \gamma \partial_t P + \omega_0^2 P = \varepsilon_0 \omega_p^2 E. \quad (2.13)$$

Magnetic dispersion is not in this slice. These volume auxiliaries are independent of the surface oscillators (6.17) and (6.18).

$J_p = \partial_t P$ is added to the impressed current. The coefficients C_a and C_b stay (2.7), built on ε_∞ and σ , and the electric update becomes

$$E \leftarrow C_a E + C_b (\nabla \times H - J_p - J). \quad (2.14)$$

$J = 0$ and $J_p = 0$ is (2.6). Lorentz stores P at integer steps, advances it explicitly from E^n , and sets $J_p^{n+1/2} = (P^{n+1} - P^n)/\Delta t$. Debye uses the centered average $E^{n+1/2} = (E^{n+1} + E^n)/2$, which couples P^{n+1} to E^{n+1} and is solved one sample at a time. TEz carries one auxiliary on E_x and one on E_y .

3 Stability, dispersion, and domain closure

3.1 CFL limit

On a uniform 2D Yee grid the leapfrog is stable for

$$\Delta t \leq \Delta t_{\text{CFL}} = \frac{1}{c\sqrt{\Delta x^{-2} + \Delta y^{-2}}}. \quad (3.1)$$

The bound is sharp for the grid mode $k_x = \pi/\Delta x$, $k_y = \pi/\Delta y$. A run at $0.99 \Delta t_{\text{CFL}}$ must stay bounded. A run at $1.01 \Delta t_{\text{CFL}}$ must grow.

3.2 Semi-discrete and fully discrete frequencies

With continuous time and Yee differences, a mode k_x, k_y oscillates at

$$\left(\frac{\omega_0}{c}\right)^2 = \left(\frac{2 \sin(k_x \Delta x/2)}{\Delta x}\right)^2 + \left(\frac{2 \sin(k_y \Delta y/2)}{\Delta y}\right)^2. \quad (3.2)$$

The leapfrog moves that frequency to the root of

$$\left(\frac{\sin(\omega \Delta t/2)}{c \Delta t}\right)^2 = \left(\frac{\sin(k_x \Delta x/2)}{\Delta x}\right)^2 + \left(\frac{\sin(k_y \Delta y/2)}{\Delta y}\right)^2, \quad (3.3)$$

provided the right-hand side is at most $(c\Delta t)^{-2}$. Because $\arcsin z > z$ on $(0, 1)$, this ω lies slightly above ω_0 . FDFD, having no time difference, must reproduce ω_0 .

A rectangular PEC cavity of size $a \times b$ has $k_x = m\pi/a$ and $k_y = n\pi/b$. TMz needs $m \geq 1$ and $n \geq 1$, because E_z vanishes on the whole boundary. TEz also allows $m = 0$ or $n = 0$, but not both. The mode shapes consistent with the stencil are

$$E_z = \sin(m\pi x/a) \sin(n\pi y/b), \quad (3.4)$$

$$H_z = \cos(m\pi x/a) \cos(n\pi y/b). \quad (3.5)$$

A pure spatial eigenmode sampled on three successive steps obeys the scalar leapfrog recurrence. Those three numbers determine ω without a Fourier transform.

3.3 Lossless invariant

$\mathbf{E}$ and $\mathbf{H}$ are never stored at the same time. The sum of their sample energies therefore oscillates by a noticeable fraction of itself near the CFL limit, even though the scheme is lossless. The quadratic form that the update conserves, when $\sigma = 0$, is

$$W^n = \frac{1}{2} \sum \varepsilon (E^n)^2 \Delta x \Delta y + \frac{1}{2} \sum \mu H^{n+1/2} H^{n-1/2} \Delta x \Delta y, \quad (3.6)$$

with the sums over the stored samples of each component. The derivation is the adjoint relation (2.3): the work done on $\mathbf{E}$ by $\text{curl}_H \mathbf{H}$ cancels the work done on $\mathbf{H}$ by $\text{curl}_E \mathbf{E}$. Conductivity removes the cancellation. Above the CFL limit W^n can stay constant while the ordinary field energy grows, because W^n is then indefinite. Boundedness is checked with W^n . Growth past the CFL limit is checked with the ordinary field energy.

3.4 PEC, PMC, and periodic walls

PEC for TMz is $E_z = 0$ on the outer node lines. PEC for TEz is $E_x = 0$ on $y \in \{0, b\}$ and $E_y = 0$ on $x \in \{0, a\}$. PMC is the dual statement, tangential $\mathbf{H} = 0$, which is a Neumann condition on the remaining field. PMC is part of the surface stack and is not in the milestone-1 unknown set.

Periodic differences replace $i - 1$ at $i = 0$ by $i = n_x - 1$, and likewise in y . A Bloch phase multiplies the wrapped sample by $e^{\pm j k_{B,x} a}$. The phase is unity until the metasurface unit-cell slice.

3.5 PML

An open domain is closed by a complex stretch of the normal coordinate, following the convolutional PML. In the frequency domain, for each axis $w \in \{x, y\}$,

$$s_w = \kappa_w + \frac{\sigma_w}{\alpha_w + j\omega\varepsilon_0}, \quad (3.7)$$

and every ∂_w in the curls is replaced by $s_w^{-1} \partial_w$. The reciprocal that the auxiliary equation integrates is

$$\frac{1}{s_w} = \frac{1}{\kappa_w} - \frac{\sigma_w / (\kappa_w^2 \varepsilon_0)}{j\omega + \alpha_w / \varepsilon_0 + \sigma_w / (\kappa_w \varepsilon_0)}. \quad (3.8)$$

Inside a PML slab of thickness d , with ρ the depth measured from the inner face and m typically 3 or 4,

$$\sigma_w(\rho) = \sigma_{\max}(\rho/d)^m, \quad \sigma_{\max} = -\frac{(m+1) \ln R(0)}{2\eta_0 d}, \quad (3.9)$$

with a target reflection $R(0)$ of order 10^{-6} to 10^{-8} . κ_w grows from 1 at the inner face to a modest $\kappa_{\max}$, and α_w falls from a small positive value at the inner face to zero at the outer PEC backing. The time-domain scheme adds one auxiliary per stretched derivative and integrates (3.8) with the same Δt as the leapfrog. This section is the specification for that slice. The milestone-1 stepper has no PML.

4 Linear algebra and thin sheets

4.1 Driven FDFD system

Eliminating $\mathbf{h}$ from (2.1) and (2.2) gives the system that is factored,

$$\text{curl}_H \text{diag}\left(\frac{1}{j\omega\mu_H}\right) \text{curl}_E \mathbf{e} + j\omega \text{diag}(\varepsilon_E) \mathbf{e} = -\mathbf{j}. \quad (4.1)$$

The unknown is the free electric vector. PEC rows are omitted rather than penalized. The matrix is complex symmetric when ε and μ are scalar, and it is stored sparse. Milestone 1 solves it with a sparse direct factorization. Two-dimensional grids of the size used in the tests factor in negligible time. Iterative solves (GMRES or BiCGSTAB, with a preconditioner) wait until a grid is large enough that the factor is the expensive part.

At a fixed real ω away from the cavity spectrum the matrix is nonsingular. A manufactured solution builds $\mathbf{j}$ by applying the left-hand side to a chosen $\mathbf{e}$ and asks the solver for that $\mathbf{e}$ back.

4.2 Cavity eigenproblem

For lossless media and $j = 0$, multiplying (4.1) through by $j\omega$ produces the generalized eigenproblem

$$K\mathbf{e} = \omega^2 M\mathbf{e}, \quad K = \text{curl}_H \text{diag}(\mu_H^{-1}) \text{curl}_E, \quad M = \text{diag}(\varepsilon_E). \quad (4.2)$$

K is real symmetric and, on a TMz PEC cavity, positive definite. On a TEz PEC cavity it is positive semi-definite with the gradient kernel of Sec. 2.2. The positive eigenvalues are the semi-discrete frequencies (3.2). Conductivity does not enter K and M . A complex permittivity belongs in the driven system (4.1), not in this real eigenproblem.

4.3 Resistive sheet

A zero-thickness electric sheet with surface impedance Z_s (ohms per square) carries

$$\hat{\mathbf{n}} \times (\mathbf{H}^+ - \mathbf{H}^-) = \mathbf{E}_{\text{av}}/Z_s. \quad (4.3)$$

The normal points from the $-$ side to the $+$ side. For a sheet of normal $\hat{\mathbf{y}}$ in TMz this is $-(H_x^+ - H_x^-) = E_z/Z_s$.

The same sheet is the pure-electric GSTC of Sec. 6 with

$$\chi_{ee} = \frac{\eta_0}{jkZ_s} = \frac{1}{j\omega\varepsilon_0 Z_s}, \quad (4.4)$$

and $\chi_{mm} = 0$. MaxwellMOM's `chi_ee_from_Zs` is this map. In the time domain a real Z_s is a shunt conductance, not a constant susceptibility: $J_z = \sigma_s E_z$ with $\sigma_s = 1/Z_s$. Placing that current in the Ampere cell of height Δy that contains the sheet adds

$$\sigma_{\text{eff}} = \sigma + \frac{1}{Z_s \Delta y} \quad (4.5)$$

to the C_a, C_b formula (2.7) on the sheet's electric samples. That is the milestone-4 update. It is the $\chi_{mm} = 0$ reduction of the symmetric cell, specialized to $\chi_{ee} \propto 1/(j\omega)$.

4.4 Complex permittivity and a Dirichlet trace

When ε and σ are real, the diagonal of (4.1) uses

$$\varepsilon_{\text{FDFD}} = \varepsilon + \frac{\sigma}{j\omega}. \quad (4.6)$$

A law that returns a complex $\varepsilon(\omega)$ has already included its loss. That array replaces (4.6) and the accompanying σ is zero, so a pole is not counted twice. The real eigenproblem (4.2) still requires real positive ε and μ and $\sigma = 0$.

PEC electric samples stay out of the unknown vector. A non-zero trace e_D , equal to the prescribed boundary values and zero on the free samples, moves onto the right-hand side,

$$A_{ff} \mathbf{e}_f = -\mathbf{j} - (Ae_D)_f. \quad (4.7)$$

The free rows of Ae_D are the array form of the left-hand side of (4.1). A zero trace is the milestone-1 solve. This is how the slab and cylinder comparisons are posed. It is not a PML.

5 Validation

Milestone 1 is a numerical check that the curls, the leapfrog, and the sparse system implement Secs. 2 and 3. The acceptance tests and the bars they use are:

Check	Bar	What is compared
Linear TMz and TEz curls	10^{-12} absolute	Centered differences of a linear field
$\text{curl}_H = \text{curl}_E^\top$	10^{-12} absolute	All four grids in Table 1
Matrix versus array curl	10^{-12} relative	Same four grids, PEC boundaries held at zero
TMz cavity (1, 1)	10^{-10} relative	Smallest FDFD eigenvalue versus (3.2)
TEz cavities (1, 0) and (1, 1)	10^{-10} relative	Positive FDFD eigenvalues versus (3.2)
Manufactured FDFD solve	10^{-10} relative	Recovered ϵ on TMz and TEz
Leapfrog invariant at $0.99 \Delta t_{\text{CFL}}$	1 percent	W^n over $2 \cdot 10^3$ steps, random TMz data
Field energy at $1.01 \Delta t_{\text{CFL}}$	growth past $10 \times$	Same data, ordinary sample energy
TMz and TEz modal ω	10^{-6} relative	Three leapfrog samples versus (3.3)
Periodic standing wave $(k_x, k_y) = (2\pi/a, 0)$	10^{-6} relative	Same recurrence versus (3.3)

The modal and standing-wave bars in the project plan were 10^{-3} , which is a fit tolerance. A pure eigenmode has no fit error, so the tests use 10^{-6} .

Milestone 2 adds the volumetric checks. The scattering rows compare the Yee solution, with the trace (4.7) taken from the formulas below, to those formulas. The gap is dispersion, and for the disk the staircase. A slab face used in a convergence pair is kept off the electric nodes of both grids, so (2.9) does not assign the face to a sample. The comparison wavelength is kept off the TEz eigenfrequencies of that closed box: $\lambda = 40\Delta$ on the 8×80 domain is one of them, and the Dirichlet problem is then singular.

Check	Bar	What is compared
Fresnel face continuity	10^{-12} absolute	Tangential E and H , both polarizations
Mie cylinder continuity	10^{-8} absolute	Tangential field and derivative at $\rho = a$
PEC cylinder coefficient	10^{-12} relative	a_n against $-(-j)^n J_n/H_n^{(2)}$
Manufactured $\sigma > 0$ and $\epsilon(\mathbf{r})$	10^{-10} relative	Recovered ϵ , both polarizations
Uniform $\epsilon_r = 4$ cavity	$10^{-10} / 10^{-6}$	FDFD versus (3.2); leapfrog versus (3.3)
Slab-loaded TMz cavity	10^{-2} and 10^{-6}	Continuous root, then leapfrog against that ω_0
Lossless staircase invariant	1 percent	W^n over 500 steps at half the CFL step
Fresnel slab, both polarizations	$2 \cdot 10^{-2}$ relative	Free samples; halving Δ drops the error by $2.5 \times$
Dielectric cylinder, both polarizations	$2 \cdot 10^{-2}$ relative	Samples 2Δ off the circle and the wall
Debye and Lorentz, one period	$3 \cdot 10^{-3}$ relative	Leapfrog against the complex- ϵ phasor

5.1 Normal-incidence Fresnel slab

A slab $y_1 \leq y \leq y_2$ of thickness d , relative permittivity ϵ_r , and $\mu = \mu_0$ sits in vacuum. The incident wave travels toward $+y$ and equals 1 at the front face. With $n = \sqrt{\epsilon_r}$, $k = \omega/c$, and $\delta = nkd$, a single-interface reflection r produces

$$R = \frac{r(1 - e^{-2j\delta})}{1 - r^2 e^{-2j\delta}}, \quad \tau = \frac{(1 - r^2) e^{-j\delta}}{1 - r^2 e^{-2j\delta}}. \quad (5.1)$$

For TMz the unknown is E_z and $r = (1 - n)/(1 + n)$. The field is

$$E_z(y) = \begin{cases} e^{-jk(y-y_1)} + R e^{jk(y-y_1)}, & y \leq y_1, \\ A e^{-jnk(y-y_1)} + C e^{jnk(y-y_1)}, & y_1 \leq y \leq y_2, \\ \tau e^{-jk(y-y_2)}, & y \geq y_2, \end{cases} \quad (5.2)$$

with $A = \frac{1}{2}(1 + R + (1 - R)/n)$ and $C = \frac{1}{2}(1 + R - (1 - R)/n)$. Then $H_x = -\partial_y E_z/(j\omega\mu_0)$: a forward vacuum wave has $H_x = E_z/\eta$ and a backward wave has $H_x = -E_z/\eta$, where $\eta = \sqrt{\mu_0/\varepsilon_0}$. Inside, the forward part of H_x carries an extra factor of n .

TEz is a different scalar. Tangential H reflects with $r_H = (n - 1)/(n + 1) = -r$, and (5.1) is evaluated at r_H . Transmission depends on r^2 , so τ is unchanged and $R_H = -R$. Interior amplitudes satisfy $A_H + C_H = 1 + R_H$ and $A_H - C_H = n(1 - R_H)$,

$$H_z(y) = \begin{cases} e^{-jk(y-y_1)} + R_H e^{jk(y-y_1)}, & y \leq y_1, \\ A_H e^{-jnk(y-y_1)} + C_H e^{jnk(y-y_1)}, & y_1 \leq y \leq y_2, \\ \tau e^{-jk(y-y_2)}, & y \geq y_2, \end{cases} \quad (5.3)$$

with $A_H = \frac{1}{2}(1 + R_H + n(1 - R_H))$ and $C_H = \frac{1}{2}(1 + R_H - n(1 - R_H))$. The lift uses $E_x = \partial_y H_z/(j\omega\varepsilon)$ and $E_y = 0$. Outside, a forward wave has $E_x = -\eta H_z$; inside, that factor is η/n . When $\varepsilon_r = 1$, both reflections vanish and $\tau = e^{-jkd}$, so each field equals the incident wave. Continuity of tangential E and H at both faces is the check on these closed forms.

5.2 Dielectric cylinder

The outgoing cylindrical wave is $H_n^{(2)}$, the same convention as MaxwellMOM's two-dimensional PEC cylinder. The incident field e^{-jkx} has the Jacobi–Anger expansion

$$e^{-jkx} = \sum_{n=-\infty}^{\infty} (-j)^n J_n(k\rho) e^{jn\varphi}. \quad (5.4)$$

Our TMz unknown is E_z . For a non-magnetic cylinder of radius a and index $m = \sqrt{\varepsilon_r}$, with $\alpha = ka$ and $\beta = mka$,

$$a_n = (-j)^n \frac{m J_n'(\beta) J_n(\alpha) - J_n(\beta) J_n'(\alpha)}{J_n(\beta) H_n^{(2)'}(\alpha) - m J_n'(\beta) H_n^{(2)}(\alpha)}. \quad (5.5)$$

The interior coefficient follows from continuity of E_z at $\rho = a$. Outside, the scattered field is $a_n H_n^{(2)}(k\rho) e^{jn\varphi}$. Inside, it is $b_n J_n(mk\rho) e^{jn\varphi}$.

TEz is the H_z problem. Tangential E brings $1/\varepsilon$, so the contrast multiplies the undifferentiated interior Bessel function,

$$a_n = (-j)^n \frac{m J_n(\beta) J_n'(\alpha) - J_n'(\beta) J_n(\alpha)}{J_n'(\beta) H_n^{(2)}(\alpha) - m J_n(\beta) H_n^{(2)'}(\alpha)}. \quad (5.6)$$

The PEC reduction used as a regression is the separate coefficient $a_n = -(-j)^n J_n(\alpha)/H_n^{(2)}(\alpha)$, not the limit $\varepsilon_r \rightarrow \infty$ of (5.5).

Later slices add comparisons that this note already fixes the formulas for, and that the code does not yet run:

- an open PEC or dielectric cylinder against Mie once the PML of Sec. 3.5 is in;
- a 3D rectangular cavity, then a sphere against the Mie series, at a size (4.1) can still factor;

- a resistive sheet against (4.3) and against one MaxwellMOM impedance run of the same case;
- a uniform GSTC sheet against the R, T formulas of Sec. 6.2;
- a dipole, a Gaussian beam, a near-to-far integral, and a Bloch cell.

Prescribed external maps are checked by confirming that the samples the stepper reads are the samples the law was given. They are not a coupled thermal or mechanical solve.

6 GSTC metasurfaces

6.1 Jump conditions

A zero-thickness sheet of normal $\hat{\mathbf{n}}$, pointing from the $-$ side to the $+$ side, replaces the tangential continuity conditions by

$$\hat{\mathbf{n}} \times (\mathbf{H}^+ - \mathbf{H}^-) = \partial_t \mathbf{P}_s, \quad (6.1)$$

$$(\mathbf{E}^+ - \mathbf{E}^-) \times \hat{\mathbf{n}} = \mu_0 \partial_t \mathbf{M}_s. \quad (6.2)$$

For a monoanisotropic sheet the surface polarizations are

$$\mathbf{P}_s = \varepsilon_0 \chi_{ee} \cdot \mathbf{E}_{av}, \quad \mathbf{M}_s = \chi_{mm} \cdot \mathbf{H}_{av}, \quad (6.3)$$

with the average of the two one-sided tangential fields. In the frequency domain ∂_t is $j\omega$. These are the same jumps as in the symmetric Yee-cell scheme of Smy, Stewart, and Gupta (arXiv:1706.10136) and the same $e^{j\omega t}$ normalization as MaxwellMOM's `rt_from_chi`: there $J = j\omega\varepsilon_0\chi_{ee}E_{av}$ and $M = j\omega\mu_0\chi_{mm}H_{av}$.

For TMz and a sheet of normal $\hat{\mathbf{y}}$, (6.1) and (6.2) become

$$-(H_x^+ - H_x^-) = \partial_t P_z, \quad (6.4)$$

$$E_z^+ - E_z^- = -\mu_0 \partial_t M_x. \quad (6.5)$$

H_y is the normal field. It is not split.

Bianisotropic coupling, when it is added, extends (6.3) to

$$\mathbf{P}_s = \varepsilon_0 \chi_{ee} \cdot \mathbf{E}_{av} + c_0^{-1} \chi_{em} \cdot \mathbf{H}_{av}, \quad \mathbf{M}_s = \chi_{mm} \cdot \mathbf{H}_{av} + \eta_0^{-1} \chi_{me} \cdot \mathbf{E}_{av}. \quad (6.6)$$

The reflective lock used in MaxwellMOM is a particular χ_{em} inside this extension. It is not part of the first sheet implementation.

6.2 Reflection and transmission

Take a uniform sheet at $y = 0$, host medium (ε, μ) on both sides, and a TMz wave at angle θ from the normal. The reflected and transmitted amplitudes are defined by $E_z^+ = TE_0$ and $E_z^- = E_0(1 + R)$ at the sheet, with the incident wave coming from $y < 0$. Substituting the plane waves into (6.4) and (6.5), with constant susceptibilities, gives

$$R + T = \frac{1 - \tilde{\alpha}}{1 + \tilde{\alpha}}, \quad T - R = \frac{1 - \tilde{\beta}}{1 + \tilde{\beta}}, \quad (6.7)$$

where $\alpha_0 = jk\chi_{ee}/2$, $\beta_0 = jk\chi_{mm}/2$, $k = \omega/c$, and

$$\tilde{\alpha} = \alpha_0 / \cos \theta, \quad \tilde{\beta} = \beta_0 \cos \theta. \quad (6.8)$$

Hence

$$R = \frac{1}{2} \left(\frac{1 - \tilde{\alpha}}{1 + \tilde{\alpha}} - \frac{1 - \tilde{\beta}}{1 + \tilde{\beta}} \right), \quad (6.9)$$

$$T = \frac{1}{2} \left(\frac{1 - \tilde{\alpha}}{1 + \tilde{\alpha}} + \frac{1 - \tilde{\beta}}{1 + \tilde{\beta}} \right). \quad (6.10)$$

At $\theta = 0$ the tildes drop off and (6.9)–(6.10) are MaxwellMOM’s normal-incidence formula. TMz with the sheet normal $\hat{\mathbf{y}}$ and the plane of incidence the xy -plane is s polarization, which that code calls TE.

TEz on the same sheet is p polarization (TM in MaxwellMOM). The cosines trade places,

$$\tilde{\alpha} = \alpha_0 \cos \theta, \quad \tilde{\beta} = \beta_0 / \cos \theta, \quad (6.11)$$

and R, T keep the form (6.9)–(6.10). A normal magnetic susceptibility χ_{mm}^{nn} enters only the s /TE electric coefficient,

$$\tilde{\alpha} \leftarrow \tilde{\alpha} + \frac{jk \sin^2 \theta \chi_{mm}^{nn}}{2 \cos \theta}, \quad (6.12)$$

which is the correction MaxwellMOM applies for a flat sheet. The first coded sheet uses tangential χ_{ee} and χ_{mm} only. Equation (6.12) is the check for the normal-component extension.

6.3 Symmetric cell

The sheet sits halfway between electric nodes E_z^- at index j and E_z^+ at index $j+1$. The magnetic sample that would have occupied that face is replaced by a pair H_x^-, H_x^+ on the two sides of a zero-thickness cut. The averages and jumps in (6.4) and (6.5) use this pair and the two electric nodes. Bulk Faraday updates for H_y , and for the H_x faces that are not the cut, are unchanged: their stencils do not cross the sheet.

In the frequency domain the cut and the two Ampere cells that touch it are the local system

$$H_x^+ - H_x^- + j\omega\varepsilon_0\chi_{ee} \frac{E_z^- + E_z^+}{2} = 0, \quad (6.13)$$

$$E_z^+ - E_z^- + j\omega\mu_0\chi_{mm} \frac{H_x^- + H_x^+}{2} = 0, \quad (6.14)$$

$$\frac{H_y|_{i,j} - H_y|_{i-1,j}}{\Delta x} - \frac{H_x^- - H_x^{\text{below}}}{\Delta y} - j\omega\varepsilon E_z^- = J_z^-, \quad (6.15)$$

$$\frac{H_y|_{i,j+1} - H_y|_{i-1,j+1}}{\Delta x} - \frac{H_x^{\text{above}} - H_x^+}{\Delta y} - j\omega\varepsilon E_z^+ = J_z^+. \quad (6.16)$$

H_x^{below} and H_x^{above} are the ordinary Yee samples one cell off the cut. They are known from the bulk Faraday update when the cell is marched in time, and they are ordinary unknowns when the same rows are assembled into (4.1). Equations (6.13) and (6.14) replace the Faraday row that used to connect E_z^- to E_z^+ across one Δy .

For a non-dispersive real χ the time-domain statement is the same pair with $j\omega$ replaced by ∂_t acting on $\mathbf{P}_s$ and $\mathbf{M}_s$. The four surface unknowns at a given step are coupled, so the cell is a 4×4 (or a 2×2 after eliminating $H_x^\pm$) solve, while the rest of the grid stays an explicit leapfrog. That local solve is the one described for the symmetric cell in arXiv:1706.10136.

Two other placements are on record there. The asymmetric cell inserts the sheet between an existing H sample and an existing E sample and adds no nodes. The tight asymmetric cell adds one electric node on one side of the cut and one magnetic node on the other, and it is the placement that paper found to converge fastest. Milestone 5 codes (6.13)–(6.16) and checks R

and T against (6.9) and (6.10). If the half-cell offset of the symmetric averages dominates the error, the tight asymmetric cell replaces it without a change to the jump conditions.

A constant real χ , independent of ω , is a convenient FDFD value and a legal reduction of (6.13)–(6.14). It is not a causal broadband model. Broadband FDTD uses a Lorentz oscillator for each resonance,

$$\chi_{ee}(\omega) = \frac{\omega_{ep}^2}{\omega_{e0}^2 - \omega^2 + j\alpha_e\omega}, \quad \partial_t^2 P_z + \alpha_e \partial_t P_z + \omega_{e0}^2 P_z = \varepsilon_0 \omega_{ep}^2 E_{z,av}, \quad (6.17)$$

$$\chi_{mm}(\omega) = \frac{\omega_{mp}^2}{\omega_{m0}^2 - \omega^2 + j\alpha_m\omega}, \quad \partial_t^2 M_x + \alpha_m \partial_t M_x + \omega_{m0}^2 M_x = \omega_{mp}^2 H_{x,av}. \quad (6.18)$$

Several poles superpose. The auxiliary variables are marched with the local cell solve. This is the dispersive extension, after the constant- χ sheet matches (6.9) and (6.10).

6.4 What waits until the uniform sheet matches

Spatially varying $\chi(\mathbf{r})$ is a different (4×4) on each cut face, with the same jumps. A Bloch cell multiplies the periodic wrap by $e^{-j\mathbf{k}_B \cdot \mathbf{L}}$ and reports R and T in the Floquet orders. Spatially dispersive $\chi(k_t)$ is a separate operator, checked against MaxwellMOM’s multi- k_t reductions, and it is not a local 4×4 . None of these three is coded before the uniform tangential sheet agrees with Sec. 6.2.

7 Software architecture

7.1 Modules

The milestone-1 tree is the part of the layout that those tests exercise. Later boxes are named now so the drivers do not have to be renamed when the sheets arrive.

Module	Responsibility
<code>grid.yee2d</code>	Counts, spacings, polarization, boundary, shapes, coordinates
<code>materials.volume</code>	Uniform, staircase, and mapped ε, μ, σ
<code>materials.dispersion</code>	Debye and Lorentz laws, auxiliaries J_p
<code>operators.curl2d</code>	<code>curl_e</code> , <code>curl_h</code> , array curls, DOF order
<code>drivers.fdt2d</code>	Leapfrog step, J and J_p , invariant (3.6)
<code>drivers.fdfd2d</code>	System (4.1), Dirichlet lift, sparse solve
<code>analytics.cavity2d</code>	Frequency (3.2) and mode shapes (3.4), (3.5)
<code>analytics.dispersion</code>	Frequency (3.3) and the three-sample recurrence
<code>analytics.fresnel</code>	Slab fields (5.2), (5.3)
<code>analytics.mie2d</code>	Cylinder series (5.5), (5.6)
<code>operators.pml</code>	Stretch (3.7), not yet
<code>materials.sheets</code>	Impedance (4.5) and the symmetric cell, not yet
<code>analytics.sheets</code>	R, T from (6.9), (6.10), not yet
<code>grid.yee3d</code>	The same curls in three dimensions, not yet

`YeeGrid2D` owns $n_x, n_y, \Delta x, \Delta y$, the polarization, and the boundary kind. Both drivers read shapes from it. A validation case is run in time or in frequency by constructing the other driver on the same object.

`UniformIsotropic.sample_tm` and `sample_te` take the grid and optional `omega` and `state` arguments. Milestone 1 passes neither. A dispersive or externally modulated law implements the same methods and returns arrays of the same shapes. The stepper does not learn about temperature.

The surface path stays off those arrays. A sheet object, when it exists, will receive the grid and replace the rows described in Sec. 4.3 or Sec. 6.3. PEC is already a boundary kind rather than a material, because it removes unknowns instead of filling coefficients.

7.2 Relation to MaxwellMOM

MaxwellMOM is a surface integral code: RWG bases, Green’s functions, and dense blocks. MaxwellFD does not import it. The shared pieces are the convention and the analytic targets.

- $e^{j\omega t}$, and the four SI constants, copied numerically.
- Sheet reflection and transmission, (6.9) and (6.10), including the oblique factors and the χ_{mm}^{nn} correction, which are the formulas behind `rt_from_chi`.
- The map (4.4) from a surface impedance to χ_{ee} .
- Mie and Fresnel results as external checks, not as shared functions.

A number computed by MaxwellMOM for a configuration both codes can run (a flat sheet, a periodic cell) is a regression oracle. It is stored as a literal in a test, not read from the other repository at runtime.

7.3 Milestone map

1. **This slice.** 2D grid, both drivers, PEC cavities, periodic dispersion, invariant (3.6).
2. Volumetric $\varepsilon(\mathbf{r})$, then $\varepsilon(\omega)$: complex permittivity in FDFD, Debye or Lorentz auxiliaries in FDTD. Slab versus Fresnel, cylinder versus 2D Mie. External maps enter only as arrays the law samples.
3. PML from Sec. 3.5, embedded PEC and PMC objects, open-region Mie. Then the 3D cell: a rectangular cavity, then a sphere small enough to factor.
4. Resistive sheet, Sec. 4.3, against the analytic R, T and one MaxwellMOM run.
5. Symmetric GSTC cell, Sec. 6.3, tangential χ first, then χ_{mm}^{nn} and the bianisotropic terms in (6.6).
6. Dipole, Gaussian beam, near-to-far, Bloch phase on the periodic wrap.
7. Profiling, Numba, iterative FDFD, GPU. Spatially varying and spatially dispersive χ after the uniform sheet matches Sec. 6.2.

Acceleration does not change the curls. Numba and CuPy, when they arrive, replace the array update and the sparse matrix-vector product. The direct factorization remains the 2D reference.

References

- [1] K. S. Yee, “Numerical solution of initial boundary value problems involving Maxwell’s equations in isotropic media,” *IEEE Trans. Antennas Propag.*, 1966.
- [2] J. A. Roden and S. D. Gedney, “Convolution PML (CPML): An efficient FDTD implementation of the CFS–PML for arbitrary media,” *Microwave Opt. Technol. Lett.*, 2000.
- [3] T. J. Smy, S. Stewart, and S. Gupta, “Integrated generalized sheet transition conditions in a Yee-cell based FDTD simulation of electromagnetic metasurfaces,” arXiv:1706.10136, 2017.
- [4] Y. Vahabzadeh, N. Chamanara, and C. Caloz, “Generalized sheet transition condition FDTD simulation of metasurface,” arXiv:1701.08760, 2017.