

FUQ-3515 ASI TS Switcher 3 ASI Inputs 2 ASI Outputs 188 TS Packet Format BNC Interface Auto-Failback Manual Switching Broadcast Headend Redundancy Solution



Product Overview

The FUQ-3515 ASI TS Switcher provides 1 main + 2 backup ASI inputs and 2 independent ASI outputs for transport stream redundancy. It performs automatic failback switching based on TS packet integrity monitoring (bitrate/sync/continuity). This 1RU rack-mount unit supports web-based control and firmware upgrades. Ideal for broadcast headend redundancy and cable TV signal backup systems.

Key feature

WEB-based management: Remote control via HTTP/HTTPS with upgrade support

Specifications

Input	3 ASI input: ASI 3 is main stream, ASI 2 is secondary stream (backup 1), ASI 1 is third stream (back up 2)	3 ASI input: ASI 3 is main stream, ASI 2 is secondary stream (backup 1), ASI 1 is third stream (back up 2)
Output	2 ASI output: ASI 4 output bypass, ASI 5 loop out ASI 3	2 ASI output: ASI 4 output bypass, ASI 5 loop out ASI 3
Interface	BNC interface	BNC interface
TS Package Format	188	188
ASI in/out bitrate	1~210Mbps	1~210Mbps
System	language	English/Chinese
System	Remote Control	web-server management (WEB)
System	Upgrade	Web upgrade
General	Size	482mmx410mmx44mm

General	Temprature	0~45■ (working); -20~80 (Storage)
General	Power Supply	110VAC±10%, 50/60Hz 220VAC±10%, 50/60Hz
General	Consumption	15W

ADD: No.10 and NO.12 Wuxing Fourth Road, Wuhou District, Chengdu, Sichuan,
P.R.China ■ICP■17000710■-1

About Us

FMUSER is a company specializing in broadcasting and television transmission systems and integrating hotel IPTV systems. The company was established in 2009 and has served over 180 countries worldwide. More than 20,000 television stations, radio stations, and hotel clients from different.

Contact:Tomleequan Email■sales@fmuser.com whatsapp: [+8613922702227](https://wa.me/8613922702227)