

CONTENT OF SPECTRA DIARY

Program cassette contains the following program:

Main program "DIARY" located at position "002" on your tape counter.

ADDITIONAL EQUIPMENT OR SUPPLIES NEEDED

1. Blank cassette. This is needed for storing your data files so that you will have permanent records of all your entries.
2. Printer (optional). If you would like hard copy records of all your entries, this program will support a printer.

INTRODUCTION

The SpectraVideo's Spectra Diary program is designed to help organize your schedule and planning calendar. With this easy-to-use Spectra Diary program, you can plan in detail your appointments, errands and important days to remember. You can specify detailed plans for any day of your life and have that information available at your fingertips for quick reference, and if you own a printer you can instantly make a permanent copy you can carry with you.

You can also quickly glance at your monthly schedule by reviewing the notes you have left on a monthly calendar page, or by reading the detailed information you have entered for any day of any year (until the year 9999) on the Zoom Page for a specific day.

SPECTRA Diary is another in a series of programs designed for SpectraVideo by Intellisoft Inc. to allow you to quickly and easily use the SV318 or SV-328 computer to make your life a little easier.

GENERAL INSTRUCTIONS

1. Read the booklet that accompanies the SpectraVideo Data Cassette recorder and become familiar with its use. Also read the manual that accompanied your SpectraVideo computer.

2. Hook up the recorder to your SV-318/328 via the permanently attached cable.
3. Hook up your computer to TV or monitor.
4. Insert your Spectra Diary program into the Data Cassette. Rewind tape completely and set the tape counter to zero. Press stop on recorder. Turn on both TV or monitor and computer.

5. When the cursor appears on the screen, type CLOAD (ENTER). This loads the SPECTRA DIARY program into the computer. Press play on tape deck as instructed by computer. After "Found: diary" and then "OK" appear on the screen, type RUN then ENTER.

The following menu will appear:

Do you wish to:
L LOAD
D DISPLAY CALENDAR
E ERASE
S STORE
QUIT-INSTANT-DIARY
B BACK TO BASIC

Here you press the letter of your choice. We will now explain these options to you one by one.

INSTRUCTIONS TO LOAD

If you haven't used the program before, if you would not press L for LOAD. However, if you HAVE used the program before, and have saved the data to a blank cassette (as we will advise you shortly), you must press LAOD if you wish to retrieve the information you stored. Since we haven't yet shown you how to make entries, we will come back to this option later in the booklet.

INSTRUCTION TO DISPLAY A CALENDAR PAGE

1. To display a particular monthly calendar page, press "D" when the menu appears after typing RUN (ENTER). The computer

will then ask you to enter a year. You may enter any year between 1 and 9999. After you enter the year of your choice, press ENTER.

2. The computer will then ask you to enter the number of a month. Any number between one and twelve is accepted. If either the year or the month number you have chosen exceeds these boundaries, you will see the message:

YEAR/MONTH OUT OF RANGE

Your entry will be erased and the computer will await a new response.

3. The computer will then display a calendar page with a heading consisting of the month and year that you have chosen, complete with the days of the week. Each box will have the appropriate date assigned to it. A "X" prompt will appear in box #1. Think of this prompt as the cursor. That is, it tells you where you are located on the screen.

4. You are now ready to position the prompt in a given box to leave a mark on the day(s) you wish to note an event. First use the built-in keyboard joystick or cursor keys to position the prompt in a given box. You may enter the box by pressing the F1 function key, or by pressing the (ENTER) key. When you enter a box, the "X" prompt will disappear and a question mark will assume the first to 10 character positions (two lines) within the box. You may type all 10 characters. Any printable character may be used, except for the graphic characters. If you fill up the box with all 10 characters then the "X" prompt will automatically reappear in its original position in the box. You may choose to exit the box before typing all 10 characters by pressing the F1 function key or the (ENTER) key.

5. Should you enter a box in which characters already exist, and then immediately exit the box, the previous set of characters will remain. Once you enter any one character,

however, your previous set of characters will be erased.

6. After you have made your short note on any particular day as a reminder of things to do (a quick summary, so to speak), you may then enter the "Zoom Page" for that day wherein you can fill in more detail of what you have planned for the day. You may enter the Zoom Page by pressing the F2 function key while you are in the home position of a box where the "X" prompt appears on the monthly calendar page. By pressing the F2 key, a clean page with an allotment of 5 lines each 25 characters in length will appear on the screen. A little figure stands in the first available position. Any printable character may be typed (except the graphic characters). In addition, you may use the (ENTER) key to advance to the next line and the backspace key to erase the previously entered character.

7. When you use up the 5 lines or complete your message, options are then as follows:

- i) To return to the monthly calendar page to the box from which you entered by hitting the F2 key.
- ii) To delete all the information that you have typed in case you make a mistake or change your mind) on the entire Zoom Page by pressing the F3 function key or the DEL key. The prompt will then reappear in the home position.
- iii) To return to the menu by hitting the F4 function key or the ESC key.

(Note: These last two options are also available when you are on the monthly calendar page. That means you may erase an entire box of characters by simply pressing the F3 key or the DEL key. One caution, though: this will automatically cease the zoom entry for that date as well: Should you wish to erase a box entry alone, enter the box by pressing the F1 key and press the space bar.)

8. You may also instruct the computer to provide you with a printed copy of a

SPECTRAVIDEO SOFTWARE AND ACCESSORIES LIMITED 90-DAY WARRANTY

SPECTRAVIDEO warrants to the original purchaser that the SPECTRAVIDEO software is free of defects in material and workmanship for a period of 90 days from the date of purchase. SPECTRAVIDEO agrees to either repair or replace, at its option, free of charge, any software discovered to be defective within the 90-day period, except of the software postage paid, with proof of date of purchase, at its Factory Service Center.

This warranty is limited to the electronic circuitry and mechanical parts originally provided by SPECTRAVIDEO and is not applicable to normal wear and tear. This warranty shall not be applicable and shall be void if the defect in the software has arisen through abuse, unreasonable use, mistreatment or

neglect. This warranty is in lieu of all other express warranties and no other representation or claims of any nature shall be binding on or obligate SPECTRAVIDEO. Any implied warranties applicable to this software are limited to the 90 days period described above. In no event will SPECTRAVIDEO be liable for any special, incidental, or consequential damage resulting from possession, use or malfunction of this software.

Some states do not allow limitations on how long an implied warranty lasts and/or the exclusion or limitation of incidental or consequential damages so the above limitations and/or exclusion or limitation of liability may not apply to you. This warranty gives you specific legal rights, and you may also have other rights which vary from state to state:

SPECTRAVIDEO INC.
P.O. BOX 350
PLAINVIEW, NY 11803

SPECTRA DIARY™

HOME MANAGEMENT & BUSINESS PROGRAM

SD-228T



SPECTRA DIARY™

HOME MANAGEMENT & BUSINESS PROGRAM

SD-228T

Tips on Handling and Storage

1. Avoid touching the tape with your fingers; you may cause drop-outs or scratches.
2. Protect your cassette from dust and damage when not in use by keeping it in its protective plastic box.
3. The tape should be wound snugly on the cassette reels; if the tape is loose, carefully wind it on to one of the reels by gently turning one of the hubs.
4. Keep the recorder head and pinch roller clean by regular use of a good cassette head cleaner.
5. Avoid prolonged exposure of cassettes to excessive heat, sunlight and strong magnetic fields. Do not store near heating appliances, TV sets or similar equipment.
6. To preserve valuable or prized recordings, punch out and remove the erasure prevention lug on the top edge of the cassette.

Copyright © 1983 by SpectraVideo International Ltd. All rights reserved.

Published by
SPECTRAVIDEO INTERNATIONAL LTD.

Second Edition
First Printing 1983
Printed in Hong Kong

Every effort has been made to supply complete and accurate information in this manual. SpectraVideo International Ltd. reserves the right to change Technical Specifications and Characteristics at any time without notice.

No part of this publication may be stored in a retrieval system, transmitted, or reproduced in any way, including photocopying, recording, or by any information storage or retrieval system, without the prior agreement and written permission from SpectraVideo International Ltd.

month of entries (including dates, box entries and zoom page entries) by pressing the F5 function key or the "P" key. (Do this from any home position on your calendar page.) Of course you will need an optional printer interface to do this.

9. You may also instruct the computer to the next monthly calendar page by pressing the "N" key from the home position in any box. Or you may step back a month by pressing the "L" key.

IMPORTANT:

1. If you wish to add new entries to a previously stored set of data, always choose the LOAD option first. This option replaces what is in your computer's memory with whatever you are loading.
2. If you choose the "L" option and press "L", the computer responds with the message "press play" on the recorder. When you do so, and the computer finishes loading, it will return you to the menu page.

INSTRUCTIONS TO ERASE INFORMATION

1. We have assumed that, as time goes by, you may wish to erase an entire block of entries from the computer's memory. To do so, press "E" for the ERASE option when the main menu appears. The computer will respond with the following message:

DELETE ALL ENTRIES UP TO:
YYYYMMDD
?

This allows you to tell the computer the date from which you wish to start your updated list of entries. It must be in the form of YYYYMMDD. For example, 19830123. This means you have chosen the year 1983, the month January (01) and the 23rd day of the month. Should you respond with fewer or more than 8 characters, the computer will remind you of your error and await a new response. Then press (ENTER).

2. When your response is acceptable, the computer checks to see that you actually

intend to begin on that date. If you respond by typing "Y", the computer will erase the earlier entries prior to the specified date and when completed will return you to the main menu. If you type any other character the computer will return you the beginning of the ERASE option.

INSTRUCTIONS TO STORE YOUR DATA

We strongly suggest that you use a blank cassette to store your entries on, rather than your master SPECTRA DIARY tape. This will greatly lessen the possibility of your Spectra Diary program being erased.

1. Remove the cassette tape that contains the Instant Diary program from the recorder and place a new, blank cassette into the recorder.
2. To choose the STORE option from the main menu, you must first have the computer display the main menu. To do so, press the F4 function key. (This will work as long as you are not inside a box on the monthly calendar page. To pop out of a box, first return to the home position inside the box by pressing the F1 key. Then press the F4 key. If you are in a zoom page, simply press the F4 key.)
3. When the main menu appears, press the "S" key. The computer will respond with the message "PRESS RECORD AND PLAY". When you press these two keys on the recorder, the computer will save your data and when it completes this task it will automatically stop the tape and place the main menu back on the screen.
4. Label the cassette tape that you use to store your data so that you will know what information is stored on which tape.

INSTRUCTIONS TO QUIT SPECTRA DIARY

When you are ready to quit the Instant Diary program, press the "Q" key. The computer will then check to see whether you wish to store the data you just typed into the computer. If

you type a "Y", the computer will send you to the STORE option where you simply follow the directions given to you earlier in the booklet. If you type "N", the computer program will immediately end. If you press any other key, the computer will ask you the question again.

INSTRUCTIONS TO ENTER BASIC

To enter BASIC without truly quitting the Instant Diary program, simply press the "B" key. The program and your entries will be put on hold and you'll be free to make the calculations of your choice. DO NOT, however, use the variable (container) names when you wish to return to the program because this will confuse the computer. When you desire to resume using the Instant Diary program type CONT (ENTER). As you probably guessed, CONT is short for continue and you'll be back in Instant Diary.

GENERAL INFORMATION

This program is designed to allow for the greatest number of entries possible, given the allotted memory space in your computer. The computer will inform you when are running out of memory space and will instruct you to return to the main menu and store and/or erase the data you have entered. Or, if you prefer, you may choose to return to a monthly calendar page and delete one or more daily entries. To repeat, you have three options to open up memory space when the computer's memory gets full:

- i) To delete entries individually by pressing the F3 function key or DEL key when in a box on the monthly calendar page.
- ii) To erase a block of entries from the beginning of your entry list by pressing the "E" option on the main menu.
- iii) To store the entire set of entries contained in the computer's memory, and then erase the entire set of entries from the computer's memory after it has been safely stored on a cassette. CAUTION: We have left this erase step up to your discretion when the computer's memory is full. There are situations in which you may wish to store

your entries, though memory space is still available. In such cases, you need not erase any entries.

To open up memory space, you must first erase these entries. If you fail to do so and then begin to enter new entries, you will run out of memory space. You will be entering information at your own risk.

AGAIN NOTE: DO NOT LOAD any data over existing entries in the computer's memory. In other words, STORE and then ERASE THE contents of the computer's memory before LOADING in new data. If you LOAD more information into memory before you have stored and erased all previous information, you will wreck havoc upon the computer's filing system. If you have just turned on your computer and wish to include previously stored information, LOAD first. Or, if you have already entered information into your computer, and now wish to consult a previous set of entries, you must first store your present entries, then erase them and then LOAD. In the interest of providing you with as much memory space as possible we have not included a merging feature.

Through careful and well-planned use of memory, Spectra Diary allows you up to 100 separate dates of entries. (A date of entry consists of the 8-character date with its 10 characters and the 5 lines of text on the zoom page.)

Should you wish to enter this many dates (somewhat over three months worth!), you will be limited to an average of 25 characters per date. Alternatively, should you wish to pack the maximum number of characters per entry date (10 characters in each box plus 125 characters on the zoom page), your allowable number of dates will be 30 – that's a complete month of character-packed entries. So you see, how you devote the computer's memory space is up to you.

You are now ready to use SPECTRA Diary. Keep in mind what we have told you and it will become an invaluable tool for your home and office use.