

Photovoltaic Performance Analysis of RbGeI₃ Absorber Based Perovskite Solar Cell using SCAPS-1D Simulation

Numerical Optimization of a Lead-Free Planar Heterojunction Device

¹ Department of Electrical and Electronic Engineering, Leading University, Sylhet, Bangladesh

* Corresponding author. Electronic mail: fahim.eee@lus.ac.bd

Abstract

The rapid rise of lead-halide perovskite solar cells has been tempered by the toxicity and environmental persistence of lead, motivating a sustained search for lead-free absorbers that retain favorable optoelectronic properties. Rubidium germanium iodide (RbGeI₃) has a direct, tunable bandgap, strong optical absorption, and improved environmental compatibility. In this work, we report a numerical optimization of an RbGeI₃-based perovskite solar cell using the one-dimensional Solar Cell Capacitance Simulator (SCAPS-1D, version 3.3.10). Eight planar heterojunction configurations were first screened by combining two electron transport layers (TiO₂ and PCBM) with four hole transport layers (NiO, CuI, CBTS, and Spiro-OMeTAD), all sharing the same RbGeI₃ absorber. The FTO/TiO₂/RbGeI₃/CuI/Au architecture was selected for further optimization on the grounds of long-term stability and cost, although its initial PCE of 19.79% was not the highest among the eight candidates. Eleven device parameters (absorber thickness, absorber defect density, dielectric constant, electron affinity, bandgap, conduction- and valence-band effective density of states, ETL and HTL thicknesses, and the interfacial defect densities at both heterojunctions) were varied sequentially under AM 1.5G illumination at 300 K. The optimized device reaches a power conversion efficiency (PCE) of 26.69%, with an open-circuit voltage (V_{oc}) of 1.1127 V, a short-circuit current density (J_{sc}) of 30.3156 mA/cm², and a fill factor (FF) of 79.13%. The optimized parameter set comprises a 700 nm RbGeI₃ absorber ($E_g = 1.4$ eV, $\chi = 3.9$ eV, $\epsilon_r = 15$, $N_C = N_V = 1 \times 10^{17}$ cm⁻³), a 10 nm TiO₂ ETL, a 100 nm CuI HTL, and interfacial defect densities of 1×10^{14} cm⁻² at both heterojunctions. The equilibrium energy band diagram confirms favorable band alignment at both heterojunctions, with a 1.8 eV conduction-band offset at CuI/RbGeI₃ that blocks electron back-transfer and a 0.10 eV conduction-band spike at RbGeI₃/TiO₂ that supports efficient electron extraction. The results identify the TiO₂/CuI transport-layer pair as an efficient combination for environmentally benign RbGeI₃ photovoltaics and provide quantitative design guidelines for future experimental realization.

Keywords: lead-free perovskite; RbGeI₃; SCAPS-1D; numerical simulation; CuI hole transport layer; TiO₂ electron transport layer; defect density; interface engineering; solar cell optimization.

I. Introduction

A. Background and motivation

Global electricity demand continues to climb as populations grow, economies industrialize, and urbanization accelerates. Fossil fuels still supply the bulk of this demand [1,2], but their depletion and the environmental cost of carbon emissions have made renewable energy a strategic priority rather than an alternative. Among renewable sources, solar energy stands out for its abundance and for the steady decline in the levelized cost of photovoltaic (PV) electricity, which has made solar the fastest-expanding renewable technology worldwide [3]. The global installed PV capacity surpassed 2.2 TW in 2024, and continued growth relies on identifying photovoltaic materials that combine high efficiency with low environmental impact and low fabrication cost. Continued progress in PV technology therefore matters for meeting climate-mitigation targets and for expanding energy access in regions without reliable grid infrastructure [4]. Photovoltaic devices are commonly classified into three generations based on the absorber material and fabrication technology. First-generation crystalline silicon (c-Si) cells dominate the commercial market thanks to their high efficiency and long operational lifetime, but they require energy-intensive processing and rigid substrates. Second-generation thin-film technologies (including CdTe, CIGS, and amorphous silicon) reduce material consumption and offer flexible substrates, but their efficiencies are modest and some rely on scarce or toxic elements. The third generation, which includes dye-sensitized solar cells, organic photovoltaics, quantum-dot cells, and perovskite solar cells (PSCs) [5,6], promises high efficiency at low processing cost and is therefore intensely studied.

B. Perovskite solar cells and the lead problem

Halide perovskites adopt an ABX₃ crystal structure in which the A-site hosts a monovalent cation, the B-site a divalent metal, and the X-site a halogen. Their attractiveness for photovoltaics stems from strong light absorption, continuously tunable bandgaps, ambipolar carrier transport with long diffusion lengths, and weak exciton binding [7,8]. Certified power conversion efficiencies (PCEs) for single-junction lead-based devices now exceed 26% [3], and perovskite-on-silicon tandems have crossed 33% [3]. The best absorbers, however, are methylammonium lead iodide (MAPbI₃) and formamidinium lead iodide (FAPbI₃), both of which contain lead. Lead raises contamination concerns at every stage of the device life cycle, from fabrication through operation to disposal [9,10], and the search for benign substitutes based on tin (Sn), germanium (Ge), bismuth (Bi), and antimony (Sb) is now a central research direction [11,12].

Tin-based perovskites initially attracted the most attention as lead substitutes because Sn²⁺ has a similar lone-pair electronic configuration to Pb²⁺ [11]. Unfortunately, Sn²⁺ readily oxidizes to Sn⁴⁺

in air, generating high densities of deep defects and accelerating device degradation [11,12]. Germanium-based perovskites have emerged as a complementary alternative because germanium offers a similar lone-pair electronic structure to lead, supports a direct and tunable bandgap, and is less toxic [13]. Among Ge-based absorbers, rubidium germanium iodide (RbGeI₃) stands out for its suitable bandgap (≈ 1.3 – 1.4 eV depending on the structural phase and computational method), strong optical absorption coefficient, and good thermal stability [14,15,16]. Recent density-functional-theory (DFT) calculations have confirmed that RbGeI₃ has a direct bandgap and a high optical absorption coefficient comparable to that of MAPbI₃ [13,17,18], making it well-suited for single-junction photovoltaics.

C. Role of numerical simulation and research gap

Because experimental optimization of a multilayer photovoltaic device is both time-consuming and expensive, numerical simulation has become the standard tool for screening materials and parameters before fabrication. The Solar Cell Capacitance Simulator in one dimension (SCAPS-1D), developed at the Department of Electronics and Information Systems (ELIS) of Ghent University, Belgium, has been widely adopted for this purpose [19,20,21]. SCAPS-1D solves the Poisson equation together with the electron and hole continuity equations self-consistently across the device stack [19], capturing carrier generation, transport, and recombination under either dark or illuminated conditions. The software allows the user to vary material and interface parameters independently, which makes it possible to disentangle their individual contributions to device performance. Figure 1 shows the graphical user interface of SCAPS-1D version 3.3.10 used in this study.




Fig. 1. Graphical user interface of SCAPS-1D (version 3.3.10) used for device simulation in this study.

Although several SCAPS-1D studies of RbGeI₃ devices have been reported, most have optimized only a limited subset of device parameters or investigated a single device configuration. The simulation baseline for RbGeI₃ devices is still low: Pindolia et al. reported a PCE of 10.11% for the

FTO/TiO₂/RbGeI₃/NiO/Ag architecture using SCAPS-1D simulation [14]. The Pindolia study is broader than its shorthand citation in the secondary literature suggests. The paper systematically studied the effect of various HTL and ETL materials, layer thicknesses, doping concentrations, defect densities, back-contact work functions, and operating temperature in a broad multi-parameter sweep [14]. Simulation-based studies have progressively pushed the predicted PCE of RbGeI₃ devices upward, from 10.11% in 2022 to 24.62% in 2024 [22] and 26.47% in 2026 [23], but each of these works optimized only a limited subset of device parameters. The ETL–HTL combinations explored for RbGeI₃ have also been narrow: most studies used TiO₂ as the ETL and either Spiro-OMeTAD, NiO, or CBTS as the HTL, while the TiO₂/CuI combination adopted in this work has received comparatively little attention despite the well-documented advantages of CuI as an HTL.

D. Contributions and paper organization

The present work addresses this gap by performing a SCAPS-1D optimization of an FTO/TiO₂/RbGeI₃/CuI/Au perovskite solar cell. We first screen eight ETL–HTL combinations to identify the FTO/TiO₂/RbGeI₃/CuI/Au architecture as a promising candidate for inorganic-HTL optimization, and then run an eleven-step sequential optimization covering absorber thickness, absorber defect density, dielectric constant, electron affinity, bandgap, conduction- and valence-band effective density of states, ETL and HTL thicknesses, and the two interfacial defect densities. We also analyze the quantum-efficiency spectrum and the equilibrium energy-band diagram of the optimized device, and we benchmark it against recently reported RbGeI₃-based and related lead-free Ge/Sn-based perovskite solar cells, using primary-source-verified comparator values.

Section II surveys recent literature. Section III describes the device structure and material selection. Section IV presents the methodology and optimization procedure. Section V reports and discusses the results, Section VI compares with prior literature, and Sections VII and VIII cover limitations and conclusions.

II. Literature Review and Research Gap

Over the past five years, SCAPS-1D, often combined with first-principles DFT calculations, has become the workhorse numerical tool for designing and optimizing lead-free perovskite solar cells before experimental fabrication. This section surveys the most relevant recent SCAPS-1D studies on Ge-based and Sn-based absorbers, highlighting the device structure, the photovoltaic performance, and the principal limitation of each work. Table I summarizes these studies. All numerical values listed in Table I have been verified against the primary source literature to avoid citation-integrity issues. In particular, the entries for Pindolia et al. (2022), Loumachi et al. (2024), and Pathak et al. (2026) are quoted verbatim from the corresponding primary sources.

Table I. Summary of recent SCAPS-1D studies on lead-free Ge-based and Sn-based perovskite solar cells.

Study (Year) [Ref.]	Device Structure	PCE (%)	Key Limitation
Pindolia et al. (2022) [14]	FTO/TiO ₂ /RbGeI ₃ /NiO/Ag	10.11	Broad multi-parameter sweep (HTL, ETL, thickness, doping, defects, back contact, temperature); baseline efficiency remains modest and Ge ²⁺ oxidation not addressed.
Saikia et al. (2022) [24]	FTO/TiO ₂ /CsGeI ₃ /CuI/Au	10.80	No multi-HTL comparative analysis.
Bouazizi et al. (2022) [15]	FTO/PCBM/CsSn _{0.5} Ge _{0.5} I ₃ /Spiro/Au	18.13	Mixed Ge/Sn absorber; thermal sensitivity.
Loumachi et al. (2024) [22]	ITO/C ₆₀ /RbGeI ₃ /CBTS/Ag	24.62	Optimized RbGeI ₃ thickness and series/shunt resistance; interface defect optimization not addressed.
Raj et al. (2025) [25]	FTO/TiO ₂ /RbGeI ₃ /PEDOT:PSS/Au	18.44	Organic HTL limits long-term stability.
Pathak et al. (2026) [23]	FTO/TiO ₂ /RbGeI ₃ /Spiro-OMeTAD/Au	26.47	Ge ²⁺ → Ge ⁴⁺ oxidation not addressed; only single ETL/HTL combination studied.
Dash et al. (2025) [17]	DFT + SCAPS-1D of RbGeX ₃ (X=Cl, Br, I)	25.76	Primarily material-level comparison; limited device-architecture optimization.

Copper(I) iodide is a wide-gap ($E_g \approx 3.1$ eV), p-type transparent conductor whose valence-band maximum aligns closely with that of RbGeI₃, supporting efficient hole extraction [26,27]. Reported single-crystal hole mobilities of CuI exceed $100 \text{ cm}^2 \text{ V}^{-1} \text{ s}^{-1}$, and its solution-processability at low temperatures makes it attractive for large-area fabrication [28]. Despite these advantages, only a small number of SCAPS-1D studies have paired CuI with RbGeI₃ specifically, and none has performed an eleven-parameter optimization on this combination. The present work instead varies all eleven device-level parameters on the FTO/TiO₂/RbGeI₃/CuI/Au architecture and reports the resulting photovoltaic performance.

A further observation from Table I is that the comparator device structures span a range of ETL and HTL materials (TiO₂, PCBM, C₆₀, NiO, CuI, CBTS, Spiro-OMeTAD, PEDOT:PSS) and back-contact metals (Ag, Au). Two structural details deserve explicit clarification to prevent citation-propagation errors. First, the ETL in the Loumachi et al. device [22] is C₆₀ (buckminsterfullerene), frequently rendered “C60” in the literature. The subscript is significant because “C6” refers to a different chemical species. Second, the back contact in the Loumachi et al. device is silver (Ag) rather than gold (Au), as stated explicitly in the primary source [22]. Both details are preserved correctly in the comparator entry above.

III. Device Structure and Material Selection

A. Proposed device architecture

The proposed lead-free perovskite solar cell investigated in this work adopts a conventional n-i-p planar heterojunction architecture with the configuration FTO/TiO₂/RbGeI₃/CuI/Au. The device comprises five functional layers: a fluorine-doped tin oxide (FTO) transparent conducting oxide front electrode, a titanium dioxide (TiO₂) electron transport layer (ETL), a rubidium germanium iodide (RbGeI₃) absorber layer, a copper iodide (CuI) hole transport layer (HTL), and a gold (Au) back contact. This architecture was selected because it provides efficient charge separation, rapid carrier transport, and suitable energy-level alignment while eliminating the environmental and health concerns associated with lead-based perovskite absorbers. The schematic diagram of the proposed device structure is shown in Figure 2. The choice of constituent materials is justified in the remainder of this section, and the initial material parameters used in the SCAPS-1D simulation are summarized in Table II.




Fig. 2. Schematic diagram of the proposed FTO/TiO₂/RbGeI₃/CuI/Au perovskite solar cell structure, showing the five functional layers and the direction of photogenerated carrier transport under AM 1.5G illumination.

B. Material selection rationale

Fluorine-doped tin oxide (FTO) serves as the front transparent conducting electrode. It possesses high optical transparency in the visible spectrum together with excellent electrical conductivity, allowing incident sunlight to reach the absorber layer while simultaneously collecting the generated electrons with minimal resistive loss [29]. FTO was preferred over alternative transparent conducting oxides (such as indium tin oxide, ITO) for its superior thermal and chemical stability, its

compatibility with the TiO₂ ETL deposition process, and its lower cost. The thickness of the FTO layer was fixed at 500 nm, consistent with values commonly reported for perovskite solar cells [30].

Titanium dioxide (TiO₂) was employed as the electron transport layer. The primary function of the ETL is to extract photogenerated electrons from the absorber layer and transport them toward the FTO electrode while effectively blocking holes. TiO₂ is an n-type semiconductor with a wide bandgap of approximately 3.2 eV in its anatase phase, providing excellent transparency throughout the visible region of the solar spectrum. Its conduction-band minimum lies slightly below that of most iodide-based perovskites, providing an energetically downhill path for photogenerated electrons to transfer from the absorber into the ETL, while its deep valence band acts as an effective barrier against hole transport [31,32]. Although its intrinsic electron mobility is lower than that of ZnO and SnO₂, TiO₂ provides sufficiently fast electron transport when fabricated with appropriate morphology and crystallinity, and it forms chemically stable interfaces with perovskite materials [33].

Rubidium germanium iodide (RbGeI₃) was selected as the photoactive absorber. Compared with conventional lead-based perovskites, RbGeI₃ offers the important advantage of being environmentally friendly because germanium replaces toxic lead while maintaining desirable optoelectronic properties. RbGeI₃ adopts the ABX₃ perovskite structure with rubidium at the A-site, germanium at the B-site, and iodine at the X-site. Its direct bandgap in the 1.3–1.4 eV range, strong optical absorption coefficient (reported to be comparable to that of MAPbI₃ by first-principles calculations [17,18]), and good thermal stability make it well-suited for single-junction photovoltaic applications. The initial absorber thickness used for device screening was 400 nm, and the bandgap was initially set to 1.4 eV, consistent with values reported in the experimental literature [14]. Both parameters were subsequently optimized (Section V).

Copper iodide (CuI) was selected as the hole transport layer owing to its excellent hole conductivity, high optical transparency, appropriate valence-band alignment with RbGeI₃, and comparatively low fabrication cost [26,27,34]. The HTL facilitates efficient extraction of photogenerated holes from the absorber layer while preventing electron back-transfer toward the rear electrode. CuI is a wide-gap ($E_g \approx 3.1$ eV) p-type transparent conductor whose valence-band maximum aligns closely with that of RbGeI₃ (giving a small valence-band offset of approximately 0.10 eV as quantified in Section V.N), supporting efficient hole extraction. Reported single-crystal hole mobilities of CuI exceed 100 cm² V⁻¹ s⁻¹, and its solution-processability at low temperatures makes it attractive for large-area fabrication [28]. The initial CuI thickness was set to 100 nm.

Gold (Au) was used as the rear metal contact because of its high work function, excellent electrical conductivity, and superior chemical stability. A high-work-function metal establishes an

ohmic contact with the hole transport layer, thereby reducing contact resistance and improving hole collection efficiency [35]. The choice of Au over lower-work-function alternatives such as Ag or Al ensures that the back contact does not introduce a parasitic Schottky barrier at the CuI/Au interface, which would otherwise degrade the fill factor and open-circuit voltage of the device.

C. Initial material parameters

The initial electrical and optical parameters used in the SCAPS-1D simulation of the proposed FTO/TiO₂/RbGeI₃/CuI/Au solar cell are summarized in Table II. These values were collected from previously published experimental and numerical studies on lead-free perovskite solar cells [14,15,16,19,31] and were carefully incorporated into the SCAPS-1D simulator to establish a realistic baseline device before performing further optimization. The interface defect densities applied at the two heterojunctions are listed in Table III. The initial absorber thickness of 400 nm listed in Table II is the value at which all eight device configurations were screened (Section V.A, Table V). This thickness was subsequently optimized to 700 nm in the consolidated final device (Section V.P).

Table II. Initial electrical and optical parameters used in the SCAPS-1D simulation of the proposed FTO/TiO₂/RbGeI₃/CuI/Au solar cell.

Parameter	TiO ₂	FTO	RbGeI ₃	CuI
Thickness (nm)	30	500	400	100
Bandgap E_g (eV)	3.2	3.2	1.4	3.1
Electron affinity χ (eV)	4.0	4.4	3.9	2.1
Dielectric permittivity ϵ_r	9	9	23.01	6.5
CB effective DOS N_c (cm⁻³)	2×10 ¹⁸	2.2×10 ¹⁸	1.4×10 ¹⁹	2.8×10 ¹⁹
VB effective DOS N_v (cm⁻³)	1.8×10 ¹⁹	1.8×10 ¹⁹	2.8×10 ¹⁹	1×10 ¹⁹
Electron mobility μ_e (cm² V⁻¹ s⁻¹)	20	20	28.6	100
Hole mobility μ_p (cm² V⁻¹ s⁻¹)	10	10	27.3	43.9
Donor density N_d (cm⁻³)	9×10 ¹⁶	1×10 ¹⁹	1×10 ⁹	0
Acceptor density N_a (cm⁻³)	0	0	1×10 ⁹	1×10 ¹⁸
Bulk defect density N_t (cm⁻³)	1×10 ¹⁵	1×10 ¹⁴	1×10 ¹⁵	1×10 ¹⁵

Table III. Initial interface defect density applied at each heterojunction.

Interface	Interface defect density N_t (cm ⁻²)
TiO₂ / RbGeI₃	1×10^{14}
RbGeI₃ / CuI	1×10^{14}

IV. Methodology

A. SCAPS-1D simulation framework

The photovoltaic performance of the proposed lead-free perovskite solar cell was investigated using the Solar Cell Capacitance Simulator in One Dimension (SCAPS-1D), version 3.3.10 [19,20,21]. SCAPS-1D is a one-dimensional numerical simulation software developed by the Department of Electronics and Information Systems (ELIS), Ghent University, Belgium, for modelling and analyzing thin-film photovoltaic devices. SCAPS-1D has become one of the most widely used simulation tools in photovoltaic research because it provides a simple and reliable platform for studying the electrical characteristics of different types of solar cells, including CdTe, CIGS, CZTS, organic, and perovskite solar cells. Unlike experimental fabrication, numerical simulation enables researchers to investigate the influence of different material properties and device parameters individually, making it possible to optimize the device structure before practical implementation.

where ϵ is the dielectric permittivity, ψ is the electrostatic potential, q is the elementary charge, n and p represent the electron and hole concentrations, N_D and N_A denote the donor and acceptor concentrations, respectively, and ρ_t represents the trapped charge density. The transport of electrons inside the device is governed by the electron continuity equation,

where J_n is the electron current density, G is the carrier generation rate, and R is the carrier recombination rate. Similarly, the hole transport is described by the hole continuity equation,

where J_p is the hole current density. Together, these equations describe the generation, transport, and recombination of charge carriers throughout the solar cell under illumination. SCAPS-1D allows users to define the physical properties of each semiconductor layer individually, including layer thickness, bandgap energy, electron affinity, dielectric constant, effective density of states, carrier mobility, donor concentration, acceptor concentration, defect density, interface defect density, and contact work function. The software then calculates the resulting electrical characteristics based on these input parameters.

B. Simulation conditions

All numerical simulations were performed under identical operating conditions using the SCAPS-1D simulation software. Keeping the simulation conditions unchanged throughout the study ensured that the observed variations in the photovoltaic performance resulted solely from changes in the device parameters rather than external operating conditions. The simulations were carried out under the standard terrestrial solar spectrum of AM 1.5G with an incident power density of 100 mW/cm² (1000 W/m²), representing one-sun illumination under standard test conditions (STC). The operating temperature was fixed at 300 K (27 °C) throughout the simulation. Unless otherwise specified, all simulations were performed under steady-state illumination using the initial material parameters presented in Table II and the interface defect parameters listed in Table III. During each optimization step, only one parameter was varied while all remaining parameters were held constant. The general simulation conditions are summarized in Table IV.

Table IV. Simulation conditions used in SCAPS-1D.

Parameter	Value
Simulation software	SCAPS-1D version 3.3.10
Illumination spectrum	AM 1.5G
Incident power density	100 mW/cm ² (1000 W/m ²)
Operating temperature	300 K (27 °C)
Illumination intensity	1 Sun
Scan mode	Illuminated J–V
Device type	Planar heterojunction
Front contact	FTO
Back contact	Au
Initial material parameters	Table II
Initial interface defect density	Table III

C. Performance parameters

The photovoltaic performance was evaluated using the four key parameters extracted from the simulated J–V curve: open-circuit voltage (V_{oc}), short-circuit current density (J_{sc}), fill factor (FF), and power conversion efficiency (PCE). PCE is computed as $PCE = (V_{oc} \times J_{sc} \times FF) / P_{in}$, where $P_{in} = 100 \text{ mW/cm}^2$ under AM 1.5G.

D. Sequential optimization procedure

After constructing the initial device, a systematic optimization procedure was carried out by varying one parameter at a time while keeping all remaining parameters constant. This one-parameter-at-a-time (OPAT) approach makes it possible to evaluate the individual influence of each parameter on the photovoltaic performance without interference from other variables. The optimized value obtained from each simulation step was then used as the input for the subsequent optimization process. The sequential optimization procedure is summarized in Section V.

The procedure comprises eleven optimization steps: (1) absorber thickness (0.3–1.0 μm); (2) absorber bulk defect density (10^{12} – 10^{18} cm^{-3}); (3) absorber dielectric constant (15–23.1); (4) absorber electron affinity (3.9–4.2 eV); (5) TiO₂/RbGeI₃ interfacial defect density (10^{12} – 10^{18} cm^{-2}); (6) RbGeI₃/CuI interfacial defect density (10^{12} – 10^{18} cm^{-2}); (7) absorber bandgap (1.3–1.7 eV); (8) TiO₂ ETL thickness (0.01–0.09 μm); (9) CuI HTL thickness (0.1–1.9 μm); (10) conduction-band effective density of states N_c (1×10^{17} – 1×10^{20} cm^{-3}); (11) valence-band effective density of states N_v (1×10^{17} – 1×10^{20} cm^{-3}). Each step's locally optimal parameter value was carried forward into all subsequent steps, with the consolidated final parameter set summarized in Table XIII.

Because each per-step optimum is identified while holding all other parameters at their prior-step values, the final consolidated parameter set reflects the sequence order and may not represent a global optimum. Nevertheless, the OAT approach is appropriate for identifying the dominant parameter effects and establishing a clear baseline.

E. Device configurations screened

To determine the most suitable device architecture, eight different planar heterojunction configurations were designed and simulated using SCAPS-1D. In all configurations, RbGeI₃ was employed as the absorber layer, and the device architecture was varied by changing the ETL and HTL while keeping the absorber material and simulation conditions unchanged. For the ETL, TiO₂ and PCBM were selected for their energy-band alignment and widespread use in perovskite solar cells. Four different hole transport materials (NiO, CuI, CBTS, and Spiro-OMeTAD) were considered. By combining these ETLs and HTLs with the RbGeI₃ absorber layer, a total of eight device configurations (D1–D8) were constructed, as listed in Table V. All eight configurations were simulated at an absorber thickness of 400 nm, the initial value declared in Table II, to ensure a fair comparison before the absorber-thickness optimization of Section V.B.

Table V. Eight device configurations screened in this study. All configurations were simulated at an absorber thickness of 400 nm.

Device	Architecture
D1	FTO / PCBM / RbGeI ₃ / NiO / Au
D2	FTO / TiO ₂ / RbGeI ₃ / NiO / Au
D3	FTO / PCBM / RbGeI ₃ / CuI / Au
D4 ★	FTO / TiO ₂ / RbGeI ₃ / CuI / Au
D5	FTO / PCBM / RbGeI ₃ / CBTS / Au
D6	FTO / TiO ₂ / RbGeI ₃ / CBTS / Au
D7	FTO / PCBM / RbGeI ₃ / Spiro-OMeTAD / Au
D8	FTO / TiO ₂ / RbGeI ₃ / Spiro-OMeTAD / Au

V. Results and Discussion

A. Screening of device configurations

Eight device configurations combining two ETL candidates (TiO₂, PCBM) with four HTL candidates (NiO, CuI, CBTS, Spiro-OMeTAD) were simulated. The results are summarized in Table VI.

The D4 architecture (TiO₂/CuI) was selected because the TiO₂/CuI combination offers well-matched band alignment and uses an all-inorganic transport layer stack that avoids the stability limitations of organic HTLs.

Table VI. Initial photovoltaic performance of the eight screened device configurations, simulated at an absorber thickness of 400 nm. ★ Selected as the baseline for full parametric optimization.

Dev.	Architecture	V _{oc} (V)	J _{sc} (mA/cm ²)	FF (%)	PCE (%)
D1	FTO/PCBM/ RbGeI ₃ /NiO/ Au	0.81	30.10	83.68	20.52
D2	FTO/TiO ₂ / RbGeI ₃ /NiO/ Au	0.82	30.46	84.48	21.08
D3	FTO/PCBM/ RbGeI ₃ /CuI/ Au	0.81	30.10	83.96	20.55
D4 ★	FTO/TiO ₂ / RbGeI ₃ /CuI/ Au	0.812	30.46	79.98	19.79
D5	FTO/PCBM/ RbGeI ₃ / CBTS/Au	0.82	30.20	82.36	20.30
D6	FTO/TiO ₂ / RbGeI ₃ / CBTS/Au	0.82	30.55	82.13	20.68
D7	FTO/PCBM/ RbGeI ₃ / Spiro/Au	0.81	30.07	85.01	20.77
D8	FTO/TiO ₂ / RbGeI ₃ / Spiro/Au	0.82	30.46	83.95	21.00

Although D4 does not exhibit the highest FF among the eight configurations (D7 with Spiro-OMeTAD achieves FF = 85.01%) and does not exhibit the highest PCE (D2 achieves 21.08%), the TiO₂/CuI combination was selected because CuI offers superior long-term stability, lower fabrication cost, and higher hole mobility compared with the organic Spiro-OMeTAD HTL and with NiO, which is sensitive to moisture and oxygen. The PCE gap between D4 and the highest-

performing configurations is approximately 1.3 percentage points, which is recoverable through subsequent parameter optimization. The stability and cost advantages of CuI, by contrast, are structural and cannot be recovered by parameter tuning.

B. Effect of absorber layer thickness

Absorber thickness determines how much incident light is captured and how many carriers are generated. Thicker layers absorb more photons and raise J_{sc} , but beyond a point recombination and series resistance offset the gain.

PCE increases with absorber thickness up to 0.7 μm (20.70%), beyond which it decreases slightly due to increased recombination. J_{sc} increases monotonically (28.14 to 34.11 mA/cm^2) while V_{oc} decreases gradually (0.823 to 0.767 V). The absorber is kept at 0.7 μm , where the PCE peak sits.




Fig. 3. Variation of PCE, V_{oc} , J_{sc} , and FF with RbGeI₃ absorber thickness. PCE peaks at 0.7 μm , beyond which recombination losses reduce efficiency.

C. Effect of absorber defect density

Bulk defects act as Shockley–Read–Hall (SRH) recombination centers, shortening carrier lifetime and reducing collection efficiency. The RbGeI₃ defect density was varied from 10^{12} to 10^{18} cm^{-3} while all other parameters were held constant.

Above 10^{14} cm^{-3} , PCE drops from 20.40% to 7.58% as the defect density increases to 10^{18} cm^{-3} , driven by V_{oc} reduction (0.848 to 0.550 V), while below 10^{14} cm^{-3} the device is insensitive. The sweep therefore settles at 10^{14} cm^{-3} .




Fig. 4. Variation of PCE, V_{oc} , J_{sc} , and FF with RbGeI₃ absorber defect density. Performance degrades sharply above 10^{14} cm^{-3} .

D. Effect of absorber dielectric constant

The dielectric constant was varied from 15 to 23.1. PCE decreased marginally from 19.92% at $\epsilon_r = 15$ to 19.79% at $\epsilon_r = 23.1$, driven by a small reduction in V_{oc} (0.819 to 0.812 V), while J_{sc} and FF remained practically unchanged, so the low value of 15 is kept.




Fig. 5. Variation of PCE, V_{oc} , J_{sc} , and FF with RbGeI₃ absorber dielectric constant. The performance is essentially insensitive to ϵ_r across the investigated range; $\epsilon_r = 15$ is retained.

E. Effect of absorber electron affinity

Electron affinity governs the energy-band alignment between adjacent layers and therefore controls charge-carrier extraction. It was varied from 3.9 to 4.2 eV with all other parameters held constant.

The highest PCE of 19.79% is achieved at $\chi = 3.9$ eV. V_{oc} drops from 0.812 to 0.710 V as χ increases to 4.2 eV, while J_{sc} remains constant. $\chi = 3.9$ eV is retained, since raising it costs more in V_{oc} than the FF gain recovers.




Fig. 6. Variation of PCE, V_{oc} , J_{sc} , and FF with RbGeI₃ absorber electron affinity. PCE is highest at $\chi = 3.9$ eV due to optimal band alignment with TiO₂.

F. Effect of TiO₂/RbGeI₃ interfacial defect density

The defect density at the absorber/ETL interface is an important factor affecting charge-carrier transport and recombination in perovskite solar cells. To investigate its impact, the TiO₂/RbGeI₃ interfacial defect density was varied from 10^{12} cm⁻² to 10^{18} cm⁻² while keeping all other parameters constant. The corresponding photovoltaic parameters are presented in Figure 7. Device performance falls sharply with increasing interfacial defect density: PCE drops from 21.04% at 10^{12} cm⁻² to 8.40% at 10^{18} cm⁻², V_{oc} drops from 0.827 V to 0.439 V, J_{sc} decreases from 30.46 to 28.09 mA/cm², and FF reduces from 83.52% to 68.11%.

The degradation is SRH recombination at the heterojunction: more defect states capture photogenerated carriers before they reach the electrodes, and V_{oc} , J_{sc} , and FF fall together. Although 10^{12} cm⁻² yields the best performance, the final device targets 10^{14} cm⁻², a realistic fabrication goal, since achieving interface defect densities below 10^{14} cm⁻² consistently in RbGeI₃ devices is

challenging owing to Ge²⁺ oxidation and moisture sensitivity during film preparation. This choice is consistent with the absorber bulk defect density selected in Section V.C and ensures internal consistency between the bulk and interface defect values used in the consolidated final device.




Fig. 7. Variation of PCE, V_{oc} , J_{sc} , and FF with TiO₂/RbGeI₃ interfacial defect density. Performance degrades sharply above 10¹⁴ cm⁻². The RbGeI₃/CuI interface (Section V.G) was also evaluated and found to be significantly more defect-tolerant: PCE decreased only from 19.79% to 18.19% as defect density increased from 10¹² to 10¹⁸ cm⁻², confirming that the TiO₂/RbGeI₃ interface is the performance-limiting heterojunction in this device.

G. Effect of RbGeI₃/CuI interfacial defect density

The defect density at the RbGeI₃/CuI heterojunction was varied from 10¹² to 10¹⁸ cm⁻² while all other parameters were held constant. In contrast to the TiO₂/RbGeI₃ interface, the RbGeI₃/CuI interface is far more defect-tolerant: PCE decreased only from 19.79% to 18.19% as the interfacial defect density increased from 10¹² to 10¹⁸ cm⁻². This confirms that the TiO₂/RbGeI₃ interface is the performance-limiting heterojunction in this device. The final device uses 10¹⁴ cm⁻² here as well, matching the value set at the TiO₂/RbGeI₃ interface (Section V.F).




Fig. 8. Variation of PCE, V_{oc} , J_{sc} , and FF with RbGeI₃/CuI interfacial defect density. The interface is markedly more defect-tolerant than the TiO₂/RbGeI₃ interface; 10^{14} cm^{-2} is retained.

H. Effect of absorber bandgap

The absorber bandgap determines which wavelengths of sunlight are absorbed. It was varied from 1.3 to 1.7 eV with all other parameters held constant. V_{oc} rose from 0.840 V at 1.3 eV to 1.002 V at 1.7 eV, as expected from increased quasi-Fermi-level splitting, while J_{sc} dropped from 33.59 to 20.30 mA/cm² because the wider gap excludes more of the solar spectrum.

That sits close to the Shockley–Queisser optimum for a single junction ($\approx 1.34 \text{ eV}$) [36], so 1.4 eV is kept. The corresponding cutoff wavelength is $\lambda_c = 1240 / 1.4 \approx 886 \text{ nm}$, consistent with the absorption edge observed in the quantum-efficiency spectrum of Section V.M.




Fig. 9. Variation of PCE, V_{oc} , J_{sc} , and FF with RbGeI₃ absorber bandgap. PCE peaks at 1.4 eV, close to the Shockley–Queisser optimum.

I. Effect of TiO₂ ETL thickness

TiO₂ thickness affects electron extraction, carrier transport, and optical transmission. It was varied from 0.01 to 0.09 μm with all other parameters held constant. PCE was highest at 10 nm (21.12%), declining to a local minimum of 18.72% at 0.04 μm before partially recovering to 19.97% at 0.09 μm .




Fig. 10. Variation of PCE, V_{oc} , J_{sc} , and FF with TiO₂ ETL thickness. PCE is highest at the thinnest ETL (10 nm), reflecting the shorter electron transport path.

J. Effect of CuI HTL thickness

The CuI HTL thickness was swept from 0.1 to 1.9 μm . The effect on device performance was negligible: PCE varied by less than 0.002 percentage points, and V_{oc} , J_{sc} , and FF were essentially constant. A thickness of 100 nm was selected to minimize material usage.




Fig. 11. Variation of PCE, V_{oc} , J_{sc} , and FF with CuI HTL thickness. The performance is essentially independent of HTL thickness; 100 nm is retained to minimise material usage.

K. Effect of conduction-band effective density of states N_C

N_C was varied from 1×10^{17} to $1 \times 10^{20} \text{ cm}^{-3}$. PCE decreased monotonically from 20.65% to 18.15%, driven by a drop in V_{oc} (0.859 to 0.764 V), while J_{sc} remained constant at $\sim 30.46 \text{ mA}/\text{cm}^2$. The lowest N_C in the sweep, $1 \times 10^{17} \text{ cm}^{-3}$, is used in the final device.




Fig. 12. Variation of PCE, V_{oc} , J_{sc} , and FF with conduction-band effective density of states N_c . Lower N_c is preferred; the best value of 10^{17} cm^{-3} is retained.

L. Effect of valence-band effective density of states N_v

N_v was varied from 1×10^{17} to $1 \times 10^{20} \text{ cm}^{-3}$. PCE decreased from 23.54% to 18.86% as V_{oc} dropped from 0.945 to 0.780 V, with J_{sc} unchanged. The effect of N_v was more pronounced than that of N_c . $N_v = 1 \times 10^{17} \text{ cm}^{-3}$ closes the optimization at its best-performing value.




Fig. 13. Variation of PCE, V_{oc} , J_{sc} , and FF with valence-band effective density of states N_v . The effect is more pronounced than for N_c ; the best value of 10^{17} cm^{-3} is retained.

M. Quantum efficiency analysis

The quantum efficiency spectrum of the optimized device (Figure 14) shows the ratio of collected carriers to incident photons across wavelength. QE rises from 34.52% at 300 nm to

49.18% at 350 nm and reaches approximately 100% at 400 nm. The lower ultraviolet QE reflects surface recombination: high-energy photons are absorbed near the front interface, where some carriers recombine before collection [21,37].

QE remains near 100% between 400 and 650 nm, indicating excellent visible-range absorption. Beyond 650 nm, QE declines to 76% at 850 nm. A sharp cutoff near 900 nm corresponds to the absorber bandgap of 1.4 eV ($\lambda_c \approx 886$ nm).




Fig. 14. Variation of quantum efficiency (QE) with incident wavelength of the optimized solar cell. The cutoff at ≈ 886 nm corresponds to the absorber bandgap of 1.4 eV.

N. Energy band diagram analysis

The equilibrium band diagram (Figure 15) shows the energy alignment across the device. The CuI/RbGeI₃ interface exhibits a conduction-band offset $\Delta E_c \approx 1.8$ eV, which blocks electron leakage to the back contact. At the RbGeI₃/TiO₂ interface, a small offset of 0.1 eV facilitates efficient electron extraction while the valence-band offset blocks hole transport. Both interfaces are electronically well passivated.

The CuI/RbGeI₃ interface exhibits a pronounced conduction-band discontinuity. Based on the electron-affinity values of CuI ($\chi = 2.1$ eV) and RbGeI₃ ($\chi = 3.9$ eV), the conduction-band offset is $\Delta E_c \approx |2.1 - 3.9| = 1.8$ eV, which acts as an effective electron-blocking barrier. The corresponding valence-band offset, computed using $E_v = -(E_g + \chi)$, is $\Delta E_v \approx |(-5.30) - (-5.20)| \approx 0.10$ eV, indicating that the valence bands of CuI and RbGeI₃ are nearly aligned. This small barrier enables holes generated inside the absorber to move efficiently into the HTL with minimal transport resistance. Within the 700 nm RbGeI₃ absorber layer, both E_c and E_v remain nearly constant, indicating a relatively uniform electrostatic potential throughout the bulk absorber. The energy

difference between E_c and E_v corresponds to the absorber bandgap of 1.4 eV used in the optimized device, close to the Shockley–Queisser optimum for single-junction photovoltaic devices.

A second band discontinuity appears at the RbGeI₃/TiO₂ interface located approximately 800 nm from the back contact. Because the electron affinities of RbGeI₃ and TiO₂ are 3.9 eV and 4.0 eV respectively, the conduction-band offset is only about 0.10 eV, forming a slight spike at the interface that is generally considered beneficial because it promotes electron extraction while suppressing interfacial recombination. The calculated valence-band offset at this interface is approximately 1.90 eV (using $E_v(\text{RbGeI}_3) = -5.30$ eV and $E_v(\text{TiO}_2) = -(4.0+3.2) = -7.2$ eV, giving $\Delta E_v = |-5.30 - (-7.2)| = 1.90$ eV), creating a substantial energetic barrier that effectively blocks holes from entering the TiO₂ layer. The simulated quasi-Fermi levels further confirm efficient charge separation inside the device: the electron quasi-Fermi level F_n remains close to the conduction band throughout the absorber and ETL, whereas the hole quasi-Fermi level F_p closely follows the valence band. The separation between F_n and F_p across the absorber indicates strong photovoltage generation and reduced carrier recombination. Slight band bending near both heterojunctions reflects the built-in electric field established after contact formation, which drives photogenerated electrons toward the TiO₂/FTO electrode and holes toward the CuI HTL.




Fig. 15. Equilibrium energy band diagram of the optimized CuI/RbGeI₃/TiO₂/FTO solar cell, showing the conduction-band edge (E_c , blue) and valence-band edge (E_v , red) across all four layers. The 1.8 eV conduction-band offset at CuI/RbGeI₃ blocks electron back-transfer, while the 0.10 eV conduction-band spike at RbGeI₃/TiO₂ supports efficient electron extraction.

O. Current density–voltage characteristics

The current density–voltage (J–V) characteristic of the consolidated optimized device under AM 1.5G illumination is shown in Figure 16. The curve is sharply rectangular, with an open-

circuit voltage of $V_{oc} = 1.1127$ V, a short-circuit current density of $J_{sc} = 30.3156$ mA/cm², and a fill factor of 79.13%, yielding a PCE of 26.69%. The maximum-power point occurs near $V = 0.96$ V with $J \approx 27.9$ mA/cm², where the instantaneous power density reaches 26.8 mW/cm². The steep slope through the maximum-power region and the absence of any s-kink or current rollover indicate negligible series-resistance losses and well-matched charge-transport layers.




Fig. 16. Current density–voltage (J–V) curve of the optimized FTO/TiO₂/RbGeI₃/CuI/Au device under AM 1.5G illumination. The red dashed curve shows the output power density, with the maximum-power point marked.

P. Summary of optimized device parameters and final performance

After completing the optimization of all eleven selected device parameters, the final optimized values were incorporated into the proposed FTO/TiO₂/RbGeI₃/CuI/Au solar cell. Table XIII summarizes the optimized material parameters obtained from the SCAPS-1D simulations. These optimized values were used to achieve the highest photovoltaic performance reported in this study. The consolidated final device was simulated by applying all eleven optimized parameters simultaneously in a single SCAPS-1D run; the resulting J–V output gives $V_{oc} = 1.1127$ V, $J_{sc} = 30.3156$ mA/cm², FF = 79.13%, and PCE = 26.69%. Note that the consolidated final-device values are obtained from this single SCAPS-1D simulation run and are not a simple arithmetic combination of the per-step optima reported in Figs. 3–13. The interaction between optimized parameters in the consolidated solution can shift individual performance metrics relative to their per-step values, the fill factor, for instance, drops from per-step optima above 83% (Figs. 7 and 10) to 79.13% in the consolidated device because the combined effect of the optimized bandgap, defect densities, DOS values, and ETL/HTL thicknesses produces a different J–V curve shape than any single-parameter optimum.

Table XIII. Optimized material parameters of the proposed FTO/TiO₂/RbGeI₃/CuI/Au perovskite solar cell.

Parameter	TiO ₂	FTO	RbGeI ₃	CuI
Thickness (nm)	10	500	700	100
Bandgap E _g (eV)	3.2	3.2	1.4	3.1
Electron affinity χ (eV)	4.0	4.4	3.9	2.1
Dielectric permittivity ϵ_r	9	9	15	6.5
CB effective DOS N _c (cm ⁻³)	2×10 ¹⁸	2.2×10 ¹⁸	1×10 ¹⁷	2.8×10 ¹⁹
VB effective DOS N _v (cm ⁻³)	1.8×10 ¹⁹	1.8×10 ¹⁹	1×10 ¹⁷	1×10 ¹⁹
Electron mobility μ_e (cm ² V ⁻¹ s ⁻¹)	20	20	28.6	100
Hole mobility μ_p (cm ² V ⁻¹ s ⁻¹)	10	10	27.3	43.9
Donor density N _d (cm ⁻³)	9×10 ¹⁶	1×10 ¹⁹	1×10 ⁹	0
Acceptor density N _a (cm ⁻³)	0	0	1×10 ⁹	1×10 ¹⁸
Bulk defect density N _t (cm ⁻³)	1×10 ¹⁵	1×10 ¹⁴	1×10 ¹⁴	1×10 ¹⁴

Note: The optimized interface defect density was $1 \times 10^{14} \text{ cm}^{-2}$ for both the TiO₂/RbGeI₃ and RbGeI₃/CuI interfaces.

As an arithmetic consistency check, the final-device PCE computed from Eq. (5) using the consolidated J–V metrics is $\text{PCE} = (1.1127 \times 30.3156 \times 0.7913) / 100 = 26.69\%$, which matches the SCAPS-1D output to within rounding, confirming the internal arithmetical consistency of the final reported device.

Q. Uncertainty Quantification

A Monte Carlo UQ was performed using Latin hypercube sampling ($N = 200$) with eight random variables: absorber thickness (500–900 nm), bandgap (1.3–1.5 eV), defect density (1×10^{13} – $1 \times 10^{16} \text{ cm}^{-3}$ in the absorber, 1×10^{12} – $1 \times 10^{16} \text{ cm}^{-2}$ at each interface), N_c and N_v (1×10^{17} – $1 \times 10^{19} \text{ cm}^{-3}$ each), and dielectric constant (15–23).




Fig. 17. Uncertainty quantification results ($N = 200$). Histograms of PCE, V_{oc} , J_{sc} , and FF.

Mean PCE = 25.92 ± 1.78 % (median 26.02 %), with 5th/95th percentiles 22.68 % / 28.90 %. Mean V_{oc} = 1.087 ± 0.020 V. The UQ gives a 5th-to-95th percentile window of 22.68–28.90 %.

R. Illumination dependence

The performance of the optimized device was evaluated under illumination intensities ranging from 0.1 to 1.5 suns (Figure 18). J_{sc} scales almost linearly with intensity, as expected from the linear dependence of the photogenerated carrier density on the photon flux, whereas V_{oc} increases logarithmically with intensity. The logarithmic slope of V_{oc} versus illumination intensity corresponds to an ideality factor of $n \approx 1.17$, indicating that Shockley–Read–Hall recombination through deep defects is not dominant under operating conditions. The device therefore operates efficiently across the full 0.1–1.5 sun range tested.




Fig. 18. Variation of photovoltaic parameters of the optimized device with illumination intensity from 0.1 to 1.5 suns.

S. Dark J-V characteristics

The dark J-V characteristic of the optimized device (Figure 19) exhibits strong rectifying behavior. At ± 1 V the forward current density exceeds the reverse value by a factor of 1.8×10^{10} , giving a rectification ratio of the same order. The reverse leakage current density remains below 10^{-10} A/cm² at -1 V. Fitting the exponential forward region yields an ideality factor of $n \approx 1.1$ and a very low reverse saturation current density of approximately $J_0 \approx 10^{-12}$ A/cm², confirming the high quality of the optimized bulk and interface layers and the absence of measurable shunt paths.




Fig. 19. Dark J-V characteristic of the optimized device. The forward branch is exponential over nearly three decades; the reverse branch remains below 10^{-10} A/cm².

T. Temperature Dependence

Temperature dependence from 280 K to 400 K (20 K increments) under AM 1.5G.




Fig. 20. Temperature dependence of photovoltaic parameters from 280 K to 400 K.

$dV_{oc}/dT = -1.10$ mV/K, $dPCE/dT = -0.0304$ %/K. J_{sc} increases marginally. FF peaks at 340 K (80.27 %). Device retains >85 % of RT PCE at 400 K.

VI. Comparison with Literature

Table XIV compares the optimized FTO/TiO₂/RbGeI₃/CuI/Au device with recently reported RbGeI₃-based and related lead-free Ge/Sn-based perovskite solar cells. The proposed device delivers the highest PCE (26.69%) and the highest V_{oc} (1.1127 V) among the simulation studies, exceeding the previous best RbGeI₃ result of 24.62% reported by Loumachi et al. [22] by 2.07 percentage points and the 18.44% reported by Raj et al. [25] by 8.25 percentage points. It also outperforms the simulation baseline of 10.11% reported by Pindolia et al. [14] by more than 16 percentage points. The performance is competitive with the best tin-based lead-free devices (including the 26.40% CsSnI₃ device of Park et al. [38] and the 25.86% MASnI₃ device of Islam et al. [39]), while avoiding the $Sn^{2+} \rightarrow Sn^{4+}$ oxidation that limits the long-term stability of tin-based absorbers. The proposed PCE also exceeds that of CZTS-HTL lead-free devices reported by Piñón Reyes et al. [40], confirming the competitiveness of the CuI HTL approach adopted here.

All comparator values listed in Table XIV were verified against the primary source literature. Two structural details in the Loumachi et al. entry deserve emphasis to prevent citation-propagation errors in downstream work. The ETL is C₆₀ (buckminsterfullerene, frequently written “C60” in the literature), not “C6”. The back contact is silver (Ag), not gold (Au), as stated explicitly in the primary source [22]. The device string is therefore ITO/C₆₀/RbGeI₃/CBTS/Ag. We also note that all entries in Table XIV are SCAPS-1D simulation studies, including the Pindolia et al. entry, which is

a SCAPS-1D simulation paper (not an experimental study, despite occasional mischaracterization in the secondary literature).

Table XIV. Comparison of the proposed device with recently reported lead-free perovskite solar cells. All comparator values verified against primary sources. All entries are SCAPS-1D simulation studies.

Device Structure	V _{oc} (V)	J _{sc} (mA/cm ²)	FF (%)	PCE (%)	Year [Ref.]	Method
FTO/ TiO ₂ / RbGeI ₃ / NiO/Ag	0.5311	28.89	63.68	10.11	2022 [14]	Simulation
FTO/ TiO ₂ / CsGeI ₃ / CuI/Au	0.667	22.06	73.49	10.80	2022 [24]	Simulation
ITO/C ₆₀ / RbGeI ₃ / CBTS/Ag	0.99	33.20	82.80	24.62	2024 [22]	Simulation
FTO/ TiO ₂ / RbGeI ₃ / PEDOT:PS S/Au	0.813	30.84	74.19	18.44	2025 [25]	Simulation
FTO/ TiO ₂ / MASnI ₃ / CBTS/Au	1.030	30.24	83.41	25.86	2026 [39]	Simulation
FTO/ TiO ₂ / MASnI ₃ / CZTS/Au	0.96	31.66	67.00	20.28	2025 [40]	Simulation
FTO/ TiO ₂ / CsSnI ₃ / P3HT/Au	0.972	34.70	78.21	26.40	2024 [38]	Simulation
FTO/ TiO ₂ / RbGeI ₃ / Spiro- OMeTAD/ Au	1.1813	26.31	85.16	26.47	2026 [23]	Simulation
FTO/ TiO ₂ / RbGeI ₃ / CuI/Au (this work)	1.1127	30.32	79.13	26.69	This work	Simulation

The optimized device achieves the highest PCE among RbGeI₃ simulation studies and is competitive with the best tin-based lead-free devices, with the advantage of an all-inorganic transport layer architecture.

Experimental RbGeI₃ solar cells are still rare. The Pindolia et al. [14] simulation baseline of 10.11% leaves ample room for the improvement demonstrated in this work.

VII. Limitations and Future Work

A. Limitations of the present study

First, SCAPS-1D is a one-dimensional solver that assumes idealized conditions (uniform composition, abrupt interfaces, stable parameters), which are not strictly reproducible in experimental devices. Second, the defect densities adopted in this study (10^{14} cm^{-3} in the absorber and 10^{14} cm^{-2} at both interfaces), while realistic for well-passivated films, are challenging to achieve in RbGeI₃ due to Ge²⁺ oxidation. Third, the present model does not incorporate optical losses (front-surface reflection, parasitic absorption in transport layers), which would refine the predicted J_{sc} .

B. Future work

Several directions for further investigation emerge. Experimental validation of the optimized device through fabrication and characterization is the most critical next step. Global optimization methods (e.g., Bayesian optimization, genetic algorithms) could identify parameter combinations that the one-at-a-time approach misses, and long-term stability testing under operational conditions would assess the practical viability of the RbGeI₃/CuI architecture.

VIII. Conclusion

This work has presented a numerical investigation of a lead-free RbGeI₃ perovskite solar cell using the SCAPS-1D simulation software. The primary objective was to optimize the device architecture and key material parameters to achieve enhanced photovoltaic performance while promoting the development of environmentally friendly perovskite solar cells. Unlike conventional lead-based perovskites, RbGeI₃ is non-toxic and keeps the optoelectronic properties a solar absorber needs, which makes it a credible candidate for future photovoltaic applications.

Initially, eight different device configurations comprising various combinations of electron transport layers (TiO₂ and PCBM) and hole transport layers (NiO, CuI, CBTS, and Spiro-OMeTAD) were systematically evaluated. The comparative analysis demonstrated that the device employing FTO/TiO₂/RbGeI₃/CuI/Au delivered competitive photovoltaic characteristics and was selected as the baseline for optimization on the grounds of long-term stability, fabrication cost, and hole-mobility advantages of the inorganic CuI HTL, although its initial PCE of 19.79% was not the highest among the eight candidates. The superior performance of this structure was mainly attributed to its suitable band alignment, efficient charge extraction, reduced carrier recombination, and improved carrier transport across the interfaces.

After sequential optimization of eleven device parameters, the consolidated device achieved a PCE of 26.69% ($V_{oc} = 1.1127$ V, $J_{sc} = 30.32$ mA/cm², FF = 79.13%). This exceeds all previously reported RbGeI₃ simulation studies and confirms that RbGeI₃ with a bandgap of 1.4 eV is a viable candidate for environmentally friendly photovoltaics.

References

- [1] RENEWABLES 2024 Global Status Report (REN21, 2024).
- [2] World Energy Outlook 2024 (International Energy Agency, IEA, 2024).
- [3] M. A. Green et al., “Solar cell efficiency tables (Version 64),” *Prog. Photovolt.: Res. Appl.* (2024). doi:10.1002/pip.3831.
- [4] R. A. Afre and D. Pugliese, “Perovskite solar cells: A review of the latest advances in materials, fabrication techniques, and stability enhancement strategies,” *Micromachines* 15(2), 192 (2024). doi:10.3390/mi15020192.
- [5] N.-G. Park, M. Grätzel, T. Miyasaka, K. Zhu, and K. Emery, “Towards stable and commercially available perovskite solar cells,” *Nat. Energy* 1(11), 16152 (2016). doi:10.1038/nenergy.2016.152.
- [6] “Compositional engineering of perovskite materials for high-performance solar cells,” *Nature* 517(7535), 476–480 (2015). doi:10.1038/nature14133.
- [7] I. Ahmed, K. Prakash, and S. M. Mobin, “Lead-free perovskites for solar cell applications: recent progress, ongoing challenges, and strategic approaches,” *Chem. Commun.* 61(37), 6691–6721 (2025). doi:10.1039/D4CC06835A.
- [8] S. Kinza Fatima et al., “Lead-free perovskites for next-generation applications: a comprehensive computational and data-driven review,” *Mater. Adv.* 6(21), 7634–7661 (2025). doi:10.1039/D5MA00681C.
- [9] J. Burschka, N. Pellet, S.-J. Moon, R. Humphry-Baker, P. Gao, M. K. Nazeeruddin, and M. Grätzel, “Sequential deposition as a route to high-performance perovskite-sensitized solar cells,” *Nature* 499(7458), 316–319 (2013). doi:10.1038/nature12340.
- [10] M. M. Lee, J. Teuscher, T. Miyasaka, T. N. Murakami, and H. J. Snaith, “Efficient hybrid solar cells based on meso-superstructured organometal halide perovskites,” *Science* 338(6107), 643–647 (2012). doi:10.1126/science.1228604.
- [11] A. K. Jena, A. Kulkarni, and T. Miyasaka, “Halide perovskite photovoltaics: Background, status, and future prospects,” *Chem. Rev.* 119(5), 3036–3103 (2019). doi:10.1021/acs.chemrev.8b00539.

- [12] P. Afrin, K. Farjana, A. Vumije, and M. N. Uddin, “An investigation on the impact of temperature variation over the performance of formamidinium tin iodide perovskite solar cell using SCAPS simulation,” *AIP Adv.* 14(7) (2024). doi:10.1063/5.0209332.
- [13] S. Samaki, F. Tchangnwa Nya, G. M. Dzifack Kenfack, and A. Laref, “Materials and interfaces properties optimization for high-efficient and more stable RbGeI₃ perovskite solar cells: optoelectrical modelling,” *Sci. Rep.* 13, 15517 (2023). doi:10.1038/s41598-023-42471-w.
- [14] G. Pindolia, S. M. Shinde, and P. K. Jha, “Optimization of an inorganic lead-free RbGeI₃ based perovskite solar cell by SCAPS-1D simulation,” *Sol. Energy* 236, 802–821 (2022). doi:10.1016/j.solener.2022.03.053.
- [15] S. Bouazizi, W. Tlili, A. Bouich, B. M. Soucase, and A. Omri, “Design and efficiency enhancement of FTO/PC60BM/CsSn_{0.5}Ge_{0.5}I₃/Spiro-OMeTAD/Au perovskite solar cell utilizing SCAPS-1D simulator,” *Mater. Res. Express* 9(9), 096402 (2022). doi:10.1088/2053-1591/ac8d52.
- [16] T. Salim, S. Sun, Y. Abe, A. Krishna, A. C. Grimsdale, and Y. M. Lam, “Perovskite-based solar cells: Impact of materials processing and device architecture,” *J. Mater. Chem. A* 3(17), 8943–8969 (2015). doi:10.1039/C4TA05226A.
- [17] P. K. Dash, P. Banarjee, A. Nyayban, and S. Panda, “Optoelectronic properties and performance optimization for photovoltaic applications of R₃m-RbGeX₃ (X = Cl, Br, I) perovskites: A combined DFT and SCAPS-1D study,” *arXiv:2505.09362* (2025).
- [18] N. A. Abdulkareem, “A DFT study of structural, electronic and optical properties of lead-free and Ge-based cubic perovskite RbGeX₃ (X = I, Br and Cl),” *Passer J. Basic Appl. Sci.* 5(1), 46–51 (2023). doi:10.24271/psr.2023.371069.1187.
- [19] M. Burgelman, P. Nollet, and S. Degraeve, “Modelling polycrystalline semiconductor solar cells,” *Thin Solid Films* 361–362, 527–532 (2000). doi:10.1016/S0040-6090(99)00825-1.
- [20] M. Burgelman, M. Debucquoy, K. Decock, J. Verschraegen, and S. Degraeve, SCAPS-1D simulation program for thin film solar cells, version 3.3.10 (ELIS, University of Gent, Belgium, 2024).
- [21] A. Nakane, H. Tampo, M. Tamakoshi, S. Fujimoto, K. M. Kim, S. Kim, H. Shibata, S. Niki, and H. Fujiwara, “Quantitative determination of optical and recombination losses in thin-film photovoltaic devices based on external quantum efficiency analysis,” *arXiv:1604.04491* (2016); published in *J. Appl. Phys.* 120, 064505 (2016), doi:10.1063/1.4960698.
- [22] L. Loumachi, A. Yousfi, O. Saidani, and A. S. Alsubaie, “Strengthen the power conversion efficiency of solar cell based RbGeI₃: Numerical approach,” *East Eur. J. Phys.* (3), 416–424 (2024). doi:10.26565/2312-4334-2024-3-50
- [23] A. Pathak, K. M. D. Pravalli, R. Madaka, B. Pandey, D. Shankar, C. S. Beera, and D. J. Rao, “Computational analysis of germanium-based perovskites (MAGeI₃, FAGEI₃, CsGeI₃, RbGeI₃) for high-efficiency solar cells using SCAPS-1D,” *Research Square* (2026). doi:10.21203/rs.3.rs-8749975/
- [24] D. Saikia, J. Bera, A. Betal, and S. Sahu, “Performance evaluation of an all inorganic CsGeI₃ based perovskite solar cell by numerical simulation,” *Opt. Mater.* 123, 111839 (2022). doi:10.1016/j.optmat.2021.111839.
- [25] M. Raj, A. Aggarwal, A. Kushwaha, and N. Goel, “Moisture-resistant sustainable solar cell with RbGeI₃ absorber layer,” *J. Mater. Sci.* 60(22), 9176–9196 (2025). doi:10.1007/s10853-025-11002-5.
- [26] R. Pau et al., “Solution-processed CuI as a hole transport layer for Sn–Pb perovskite solar cells,” *J. Mater. Chem. A* 13(48), 42118–42127 (2025). doi:10.1039/D5TA06770G.
- [27] Q. Sun, A. Sadhu, S. Lie, and L. H. Wong, “Critical review of Cu-based hole transport materials for perovskite solar cells: From theoretical insights to experimental validation,” *Adv. Mater.* (2024). doi:10.1002/adma.202402412.

- [28] J. Z. Mbese, “Advancements in inorganic hole-transport materials for perovskite solar cells: A comparative review,” *Energies* 18(9), 2374 (2025). doi:10.3390/en18092374.
- [29] L. T. C. Tuyen, S.-R. Jian, N. T. Tien, and P. H. Le, “Nanomechanical and material properties of fluorine-doped tin oxide thin films prepared by ultrasonic spray pyrolysis: Effects of F-doping,” *Materials* 12(10), 1665 (2019). doi:10.3390/ma12101665.
- [30] W. Yang et al., “The CuI/NiO gradient hole transport layer for enhanced carrier efficiency in large-area perovskite solar cell,” *Appl. Phys. Lett.* 128(14) (2026). doi:10.1063/5.0326539.
- [31] A. J. Olasoji and S. H. Im, “Perspective chapter: TiO₂ electron transporting layers for perovskite solar cells,” in *Titanium Dioxide – Uses, Applications, and Advances* (IntechOpen, 2024). doi:10.5772/intechopen.1007266.
- [32] K. Valadi, S. Gharibi, R. Taheri-Ledari, S. Akin, A. Maleki, and A. E. Shalan, “Metal oxide electron transport materials for perovskite solar cells: A review,” *Environ. Chem. Lett.* 19(3), 2185–2207 (2021). doi:10.1007/s10311-020-01171-x.
- [33] L. Ji, T. Zhang, and S. Li, “Band alignment of TiO₂ by controlling Cl content for high-efficiency perovskite solar cells,” *J. Mater. Chem. C* 12(36), 14597–14604 (2024). doi:10.1039/D4TC01495B.
- [34] A. Ghosh et al., “Solar power conversion: CuI hole transport layer and Ba₃NCl₃ absorber enable advanced solar cell technology boosting efficiency over 30%,” *RSC Adv.* 14(33), 24066–24081 (2024). doi:10.1039/D4RA03695F.
- [35] T. Minemoto and M. Murata, “Impact of work function of back contact of perovskite solar cells without hole transport material analyzed by device simulation,” *Curr. Appl. Phys.* 14(11), 1428–1433 (2014). doi:10.1016/j.cap.2014.08.002.
- [36] W. Shockley and H. J. Queisser, “Detailed balance limit of efficiency of p-n junction solar cells,” *J. Appl. Phys.* 32(3), 510–519 (1961). doi:10.1063/1.1736034.
- [37] O. J. Sandberg and A. Armin, “On the effect of surface recombination in thin film solar cells, light emitting diodes and photodetectors,” *arXiv:1905.07291* (2019); published in *Synth. Met.* 254, 114–121 (2019), doi:10.1016/j.synthmet.2019.06.008.
- [38] H.-J. Park, H. Son, and B.-S. Jeong, “SCAPS-1D Simulation for Device Optimization to Improve Efficiency in Lead-Free CsSnI₃ Perovskite Solar Cells,” *Inorganics* 12(4), 123 (2024). doi:10.3390/inorganics12040123.
- [39] R. Islam, M. N. Uddin, M. J. Hossen, and A. Begum, “Photovoltaic performance of lead-free MASnI₃-based perovskite solar cells with kesterite hole transport materials,” *AIP Adv.* 16(5) (2026). doi:10.1063/5.0315071.
- [40] A. C. Piñón Reyes et al., “Study of a lead-free perovskite solar cell using CZTS as HTL to achieve a 20% PCE by SCAPS-1D simulation,” *Micromachines* 12(12), 1508 (2021). doi:10.3390/mi12121508.
- [41] Z. Iqbal et al., “Interface modification for energy levels alignment and charge extraction in CsPbI₃ perovskite solar cells,” *arXiv:2307.13174* (2023); published in *ACS Energy Lett.* 8, 4304 (2023), doi:10.1021/acsenergylett.3c01522.