

Wurlitzer 534 Amplifier. Values here were cross checked with the schematic. Some capacitors are in the PSU (C-27 & C-28) so they are not in the photos.

Quantity	Value (MFD / uF)	Voltage Rating	Type	Item	Image Location	Where	Link	Ordered?	Notes
3x	30/20/20/25	500/400/400/50	Can Multi-Electrolytic	C-25,C-26,C-24	BA,BB, PSUA	2x on Outer Case, 1x on PSU	Possible direct replacement: (http://www.digikey.com)		Replace with below:
	30	500	Electrolytic	C-24A,C-25A,C-26A	A	A	need: 3x		Semi-circle
	20	400	Electrolytic	C-24B,C-25B,C-26B	A	A	need: 3x		Square
	20	400	Electrolytic	C-25C,C-26C	A	A	need: 2x		Triangle
	25	50	Electrolytic	C-24D,C-25D	A	A	need: 2x		No-shape
2x	0.0005	1800	Paper (film)	C-23	BC,BD	V9/V11 pin 9	https://www.digikey.com		link is for smd, wire leads need to be added
4x	0.39	100	Plastic Film	C-20,C-21	BE,BF,BG,BH	Around Loudness pot	https://www.digikey.com		Screwed in between metal plate and case
2x	270 (MMFD / pF) N/A (100?)		Ceramic	C-22	BI,BJ	A/B Treble between 1 & 4	https://www.digikey.com		Voltage rating unknown
1x	0.01	1000	Ceramic	C-16	BK	V7 pin 1&6	https://www.digikey.com		Voltage on schematic is 180v, on cap is 1kv
1x	1	200	Paper (film)	C-17	BL	V7 pin 2 (under c-18)	https://www.digikey.com		
1x	2	50	Paper (film)	C-18	BM	after 1.5M res after V7 pin 2	https://www.digikey.com		bumblebee capacitor: (Orange, White, Red, White, Yellow)
2x	0.0039	200	Paper (film)	C-19	BN,BO	On business pot	https://www.digikey.com		The type I pulled was rated for 200v, not 400v
1x	0.1	400	Paper (film)	C-27	PSUB	In PSU	https://www.digikey.com		
6x	0.047	400	Paper (film)	C-10,C-11,C-12	A,B,C,D,E,G		https://www.digikey.com		
6x	25	25	Electrolytic	C-13,C-2,C-4	F,H,N,O,P,Q		https://www.digikey.com		More exact (expensive) replacement: https://www.digikey.com/en/products/detail/vishay
2x	0.01	400	Paper (film)	C-8	I,J		https://www.digikey.com		
2x	0.1	200	Paper (film)	C-5	K,L		https://www.digikey.com		
1x	20	50	Electrolytic	C-14	M		https://www.digikey.com		
2x	470 (MMFD / pF)		Ceramic	C-9	R,S		https://www.digikey.com		
1x	0.001		Ceramic	C-6	T		https://www.digikey.com		
1x	560 (MMFD / pF)		Ceramic	C-7	U		https://www.digikey.com		
3x	0.01		Ceramic	C-3,C-15	V,W,X		https://www.digikey.com		
2x	270 (MMFD / pF)		Ceramic	C-1	Y,Y2		https://www.digikey.com		
1x	0.0082		Ceramic	C-30	Z		https://www.digikey.com		
1x	0.0047		Ceramic	C-29	ZA		https://www.digikey.com		
7x	4	25	non-polarized	C-28	?	Not sure where, there is no part number either. Maybe it is not used?			

Wurlitzer 2300S Junction Box and Stepper Unit.

Quantity	Value (MFD / uF)	Voltage Rating	Type	Image Location	Where	Link	Ordered?	Notes
1x	0.01		Paper (film)	A	Between 1&2 of wall box	https://www.digikey.com		bumblebee capacitor: (Brown, Black, Orange, White, Yellow)
1x	0.022		Paper (film)	B	service switch, rev. switch, record	https://www.digikey.com		bumblebee capacitor: (Red, Red, Orange, Black, Yellow)
2x	0.1	400	Paper (film)	C,D	wall box pin 2, chassis plug	https://www.digikey.com		
1x	0.1	200	Paper (film)	E	TR3, next to 27 ohm	https://www.digikey.com		
1x	20	50	Electrolytic	F	TR1, next to 51 ohm	https://www.digikey.com		
1x	65-93	50 VAC		G		https://www.digikey.com		AC Capacitor
1x	0.5	400	Paper (film)	H	next to 27 ohm res	https://www.digikey.com		
1x	100	50	Electrolytic	I		https://www.digikey.com		
1x	250	50	Electrolytic	J		https://www.digikey.com		Schematic says 250 MFD, physically says 150... tested and got 250

Links to order all: [https://www.digikey.com](#) (might be dead)

