Based on the document provided, here are the CLI commands extracted and organized step-by-step.

1. Router 1 (R1) - Initial IP Configuration

Cisco CLI

```
enable
configure terminal
hostname R1

interface FastEthernet0/0
 ip address 10.0.0.1 255.0.0.0
 no shutdown
 exit

interface Serial0/0/0
 ip address 100.0.0.1 255.0.0.0
 clock rate 64000
 bandwidth 64
 no shutdown
 exit
```

2. Router 2 (R2) - Initial IP Configuration

Cisco CLI

```
enable
configure terminal
hostname R2

interface FastEthernet0/0
 ip address 192.168.1.1 255.255.255.0
 no shutdown
 exit

interface Serial0/0/0
 ip address 100.0.0.2 255.0.0.0
 no shutdown
 exit
```

3. Configure Dynamic NAT on R1

Step 1: Create Access List (Define traffic to translate)

Cisco CLI

```
access-list 1 permit 10.0.0.10 0.0.0.0
access-list 1 permit 10.0.0.20 0.0.0.0
access-list 1 deny any
```

Step 2: Create NAT Pool (Define available public IPs)

Cisco CLI

```
ip nat pool ccna 50.0.0.1 50.0.0.2 netmask 255.0.0.0
```

Step 3: Map Access List to Pool

Cisco CLI

```
ip nat inside source list 1 pool ccna
```

Step 4: Define Inside and Outside Interfaces

Cisco CLI

```
interface FastEthernet 0/0
 ip nat inside
 exit

interface Serial0/0/0
 ip nat outside
 exit
```

4. Configure Static NAT on R2 (Recap)

Cisco CLI

```
ip nat inside source static 192.168.1.10 200.0.0.10

interface Serial 0/0/0
 ip nat outside
 exit

interface FastEthernet 0/0
 ip nat inside
 exit
```

configure terminal

ip route 50.0.0.0 255.0.0.0 100.0.0.1

end

write memory

5. Configure Static Routing

On Router 1 (R1):

Cisco CLI

```
ip route 200.0.0.0 255.255.255.0 100.0.0.2
```

On Router 2 (R2):

Cisco CLI

```
ip route 50.0.0.0 255.0.0.0 100.0.0.1
```

6. Testing & Verification

Laptop0 (Command Prompt):

DOS

```
ipconfig
ping 200.0.0.10
ping 192.168.1.10
```

Laptop2 (Command Prompt):

(Note: This ping should fail as it is not in the ACL)

DOS

```
ping 200.0.0.10
```

Router 1 (R1 - Verification):

Cisco CLI

```
show ip nat translation
show ip access-lists 1
```