

Date:		cCARD Pinout:		F280039C		HSEC Pinout:			
15Oct2021						2.17			
	HSEC pin	MCU pin	MCU Usage for Std	HSEC cCARD standard	HSEC cCARD standard	MCU Usage for Std	MCU pin	HSEC pin	
Analog	1	-		JTAG-EMU1	JTAG-EMU0		-	2	
	3	TMS	TMS	JTAG-TMS	JTAG-TRSTn		-	4	
	5	TCK	TCK	JTAG-TCK	JTAG-TDO	TDO	GPIO-37/TDO	6	
	7	VSS		GND	JTAG-TDI	TDI	GPIO-35/TDI	8	
	9	A0, B15, C15, DACA_OUT	Analog	ADC1 (and/or DACA)	GND		VSS	10	
	11	A1, B7, DACB_OUT	Analog	ADC1 (and/or DACB)	ADC2	Analog	B3, VDAC	12	
	13	-		GND	ADC2	Analog	B2, C6	14	
	15	A2, B6, C9	Analog	ADC1 (and/or CMPIN+)	GND			16	
	17	A4, B8	Analog	ADC1	ADC2	Analog	B12,C2	18	
	19	VSS		GND	ADC2	Analog	B4, C8	20	
	21	A5	Analog	ADC1 (and/or CMPIN+)	GND		VSS	22	
	23	A6	Analog	ADC1	ADC2	Analog	B11	24	
	25	A10, B1, C10	Analog	ADC (and/or CMPIN+)	ADC2	Analog	B5	26	
	27	A11, B10, C0	Analog	ADC	ADC	Analog	C1	28	
	29	-		GND	ADC	Analog	A8	30	
	31	B0, C11	Analog	ADC	Rsv		-	32	
	33	A7, C3	Analog	ADC	ADC	Analog	A9	34	
	35	VSS		GND	ADC	Analog	A14, B14, C4	36	
	37	A12, C5	Analog	ADC	GND		VSS	38	
	39	A3, B9, C7	Analog	ADC	ADC	Analog	C14	40	
	41	-		Rsv	ADC		-	42	
	43	-		VREFLO	Rsv		-	44	
	45	VREFHIABC *	VREFHI	VREFHI	GND		VSS	46	
	47	VSS		GND	SVO			48	
	Digital	49	GPIO-00	EPWM1_A	PWM1A	PWM3A	EPWM3_A	GPIO-04	50
		51	GPIO-01	EPWM1_B	PWM1B	PWM3B	EPWM3_B	GPIO-05	52
		53	GPIO-02	EPWM2_A	PWM2A	PWMA	EPWM4_A	GPIO-06	54
		55	GPIO-03	EPWM2_B	PWM2B	PWMB	EPWM4_B	GPIO-07	56
57		GPIO-08	EPWM5_A	PWMA	PWMA or TZ1	EPWM7_A	GPIO-12 @	58	
59		GPIO-09	EPWM5_B	PWMB	PWMB or TZ2	EPWM7_B	GPIO-13 @	60	
61		GPIO-10	EPWM6_A	PWMA	PWMA or TZ3	EPWM8_A	GPIO-14	62	
63		GPIO-11 @	EPWM6_B	PWMB	PWMB or TZ4	EPWM8_B	GPIO-15	64	
65				GND	Rsv			66	
67		GPIO-16	SPIA_SIMO	SPISIMO	QEPA or McBSP-MDX	EQEP1_A	GPIO-20	68	
69		GPIO-17	SPIA_SOMI	SPISOMI	QEPB or McBSP-MDR	EQEP1_B	GPIO-21	70	
71		GPIO-18/X2 ##	SPIA_CLK	SPICLK	QEPA or McBSP-MCLKX	EQEP1_STROBE	GPIO-22	72	
73		GPIO-19/X1 ##	SPIA_STE	SPISTE	QEPI or McBSP-MFSX	EQEP1_INDEX	GPIO-23	74	
75		GPIO-24 **	SPIB_SIMO	eCAP or SPISIMO	SCIRX/UARTRX	SC1A_RX	GPIO-28 @	76	
77		GPIO-25 @	SPIB_SOMI	eCAP or SPISOMI	SCITX/UARTTX or ERRORSTS	SC1A_TX	GPIO-29 @	78	
79		GPIO-26 @	SPIB_CLK	eCAP or SPICLK	CANRX	CANA_RX	GPIO-30	80	
81		GPIO-27 @	SPIB_STE	eCAP or SPISTE	CANTX	CANA_TX	GPIO-31	82	
83		VSS		GND	SVO			84	
85		GPIO-32 **	I2CA_SDA	I2CSDA	GPIO	GPIO	GPIO-34	86	
87		GPIO-33	I2CA_SCL	I2CSCL	GPIO	GPIO	GPIO-37/TDO	88	
89		GPIO-40	GPIO	GPIO	GPIO	GPIO	GPIO-35/TDI	90	
91		GPIO-41	GPIO	GPIO	GPIO	GPIO	GPIO-44	92	
93		GPIO-47	GPIO	GPIO	GPIO	GPIO	GPIO-58	94	
95		GPIO-59	GPIO	GPIO	GPIO	GPIO	GPIO-60	96	
97		VSS		GND	SVO			98	
99		GPIO-48	SD1_D1	SD-D	QEPA	EQEP2_A	GPIO-54	100	
101		GPIO-49	SD1_C1	SD-C	QEPB	EQEP2_B	GPIO-55	102	
103		GPIO-50	SD1_D2	SD-D	QEPA	EQEP2_STROBE	GPIO-56	104	
105		GPIO-51	SD1_C2	SD-C	QEPB	EQEP2_INDEX	GPIO-57	106	
107		GPIO-52	SD1_D3	SD-D	GPIO or McBSP-MCLKR	GPIO	GPIO-61	108	
109		GPIO-53	SD1_C3	SD-C	GPIO or McBSP-MFSR			110	
111		VSS		GND	SVO			112	
113				Rsv	Rsv			114	
115				Rsv	Rsv			116	
117				Rsv	Rsv			118	
119		VDDIO	VDDIO	VDDIO	VDD	VDD	VDD	120	
					Device Reset (Active low)	XRSn	XRSn	120	
Digital		121			GPIO	GPIO			122
		123			GPIO	GPIO			124
		125			GPIO	GPIO			126
		127			GPIO	GPIO			128
		129			GPIO	GPIO			130
		131			GPIO	GPIO			132
		133			GPIO	GPIO			134
		135			GND	Rsv			136
		137			GPIO	GPIO			138
		139			GPIO	GPIO			140
		141			GPIO	GPIO			142
		143			GPIO	GPIO			144
		145			GPIO	GPIO			146
		147			GPIO	GPIO			148
		149			GPIO	GPIO			150
		151			GPIO	GPIO			152
		153			GPIO	GPIO			154
		155			GPIO	GPIO			156
		157			GND	SVO			158
		159			GPIO	GPIO			160
161				GPIO	GPIO			162	
163				GPIO	GPIO			164	
165				GPIO	GPIO			166	
167				GPIO	GPIO			168	
169				GPIO	GPIO			170	
171				Rsv	Rsv			172	
173				Rsv	Rsv			174	
175				Rsv	Rsv			176	
177				Rsv	ERRORSTS			178	
179				GND	SVO			180	