Navigation map

Device-first firmware / current source routes. Physical verification is separate.

01 / Connect

No saved Wi-Fi

Not connected > Tap to pair > Wi-Fi setup. App download QR installs the app; Show pairing QR starts Bluetooth provisioning.

Saved Wi-Fi

Wait for association/IP. Recovery offers Set up Wi-Fi or Later; saved credentials remain.

Local Codex link

Wi-Fi ready without a link prepares a code. A saved link searches its PC. BOOT > Options > Connections manages Keep link, Pair again or confirmed Forget.

02 / Dashboard and Options

Counter / carousel

Counter mode defaults On: swipe reset, context and model pages. When Off, the enabled statistics carousel and Muse Home are available.

BOOT / Options pages

1: Connections, Codex stats, Timer. 2: Visible screens, Display, Behavior. 3: Restart device, Factory reset, Quick guide. Behavior > More... > More... contains Counter mode.

About and visibility

System > Memory > Firmware > project QR. Saved changes require confirmed storage. Arrows fade after 10 seconds; reveal before touching again.

03 / Events and local tools

Questions

Open > numbered choice rows > full review > Send. Recipient acknowledgement permits Reply sent. Back, offline and timeout never answer automatically.

Power, timer and sound

PWR toggles standby. Timer keeps running after Back. Authenticated events can wake retained-link standby. Sounds and quiet hours govern optional cues.

Optional voice

Default: no microphone acquisition. The wake-word variant uses Sophia for standby wake; Codex voice capture is separately gated and excluded from that profile.

09 November 2026 / ERRATA	Map page 1: carousel, Options, local tools and recipient delivery.
12 November 2026 / ERRATA	Map page 1: Counter mode, wake-only profile and quiet hours; device verification remains separate.