# Common inductive proximity sensors series - M30 size DC 4 wire

#### Highlights

## Inductive sensor

When the metal conductive objects close to the magnetic field and reach the induction area, high-frequency alternating magnetic field generated by a LC oscillation circuit, which is composed of a coil wound on a ferrite, through the eddy current effect generated by internal of metal objects to achieve non-contact detection.

#### Standards

All inductive proximity sensors conform to IEC 60947-5-2.

#### Housing material


The housing material of sensor including nickel plated copper, also stainless steel and plastic with resistance of compression and temperature rapid change. Most of square sensor is plastic housing. These materials can also be used to produce square sensors with adjustable sensing surface or compact (small square) sensors. Such sensors can be used in the occasions of limited installation space or required large detection range.



Product parameters

#### Features:

- Diameter M30
- Sensing distance: P/N table
- Body material: Nickel plated brass
- Built-in electric protection
- Output: See P/N table
- Connection:
- M12 Connector , 4 pins , Male type • Power supply: 24V DC, 4 wires





Ten meter angled cable (P/N: V5PN-AM12410OF) (available) M12, 4 PIN, Male type, IP67, Straight, Female, Screw connection (P/N: EAM12MC4001A) (available)

**V**<sub>5</sub> Group

 $\epsilon$ 


LECHI	JIC A I	INFORMATION	

INDUCTIVE SPECIFICATION					
	Sensing Distance	See P/N table			
	Correction Factor	Nav-ferrous metal Fe360 Aluminum Brass Copper Stainless Steel Cast Iron Nickel	Factor 1 0.35 ~ 0.45 0.35 ~ 0.5 0.35 ~ 0.45 0.35 ~ 0.45 0.93 ~ 1.05 0.65 ~ 0.75		
	Mounting Non Flush type installation				
	Switching Histeresis	< 10%			
ELECTRICAL DATA					
	Operating Voltage	10~30V DC			
	Switching Frequency	300Hz / 150Hz			
	Voltage Drop	≤ 2.0 V			
	Leakage Current	< 0.01mA			
	Load Current	200 mA			
	No Load Current	≤ 10 mA (24V DC)	10 mA (24V DC)		

	Load Current	200 mA
	No Load Current	≤ 10 mA (24V DC)
	Hysteresis	< 15% (Sr)
	Repeatability	< 1.0% (Sr)
	Temperature Drift	< 1.0% (Sr)
	Short Circuit Protection	Yes
	Overload Protection	Yes
	Polarity Reversal Protection	Yes
ENVIRONMENT DATA		
	Ambient Temperature	-2570 ℃
	Ingress Protection	IP67
MECHANICAL DATA		
	Housing Material	Nickel plated brass
	Face Material	PBT
ELECTRICAL CONNECTION DATA		
	Connector	M12 Connector , 4 pins , Male type
ACCESORIES		
	Cable	Two meter angled cable (P/N: V5PN-AM12402OF) (available)

#### ■ Input/Output circuit

# DC 4 wire PNP - N.O & NC



Cable

### Application


Inductive proximity switch is a low cost method for non-contact detection of metal objects, which is widely used in the following sectors, such as:

- Automotive Industry
- Metallurgical sector
- Machine tool sector - Robot industry
- Conveyor system
- Paper and printing industry
- Mechanical Engineering

#### ■ P/N table

Sensing distance	Sn: 15mm	Sn: 25mm	
4 Wire , PNP, NO+NC	VL1D-NF30P-15NO/NC-SM12	VL1D-NF30P-25NO/NC-SM12	
4 Wire , NPN, NO+NC	VL1D-NF30N-15NO/NC-SM12	VL1D-NF30N-25NO/NC-SM12	

#### Installation



 Sn
 D1
 D2
 D3

 M3015
 ≥22
 ≥60
 ≥30

 M3025
 ≥40
 ≥60
 ≥30

Tightening torque of the fastening

M12 Connector, 4 pin