Welcome Conditions

Time Limit: **1 sec** Memory: **256 MB**

Description

Given two numbers A and B. Print **"Yes"** if A is **greater than or equal to** B. Otherwise print **"No"**.

Input Format

The first line contains T, the number of test cases.
Then, for each test case, a line contains two space-separated integers A and B.

Output Format

Print "Yes" or "No" according to the statement.

Constraints

$1 \le T \le 10$
$1 \le A, B \le 100$

Sample Input 1	Sample Output 1
1 10 9	Yes

int a
int b
test = (a >= b) ? Yes : No;

```cpp
#include <bits/stdc++.h>
using namespace std;

int main(){
    ios_base::sync_with_stdio(false);
    cin.tie(NULL);

    int A, B, T;
    string output;

    cin >> T;
    cin >> A >> B;

    output = (A>=B)? "Yes":"No";

    cout << output;

    return(0);
}
```

Max and Min

Time Limit: **1 sec** Memory: **256 MB**

Description

Given 3 numbers A, B and C, print the **minimum** and the **maximum** numbers.

Input Format

Only one line containing 3 numbers A, B and C.

Output Format

Print the **minimum** number followed by a single space then print the **maximum** number.

Constraints

$-10^5 \le A, B, C \le 10^5$

Sample Input 1	Sample Output 1
1 2 3	1 3

if (A>B && A>C)
{ if B>C → C A
else B A

```cpp
#include<bits/stdc++.h>
using namespace std;

int main(){
    ios_base::sync_with_stdio(false);
    cin.tie(NULL);

    int A, B, C;

    cin >> A >> B >> C;

    if ((A>B)&&(A>C)){
        if (C>B){cout << B << " " << A;}
        else {cout << C << " " << A;}
        }
    else if ((B>A)&&(B>C)){
        if (A>C){
            cout << C << " " << B;
        } else {cout << A << " "  << B;}
    }
    else {
        if (A>B){
            cout << B << " " << C;
        } else {cout << A << " " << C;}
    }
    return(0);

    }
```

Power Of Two

Time Limit: **1 sec** Memory: **256 MB**

Description

Given a number N. Determine whether N is power of 2 or not.

Input Format

Only one line contains a number N.

Output Format

Print "**YES**" if N is power of 2 otherwise, print "**NO**".

Constraints

$1 \le N \le 10^{18}$

Sample Input 1	Sample Output 1
8	YES

For every corresponding pair of bits, it outputs a `1` only if both bits are `1`. Otherwise, it outputs a `0`.

- `1 & 1 = 1`
- `1 & 0 = 0`
- `0 & 1 = 0`
- `0 & 0 = 0`

"&" bitwise and

Imp concept

```cpp
#include <bits/stdc++.h>
using namespace std;
int main(){
    ios_base::sync_with_stdio(false);
    cin.tie(NULL);

    long long N;

    cin >> N;

    if (((N)&(N-1))==0) {cout << "YES";}
    else {cout << "NO";}

    return(0);
}
```

precedence is important