

run-helixqa-androidtv.sh

Revision: 1 **Last modified:** 2026-06-29T13:15:00Z

Overview

Autonomous 4-phase HelixQA campaign for the Android TV app on all connected ADB-reachable TV devices: Setup → Doc-Driven Verification → Curiosity Exploration → Report & Cleanup. Records screen video, captures screenshots, generates a report.

Prerequisites

- catalog-api running and host-reachable (pass `--api-url http://localhost:<port>`).
- ADB-connected Android TV device(s) (leanback/television feature).
- ffmpeg for recording assembly.

Usage

```
./scripts/run-helixqa-androidtv.sh --api-url http://localhost:28080 --timeout 30
```

§11.4.117 pixel-oracle login (2026-06-29 fix)

The TV build is Jetpack-Compose-for-TV; its accessibility hierarchy is EMPTY (uiautomator dump = 0 nodes). The prior login used hierarchy bounds (never found the fields) and verified success by grepping the same empty dump for “Sign In” — which on an empty dump ALWAYS reported “past login” (a §11.4.107(2) PASS-bluff). login_on_device now: - Enters server URL / username / password via fixed coordinates calibrated on the 1920x1080 login screen, submits via the IME ENTER (DONE) action. - VERIFIES login by §11.4.69 sink-side evidence: polls the device okhttp log for a real /api/v1 catalog response. Cannot be faked by a blank UI

dump. The adb reverse now forwards device :8080 to the host's actual API port (parsed from --api-url), so the app's default localhost:8080 reaches the API on :28080.

Edge cases

- Empty Compose hierarchy → pixel-oracle path (above), no hierarchy dependency.
- API on a non-8080 host port → handled via API_PORT extraction + reverse forward.

Related

- scripts/run-helixqa.sh, scripts/run-helixqa-android.sh (phone variant).

Last verified

2026-06-29 — login VERIFIED (sink-side catalog fetch), Phase 2 reached on MIBOX4.