PLM R91 Single Phase Din Rail Energy Meter

Basic Function

- Suit for 110V, 120V, 220V, 230V, 240V AC low voltage system
- Measure U, I, P, Q, S, PF, kWh, kvarh, LCD display U, I, P, kWh
- 6 +1 digits LCD display (999999.9 kWh)
- LED indicates pulse output
- Password protection
- One key for up/down page, one key for programming
- Small size: 100*36*65mm
- RS485 port , MODBUS-RTU or DTL645 protocol (Optional)
- 35mm DIN rail installing, standard DIN ED5002
- Standard: IEC62053-21

Technical Specification

Display	6 +1 digits LCD display (999999.9 kWh)
Accuracy	kWh Class 1.0
Rated voltage	AC 220Vph-N or 120Vph-N (Optional)
	Range: 0.8Un~1.2Un
Rated(Max.) current	5 (63)A
Start current	0.4%Ib
Power consumption	<2W
Frequency	50Hz/ 60Hz (Optional)

Pulse output	1 channels
Communication	RS485 port, MODBUS-RTU and DTL645 communication protocol
	Address: 1~247
	Baud rate: 2400, 4800, 9600bps (Default)
Creeping	Anti-creeping logic design
Dimension (L*W*H)	100*36*65mm
Weight	190g
Environment	Operating temperature: -20℃~ +55 ℃ Storage temperature: -25℃~ +70 ℃ Humidity: 5%~95% non-condensing

Order Information

PLM R91 -- ①-- ②

V1 ***V2***	230Vac (Direct) (Suit for 220, 230, 240Vac ph-N) 110Vac (Direct) (Suit for 110, 120Vac ph-N)
50 ***60***	50Hz 60Hz

Example: Model No. PLM R91-V1-50, which indicate the device provides one RS485, one pulse output, rated input voltage 230Vac, frequency 50Hz, rated current 5(63A).

Note: Communication Protocol default to MODBUS-RTU Protocol , if customer need DTL645 protocol, please mention us when placing order

atandra
measure. protect. conserve

Atandra Energy Private Limited
No. 5, Kumaran Street, Pazhavanthangal, Chennai - 600 114
Tel: +91 44 4278 0700 | 4278 0600
www.atandra.in | energy@atandra.in

Chennai | Coimbatore | Bengaluru | Hyderabad | Vishakapatnam | Mumbai | Pune
Ahmedabad | New Delhi | Madurai | Kochi | Tirupur

OUR DEALER