

Denodo Developer V9.0 for Raspberry Pi - Quickstart

Denodo Developer offers the standard features of the award-winning Denodo Platform 9.0 in an easy-to-use format. It is free to download, fast to deploy, and easy to use. This document will guide you to set up the Raspberry Pi image.

Hardware and Software requirements



- Raspberry Pi 4 or 5 4GB
- 32Gb microSD card
- USB-C Power supply

- Denodo 9 Developer RPI image
- Denodo 9 Developer License

3 Steps activation



Install

- **Read the documentation on the next page**
- Insert the **configured** SD Card in your Raspberry Pi
- Power it up (wait 1 minute)




Connect

- Connect to <http://denodo-pi.local>
- **Alternatively find its IP**
- You should find the landing page



Try Denodo Developer

- Take a tour
- Login: **admin / admin**



Register your Denodo Developer license

- Register and download your **Denodo Developer license**
<https://community.denodo.com/express/download>
- Insert the SD card into your desktop and copy the license file to the following location
/bootfs/denodo/denodo-developer-lic-9.lic

Setting up the WiFi

- On SD card edit **/bootfs/network-config** using your preferred **Linux** text editor. Ensure the encoding is **UTF-8** and ensure line endings are **LF**
- Replace the **<SSID>** and **<Wifi-Password>** with your Wifi network SSID and Password

Advance configuration

- The **Denodo AI-SDK** and **Sample Chatbot** are also installed. To use it you will need to provide **sdk_config.env** and **chabot_config.env** under **/bootfs/denodo/**
- There is also a **PostgreSQL** database install with a data base **denodo**, user/password:
denodo/password
- You can SSH on the box with **denodo/password**

Creating a brand new Denodo-PI SD-Card

You must have a Debian Image for Raspberry PI With Denodo installed. You build this image from the Denodo-PI project from GitHub <https://github.com/vfagesgo/denodo-pi> you can find further instruction to build the image.