

Vibe-IC — All Steps: Phase → Stage → Step (v2.3.0)

Every step of the full flow, organised as **Phase → Stage → Step** with a **single continuous numbering 1 → 43** (starting from Stage 1's Spec-to-RTL). Phase 1's document-generation steps are labelled **D1–D5** (pre-flow, not counted in 1→43); two parallel tracks — **Analog A1–A9** and **Mixed-signal M1–M4** — run alongside.

v2.3.0 highlights (aligned with the industry-standard flow, fixed once before official release):

- **Step 14 moved into Stage 2:** it is the synthesis→PnR handoff QA (the synthesis stage's closing gate), not a physical-design step; marked open-source-Yosys-specific.
- **New Step 28: PERC / Reliability sign-off** — ESD pad-ring + discharge topology, latch-up well-tap, cross-voltage-domain protection; mirrors the industry's standalone Calibre-PERC sign-off deck as an enforced numbered step (old 28–41 renumbered to 29–42).
- **New Step 43: Reliability qualification (HTOL)** — long-duration operating-life qual, distinct from Step 42's burn-in (infant-mortality screen).
- Every step now carries **Input / Output** columns (outputs derive from the flow yaml's `required_outputs`).

Phase → Stage map

- **Phase 1** — Specification & documents: two entries (**Agent path · doc-gen path D1–D5**) + optional architecture-exploration front-ends
 - **Phase 2** — RTL → synthesis: Stage 1 (RTL+verification) · Stage 2 (constraints+synthesis+DFT+handoff gate)
 - **Phase 3** — Physical → Tapeout: Stage 3 (physical+sign-off) · Stage 4 (output+tapeout) · Stage 5 (manufacturing & test)
 - **Parallel** — Analog A1–A9 · Mixed-signal M1–M4
-

Phase 1 — Specification & documents

Two entries; both produce the same L-series design documents that feed Phase 2:

- phase1/input_prompt/ — free text / natural language → **Agent path**
- phase1/input_doc/ — existing documents / structured YAML → **doc-gen path** (D1–D5)

Agent path (free-text input)

Agent	What it does
PM Agent	User-facing: turns natural-language requirements into design facts, asks one plain-language question per gap, hands off once confirmed.
IC Expert Agent	Behind the PM: reviews every layer with silicon expertise, fills sensible defaults, cross-layer consistency checks. Never user-facing.

Flow: user free text → PM Agent → IC Expert Agent → finalised L-series documents.

doc-gen path D1–D5 (existing-document input)

#	Step	What it does	Input	Output
D1	Doc extraction → L1–L13	Ingest prompt/docs into input_doc/ and deterministically extract the core design layers.	user docs / prompt	L1–L13 JSON
D2	Core design-layer docs L1–L13	Deterministic extraction of datasheet, FRS, register map, etc.	D1 plain text	L1_DATASHEET ... L13
D3			L1–L13	

#	Step	What it does	Input	Output
	Extended docs L14–L23	Protocol, timing, power intent (L21), skeletons.		L14–L23 JSON
D4	Protocol-class synthesis	Detect the IC's protocol class (81 classes) and synthesise class facts.	full input text	ic_class + protocol facts
D5	Coverage report	Verify the input documents landed completely in the L docs.	input docs + L docs	parity / coverage report

Architecture-exploration front-ends (optional, feed Step 1)

Front-end	What it does	Input	Output
architecture-explore	Design-space exploration (pipeline depth / parallelism / memory vs PPA, Pareto filter).	L docs + perf targets	architecture decisions (feed Step 1)
hls-c2rtl	C/C++/SystemC → RTL via HLS (open-source XLS, etc.).	C/SystemC model	RTL (verified from Step 2 onward)
SpinalHDL/Chisel front-end	eda_spinalhdl_gen emits Verilog from Scala HDL.	SpinalHDL source	Verilog RTL

Phase 2 — RTL → synthesis

Stage 1 — RTL generation & verification

#	Step	What it does	Input	Output
1	Spec-to-RTL	Author synthesizable RTL from the L-series docs (SoC/CPU classes may take the IP-catalog reuse + glue path).	L1–L23 docs	rtl/ *.v(.sv) · coverage report
2	 Lint (RTL hygiene)	Static RTL style/bug checks; auto-fixable issues fixed first.	RTL	lint reports (hygiene / ROM-init)
3	 CDC / RDC check	Clock-domain / reset-domain crossing safety.	RTL	CDC/RDC reports (crossing / async / reset-dep)
4	 Simulation (testbench + coverage)	Per-IC oracle testbench functional simulation (golden compares) + coverage measurement.	RTL · L10 test cases	sim logs · results.xml · coverage report
5	 Formal verification (assertions)	Prove key properties hold (all_proved requires the .sby + SymbiYosys evidence chain).	RTL · L3 constraints	.sby · formal results · full-stack TB results

#	Step	What it does	Input	Output
6	FPGA early prototype	Pre-synthesis behavioral prototype on FPGA.	RTL · board constraints	.sof · map report · FPGA verification audit

Stage 2 — Constraints, synthesis, DFT & handoff gate

#	Step	What it does	Input	Output
7	Constraint setup (SDC + PVT matrix)	Author timing constraints (SDC) + PVT corner matrix; power intent modelled via L21.	L8 timing · L21 · PDK liberty	*.sdc · pvt_matrix.json
8	 SDC validation	Validate constraint correctness, completeness, and exception (false_path/multicycle) justification.	SDC · L8	SDC check report
9	Synthesis (Yosys → mapped netlist)	Synthesize RTL and technology-map (dfflibmap + abc -liberty) to the standard-cell netlist.	RTL · SDC · liberty	synth/netlist.v · area stats
10	 Pre-layout STA (multi-corner)	Pre-layout static timing analysis (SS/TT/FF).	netlist · SDC · liberty	pre-PnR timing report + summary
11	DFT insertion (scan chain + ATPG)	Insert scan chains + generate patterns	netlist	scan netlist · ATPG coverage report

#	Step	What it does	Input	Output
		(open-source Fault: scan + stuck-at ATPG + TAP; MBIST/LBIST/ compression out of open-source scope).		
12	Post-DFT optimization (resynth / buffering)	Re-optimize timing/area after DFT insertion.	scan netlist	post_dft_netlist.v
13	 Equivalence check (RTL $\equiv$ netlist)	Formally prove gate-level netlist $\equiv$ RTL (LEC).	RTL · post-DFT netlist	LEC report
14	 Synthesis handoff gate (pre-PnR Yosys audit)	Synthesis→PnR handoff QA: synth script + netlist audit (open-source-Yosys specific ; the synthesis stage's closing gate).	synth script · netlist	handoff audit reports

Phase 3 — Physical design → Tapeout

Stage 3 — Physical design & sign-off

#	Step	What it does	Input	Output
15	Floorplan + PDN	Chip floorplan + power delivery network; tapcell insertion	netlist · hardmacro LEFs (pdk_local/ auto-included)	floorplan.def · PDN

#	Step	What it does	Input	Output
		(latch-up well-ties, SKY130 14 μm rule).		
16	Clock planning	Clock-tree distribution strategy.	floorplan	clock_plan.json
17	Placement (global + detailed)	Place standard cells.	floorplan · netlist	placed.def
18	Spare-cell + ECO-prep insertion	Pre-place spare cells / ECO readiness so later fixes are metal-only.	placed.def	spare_cells.json · coverage report
19	CTS (clock tree synthesis)	Build and balance the clock tree.	placed.def · clock plan	post_cts.def · clock-tree report
20	 Post-CTS hold fixing	Repair hold violations after CTS (the runner repeats hold repair post-global-route).	post_cts.def	post_hold.def
21	Routing (global + detailed)	Complete all signal routing.	post_hold.def	routed.def · router DRC report
22	Parasitic extraction (SPEF)	Extract post-route parasitics.	routed.def · tech LEF	SPEF
23	 Post-route STA (multi-corner sign-off)	Sign-off timing with real parasitics (MMMC =	netlist · SPEF · SDC · multi-corner liberty	post-route timing report · per_corner/

#	Step	What it does	Input	Output
		per-corner loop, one report per corner).		
24	 IR drop	Power-grid voltage-drop analysis, PASS/FAIL vs the 5%-of-VDD budget.	routed.def (PSM)	IR report (worst μV + budget verdict)
25	 EM check (electromigration)	Current-density / metal-lifetime screen.	routed.def (PSM - enable_em)	EM report + per-segment currents
26	 Antenna check	Detect + repair process-antenna violations.	routed.def	antenna report
27	 Signal integrity (crosstalk)	Crosstalk/noise screen (SPEF coupling-cap; advisory tier explicitly named).	SPEF	SI report (incl. >0.9 coupling watch-list)
28	 PERC / Reliability sign-off (ESD + latch-up + cross-domain)	(new) Enforced sign-off: ESD pad-ring + discharge topology, latch-up well-tap, cross-voltage-domain protection;	routed.def · step-24–27 reports	perc_equivalent.json · PERC memo · gate verdict

#	Step	What it does	Input	Output
		device-physics sizing stays a named manual-review item.		
29	Post-layout gate-level simulation (SDF)	Gate-level sim with SDF delays to confirm post-layout function (honest SKIP when no SDF re-sim ran).	gate netlist · SDF · TB	post-sim results
30	Post-layout SPICE verification	Transistor-level correlation for critical paths + analog blocks.	SPICE decks · SPEF	SPICE correlation report
31	 Physical verification (DRC + LVS + ERC + density)	Sign-off physical rules incl. per-layer CMP density window; LVS = Magic extraction + real netgen compare.	GDS · gate netlist · PDK decks	sign-off DRC · LVS · ERC reports
32	 ECO (repair loop)	Engineering-change repair loop when sign-off finds issues.	sign-off reports	ECO log or no-ECO flag

Stage 4 — Output & Tapeout

#	Step	What it does	Input	Output
33	Power analysis (post-layout)	Full-chip power sign-off (post-layout vectorless OpenSTA report_power; optional VCD vector mode).	netlist · SDC · liberty (+ optional VCD)	power report (leakage+dynamic, analysis_mode)
34	Metal fill (density fill insertion)	Std-cell-row filler placement (white-space); per-layer metal CMP density screened by Step 31's KLayout deck.	routed.def	filled.def · density report
35	Tapeout checklist (final sign-off)	Item-by-item final confirmation (substance checks: DRC counts, evidence chains).	all sign-off reports	tapeout_checklist.json
36	GDSII output	Stream the foundry-deliverable GDSII (only when Step 31 PV is fully clean).	routed.def · merged GDS	sign-off *.gds
37	Foundry handoff (mask spec + WAT + scribe + corner vectors)	Foundry physical mask kit: mask spec + WAT plan + scribe PCM + corner ATE vectors (chip-specific; foundry-supplied fields named PENDING_FOUNDRY_*).	GDS · netlist stats · L10 cases	mask_spec.json · wat_plan.json · scribe · corner_test_vectors.json
38	FPGA final sign-off (on-board test)	Final FPGA recompile + on-board attestation with hardware evidence.	RTL · board	final .sof · on_board_pass.json

Stage 5 — Manufacturing & test (post-fab; triggers on silicon receipt)

#	Step	What it does	Input	Output
39	Fabrication (foundry, external)	Foundry mask-set + wafer fab (OPC/RET are foundry-side mask synthesis).	foundry handoff kit	mask/wafer intake attestations
40	Wafer sort / probe test	Wafer probing, good-die selection; yield independently re-derived vs target.	wafer lot · probe card	wafer_sort_yield.json · wafer_map.csv
41	Packaging (assembly)	wirebond / FC-CSP / WLCSP assembly.	good dies	packaging_log.json
42	Final test (ATE + burn-in)	Post-package final test (functional + parametric + burn-in infant-mortality screen).	packaged units · ATE patterns	final_test_yield.json · burn_in_results.json
43	Reliability qualification (HTOL / FIT)	(new) Long-duration HTOL qual (device-hours / failures / FIT attestation; required for automotive/medical grades, dormant for	HTOL chamber results	htol_results.json verdict

#	Step	What it does	Input	Output
		consumer MPW).		
		Out-of-flow lab steps (unnumbered): PFA/EFA (destructive FIB/SEM/EMMI failure analysis) and silicon characterization (shmoo) — data originates from external equipment; the plugin owns the data-analytic root-cause layer (wafer_map_pattern_classify, yield-diagnostic).		

Parallel tracks

Analog A1–A9 (parallel to Stages 1–3)

#	Step	What it does	Input	Output
A1	Analog spec extraction	Extract per-block analog specs from the L docs.	L5 ADI spec	spec.json
A2	Topology selection	Choose the circuit topology per spec.	spec.json	topology.md
A3	Netlist generation	Generate the SPICE netlist.	topology · PDK models	<block>.sp
A4	Corner sweep (PVT)	PVT corner sweep + Monte-Carlo yield (mc_yield_pct ≥ 95% gate).	.sp · PDK corner libs	corner_results.json (executed/derived counts)
A5	Analog layout	Complete the analog layout.	netlist	layout.mag / GDS
A6	Block physical verification (per-block DRC + LVS)	Per-block DRC + LVS before merge (catches block-level errors top-	block GDS · netlist	DRC clean / LVS match flags

#	Step	What it does	Input	Output
A7	 Post-layout resimulation	level PV would mask). Re-simulate with extracted parasitics; compare pre-vs-post specs (>10% degradation loops to A3).	layout parasitics · spec	pre_vs_post.json
A8	Hardmacro generation (LEF + Liberty + GDS + Verilog)	Package the block for Stage-3 consumption.	layout · characterisation	4-file hardmacro
A9	 Co-simulation / HW verification	Mixed digital+analog simulation and hardware-in-the-loop verification.	hardmacro · digital RTL	cosim / HW measurement results

Mixed-signal M1–M4 (triggered when analog blocks exist)

#	Step	What it does	Input	Output
M1	Top-level integration (A+D GDS merge)	Merge digital + analog GDS, place macros; run top-level LVS on the merged GDS (Magic extraction + netgen,	digital GDS · hardmacro GDS	top_merged.gds · merge/LVS report

#	Step	What it does	Input	Output
		macros blackboxed).		
M2	Power domain verification (level shifter / isolation)	Structural verification of cross-domain level-shifters / isolation (plus a DEF-level cross-domain sign-off check).	L21 · merged design	power_domain / level_shifter / isolation reports
M3	Mixed-signal verification (AMS co-sim)	AMS co-simulation + interface signal integrity.	merged design · cosim TB	cosim results · interface SI report
M4	Mixed-signal sign-off	Top-level verdict rolled up from M1–M3.	M1–M3 reports	signoff.json

Totals

Phase	Stages	Steps
Phase 1 — Specification & documents	two entries (Agent · doc-gen) + architecture front-ends	D1–D5 + PM Agent · IC Expert Agent
Phase 2 — RTL → synthesis	Stage 1 · Stage 2	1–14
Phase 3 — Physical → Tapeout	Stage 3 · Stage 4 · Stage 5	15–43
Parallel	Analog · Mixed-signal	A1–A9 · M1–M4

43 sequential steps (Stage 1: 1–6 · Stage 2: 7–14 · Stage 3: 15–32 · Stage 4: 33–38 · Stage 5: 39–43), plus Phase 1 (Agent path & doc-gen path D1–D5) and the two parallel tracks (Analog A1–A9 · Mixed-signal M1–M4). Preflight: P0 (environment health check). Orchestrator `vibe_ic_one_shot_runner.py` runs Phase 1 → Phase 2 → Analog → Phase 3.

Out of scope (declined with reasons): OPC/RET (foundry-side), commercial hardware emulators (FPGA path covers the intent), MBIST/LBIST/EDT compression (no open-source engines), PFA/EFA, BSR/BSDL, automatic clock gating (no characterized ICG cell in sky130; manual RTL clock gating remains available), via-doubling/CAA (commercial DFM).

繁體中文版：ALL_STEPS_v2.3.0.zh-TW.md.