

Trainings ▾

Specifications

Starting Motor Circuit:

Maximum resistance:

12-VDC	0.00075 ohm
24-VDC	0.002 ohm

Starting Motor Circuit:

Maximum Voltage Drop:

12-VDC	1.95-VDC
24-VDC	1.7-VDC

Industrial Applications

Unaided Cold Start:

Maximum Ambient Temperature	-12°C [10°F]
Minimum Cranking Speed Required	120 rpm

Generator Drive Applications

Minimum Ambient Temperature for Cold Start With Coolant Heated to Rated Speed	-14°C [7°F]
Minimum Ambient Temperature for Unaided Cold Start to Low Idle Speed	-4°C [25°F]
Minimum Ambient Temperature for NFPA 110 Cold Start (90°F minimum coolant temperature)	0°C [32°F]

Minimum recommended battery capacity:				
System Voltage	Ambient Temperature			
	-18°C [0°F]		0°C [32°F]	
	Cold Cranking Amperes	ReserveCapacit y ¹ Minutes	Cold Cranking Amperes	ReserveCapacit y ¹ Minutes
12-VDC	1800	640	1280	480

System Voltage	Ambient Temperature			
	-18°C [0°F]		0°C [32°F]	
	Cold Cranking Amperes	ReserveCapacity ¹ Minutes	Cold Cranking Amperes	ReserveCapacity ¹ Minutes
24-VDC ²	900	320	640	240
1. The number of plates within a given battery size determines reserve capacity. Reserve capacity determines the length of time that sustained cranking can occur. 2. Cold Cranking Amperes rating are based on two 12-VDC batteries in series.				
A minimum of 6.5 VDC at the power connector is required to power up the ECM.				

Last Modified: 05-Apr-2011
