

Trainings ▾

Specifications

Minimum Recommended Battery Capacity:

System Voltage		Ambient Temperatures		
			-18°C [0°F]	
			Cold Cranking Amperes	Reserve Capacity* Amperes
12 VDC				
	Automotive and Power Generation		1800	540
	Industrial		2700	360
24 VDC**				
	Automotive and Power Generation		900	270
	Industrial		1350	360

* The number of plates within a given battery size determines reserve capacity. Reserve capacity determines the length of time that sustained cranking can occur.

**CCA ratings are based on two 12-VDC batteries in series.

A minimum of 6 VDC at the OEM connector is required to power up the ECM.

Minimum Battery Capacity:

12-VDC Starter 400 ampere-hours to 1800 cold cranking amps @ -18°C [0°F] 24-VDC Starter 200 ampere-hours to 900 cold cranking amps @ -18°C [0°F]

Maximum Starting Circuit Resistance:

12-VDC Starter 0.00075 ohm 24-VDC Starter 0.00200 ohm

Battery Cable Sizes - American Wire Gauge (maximum length in cranking motor circuit):

12-VDC:

No. 00 3.7 m [12 ft] No. 000 4.9 m [16 ft] No. 0000 or Two No. 0* 6.1 m [20 ft] Two No. 00 7.6 m [25 ft]

Battery Cable Sizes - American Wire Gauge (maximum length in cranking motor circuit):

12-VDC High Output:

No. 00 2.1 m [7 ft] No. 000 2.7 m [9 ft] No. 0000 or Two No. 0* 3.7 m [12 ft] Two No. 00 4.3 m [14 ft]

Battery Cable Sizes - American Wire Gauge (maximum length in cranking motor circuit):

24 to 32 VDC:

No. 00 6.1 m [20 ft] No. 000 8.2 m [27 ft] No. 0000 or Two No. 0* 10.7 m [35 ft] Two No. 00 13.7 m [45 ft]

Minimum Ambient Air Temperature without Starting Aid Minimum Cranking Speed without Starting Aid	-1°C [30°F] 130 rpm
---	---------------------

* Two strands of No. 0 cable can be used in place of one No. 0000 cable, provided that connections are carefully made to make sure equal current flow exists in each parallel cable.