Printer Setup Guide

Windows till · receipt printer via QZ Tray

What you need: a Windows computer (the till), the receipt printer with its **USB cable** (or an **Ethernet cable**), and internet.
There are 4 steps: install QZ Tray → install the printer → choose it in the app → test the print.

Step 1 — Install QZ Tray

QZ Tray is the free helper that lets the app talk to the printer. You install it once.

1. Open your browser and go to `qz.io/download`
2. Click the big **Download** button.
3. Open the downloaded file (it looks like `qz-tray-….exe`).
4. Click **Next** → **Next** → **Install/Finish**. If Windows asks for permission, click **Yes**.
5. When the green bar reaches the end and says **completed**, click **Close**.

> ✓ A small **QZ Tray icon** now sits near the clock (bottom-right). Leave it running.
> (Don’t see it? Click the small **^** arrow next to the clock.)

Step 2 — Install the printer in Windows

Option A — USB cable (most common)

1. Plug the USB cable into the printer **and** the PC. Turn the printer **on**.
2. Right-click the **Start** button → **Device Manager**.
3. Expand **Universal Serial Bus controllers**. You should see **“USB Printing Support”**.

   > ✓ This means Windows can see the printer.

   > Nothing appears? Try a different USB port, and make sure the printer is switched on.

4. Now add it as a printer:
   a. **Settings** → **Bluetooth & devices** → **Printers & scanners**.
   b. Click **Add device**, then **“The printer that I want isn’t listed”** (Add manually).
   c. Choose **“Add a local printer or network printer with manual settings”** → Next.
   d. Select **Use an existing port** → pick `USB001` (or `USB002`) → Next.
   e. Manufacturer: **Generic** | Printer: **Generic / Text Only** → Next.
   f. Name it e.g. `POS-80C` → Next → **Finish**.

Option B — Network cable (no driver needed)

1. Plug an **Ethernet cable** from the printer’s LAN port into your router.
2. Power the printer off and on.
3. Print a self-test: turn the printer **off**, hold **FEED**, turn it **on** while holding, release after a few seconds. A slip prints with the **IP address**.
4. You’ll enter that IP in Step 3 (choose **Network** instead of a USB printer).

> ✓ Network printing skips Windows drivers entirely — often the easiest way.

Step 3 — Choose the printer in the app

1. Open the app and log in.

2. Go to **Cashier → Print settings**.
3. Make sure QZ Tray shows **Connected**. If not, click **Connect** (click **Allow** if asked).
4. Click **Refresh printers**.
5. Choose your printer:
   - **USB printer:** pick it from the list (e.g. `POS-80C`).
   - **Network printer:** click **Add printer → Network**, enter the printer's **IP** and port `9100`.
6. Set it as the **till printer**.

Step 4 — Test the print

1. On the Print settings page, click **Test Print**.
2. A small slip should come out of the printer. ✓ **You're done!**

Make it silent (no "Allow" popup every time) — recommended

1. Download the **One-click setup (Windows)** from the app's Print settings page (opens `mrk-till-setup.zip`).
2. Unzip it, then double-click `setup.bat`. Click **Yes** on the Windows admin prompt.
3. Restart QZ Tray when it's done.

Troubleshooting

Problem	Fix
Your printer isn't in the app's list	It isn't installed in Windows yet — do Step 2.
Prints gibberish / random symbols	Wrong driver. Redo Step 2 and choose **Generic / Text Only**.
"Allow / Block" popup on every print	Run `setup.bat` (see above) to trust the MRK certificate.
Nothing prints at all	Check the QZ Tray icon is near the clock, the printer is on, and the app says **Connected**.