



MRK Hotels POS — Cloud Printing Package

What we are adding, why we need it, what you must provide, and the installer's step-by-step guide.

1. The problem we are solving

Receipts are printed on the **Romeson RM80ZJ** till printer. On the client's side this works with the existing E-Zee POS because E-Zee is a **desktop program installed on the same computer (PC-2) the printer is connected to**. It talks directly to the printer's Windows driver.

MRK Hotels POS is a **cloud web application** opened in a browser. Browsers are deliberately blocked from controlling hardware on another machine, and the RM80ZJ uses a **vendor-specific driver** that does not appear as a standard port to the browser. As a result, a browser on any device — including PC-2 itself — cannot drive this printer on its own.

Without a connector	With the MRK connector
Web app in a browser cannot reach the USB printer on another machine.	A small connector program on PC-2 forwards print jobs from the web app to the Windows printer driver — exactly how E-Zee reaches it.

This is the standard approach used by every cloud POS (Square, Loyverse, PushPrinter, Bard): a small local “agent” beside the printer. The connector below is that piece for MRK.

1b. The good news — almost no work for you

Installing the connector is a **few minutes, one time**, and needs **no technical work**: copy one folder, then **right-click a file and choose “Run as administrator”**. There are **no commands to type**, no Command Prompt needed, no new printer driver, and nothing to reconfigure — the connector starts **automatically with Windows** from then on.

What the client/installer does, in short:

- Install **Node.js** once (free; the installer's Next-Next-Finish wizard, ~30 seconds).
- Copy the **printer-bridge** folder onto the printer PC (PC-2).
- **Right-click install-start.bat → Run as administrator**. Done.

Everything else (confirming receipts print correctly and matching the layout to the printer) is handled by us on site.

2. What the MRK connector is

A small, self-contained program (about 36 KB, no installation wizard and no extra dependencies) that runs on PC-2. It is invisible once running and does only two things:

- Listens on the network (**port 9720**) for print jobs sent by the MRK web app.
- Forwards each job to the **Windows default printer** (the RM80ZJ) through its normal driver.

It uses the same Windows driver E-Zee already uses, so the printer requires no new driver. The connector is independent of the browser: it is a background program, not a webpage.

The package contains **eight small files**: the program itself (five files) plus three helper files — **install-start.bat** (one-click install, no typing), **setup-service.bat** (installs the connector to start automatically with Windows) and **uninstall-service.bat** (removes it). The whole package is still tiny (about 45 KB) and needs no extra dependencies.

3. What we need from you (to prepare for a test)

To make printed receipts appear exactly as expected, we require the following before or during an on-site test:

Item	Why we need it
Node.js (LTS) installed on PC-2 (free, from nodejs.org)	Runs the connector program on the printer computer.
The EIGHT package files placed in one folder on PC-2 (e.g. C:\mrk-printer-bridge)	These are the connector program files; we will copy them for you.
The RM80ZJ set as the default printer in Windows	The connector prints to whatever Windows printer is the default (E-Zee likely already set it).
The local IP address of PC-2 (or a Tailscale address for remote printing)	This is the address the web app uses to reach the connector, e.g. http://192.168.1.50:9720 .
Permission to install and to open Windows port 9720 through the firewall	Lets the web app reach the connector over the network.

4. Step-by-step installation on PC-2 (Windows)

These steps are for the installer. Each step is done once; after completion the connector starts automatically every time the computer is switched on — no reconfiguration needed.

Step 1 — Install Node.js (if not already present)

Open a browser on PC-2, go to <https://nodejs.org> and download the **LTS** installer (e.g. node-v20.x.x-x64.msi). Run it and click through the wizard accepting the defaults (roughly 30 seconds). No technical setup needed.

Step 2 — Place the package on PC-2

Copy the **printer-bridge** folder (8 files) to a permanent location on PC-2, for example **C:\mrk-printer-bridge**. This is the connector program.

Step 3 — One click to install (no commands to type)

Find **install-start.bat** inside the folder, **right-click** it and choose **Run as administrator**. It installs the connector to start automatically with Windows and starts it right away. You do not need to open Command Prompt or type anything.

Step 4 — Allow it through the Windows firewall

When Windows asks about allowing access on private networks, tick **Private networks** and click **Allow access**. (If no prompt appears, this step is already satisfied for local use.)

Step 5 — Verify the connector is running

On PC-2, open a browser and visit **http://localhost:9720/health**. You should see a short JSON message starting with **{"ok": true}** confirming the connector is up.

Step 6 — Point MRK at the connector (once, done by us on site)

In MRK, open the cashier panel's **Print Settings** and select **Network printer**. Enter the connector's address: **http://192.168.1.x:9720** (replace **192.168.1.x** with PC-2's local IP address). Save.

Step 7 — Test a print (done by us on site)

Place and settle a test order. The receipt should come out of the RM80ZJ. (We tune the receipt formatting to match the printer exactly during this test.)

5. Honest expectation for the on-site test

Expected to work

To be confirmed on site

The connector fully replaces the browser's missing ability to reach the printer. Because the printer's Windows driver already works (E-Zee uses it), the connector will send jobs to that working driver.

The exact receipt layout on the RM80ZJ (fonts, widths, cutter). Thermal printers interpret ESC/POS slightly differently, so we adjust formatting during the first on-site test. This is formatting, not a connectivity issue.

Bottom line: this connector is the missing middleman that lets the cloud web app print to the RM80ZJ the way E-Zee does. It will be installed once on PC-2 and tested on site to confirm and fine-tune the printed output.

One operating note: receipts print whenever the till computer (PC-2) is turned on and the connector is running — exactly the same requirement E-Zee already has (its app also lives on PC-2). If PC-2 is switched off, no printing happens from any machine. With the auto-start service installed (Step 3), the connector comes back by itself and **nothing needs to be configured or run again** after the PC restarts. If the hotel ever wants printing to work even when that PC is off, the RM80ZJ can later be connected over its LAN port instead of USB — a separate optional change.