

GE23131-Programming Using C-2024

Quiz navigation

[Show one page at a time](#)[Finish review](#)

Status	Finished
Started	Monday, 23 December 2024, 5:33 PM
Completed	Monday, 11 November 2024, 8:56 PM
Duration	41 days 20 hours

Question 1

Correct

Marked out of
3.00[Flag question](#)

Write a program that prints a simple chessboard.

Input format:

The first line contains the number of inputs T.

The lines after that contain a different values for size of the chessboard

Output format:

Print a chessboard of dimensions size * size. Print a Print W for white spaces and B for black spaces.

Input:

Go to Settings to activate Windows.

REC-CIS

Input:

2

3

5

Output:

WBW

BWB

WBW

WBWBW

BWBWB

WBWBW

BWBWB

WBWBW

Answer: (penalty regime: 0 %)

```
1 #include <stdio.h>
2 int main(){
3     int v;
4     scanf("%d", &v);
```

Activate Windows
Go to Settings to activate Windows.

REC-CIS

```
3 int v;  
4 scanf("%d",&v);  
5 while(v>0){  
6     int x;  
7     scanf("%d",&x);  
8     if(x<0){  
9         x=-x;  
10    }  
11    char a='W';  
12    for(int i=0;i<x;i++){  
13        for(int j=0;j<x;j++){  
14            printf("%c",a);  
15            if(a=='W'){  
16                a='B';  
17            }  
18            else{  
19                a='W';  
20            }  
21        }  
22        printf("\n");  
23        if(x%2==0){  
24            if(a=='W'){  
25                a='B';  
26            }  
27            else{  
28                a='W';  
29            }  
30        }  
31    }  
32    v--;  
33 }  
34 }
```

Activate Windows
Go to Settings to activate Windows.

REC-CIS

```
26         }  
27     else{  
28         a='W';  
29     }  
30 }  
31 }  
32 v--;  
33 }  
34 }
```

	Input	Expected	Got	
✓	2	WBW	WBW	✓
	3	BWB	BWB	
	5	WBW	WBW	
		WBWBW	WBWBW	
		BWBWB	BWBWB	
		WBWBW	WBWBW	
		BWBWB	BWBWB	
		WBWBW	WBWBW	

Passed all tests! ✓

Question 2
Correct

Let's print a chessboard!

Activate Windows
Go to Settings to activate Windows.

REC-CIS

Correct

Marked out of
5.00 Flag question

Write a program that takes input:

The first line contains T , the number of test cases

Each test case contains an integer N and also the starting character of the chessboard

Output Format

Print the chessboard as per the given examples

Sample Input / Output

Input:

2

2 W

3 B

Output:

Activate Windows
Go to Settings to activate Windows.

REC-CIS

Answer: (penalty regime: 0 %)

```
1 #include <stdio.h>
2 int main(){
3     int v;
4     scanf("%d",&v);
5     while(v!=0){
6         char a;
7         int x;
8         scanf("%d %c",&x,&a);
9         for(int i=0;i<x;i++){
10             for(int j=0;j<x;j++){
11                 printf("%c",a);
12                 if(a=='W'){
13                     a='B';
14                 }
15                 else{
16                     a='W';
17                 }
18             }
19             if((x%2)==0){
20                 if(a=='W'){
21                     a='B';
22                 }
23                 else{
24                     a='W';
25                 }
26             }
27             printf("\n");
28         }
29         v--;
30     }
31     return 0;
32 }
```

Activate Windows
Go to Settings to activate Windows.

REC-CIS

```
21         d = B ;
22     }
23     else{
24         a='W';
25     }
26 }
27 printf("\n");
28 }
29 v--;
30 }
31 return 0;
32 }
```

	Input	Expected	Got	
✓	2	WB	WB	✓
	2 W	BW	BW	
	3 B	BWB	BWB	
		WBW	WBW	
		BWB	BWB	

Passed all tests! ✓

Question 3

Correct

Marked out of

Decode the logic and print the Pattern that corresponds to given input.

Activate Windows

Go to Settings to activate Windows.

Question **3**

Correct

Marked out of
7.00

[Flag question](#)

Decode the logic and print the Pattern that corresponds to given input.

If N= 3

then pattern will be :

10203010011012

**4050809

****607

If N= 4, then pattern will be:

1020304017018019020

**50607014015016

****809012013

*****10011

Constraints

Activate Windows
Go to Settings to activate Windows.

REC-CIS

 $2 \leq N \leq 100$

Input Format

First line contains T, the number of test cases

Each test case contains a single integer N

Output

First line print Case #i where i is the test case number

In the subsequent line, print the pattern

Test Case 1

3

3

4

5

Output

Activate Windows
Go to Settings to activate Windows.

REC-CIS

Output

Case #1

10203010011012

**4050809

****607

Case #2

1020304017018019020

**50607014015016

****809012013

*****10011

Case #3

102030405026027028029030

**6070809022023024025

****10011012019020021

*****13014017018

*****15016

Answer: (penalty regime: 0 %)

Activate Windows

```
1 #include <stdio.h>
2 int main(){
```

REC-CIS

```
2. int main(){
3.     int v,c=0;
4.     scanf("%d",&v);
5.     while(v!=0){
6.         c++;
7.         int a;
8.         scanf("%d",&a);
9.         int s1=10,s2=(a*a*10)+10;
10.        printf("Case #d\n",c);
11.        for(int i=0;i<a;i++){
12.            for(int j=0;j<i;j++){
13.                printf("***");
14.            }
15.            for(int j=0;j<a-i;j++){
16.                printf("%d",s1);
17.                s1+=10;
18.            }
19.            for(int j=0;j<a-i;j++){
20.                if((j+1)==(a-i)){
21.                    printf("%d",((s2+(j*10))/10));
22.                }
23.                else{
24.                    printf("%d", (s2+(j*10)));
25.                }
26.            }
27.            s2--(a-i)*10;
28.            s2+=10;
29.            printf("\n");
30.        }
31.        v--;
32.    }
33.    return 0;
34. }
35. }
```

Activate Windows
Go to Settings to activate Windows.

REC-CIS

	Input	Expected	Got	
✓	3	Case #1	Case #1	✓
	3	10203010011012	10203010011012	
	4	**4050809	**4050809	
	5	****607	****607	
		Case #2	Case #2	
		1020304017018019020	1020304017018019020	
		**50607014015016	**50607014015016	
		****809012013	****809012013	
		*****10011	*****10011	
		Case #3	Case #3	
		102030405026027028029030	102030405026027028029030	
		**6070809022023024025	**6070809022023024025	
		****10011012019020021	****10011012019020021	
		*****13014017018	*****13014017018	
		*****15016	*****15016	

Passed all tests! ✓

Activate Windows
Go to Settings to activate Windows.

Finish review

GE23131-Programming Using C-2024

Quiz navigation

[Show one page at a time](#)[Finish review](#)

Status	Finished
Started	Monday, 23 December 2024, 5:33 PM
Completed	Tuesday, 19 November 2024, 6:32 PM
Duration	33 days 23 hours

Question 1

Correct

Marked out of 3.00

[Flag question](#)

The k -digit number N is an Armstrong number if and only if the k -th power of each digit sums to N .

Given a positive integer N , return true if and only if it is an Armstrong number.

Example 1:

Input:

153

Output:

Activate Windows
Go to Settings to activate Windows.

REC-CIS

true

Explanation:

153 is a 3-digit number, and $153 = 1^3 + 5^3 + 3^3$.

Example 2:

Input:

123

Output:

false

Explanation:

123 is a 3-digit number, and $123 \neq 1^3 + 2^3 + 3^3 = 36$.

Activate Windows
Go to Settings to activate Windows.



Type here to search



REC-CIS

```
1 #include<stdio.h>
2 int main(){
3     int a,b=0,c,e=0;
4     scanf("%d",&a);
5     if(a<0){
6         a=-a;
7     }
8     c=a;
9     while(c!=0){
10         c/=10;
11         e++;
12     }
13     c=a;
14     while(c!=0){
15         int d=c%10;
16         int f=1;
17         for(int i=0;i<e;i++){
18             f*=d;
19         }
20         b+=f;
21         c/=10;
22     }
23
24
25
26     if(a==b){
27         printf("true");
28     }
29     else{
30         printf("false");
31     }
32 }
33 }
```

Activate Windows
Go to Settings to activate Windows.

REC-CIS

```
12
13     }
14     c=a;
15     while(c!=0){
16         int d=c%10;
17         int f=1;
18         for(int i=0;i<e;i++){
19             f*=d;
20         }
21         b+=f;
22         c/=10;
23
24     }
25
26     if(a==b){
27         printf("true");
28     }
29     }
30     else{
31         printf("false");
32     }
33 }
```

	Input	Expected	Got	
✓	153	true	true	✓
✓	123	false	false	✓

Passed all tests! ✓

Activate Windows
Go to Settings to activate Windows.

Passed all tests! ✓

Question 2

Correct

Marked out of 5.00

Flag question

Take a number, reverse it and add it to the original number until the obtained number is a palindrome. Constraints $1 \leq \text{num} \leq 99999999$ Sample Input 1 32 Sample Output 1 55 Sample Input 2 789 Sample Output 2 66066

Answer: (penalty regime: 0 %)

```
1 #include<stdio.h>
2 int main(){
3     int rn,n,nt=0,i=0;
4     scanf("%d",&n);
5     do{
6         nt=n;
7         rn=0;
8         while(n!=0){
9             rn=rn*10+n%10;
10            n=n/10;
11        }
12        n=nt+rn;
13        i++;
14    }
15    while(rn!=nt || i==1);
16    printf("%d",rn);
17    return 0;
18 }
19 }
```

Activate Windows
Go to Settings to activate Windows.

REC-CIS

```
1 // C program to calculate the reverse of a number
2 int main(){
3     int rn,n,nt=0,i=0;
4     scanf("%d",&n);
5     do{
6         nt=n;
7         rn=0;
8         while(n!=0){
9             rn=rn*10+n%10;
10            n=n/10;
11        }
12        n=nt+rn;
13        i++;
14    }
15    while(rn!=nt || i==1);
16    printf("%d",rn);
17    return 0;
18 }
19 }
```

	Input	Expected	Got	
✓	32	55	55	✓
✓	789	66066	66066	✓

Passed all tests! ✓

Activate Windows
Go to Settings to activate Windows.

Question 3

Correct

Marked out of
7.00

Flag question

A number is considered lucky if it contains either 3 or 4 or 3 and 4 both in it. Write a program to print the nth lucky number. Example, 1st lucky number is 3, and 2nd lucky number is 4 and 3rd lucky number is 33 and 4th lucky number is 34 and so on. Note that 13, 40 etc., are not lucky as they have other numbers in it.

The program should accept a number 'n' as input and display the nth lucky number as output.

Sample Input 1:

3

Sample Output 1:

33

Explanation:

Here the lucky numbers are 3, 4, 33, 34, and the 3rd lucky number is 33.

Sample Input 2:

Activate Windows
Go to Settings to activate Windows.

REC-CIS

```
1 #include<stdio.h>
2 int con(int a){
3     int c=a;
4     while(c!=0){
5         int d=c%10;
6         if(d!=3 && d!=4){
7             return 0;
8         }
9         c=c/10;
10    }
11    return 1;
12 }
13
14 int main(){
15     int a,b=0;
16     scanf("%d",&a);
17     while(a!=0){
18         b++;
19         if(con(b)){
20             a--;
21         }
22     }
23     printf("%d",b);
24 }
25
26 }
```

	Input	Expected	Got	
✓	34	33344	33344	✓

Activate Windows
Go to Settings to activate Windows.

REC-CIS

```
11     }
12     return 1;
13
14 }
15 int main(){
16     int a,b=0;
17     scanf("%d",&a);
18     while(a!=0){
19         b++;
20         if(con(b)){
21             a--;
22         }
23     }
24     printf("%d",b);
25 }
26 }
```

	Input	Expected	Got	
✓	34	33344	33344	✓

Passed all tests! ✓

Activate Windows
Go to Settings to activate Windows.

Finish review