


Attachment 2 – Material Master INC Value Standardization Rules
Page 1 of 3

1.0 **PURPOSE**

- 1.1 Following standardization rules allows consistent data input in SAP Material Master Description fields and INC classification panel. Inconsistent data formats reduce the likelihood of a successful search.

2.0 **MATERIAL SHORT TEXT FORMATION RULES**

- 2.1 Only use UPPER case text except to denote units (kg, Hz, mA, etc.).
- 2.2 Nouns should not be abbreviated.
- 2.3 Modifier can be abbreviated and should be separated from noun with a comma (,).
- 2.4 Noun and modifier should be separated from characteristics values with a colon (:).
- 2.5 Use commas between different characteristics (spaces may be omitted). See Figure 1 – Short Text Format.
- 2.6 Do not input part number in short text.



NOUN,MODIFIER:CHAR 1,CHAR 2,CHAR 3,CHAR N

Figure 1 – Short Text Format

3.0 **INC CLASSIFICATION VALUE INPUT RULES**

- 3.1 Always use UPPER case text only.
- 3.2 Lower case is allowed for units of measurement such as Hz, kg, and mA.
- 3.3 Input the unit at the end of value (e.g., 120V not VAC 120).
- 3.4 Remove irrelevant special characters such as ©, ™, etc.
- 3.5 When an attribute demands multiple values and has a single unit, input the unit at the end of value.
- 4 ~ 20mA; 10 X 20 X 50mm (Correct)
 - 4mA ~ 20mA; 10mm X 20mm X 50mm (Wrong)
- 3.6 When an attribute demands multiple values and has different units, each value can be input with appropriate unit (e.g., SEAT GASKET SIZE: 9-3/4"ID X 10-1/2"OD X 12'L).
- 3.7 Use (") for inches, (') for feet, and (-) to denote ranges.
- 3.8 Represent the physical dimensions as Width, Length, Height, then Thickness, if applicable.
- WD X LG X HT
 - WD X LG X HT X THK

The value in the field will have the format of 15"W X 10M L X 10"H.

Attachment 2 – Material Master INC Value Standardization Rules
Page 2 of 3

- 3.9 For SIZE in diameter: ID (comes first), OD (after ID), then THK for thickness.
- ID X OD X THK
- 3.10 Dimensions for connectors of different types of material may put abbreviations next to the dimension of the material. This can be done with male/female adapters.
- SIZE (PIPE ADAPTER): 1/8"FNPT X 3/4"MNPT
- 3.11 Amperes, watts, and volts should have the number, immediately followed by (A, W, or V).
- AMPERAGE: 6A
 - AMPERAGE: 3mA
 - VOLTAGE: 130V
 - VOLTAGE: 24VDC
- 3.12 Separate multiple values with a slash (e.g., 115/230V, 50/60Hz).
- 3.13 For characteristic ELECTRICAL RATING, enter values as follows:
- 3.13.1 AC voltage with only a V suffix, dropping the AC.
- 3.13.2 DC voltage as VDC.
- 3.13.3 Amperage (A), Phase (PH), Hertz (Hz), Wattage (W), Horsepower (HP), Volt Amps (VA) and OHM if available. If there is a dual rated voltage, label as such (i.e., 24VAC/DC). See Figure 2 – Example Electrical Rating.
- ELECTRICAL RATING: 120V 1A 1PH 50/60Hz
- Figure 2 – Example Electrical Rating
- 3.13.4 For characteristic TEMPERATURE RATING, enter Celsius first followed by the Fahrenheit temperature range.
- TEMPERATURE RATING: 57 DEG C (135 DEG F)
- 3.14 Focus on filling maximum number of characteristics values in an INC.
- 3.15 If correct INC is not available in SAP, contact Cataloging team to create.
- 3.16 Ensure to input values for important attributes.
- 3.17 For materials that have a specific setpoint, be sure to input the value.
- 3.18 Use abbreviations only from the approved abbreviation table.

Attachment 2 – Material Master INC Value Standardization Rules
Page 3 of 3

4.0 DATA STANDARDIZATION RULES FOR MANUFACTURER NAME AND PART NUMBER

4.1 Manufacturer

4.1.1 Abbreviations “Co.,” “Inc.,” and “Corp.” must be left off the manufacturer name. In addition, manufacturer should not have its name abbreviated unless it is its proper name. For example, do not enter GE (General Electric), but S&S is correct. The ampersand (&) should be used instead of “and” or “+”. No spaces are used in abbreviated names such as S&S.

- General Electric
- S&S
- Turtle & Hughes
- Bussman

4.2 Part Number

4.2.1 Part Numbers should not include dashes and spaces unless the dash and space are specified in the vendor literature as part of the part number. Additional spaces should be taken out also, except when they differentiate information [i.e., 6313 5/8” (5/8 is a measure, and the number would lose meaning as 63135/8”)]. P/N and # should not be used, since part number is implied. Brand names should be entered, such as “Unirex 220” (include space). Examples:

- Fuse – NOS-6 (when specified in manufacturer literature as NOS-6)
- Bearing – 6313ZZ 5/8”
- Tools – 9HT23221