# 5X7 Dot Character VFD Module   CU16025ECPB-W6J

- ❑ **2 X 16 Characters 5mm High**
- ❑ **LCD Compatible Design**
- ❑ **Operating Temp -40°C to +85°C**
- ❑ **Single 5V Supply with Power Save Mode**
- ❑ **High Brightness Blue Green Display**
- ❑ **Selectable 4/8 bit M68/i80 Interface**
- ❑ **ASCII + Extended Character Font**
- ❑ **8 User Definable Character RAM**
- ❑ **4 Level Brightness Control Function**

The module includes the Vacuum Fluorescent Display glass, driver and micro-controller ICs with refresh RAM, character generator and interface logic.
The high speed 8 bit parallel interface is 5V CMOS compatible suitable for connection to a host CPU bus which can be set to M68 or i80 series interface by a solder link on the module. Brightness control and power down functions are provided. A full data sheet is available.

14 x ⌀ 1.0

Dimensions in mm & subject to tolerances. Mounting holes 2.5mm dia.

ELECTRICAL SPECIFICATION

Parameter	Symbol	Value	Condition
Power Supply Voltage	V_{CC}	5.0VDC +/- 5%	G_{ND}=0V
Power Supply Current	I_{CC}	150mADC typ.	Vcc=5V
Logic High Input	V_{IH}	2.0VDC min.	Vcc=5V
Logic Low Input	V_{IL}	0.8VDC max.	Vcc=5V
Logic High Output	V_{OH}	Vcc-0.4VDC min.	I_{OH} = -1.6mA
Logic Low Output	V_{OL}	0.4VDC max.	I_{OH} =1.6mA

The power on rise time should be less than 50ms.The inrush current at power on can be 2 x Icc.
The Icc current is 10mA maximum while in power down mode.

OPTICAL and ENVIRONMENTAL SPECIFICATIONS

Parameter	Value
Character Size/Pitch (XxY mm)	2.46 x 4.76/3.26 x 6.01
Dot Size/Pitch (XxY mm)	0.38 x 0.56/0.52 x 0.7
Luminance	700 cd/m^2 (204 fL) Typ.
Colour of Illumination	Blue-Green (Filter for more colours)
Operating Temperature	-40°C to +85°C
Storage Temperature	-50°C to +85°C
Operating Humidity (non condensing)	20 to 80% RH @ 25°C

SOFTWARE COMMANDS

Instruction	R/W̄	RS	D0-D7
Clear Display	L	L	01H
Cursor Return Home	L	L	02H-03H
Entry Mode Set	L	L	04H-07H
Display ON/OFF	L	L	08H-0FH
Cursor/Display Shift	L	L	10H-1FH
Function Set	L	L	20H-3FH
Brightness Set	L	H	00H-03H
Set CG RAM Addr.	L	L	40H-7FH
Set DD RAM Addr.	L	L	80H-E7H
Read BUSY/Addr.	H	L	00H-FFH
Write Data to RAM	L	H	00H-FFH
Read Data from RAM	H	H	00H-FFH

PIN CONNECTIONS

Pin	Sig	Pin	Sig
1	G_{ND}	2	V_{CC}
3	(FNC)	4	RS
5	R/W̄ #	6	E #
7	DB0	8	DB1
9	DB2	10	DB3
11	DB4	12	DB5
13	DB6	14	DB7

TIMING PARAMETERS (min)

(E)nable Cycle Time	1000ns
(E)nable Pulse Width	450ns
Hold after (E)nable	10ns

CHARACTER FONT

JUMPER LINKS
 # Interface M68/i80
When jumper link JP2 is soldered, these inputs change to i80 series CPU control lines.
Pin 5= /WR Pin 6 = /RD

Pin 3 (Fnc) Input
This is normally open circuit. If pads JP1.1 and JP1.2 are linked. Pin 3 = /Reset.

NORITAKE ITRON VFD MODULES   2x16, 5mm Dot Character