MSCC Software Versions Addendum

Release R11-13-5 · 2026-11-13

The Operator's Guides describe how MSCC works; this addendum lists the version numbers that go with the current release. It is updated with every release, so the guides don't change when only version numbers do. Downloads and what changed in each release: https://github.com/w4mmp-ron/mscc-station/releases (Windows details: `installers/windows/CHANGELOG.md`).

Installers

Computer	File
Windows	`mscc-net9-R11-13-5-install.exe` (installs to `C:\mscc-net9`; uninstall from Apps & features)
Raspberry Pi (64-bit Pi OS, Pi 4 / Pi 5)	`mscc_1.0.92_arm64.deb` (required) and `mscc-avalonia_1.7.00_arm64.deb` (optional)

MSCC programs

Program	Windows	Raspberry Pi
MSCC client	WPF, title bar 11.13.6	MSCC Avalonia 1.7.00 (optional)
ms-sdr (server)	3.211	3.208
recv (receive server)	3.154	3.155
trans (transmit server)	3.159	3.160

The Windows and Raspberry Pi servers do the same job; their numbers differ because each build counts up on its own (recv / trans on the Pi also have a Linux-only sound card fix for Ultimus radios).

Radio firmware

The radio's firmware must be at least the version below for this release (the calibration is stored in the radio). After you connect, the client's title bar shows the radio's firmware as **FW: major.minor**; the major number tells which radio it is. If yours is lower, update it (Operator's Guide, Chapter 3).

Radio	Firmware	Status
Proficio Legacy	1.236	
Geminus MKII	2.154	new in R11-12-3, **not tested on a radio yet**
Proficio MKII PTT	3.244	new in R11-12-3, **not tested on a radio yet**
Proficio MKII ATU	4.245	new in R11-12-3, **not tested on a radio yet**
Geminus Legacy	5.153	
Ultimus Legacy	6.236	
Ultimus MKII ATU	7.245	new in R11-12-3, **not tested on a radio yet**
Ultimus MKII PTT	8.244	new in R11-12-3, **not tested on a radio yet**
Black Pill board (any radio)	3.16	tested (Proficio MKII)
Black Pill update tools (Pi window new)	R11-12-6	Pi tested; Windows: checks tested, no flash yet

The five new PSoC versions add only the keyer update over USB. If you don't need that, you can stay on the version before (2.153, 3.243, 4.244, 7.244, 8.243) until they are tested.

Where the files are: Windows `C:\mscc-net9\PSoC Firmware\<Radio>\` and `C:\mscc-net9\Black Pill Firmware\`; Raspberry Pi `/usr/share/mscc/firmware/<Radio>/` and `/usr/share/mscc/firmware/black-pill/`.

Keyer (daughter board: Proficio, Geminus and Ultimus MKII)

Item	Version	Status
Keyer firmware	`Keyer-MCU-app-20261112.hex`	tested (Proficio MKII with Black Pill)
Keyer bootloader (put on once with the PICkit)	version 2, in `Keyer-MCU-full-20261112.hex`	tested
Keyer Firmware Update (window and command line)	R11-12-4	tested on Windows and Raspberry Pi

Keyer Firmware Update needs radio firmware with the keyer update: Black Pill 3.16, or the PSoC versions marked new above (2.154, 3.244, 4.245, 7.245, 8.244). Files: Windows `C:\mscc-net9\Keyer Firmware\`, Raspberry Pi `/usr/share/mscc/firmware/keyer/`.