===LAB 5====

Task 1: Find Max value in array

```
[org 0x0100]

MOV CX, 3
MOV SI, 1
MOV BL, [arr]
label:
MOV AL, [arr+SI]
cmp AL, BL
JBE SKIP
MOV BL, AL
SKIP:
INC SI
LOOP label
MOV AX, 4c00h
INT 21H
arr: db 10, 20, 50, 40
```

Task 2: Find Min value in array

```
[org 0x0100]

MOV CX, 3
```

```
MOV SI, 1
MOV BL, [arr]
label:
MOV AL, [arr+SI]
cmp AL, BL
JAE SKIP
MOV BL, AL
SKIP:
INC SI
LOOP label
MOV AX, 4c00h
INT 21H
arr: db 10, 20, 50, 40
```

Task 3: Search 25 in array

```
[org 0x0100]

MOV SI, 0
MOV CX, 3
label:
MOV Al, [arr+SI]
CMP Al, 25
JE exit
INC SI
```

```
LOOP label

exit:

MOV AX, 4c00h

INT 21H


arr: db 10, 20, 25, 50
```