

MODULE		DI	DO	AI
0	Siemens S7-1200 PLC: CPU 1214C	14	10	2AI-V
1	Siemens S7-1200 Exp.: 16DI/16DO	16	16	0
2	Siemens 7" HMI: TP700 Comfort	0	0	0
3	eWON Cosy+WiFi M2M Remote Router with WiFi & LAN : EC7133J	0	0	0
TOTAL		30	26	2AI

Sr. No.	Digital Input	Sym.	No.	Module
1	Emergency Switch	SW1	I0.0	0
2	Reserve Digital Input 3		I0.1	
3	Fault Reset Switch	SW2	I0.2	
4	Start Switch	SW3	I0.3	
5	Stop Switch	SW4	I0.4	
6	Lid Open Switch	SW5	I0.5	
7	Lid Close Switch	SW6	I0.6	
8	Lid Interlock Switch	SW7	I0.7	
9	Lid Open Sensor	S1	I1.0	
10	Lid Close Sensor	S2	I1.1	
11	Process Tank Level Switch	FS1	I1.2	
12	Weir Tank Level Switch	FS2	I1.3	
13	Ultrasonic 1 Healthy Signal	US1	I1.4	
14	Ultrasonic 2 Healthy Signal	US2	I1.5	
15	Ultrasonic 3 Healthy Signal	US3	I2.0	1
16	Ultrasonic 4 Healthy Signal	US4	I2.1	
17	Ultrasonic 5 Healthy Signal	US5	I2.2	
18	Ultrasonic 6 Healthy Signal	US6	I2.3	
19	Ultrasonic 7 Healthy Signal	US7	I2.4	
20	Ultrasonic 8 Healthy Signal	US8	I2.5	
21	Ultrasonic 9 Healthy Signal	US9	I2.6	
22	Ultrasonic 10 Healthy Signal	US10	I2.7	
23	Thermostat Input		I3.0	
24	Surge Arrestor		I3.1	
25	Heater Contactor Feedback		I3.2	
26	MPCB Feedback of Pump & Motor		I3.3	
27	MPCB Feedback of Heater		I3.4	
28	Lid Middle Sensor	S3	I3.5	
29	Reserve Digital Input 2		I3.6	
30	Reserve Digital Input 1		I3.7	

Sr. No.	Analog Input	Sym.	No.	Module
1	Process Tank Temperature Input	RTD-V	IW64	0
2	Reserve Analog Input 1		IW66	

Sr. No.	Digital Output	Sym.	No.	Module
1	Lid Open	M1	Q0.0	0
2	Lid Close	M1	Q0.1	
3	Reserve Digital Output 7		Q0.2	
4	Reserve Digital Output 6		Q0.3	
5	Filtration Pump	M2	Q0.4	
6	Heater	H1	Q0.5	
7	Ultrasonic On	US1-10	Q0.6	
8	Start Switch LED	L1	Q0.7	
9	Stop Switch LED	L2	Q1.0	
10	Lid Open Switch LED	L3	Q1.1	
11	Lid Close Switch LED	L4	Q2.0	1
12	Lid Interlock Switch LED	L5	Q2.1	
13	Green Lamp	L6	Q2.2	
14	Orange Lamp	L7	Q2.3	
15	Red Lamp	L8	Q2.4	
16	Buzzer	BZ1	Q2.5	
17	Ultrasonic Power Control Ampl 0	US1-10	Q2.6	
18	Ultrasonic Power Control Ampl 1	US1-10	Q2.7	
19	Ultrasonic Power Control Ampl 2	US1-10	Q3.0	
20	Ultrasonic Degas On	US1-10	Q3.1	
21	Reserve Digital Output 5		Q3.2	
22	Reserve Digital Output 4		Q3.3	
23	Auto Fillup Valve(Electrical)	EY1	Q3.4	
24	Reserve Digital Output 3		Q3.5	
25	Reserve Digital Output 2		Q3.6	
26	Reserve Digital Output 1		Q3.7	