SIL EL - Ethiopian Latin Keyboard

The "SIL EL - Ethiopian Latin" keyboard is intended to support keying many Ethiopian latin-based scripts.

Special Vowels - Small Letters

keys:		; e	: e	; i		; o		; u	
or:		e <		i <		o <		u <	
or:	] a	] e	= e	i =	] i	] o	= o	u =	] u
	Λ	ɛ	ə	ɨ	ɩ	ɔ	ø	ʉ	ʊ
	028C	025B	0259	0268	0269	0254	00F8	0289	028B

Special Vowels - Capital Letters

keys:		; E	: E	; I		; O		; U	
or:		E <		I <		O <		U <	
or:	] A	] E	= E	I =	] I	] O	= O	U =	] U
	Λ	Ɛ	Ə	Ɨ	Ɩ	Ɔ	Ø	Ʉ	Ʊ
	0245	0190	018F	0197	0196	0186	00D8	0244	01B2

Special Consonants - Small Letters

keys:	; b	; c	; d	; g	] g	; h	; n	: n	; s
or:	b <	c <	d <	g <			n <	= n	s <
or:							] n		
	ɓ	ç	ɗ	ɠ	ɣ	ħ	ŋ	ɲ	ʃ
	0253	00E7	0257	0260	0263	0127	014B	0272	0283

Special Consonants - Capital Letters

keys:	; B	; C	; D	; G	] G	; H	; N	: N	; S
or:	B <	C <	D <	G <			N <	= N	S <
							] N		
	Ɓ	Ç	Ɗ	Ɠ	Ɣ	Ħ	Ŋ	Ɲ	ʆ
	0181	00C7	018A	0193	0194	0126	014A	019D	0286

Special "Non-Punctuation Word Forming" Characters

keys:	; X	; x	]] (rota)	;'	]:
description:	glottal	pharyngeal	ejective or glottal stop	saltillo - straight glottal	postposed subject marker
	ʔ	ʕ	ʼ	ꞌ	:
	0294	0295	02BC	A78C	A789

Diacritics

First type the keystrokes from the leftmost column, followed by the keystroke at the top of the column.

keys:	1	2	3	4	5	6	7	8	9	0	# or [
	◌́	◌̀	◌̂	◌̆	◌̃	◌̓	◌̋	◌̏	◌̄	◌̱	◌̈
	composed, else +0301	composed, else +0300	composed, else +0302	composed, else +030C	composed, else +0303	composed, else +0315	composed, else +030B	composed, else +030F	composed, else +0304	composed, else +0331	composed, else +0308

Diacritic Reference Table

First type the keystrokes from the leftmost column, followed by the keystroke at the top of the column.

For example, pressing "u" and then "1" produces "ú" or pressing "E" and then "4" produces "Ě"

keys:	1	2	3	4	5	6	7	8	9	0	# or [
a	á 00E1	à 00E0	â 00E2	ǎ 01CE			a̋ 0061 (+030B)	ȁ 0201	ā 0101	a̱ 0061 (+0331)	ä 00E4
A	Á 00C1	À 00C0	Â 00C2	Ǎ 01CD			A̋ 0041 (+030B)	Ȁ 0200	Ā 0100	A̱ 0041 (+0331)	Ä 00C4
]a	Λ́ 028C (+0301)	Λ̀ 028C (+0300)	Λ̂ 028C (+0302)	Λ̌ 028C (+030C)					Λ̄ 028C (+0304)	Λ̱ 028C (+0331)	
]A	Ʌ́ 0245 (+0301)	Ʌ̀ 0245 (+0300)	Ʌ̂ 0245 (+0302)	Ʌ̌ 0245 (+030C)					Ʌ̄ 0245 (+0304)	Ʌ̱ 0245 (+0331)	
b	b́ 0062 (+0301)										
B	B́ 0042 (+0301)										
c						c̓ 0063 (+0315)					
C						C̓ 0043 (+0315)					
e	é 00E9	è 00E8	ê 00EA	ě 011B			e̋ 0065 (+030B)	ȅ 0205	ē 0113	e̱ 0065 (+0331)	ë 00EB

keys:	1	2	3	4	5	6	7	8	9	0	# or [
E	É 00C9	È 00C8	Ê 00CA	Ě 011A			E̋ 0045 (+030B)	Ȅ 0204	Ē 0112	E̱ 0045 (+0331)	Ë 00CB
; e e <] e	ɛ́ 025B (+0301)	ɛ̀ 025B (+0300)	ɛ̂ 025B (+0302)	ɛ̌ 025B (+030C)					ɛ̄ 025B (+0304)	ɛ̱ 025B (+0331)	ɛ̈ 025B (+0308)
; e 0 e < 0] e 0											ɛ̱̈ 025B (+0331 +0308)
; E E <] E	Ɛ́ 0190 (+0301)	Ɛ̀ 0190 (+0300)	Ɛ̂ 0190 (+0302)	Ɛ̌ 0190 (+030C)					Ɛ̄ 0190 (+0304)	Ɛ̱ 0190 (+0331)	Ɛ̈ 0190 (+0308)
; E 0 E < 0] E 0											Ɛ̱̈ 0190 (+0331 +0308)
: e = e									ə̄ 0259 (+0304)		
: E = E									Ə̄ 018F (+0304)		
g	ǵ 0067 (+0301)										
G	Ǵ 0047 (+0301)										
i	í 00ED	ì 00EC	î 00EE	ǐ 01D0			i̋ 0069 (+030B)	ȉ 0209	ī 012B	i̱ 0069 (+0331)	ï 00EF
I	Í 00CD	Ì 00CC	Î 00CE	Ǐ 01CF			I̋ 0049 (+030B)	Ȉ 0208	Ī 012A	I̱ 0049 (+0331)	Ï 00CF
; i i < i =	ɨ́ 0268 (+0301)	ɨ̀ 0268 (+0300)	ɨ̂ 0268 (+0302)	ɨ̌ 0268 (+030C)			ɨ̋ 0268 (+030B)	ɨ̏ 0268 (+030F)	ɨ̄ 0268 (+0304)	ɨ̱ 0268 (+0331)	ɨ̈ 0268 (+0308)
; I I < I =	Ɨ́ 0197 (+0301)	Ɨ̀ 0197 (+0300)	Ɨ̂ 0197 (+0302)	Ɨ̌ 0197 (+030C)			Ɨ̋ 0197 (+030B)	Ɨ̏ 0197 (+030F)	Ɨ̄ 0197 (+0304)	Ɨ̱ 0197 (+0331)	Ɨ̈ 0197 (+0308)
] i	ɩ́ 0269 (+0301)	ɩ̀ 0269 (+0300)	ɩ̂ 0269 (+0302)	ɩ̌ 0269 (+030C)					ɩ̄ 0269 (+0304)	ɩ̱ 0269 (+0331)	

keys:	1	2	3	4	5	6	7	8	9	0	# or [
] ɪ	Í 0196 (+0301)	Ì 0196 (+0300)	Î 0196 (+0302)	Ǐ 0196 (+030C)					Ī 0196 (+0304)	I̱ 0196 (+0331)	
k						k̕ 006B (+0315)					
K						K̕ 004B (+0315)					
m	ḿ 1E3F	m̀ 006D (+0300)							m̄ 006D (+0304)		
M	Ḿ 1E3E	M̀ 004D (+0300)							M̄ 004D (+0304)		
n	ń 0144	ǹ 006E (+0300)		ñ 00F1					n̄ 006E (+0304)		
N	Ń 0143	Ǹ 004E (+0300)		Ñ 00D1					N̄ 004E (+0304)		
; n n <	ŋ́ 014B (+0301)								ŋ̄ 014B (+0304)		
; N N <	Ŋ́ 014A (+0301)								Ŋ̄ 014A (+0304)		
o	ó 00F3	ò 00F2	ô 00F4	ǒ 01D2			ő 0151	ȍ 020D	ō 014D	o̱ 006F (+0331)	ö 00F6
O	Ó 00D3	Ò 00D2	Ô 00D4	Ǒ 01D1			Ő 0150	Ȍ 020C	Ō 014C	O̱ 004F (+0331)	Ö 00D6
; o o <] o	ɔ́ 0254 (+0301)	ɔ̀ 0254 (+0300)	ɔ̂ 0254 (+0302)	ɔ̌ 0254 (+030C)					ɔ̄ 0254 (+0304)	ɔ̱ 0254 (+0331)	ɔ̈ 0254 (+0308)
; O O <] O	Ɔ́ 0186 (+0301)	Ɔ̀ 0186 (+0300)	Ɔ̂ 0186 (+0302)	Ɔ̌ 0186 (+030C)					Ɔ̄ 0186 (+0304)	Ɔ̱ 0186 (+0331)	Ɔ̈ 0186 (+0308)
s						s̕ 0073 (+0315)					
S						S̕ 0053 (+0315)					
t	t́ 0074 (+0301)					t̕ 0074 (+0315)					
T	T́ 0054 (+0301)					T̕ 0054 (+0315)					

keys:	1	2	3	4	5	6	7	8	9	0	# or [
u	ú	ù	û	ǔ			ű	ṳ̀	ū	ṵ	ü
	00FA	00F9	00FB	01D4			0171	0215	016B	0075 (+0331)	00FC
U	Ú	Ù	Û	Ǔ			Ű	Ṳ̀	Ū	U̱	Ü
	00DA	00D9	00DB	01D3			0170	0214	016A	0055 (+0331)	00DC
; u **u <** **u =**	ʉ́	ʉ̀	ʉ̂	ʉ̌			ʉ̋	ʉ̏	ʉ̄	ʉ̱	ʉ̈
	0289 (+0301)	0289 (+0300)	0289 (+0302)	0289 (+030C)			0289 (+030B)	0289 (+030F)	0289 (+0304)	0289 (+0331)	0289 (+0308)
; U **U <** **U =**	Ʉ́	Ʉ̀	Ʉ̂	Ʉ̌			Ʉ̋	Ʉ̏	Ʉ̄	Ʉ̱	Ʉ̈
	0244 (+0301)	0244 (+0300)	0244 (+0302)	0244 (+030C)			0244 (+030B)	0244 (+030F)	0244 (+0304)	0244 (+0331)	0244 (+0308)
] u	ʋ́	ʋ̀	ʋ̂	ʋ̌					ʋ̄	ʋ̱	
	028B (+0301)	028B (+0300)	028B (+0302)	028B (+030C)					028B (+0304)	028B (+0331)	
] U	Ʋ́	Ʋ̀	Ʋ̂	Ʋ̌					Ʋ̄	Ʋ̱	
	01B2 (+0301)	01B2 (+0300)	01B2 (+0302)	01B2 (+030C)					01B2 (+0304)	01B2 (+0331)	

Punctuation

The keystrokes are at the top of the column.

"Rota" keying example:

> Pressing " **'** " one time produces " ' "
>
> Pressing " **'** " a second time produces " ' "
>
> Pressing " **'** " a third time produces " **'** "
>
> Pressing " **'** " a fourth time cycles to produce " ' " again

keys:	**"** (rota)	**" "** (rota)	**" " "** (rota)	**<** **"**	**>** **"**
description:	opening double quote	closing double quote	straight double quote	opening double angle quote	closing double angle quote
	"	"	"	«	»
	201C	201D	0022	00AB	00BB
keys:	**'** (rota)	**' '** (rota)	**' ' '** (rota)	**<** **'**	**>** **'**
description:	opening single quote	closing single quote	straight single quote	opening angle quote	closing angle quote
	'	'	'	‹	›
	2018	2019	0027	2039	203A

Note on this Document

This document was originally created as an .odt file using [LibreOffice](#) and then converted to PDF. The HTML variant of this document was created using LibreOffice's Export feature, and then was cleaned up using [tidy](#) with this command:

```
tidy -w 80 -i -utf8 -ashtml -o output-file.html input-file.html
```

Technical Support

For limited technical support, please contact:

Website: www.silethiopia.org

Email: computer_ethiopia@sil.org