

Query Component Detail Data Interface

Request URL :

https://open.jlpcb.com/overseas/openapi/component/getComponentDetailByCode

Request Type :POST

Interface Description:

Query Component Details by C Code

Request Parameters :

Parameter Description :

Header Parameters

Parameter name	Type	Required	Description
Authorization	String	Yes	Signature authentication Generate authentication data
Content-Type	String	Yes	Please set it to application/json
Accept	string	Yes	Please set it to application/json

Body Parameters

Parameter name	Type	Required	Description
componentCodes	String[]	Yes	An array of component codes for batch querying. Supports up to 1000 component codes.

Code Example:

```

OkHttpClient client = new OkHttpClient().newBuilder().build();
MediaType mediaType = MediaType.parse("application/json");
RequestBody body = RequestBody.create(mediaType,
"{\"componentCodes\": [\"C8734\", \"C82899\"]}");
Request request = new Request.Builder()
    .url("https://your-domain.com/overseas/openapi/component/getComponentDetailByCode")
    .method("POST", body)
    .addHeader("Content-Type", "application/json")
    .build();
Response response = client.newCall(request).execute();

```

Response Data:

```

{
  "code": 200,
  "message": "success",
  "data": {
    "componentDetailResponseVOList": [
      {
        "componentCode": "C8734",
        "componentModel": "STM32F103C8T6",
        "componentSpecification": "LQFP-48",
        "firstTypeName": "Microcontrollers",
        "secondTypeName": "ARM Microcontrollers",
        "libraryType": "Basic",
        "description": "ARM Cortex-M3 MCU, 72MHz, 64KB Flash, 20KB RAM",
        "datasheetUrl":
"https://www.st.com/resource/en/datasheet/stm32f103c8.pdf",
        "solderJointCount": 48,
        "priceRanges": [
          {
            "startQuantity": 1,
            "endQuantity": 9,
            "unitPrice": 1.5000
          },
          {
            "startQuantity": 10,
            "endQuantity": 99,
            "unitPrice": 1.2500
          },
          {
            "startQuantity": 100,
            "endQuantity": 999,
            "unitPrice": 1.0000
          }
        ],
        "stockCount": 10000,
        "parameters": [
          {
            "parameterName": "Core",
            "parameterValue": "ARM Cortex-M3"
          },
          {
            "parameterName": "Flash Size",
            "parameterValue": "64KB"
          },
          {
            "parameterName": "RAM Size",
            "parameterValue": "20KB"
          }
        ]
      }
    ]
  }
}

```

```

        {
            "parameterName": "Operating Voltage",
            "parameterValue": "2.0V ~ 3.6V"
        }
    ],
    "assemblyComponentFlag": true,
    "eccnCode": "3A991.a.2",
    "rohsFlag": true
},
{
    "componentCode": "C82899",
    "componentModel": "ESP32-WROOM-32",
    "componentSpecification": "SMD-38",
    "firstTypeName": "RF/Wireless",
    "secondTypeName": "WiFi Modules",
    "libraryType": "Extended",
    "description": "WiFi & Bluetooth Module, 2.4GHz, PCB Antenna",
    "datasheetUrl":
"https://www.espressif.com/sites/default/files/documentation/esp32-wroom-32_datasheet_en.pdf",
    "solderJointCount": 38,
    "priceRanges": [
        {
            "startQuantity": 1,
            "endQuantity": 9,
            "unitPrice": 3.2000
        },
        {
            "startQuantity": 10,
            "endQuantity": 99,
            "unitPrice": 2.8900
        },
        {
            "startQuantity": 100,
            "endQuantity": 999,
            "unitPrice": 2.5000
        }
    ],
    "stockCount": 5000,
    "parameters": [
        {
            "parameterName": "Protocol",
            "parameterValue": "WiFi 802.11 b/g/n, Bluetooth v4.2"
        },
        {
            "parameterName": "Frequency",
            "parameterValue": "2.4GHz"
        },
        {
            "parameterName": "Antenna",
            "parameterValue": "PCB Antenna"
        },
        {
            "parameterName": "Operating Voltage",
            "parameterValue": "3.0V ~ 3.6V"
        }
    ],
    "assemblyComponentFlag": true,
    "eccnCode": "5A002.a.1",
    "rohsFlag": true
},
{
    "componentCode": "C15663",
    "componentModel": "1N4007",
    "componentSpecification": "DO-41",
    "firstTypeName": "Diodes",
    "secondTypeName": "Rectifier Diodes",
    "libraryType": "Basic",
    "description": "Rectifier Diode, 1000V, 1A",
    "datasheetUrl":
"https://www.diodes.com/assets/Datasheets/ds28002.pdf",
    "solderJointCount": 2,

```

```
"priceRanges": [
  {
    "startQuantity": 1,
    "endQuantity": 99,
    "unitPrice": 0.0200
  },
  {
    "startQuantity": 100,
    "endQuantity": 999,
    "unitPrice": 0.0150
  },
  {
    "startQuantity": 1000,
    "endQuantity": 9999,
    "unitPrice": 0.0120
  }
],
"stockCount": 50000,
"parameters": [
  {
    "parameterName": "Voltage - DC Reverse (Vr)",
    "parameterValue": "1000V"
  },
  {
    "parameterName": "Current - Average Rectified (Io)",
    "parameterValue": "1A"
  },
  {
    "parameterName": "Voltage - Forward (Vf)",
    "parameterValue": "1.1V @ 1A"
  },
  {
    "parameterName": "Operating Temperature",
    "parameterValue": "-65°C ~ 175°C"
  }
],
"assemblyComponentFlag": true,
"eccnCode": "EAR99",
"rohsFlag": true
}
]
```

ResponseStatus	StatusDescription
200	success
401	unauthorized
403	forbidden
429	too many requests
4XX	param error
500	inner server error

componentCode	Code
componentModel	model
componentSpecification	Component Package

firstTypeName	First Type
secondTypeName	Second Type
libraryType	Library Type
description	Description
datasheetUrl	Data sheet file ID
solderJointCount	Number of solder joints
priceRanges	Price ranges
startQuantity	Starting quantity
endQuantity	End Quantity
unitPrice	price
stockCount	stock quantity
parameters	parameter
eccnCode	ECCN code
rohsFlag	Rohs
assemblyComponentFlag	Is Fabricated Component?