

# Query Private Component Library Interface

**Request URL :**

<https://open.jlpcb.com/overseas/openapi/component/getPrivateComponentLibrary>

**Request Type :**POST

## Interface Description:

Query the private component library of authenticated customers

**Request Parameters :**

Parameter Description :

### Header Parameters

| Parameter name | Type   | Required | Description                                              |
|----------------|--------|----------|----------------------------------------------------------|
| Authorization  | String | Yes      | Signature authentication<br>Generate authentication data |
| Content-Type   | String | Yes      | Please set it to application/json                        |
| Accept         | string | Yes      | Please set it to application/json                        |

### Body Parameters

| Parameter name | Type    | Required | Description                                   |
|----------------|---------|----------|-----------------------------------------------|
| pageNum        | Integer | Yes      | Page number, starting from 1,<br>default is 1 |
| pageSize       | Integer | Yes      | Page size, default is 100                     |

Code Example:

```

OkHttpClient client = new OkHttpClient().newBuilder().build();
MediaType mediaType = MediaType.parse("application/json");
RequestBody body = RequestBody.create(mediaType,
"{\"pageNum\":1,\"pageSize\":100}");
Request request = new Request.Builder()
    .url("https://your-
domain.com/overseas/openapi/component/getPrivateComponentLibrary")
    .method("POST", body)
    .addHeader("Content-Type", "application/json")
    .build();
Response response = client.newCall(request).execute();

```

Response Data:

```

{
  "code": 200,
  "message": "success",
  "data": {
    "list": [
      {
        "componentModel": "STM32F103C8T6",          // Model
        "componentSpecification": "LQFP-48",        //Package
        "componentCode": "C8734",                  // cCode
        "jlcpcbParts": 1000,                        // JLCPCB Parts
        "globalSourcingParts": 500,                 // Global Sourcing Parts
        "consignedParts": 200,                     // Consigned Parts
        "idleStock": 50                             // Idle Stock
      },
      {
        "componentModel": "ESP32-WROOM-32",
        "componentSpecification": "SMD-38",
        "componentCode": "C82899",
        "jlcpcbParts": 800,
        "globalSourcingParts": 300,
        "consignedParts": 100,
        "idleStock": 25
      }
    ],
    "pageNum": 1,                                // Current page
    "pageSize": 100,                             // Page size
    "total": 1500                                // Total records
  }
}

```

| Response Status | Status Description |
|-----------------|--------------------|
| 200             | success            |
| 401             | unauthorized       |
| 403             | forbidden          |
| 429             | too many requests  |
| 4XX             | param error        |

