



Given that EAX: FE2C1422 EBX: ABCDEF12 EDX: 1234ABCD show what would be in the affected register after each of the below. Assume for EACH question that before each execution, the registers have the original values above. Be sure to give the name(s) of the affected register(s).

(2) CBW eax: FE2C0022 ✓

(2) CWD edx: 12340000 ✓ eax: FE2C1422

(4) CWDE eax: 00001422 ✓

(4) CDQ edx: FFFFFFFF ✓ eax: FE2C1422

(2) MOVZX EAX, BL eax: 00000012 ✓

(2) MOVSX EAX, DL eax: FFFFFFFC ✓

Download, assemble and link Quiz5.asm. Run the debugger and answer the below:

(2) What is the address of the beginning of the code segment? 00401000 ✓ *FFP*

(2) What is the address of the beginning of the data segment? 0018FF94 ✓ *1st find data element*

(2) What is the address of the BEGINNING (BOTTOM) of the stack segment? 0018FE8C ✓

(3) What are the three instructions mentioned in class covered to date that do not affect the flag settings?

mov push pop

(1 pt each answer) READ CAREFULLY: For each of the blanks below, write down the value that is CURRENTLY in the source field, then write what you would EXPECT to see in the destination field. After you have done that, execute the instruction and verify that what you EXPECTED to find was, indeed, what actually happened. For those instructions where you are to write the flag settings, determine what the settings are AFTER the instruction was executed.

	Value in the Destination field BEFORE execution	Anticipated value in destination (BEFORE)	
mov ax, wT	<u>3388 ✓</u>	<u>FFE7 ✓</u>	
add ax, wT+2	<u>FFE7 ✓</u>	<u>FFF8 ✓</u>	flags: OF <u>0</u> SF <u>1</u> ZF <u>0</u> PF <u>0</u> CF <u>0</u>
mov ebx, 5	<u>7EFOE000 ✓</u>	<u>00000005 ✓</u>	
add ebx, dA	<u>00000005 ✓</u>	<u>0000002C ✓</u>	flags: OF <u>0</u> SF <u>0</u> ZF <u>0</u> PF <u>0</u> CF <u>0</u>
mov ebx, offset wZ	<u>0000002C ✓</u>	<u>00404007 ✓</u>	

✓ 2