

Can You Hear Me Now?

An Introduction to Coding Theory

William J. Turner

Department of Mathematics & Computer Science
Wabash College
Crawfordsville, IN 47933

19 October 2004



1 Coding Theory

- Coding Theory vs. Cryptography
- Error Detecting Codes and Error Correcting Codes

2 Linear Codes

- Linear Algebra and Coding Theory
- Encoding and Decoding
- Detecting and Correcting Errors

1 Coding Theory

- Coding Theory vs. Cryptography
- Error Detecting Codes and Error Correcting Codes

2 Linear Codes

- Linear Algebra and Coding Theory
- Encoding and Decoding
- Detecting and Correcting Errors

Coding Theory vs. Cryptography

Coding Theory

Efficient and reliable communication in an uncooperative (possibly hostile) environment.

- Encode and decode
- *Clear* communication

Coding Theory vs. Cryptography

Coding Theory

Efficient and reliable communication in an uncooperative (possibly hostile) environment.

- Encode and decode
- *Clear* communication

Cryptography

Disguising messages so only certain people can see through the disguise.

- Encrypt and decrypt
- *Hidden* communication

Applications of Coding Theory

Example (Digital communication)

- Email, internet, intranet
- Radio, satellite
- Photographs from deep space
- Remote control of unmanned drones

Applications of Coding Theory

Example (Digital communication)

- Email, internet, intranet
- Radio, satellite
- Photographs from deep space
- Remote control of unmanned drones

Example (Products)

- Store scanners (bar codes)
- International Standard Book Number (ISBN)

1 Coding Theory

- Coding Theory vs. Cryptography
- Error Detecting Codes and Error Correcting Codes

2 Linear Codes

- Linear Algebra and Coding Theory
- Encoding and Decoding
- Detecting and Correcting Errors

Error Detecting Codes vs. Error Correcting Codes

Error Detecting Codes

Detect when an error occurs in transmission.

Error Detecting Codes vs. Error Correcting Codes

Error Detecting Codes

Detect when an error occurs in transmission.

Error Correcting Codes

Detect and *correct* errors in transmission.

Repetition Code

Idea

Send each letter or word multiple times.

Repetition Code

Idea

Send each letter or word multiple times.

Example (Send each letter of message twice)

- Receive message 2234.
- Detect error in second digit: 3 or 4?

Repetition Code

Idea

Send each letter or word multiple times.

Example (Send each letter of message twice)

- Receive message 2234.
- Detect error in second digit: 3 or 4?

Example (Send each letter of message three times)

- Receive message 222343.
- Correct error in second letter: 3.

Parity Check

Idea

- Augment binary messages with an extra bit to make an even number of 1s.
- If you receive a message with an odd number of bits, you know an error occurred in transmission.

Parity Check

Idea

- Augment binary messages with an extra bit to make an even number of 1s.
- If you receive a message with an odd number of bits, you know an error occurred in transmission.

Examples (Seven Bits + Parity Check)

- ① $22 \rightarrow (0, 0, 1, 0, 1, 1, 0) \rightarrow (0, 0, 1, 0, 1, 1, 0, 1)$
- ② $23 \rightarrow (0, 0, 1, 0, 1, 1, 1) \rightarrow (0, 0, 1, 0, 1, 1, 1, 0)$

International Standard Book Number (ISBN)

Idea

Ten-digit number (codeword) assigned by publisher:

$$x_1 x_2 x_3 x_4 x_5 x_6 x_7 x_8 x_9 x_{10}$$

- x_1 : language
- $x_2 x_3$: publisher
- $x_4 x_5 \cdots x_9$: book (assigned by publisher)
- x_{10} : assigned so $\sum_{i=1}^{10} i x_i \equiv 0 \pmod{11}$

International Standard Book Number (ISBN)

Idea

Ten-digit number (codeword) assigned by publisher:

$$x_1 x_2 x_3 x_4 x_5 x_6 x_7 x_8 x_9 x_{10}$$

- x_1 : language
- $x_2 x_3$: publisher
- $x_4 x_5 \cdots x_9$: book (assigned by publisher)
- $x_{10} = \sum_{i=1}^9 i x_i \bmod 11$

International Standard Book Number (ISBN)

Idea

Ten-digit number (codeword) assigned by publisher:

$$x_1 x_2 x_3 x_4 x_5 x_6 x_7 x_8 x_9 x_{10}$$

- x_1 : language
- $x_2 x_3$: publisher
- $x_4 x_5 \cdots x_9$: book (assigned by publisher)
- $x_{10} = \sum_{i=1}^9 i x_i \bmod 11$

Possible to

- Detect and correct error in one digit.
- Detect transposition of two digits.

International Standard Book Number (ISBN)

Example (*Accelerated C++* by Koenig and Moo)

- Published in English: $x_1 = 0$
- Published by Addison-Wesley: $x_2x_3 = 20$
- $x_4x_5 \cdots x_9 = 170353$
- $x_{10} = ??$

International Standard Book Number (ISBN)

Example (*Accelerated C++* by Koenig and Moo)

- Published in English: $x_1 = 0$
- Published by Addison-Wesley: $x_2x_3 = 20$
- $x_4x_5 \cdots x_9 = 170353$
- $x_{10} = ??$

$$\begin{aligned}\sum_{i=1}^9 i x_i &= 1 \cdot 0 + 2 \cdot 2 + 3 \cdot 0 + 4 \cdot 1 + 5 \cdot 7 \\ &\quad + 6 \cdot 0 + 7 \cdot 3 + 8 \cdot 5 + 9 \cdot 3 \\ &= 131\end{aligned}$$

International Standard Book Number (ISBN)

Example (*Accelerated C++* by Koenig and Moo)

- Published in English: $x_1 = 0$
- Published by Addison-Wesley: $x_2x_3 = 20$
- $x_4x_5 \cdots x_9 = 170353$
- $x_{10} = ??$

$$\sum_{i=1}^9 i x_i = 131$$

$$\sum_{i=1}^9 i x_i \bmod 11 = 10$$

International Standard Book Number (ISBN)

Example (*Accelerated C++* by Koenig and Moo)

- Published in English: $x_1 = 0$
- Published by Addison-Wesley: $x_2 x_3 = 20$
- $x_4 x_5 \cdots x_9 = 170353$
- $x_{10} = ??$

$$\sum_{i=1}^9 i x_i = 131$$

$$\sum_{i=1}^9 i x_i \bmod 11 = 10$$

$$x_{10} = X$$

International Standard Book Number (ISBN)

Example (*Accelerated C++* by Koenig and Moo)

- Published in English: $x_1 = 0$
- Published by Addison-Wesley: $x_2 x_3 = 20$
- $x_4 x_5 \cdots x_9 = 170353$
- $x_{10} = ??$

$$\sum_{i=1}^9 i x_i = 131$$

$$\sum_{i=1}^9 i x_i \bmod 11 = 10$$

$$x_{10} = X$$

ISBN: 020170353X

1 Coding Theory

- Coding Theory vs. Cryptography
- Error Detecting Codes and Error Correcting Codes

2 Linear Codes

- Linear Algebra and Coding Theory
- Encoding and Decoding
- Detecting and Correcting Errors


Idea

- A *vector* has a magnitude and direction.
- Adding two vectors together creates a new vector that might have a new direction.
- Multiplying a vector by a *scalar* changes its magnitude but not its direction.
- *Vector space* is set of all such combinations of vectors.

Vector Space

Example ($\mathbb{R}^2$ over the field $\mathbb{R}$)

- $\mathbb{R}$ is field of real numbers.
- $\mathbb{R}^2$ is set of all pairs of real numbers.
I.e., all points on two-dimensional plane.



Example ($\mathbb{Z}_2^n$ over the field $\mathbb{Z}_2$)

- $\mathbb{Z}_2$ is field of integers modulo 2.

$$1 + 1 = 2 \bmod 2 = 0$$

- $\mathbb{Z}_2^n$ is set of all n -tuples of 0s and 1s.

$$\begin{bmatrix} 1 & 0 & 1 & 1 & 0 & 1 & 0 \end{bmatrix} \in \mathbb{Z}_2^7$$

Definition (Linear Code)

A subspace of a vector space.

I.e., a subset of a vector space that is itself a vector space.

Linear Codes

Definition (Linear Code)

A subspace of a vector space.

I.e., a subset of a vector space that is itself a vector space.

Example ($C_{7,4}$)

The set linear combinations (span) over $\mathbb{Z}_2$ of

$$u_1 = (1, 0, 0, 0, 0, 1, 1)$$

$$u_2 = (0, 1, 0, 0, 1, 0, 1)$$

$$u_3 = (0, 0, 1, 0, 1, 1, 0)$$

$$u_4 = (0, 0, 0, 1, 1, 1, 1)$$

Every vector in $C_{7,4}$ is a unique linear combination of $\{u_1, u_2, u_3, u_4\}$ because these four vectors are *linearly independent*.

$\{u_1, u_2, u_3, u_4\}$ forms a *basis* for $C_{7,4}$.

1 Coding Theory

- Coding Theory vs. Cryptography
- Error Detecting Codes and Error Correcting Codes

2 Linear Codes

- Linear Algebra and Coding Theory
- Encoding and Decoding
- Detecting and Correcting Errors

Encoding a Message

Idea

Use word's bits as scalars for linear combination of basis vectors.

Encoding a Message

Idea

Use word's bits as scalars for linear combination of basis vectors.

Example ($C_{7,4}$)

- Want to encode the word $x = (1, 0, 1, 1)$.
- Encode x as $w = 1u_1 + 0u_2 + 1u_3 + 1u_4 = (1, 0, 1, 1, 0, 1, 0)$.

Encoding a Message

Definition (Generator Matrix)

- A matrix formed from the basis vectors of a linear code.
- Encode word by multiplying with generator matrix.

Encoding a Message

Definition (Generator Matrix)

- A matrix formed from the basis vectors of a linear code.
- Encode word by multiplying with generator matrix.

Example ($C_{7,4}$)

$$G = \begin{bmatrix} 1 & 0 & 0 & 0 & 0 & 1 & 1 \\ 0 & 1 & 0 & 0 & 1 & 0 & 1 \\ 0 & 0 & 1 & 0 & 1 & 1 & 0 \\ 0 & 0 & 0 & 1 & 1 & 1 & 1 \end{bmatrix}$$

$$w = xG = [1 \quad 0 \quad 1 \quad 1 \quad 0 \quad 1 \quad 0]$$

Decoding a Message

Idea

Solve the linear system

$$xG = w$$

or

$$G^T x^T = w^T$$

Decoding a Message

Idea

Solve the linear system

$$xG = w$$

or

$$G^T x^T = w^T$$

Example ($C_{7,4}$)

Suppose received message $w = (0, 1, 1, 0, 0, 1, 1)$.

$$w = xG \implies x = [0 \quad 1 \quad 1 \quad 0]$$

1 Coding Theory

- Coding Theory vs. Cryptography
- Error Detecting Codes and Error Correcting Codes

2 Linear Codes

- Linear Algebra and Coding Theory
- Encoding and Decoding
- Detecting and Correcting Errors

Detecting and Correcting Errors

Idea

- Use a matrix H whose (left) null space is the linear code.
I.e., $wH = 0$ for every codeword w .
- If $wH \neq 0$, an error must have occurred.
- wH may tell us where error occurred.

Detecting Errors

Example ($C_{7,4}$)

$$H = \begin{bmatrix} 0 & 0 & 1 \\ 0 & 1 & 0 \\ 0 & 1 & 1 \\ 1 & 0 & 0 \\ 1 & 0 & 1 \\ 1 & 1 & 0 \\ 1 & 1 & 1 \end{bmatrix}$$

- Suppose received message $w = (0, 1, 1, 1, 0, 1, 1)$.
- $wH = \begin{bmatrix} 0 & 1 & 0 \end{bmatrix} \neq 0$ so an error must have occurred.

Correcting Errors

Example ($C_{7,4}$)

- $wH = \begin{bmatrix} 0 & 1 & 0 \end{bmatrix} \neq 0$
- wH is second row of $H \implies$ error is second entry of w .
- Correct $w_c = (0, 0, 1, 1, 0, 1, 1)$.
- Decode $x = (0, 0, 1, 1)$.

Detecting and Correcting Errors

Definition (Hamming Distance)

The distance between two codewords is the number of bits in which they differ.

Detecting and Correcting Errors

Definition (Hamming Distance)

The distance between two codewords is the number of bits in which they differ.

Example ($C_{7,4}$)

$$d(u_1, u_2) = 4$$

$$d(u_1, u_4) = 3$$

Detecting and Correcting Errors

Idea

Suppose $\min_{u,v \in C} \{d(u,v)\} = d$.

Detecting and Correcting Errors

Idea

Suppose $\min_{u,v \in C} \{d(u,v)\} = d$.

- Can detect at most $d - 1$ errors.
 - Change d bits $\implies$ may get another codeword.

Detecting and Correcting Errors

Idea

Suppose $\min_{u,v \in C} \{d(u,v)\} = d$.

- Can detect at most $d - 1$ errors.
 - Change d bits $\implies$ may get another codeword.
- Can correct at most $d/2 - 1$ errors.
 - Change $d/2$ bits $\implies$ may be closer to different codeword.

Example ($C_{7,4}$)

$$\min_{u,v \in C_{7,4}} \{d(u,v)\} = 3$$

Detecting and Correcting Errors

Example ($C_{7,4}$)

$$\min_{u,v \in C_{7,4}} \{d(u,v)\} = 3$$

- Can detect at most 2 errors.
 - Start with word $x = (1, 0, 0, 0)$.
 - Encode as $w = (1, 0, 0, 0, 0, 1, 1)$.
 - Three errors during transmission to receive $\bar{w} = (0, 0, 0, 1, 1, 1, 1)$.
 - Decode message $\bar{x} = (0, 0, 0, 1)$.

Detecting and Correcting Errors

Example ($C_{7,4}$)

$$\min_{u,v \in C_{7,4}} \{d(u,v)\} = 3$$

- Can detect at most 2 errors.
 - Start with word $x = (1, 0, 0, 0)$.
 - Encode as $w = (1, 0, 0, 0, 0, 1, 1)$.
 - Three errors during transmission to receive $\bar{w} = (0, 0, 0, 1, 1, 1, 1)$.
 - Decode message $\bar{x} = (0, 0, 0, 1)$.
- Can correct at most 1 errors.
 - Start with word $x = (1, 0, 0, 0)$.
 - Encode as $w = (1, 0, 0, 0, 0, 1, 1)$.
 - Two errors during transmission to receive $\bar{w} = (1, 1, 1, 0, 0, 1, 1)$.
 - “Correct” message as $\bar{w}_c = (0, 1, 1, 0, 0, 1, 1)$.
 - Decode message $\bar{x} = (0, 1, 1, 0)$.

Detecting and Correcting More Errors

Idea

Must increase distance between codewords.

Detecting and Correcting More Errors

Idea

Must increase distance between codewords.

- Want to correct e errors.

Detecting and Correcting More Errors

Idea

Must increase distance between codewords.

- Want to correct e errors.
- Must be able to move distance e from a codeword and still remain at least distance $e + 1$ from any other codeword.

Detecting and Correcting More Errors

Idea

Must increase distance between codewords.

- Want to correct e errors.
- Must be able to move distance e from a codeword and still remain at least distance $e + 1$ from any other codeword.
- Consider *sphere* of radius e around each codeword.

Detecting and Correcting More Errors

Idea

Must increase distance between codewords.

- Want to correct e errors.
- Must be able to move distance e from a codeword and still remain at least distance $e + 1$ from any other codeword.
- Consider *sphere* of radius e around each codeword.
- Spheres of any pair of codewords cannot intersect.

Detecting and Correcting More Errors

Idea

Must increase distance between codewords.

- Want to correct e errors.
- Must be able to move distance e from a codeword and still remain at least distance $e + 1$ from any other codeword.
- Consider *sphere* of radius e around each codeword.
- Spheres of any pair of codewords cannot intersect.
- Increase $e \implies$ increase size of spheres
 - Fewer spheres can fit in same box.
 - Need bigger box to keep same number of spheres.

Detecting and Correcting More Errors

Idea

Must increase distance between codewords.

- Want to correct e errors.
- Must be able to move distance e from a codeword and still remain at least distance $e + 1$ from any other codeword.
- Consider *sphere* of radius e around each codeword.
- Spheres of any pair of codewords cannot intersect.
- Increase $e \implies$ increase size of spheres
 - Fewer spheres can fit in same box.
 - Need bigger box to keep same number of spheres.

Sphere packing problem

-  RAYMOND HILL (1986).
A First Course in Coding Theory.
Oxford University Press, Oxford.
-  RICHARD HILL (1996).
Elementary Linear Algebra with Applications.
Harcourt, Orlando, 3rd edition.