

The Response sentence to set format is:

\$PTNLRPT,a*hh<CR><LF>

Field	Description
a	Status (A - success; V - failure)
hh	Checksum

RT - Reset

Use this sentence to Set the reset type. No query is supported.

\$PTNLART,b,c*hh<CR><LF>

Field	Description
a	Mode: S - Set R - Response
b	Command C = Cold software reset, Erases RAM (including the customer configuration in RAM) and restarts F = Factory software reset. Erases the customer configuration, the almanac, ephemeris and last position in Flash Memory and in SRAM
c (decimal integer)	Flash operation 0 - Do not do any Flash operation 1 - Reserved 2 - Store user configuration to Flash Memory 3 - Reserved 4 - Reserved 5 - Erase user configuration from Flash Memory 6 - Reserved
hh	Checksum

NOTE - A successful command is followed by a \$PTNLRRT,A*3F response. An incorrect command will be followed by a \$PTNLRRT,V*28 response.

NOTE - To save the user configuration to flash memory, send command \$PTNLSRT,C,2*22.

TF - Receiver Status and Position Fix

Use this sentence to get the receiver status and position fix. The Query sentence format is:

\$PTNLQTF*hh<CR><LF>

The Response to query sentence format is:

```
$PTNLaTF,b,c,xxxxxx,xx,x,1111.11111,d,yyyyy.yyyyy,e,xxxx
x,x.x,x.x,x.x*hh<CR><LF>
```

Field	Description
a	Mode: Q - Query S - Set R - Response
b	BBRAM status on startup (A = valid; V = invalid)
c	Almanac completion status (A = complete; V = incomplete)
xxxxxx	GPS time of week (in seconds)
xx	Number of satellites in use, 00 - 12, may be different from the number in view.
x	Position fix source (0 = no fix; 1 = Stationary Mode, 2 = 2D fix; 3 = 3D fix)
1111.1111	Latitude of the current position fix d
yyyyy.yyyyy	Longitude of the current position fix
e	E W
xxxxx	Antenna altitude re: mean-sea-level (MSL geoid, meters)
x.x	'East' component of ENU velocity (m/s)
x.x	'North' component of ENU velocity (m/s)
x.x	'Up' component of ENU velocity (m/s)
hh	Checksum

UT - UTC data

Use this sentence to query or set UTC data.

```
$PTNLaUT, hhhhhhhh, hhhhhh, hh, hh, hhhh, hhhh, hh, hh*hh<CR><LF>
```

Field	Description
a	Mode: Q - Query S - Set R - Response
hhhhhhh	A_0, HEX data conforming to GPS ICD 200
hhhhh	A_1, HEX data conforming to GPS ICD 200