STUDENT PROJECTS LABORATORY - LOCKOUT / TAGOUT [LOTO] PROCEDURE

ENERGY ISOLATION SPECIFICATION | ASSET: FAB-01 | TAG: 15-015M1

General International 15-015M1 6"x48" Belt / 12" Disc Sander

Authorized LOTO Personnel: Sr. Instructional Lab Supervisor (Max Wright) & Student Research Assistants (SRAs)

Notification Channel: Max Wright - Teams / Text Message | Zone: Zone 5: Fabrication, Sheet Metal & Abrasive Finishing (FAB)

STEP 1 - NORMAL MACHINE SHUTDOWN PROCEDURE

Red power switch to OFF position (Front face).

STEP 2 - HAZARDOUS ENERGY SOURCES, MAGNITUDES & ISOLATION POINTS

Source #1: Electrical (120V AC)

Isolation Location: Ceiling cord drop plug.

Lockout Procedure: Unplug cord drop from ceiling receptacle and install Rotating Electrical Plug Lockout.

STEP 3 - STORED / RESIDUAL ENERGY DISSIPATION

Wait for abrasive belt and 12" disc to coast to a complete stop.

STEP 4 - ZERO-ENERGY VERIFICATION ('TRY' STEP)

Toggle red power switch ON to verify zero electrical energy.