STUDENT PROJECTS LABORATORY - LOCKOUT / TAGOUT [LOTO] PROCEDURE

ENERGY ISOLATION SPECIFICATION | ASSET: FAB-04 | TAG: GRIND-PED-01

Pedestal Bench Top Grinders & Deburring Station

Authorized LOTO Personnel: Sr. Instructional Lab Supervisor (Max Wright) & Student Research Assistants (SRAs)

Notification Channel: Max Wright - Teams / Text Message | Zone: Zone 5: Fabrication, Sheet Metal & Abrasive Finishing (FAB)

STEP 1 - NORMAL MACHINE SHUTDOWN PROCEDURE

Power switch to OFF position (Front lower center).

STEP 2 - HAZARDOUS ENERGY SOURCES, MAGNITUDES & ISOLATION POINTS

Source #1: Electrical (120V AC)

Isolation Location: 120V electrical cord & plug.

Lockout Procedure: Unplug grinder and apply Rotating Electrical Plug Lockout to electrical plug.

STEP 3 - STORED / RESIDUAL ENERGY DISSIPATION

Wait for high-inertia grinding and wire wheels to coast to a complete standstill (1-2 minutes).

STEP 4 - ZERO-ENERGY VERIFICATION ('TRY' STEP)

Toggle front power switch ON and verify grinding wheel does not spin.