5G TABLET SERIES

XH-700 5G 10.1-Inch Rugged Android Tablet

A 10.1-inch IP67 tablet on the UNISOC UIS7885 platform: eight cores to 2.7 GHz with an 8 TOPS NPU, 8 GB + 128 GB or 16 GB + 256 GB, a 1200 × 1920 display and a 3.8 V / 10000 mAh battery. 5G, an independent BeiDou receiver and a 48 MP rear camera are on the standard build.



10.1-inch IPS at 1200 × 1920 and 400 nits, 10-point G+G capacitive touch.

UNISOC UIS7885, octa-core to 2.7 GHz with an 8 TOPS NPU; Android 13 or Ubuntu.

8 GB + 128 GB or 16 GB + 256 GB, TF card expansion to 512 GB.

5G SA/NSA, WiFi 5 dual-band, Bluetooth 5.0 and 13.56 MHz NFC.

IP67 sealing and a 1.2 m drop rating; operating range −10 to +50 °C.



Front, rear and side views: hand strap, side keys, ports and the 12-pin pogo pad for a dock.

Display, platform and battery

Display	10.1-inch IPS, FHD 1200 × 1920, 400 nits
Touch panel	10-point G+G capacitive touchscreen
Processor	UNISOC UIS7885, octa-core up to 2.7 GHz, 8 TOPS NPU
Operating system	Android 13 or Ubuntu; the build is fixed at order stage
Memory / storage	8 GB + 128 GB or 16 GB + 256 GB; TF card expansion to 512 GB
Battery	3.8 V / 10000 mAh; USB-C PD fast charge up to 18 W. The specification lists capacity only, not runtime
Cameras	8 MP front; 48 MP rear autofocus with high-brightness LED flash; 8 MP rear macro optional
Dimensions / weight	251 × 170 × 14.6 mm; under 650 g
Audio	2 W stereo speakers; dual microphone with noise reduction
Keys	Power, volume up/down, scan key and Fn key
Sensors	Gravity sensor, gyroscope and magnetic sensor; vibration motor

Connectivity and positioning

5G	SA/NSA: N1 / N3 / N5 / N8 / N28 / N41 / N78 / N79; MIMO: N1 / N41 / N78 / N79
4G LTE	B1 / B3 / B5 / B8 / B34 / B38 / B39 / B40 / B41; MIMO: B1 / B3 / B41
3G	WCDMA B1 / B5 / B8
WiFi	802.11 a/b/g/n/ac, dual-band 2.4 GHz and 5 GHz
Bluetooth	Bluetooth 5.0
GNSS	BeiDou, GPS, GLONASS and Galileo, with an independent BeiDou receiver and RTK positioning
SIM / TF	2 × Nano-SIM and 1 × TF, three-choose-two

The list above is the global build. If your operator uses a band outside it — several North American and Latin American LTE bands are not in that list — send the band table with the enquiry so the build is confirmed against it instead of assumed.

Data capture and interfaces

NFC (standard)	13.56 MHz; ISO/IEC 14443-A/B, 15693 and NFC; read distance 2–5 cm
Fingerprint unlock (standard)	Power-key fingerprint sensor

Fingerprint capture (optional)	Capacitive FAP20: 23 × 35 mm sensor, 256 × 360 px, 500 dpi, 8-bit grayscale
Barcode scanning (optional)	2D imager with an optical resolution of 3 mil or better
ID card reader (optional)	Offline ID module; read distance 2–5 cm, response under 1.5 s
Wired	USB-C with OTG and PD fast charge; 12-pin pogo pin

The optional items are added at order stage. Confirm the module, the SDK and the output format your application expects before the build starts — that is the part that changes the schedule, not the hardware itself.

Operating conditions and accessories

Ingress protection	IP67
Drop	1.2 m
Operating temperature	−10 °C to +50 °C
Storage temperature	−40 °C to +70 °C
Humidity	5%–95% RH, non-condensing
In the box	Power adapter, USB cable, battery, screen protector, manual and wrist strap

Where it fits

Store and retail operations: the 10.1-inch screen is large enough for a product list or a queue-ticket application at a counter, and the 48 MP camera reads labels and shelf edges without a separate handheld. The use cases published for this model are store management and retail management, which is a counter-and-aisle job rather than a warehouse one.

Warehouse and stock counts: with the optional 2D imager the tablet handles receiving, put-away and cycle counts; without it, it is a 5G terminal for the applications that only need a screen and a keyboard. Compare it with a handheld PDA if the work is one-handed picking at height — 650 g in one hand for a full shift is a different proposition from 250 g.

Outbound and dispatch: 5G, independent BeiDou and a 10000 mAh battery suit a device that leaves the building. The band set is the constraint to check first, not the hardware.

Configure your XH-700

Tell us the operating system build (Android 13 or Ubuntu), the optional modules, the SIM and TF arrangement, the band set for your market and the quantity. We will confirm the build, the sample plan and the certification scope in writing. See the OEM and ODM options if the housing, branding or software image has to change, and certification support for radio approvals.

Related guides

Choosing between a tablet and a handheld for the same team is covered in the industrial tablet buying guide. If this device is heading into a tender, the RFP note lists the specifications worth writing down. The cost-of-ownership note

covers what the second and third year actually cost. The direct comparison with the 8-inch model is on XH-700 vs XH-800. For the thicker 10.1-inch build with PTT keys and an RJ45 option, see XH-500 vs XH-700.

Ordering information

MOQ	2 units, the same as the rest of the range. One for the field trial, one for application and device-management testing.
Sample and production	A sample is built in about 3 days and production runs about 25 days from sample approval for our published terms. The XH-700 is a newer model, so its first build is scheduled in writing with the quotation rather than assumed from those figures.
Certification	Radio approvals are not listed in the specification. CE, UKCA, FCC or local type approval is scoped and quoted per project before production, against the market you actually ship to. GMS is not listed either; say so if your application depends on it.
Packaging	Retail box contents and carton dimensions are provided with the confirmed configuration and quotation; pallet quantities and incoterms are agreed with the order.

Request a quote

Send the quantities, the band set for your market, the modules you need and the date units have to be on site. We reply with the configuration, the sample plan and a written price.

The commercial questions — order size, timing, warranty and shipping — are answered on the FAQ page.