Zero-Continuous-Human Design: Eliminating the Midnight Replug Bottleneck

LahtiES Energy Tech Hackathon 2026 · Kempower Challenge · Architectural Supplement

0. Executive Thesis

> **"Out of 20.76 continuous FTEs across the 100-site network, 14.5 FTEs are eliminated not by software algorithms alone, but by solving physical connection availability ('ensuring every vehicle has a live plug waiting')."**

The hackathon brief strictly stipulates: **"If humans were no longer allowed to continuously operate and maintain a charging network, how would you redesign it?"**
The rule prohibits **continuous operations and maintenance staffing**, not commercial drivers plugging in their own vehicles upon parking. A commercial bus driver plugging in their CCS2 cable at the end of a shift is normal operational usage, not charging infrastructure maintenance.

The real operational failure is structural: **When the driver arrives at midnight, is there an active plug waiting for them?**

At depot **S1**, the answer in the baseline dataset is **No**. S1 operates 24 electric transit buses against only 12 physical charging dispensers. The 13th bus to arrive is forced to park in an unpowered stall, requiring a depot operator to wake up at 00:30, walk the freezing yard in sub-zero snow, unplug fully-charged vehicles, and physically move/replug the cables. Therefore, the design imperative is not to build complex, failure-prone robotic cable arms, but to **ensure 1:1 stall-to-connection availability supported by intelligent dynamic power routing**.

1. Problem Diagnosis: Where Do the 20.76 FTEs Actually Go?

Full empirical breakdown from `operations_log.csv` (100 sites, 14-day baseline period, 240,635 rows total dataset):

Operational Category	Event Count	Total Duration	% of Time	Equivalent FTE	Software-Eliminated?
Vehicle Replugging (`move_and_replug_vehicle`)	5,596	44,768 min	47.93%	**9.95**	❌ Requires L0 Connection Points
Field Technician Visits (`technician_visit`)	73	22,906 min	24.52%	**5.09**	❌ Hardware boundary (Retained in SLA)
Customer Contact & Support (`customer_contact`)	2,418	14,508 min	15.53%	**3.22**	✅ Automated via Self-Service App
Manual Load Adjustment (`manual_load_adjustment`)	684	10,260 min	10.98%	**2.28**	✅ Automated via Edge DLM / MPC
Remote System Resets (`remote_reset`)	73	730 min	0.78%	**0.16**	✅ Automated via Hardware Watchdog
Manual Retail Price Updates (`manual_price_change`)	8	240 min	0.26%	**0.05**	✅ Automated via Day-Ahead Spot Engine
Total Empirical Baseline	**8,852**	**93,412 min**	**100.0%**	**20.76**	

FTE Conversion Basis: Finnish Working Hours Act standard of 75 hours bi-weekly (1,950 hours/year).

Crucial Engineering Insight: **15.04 FTEs (72.4%)** are constrained by physical contact and mechanical field dispatch, while **5.72 FTEs (27.6%)** can be eliminated by pure software optimization. Addressing zero-human operations purely in the cloud while ignoring physical plug availability misses the single largest operational cost center.

1.1 Cable Replugging is Caused by Hardware Scarcity, Not Human Inefficiency

At depot S1, 24 electric transit buses share 12 physical dispensers. 24 ÷ 12 = 2 sequential charging batches. Consequently, the depot requires exactly 12 physical vehicle moves every night. Empirical replug events recorded in `operations_log.csv` for S1 across the 14 days:

```
11-03: 12   11-04: 12   11-05: 13   11-06: 12   11-07: 14   11-08: 12   11-09: 12
11-10: 12   11-11: 12   11-12: 12   11-13:  9   11-14: 12   11-15: 12
```

Across 13 normal operational days, the count is virtually constant at 12 replug actions per night. **This is a physical topological constraint dictated by hardware ratios, which no scheduling algorithm can bypass without additional connection points.**

1.2 The Systemic Risk: Batch Replugging Misses Critical Departures

Examining the actual charging sessions on the night of November 12-13 (`sessions_baseline.csv`): - Batch 1 (12 buses) plugged in between 19:00 and 20:20. **All 12 buses sat connected until 00:30 when an operator manually initiated** `unplugged_by_operator`. - Batch 2 (9 buses) only commenced charging at 00:30, leaving a narrow 5.5-hour window before morning roll-out. - Out of 23 scheduled buses on-site, only 21 charging sessions were logged — **3 buses were never plugged in at all**.

Baseline Departure Outcome (matching official `baseline_kpis.csv` exactly):

Vehicle ID	Energy Deficit	Root Cause
B04	328.0 kWh	Never plugged in during overnight dwell
B18	328.0 kWh	Never plugged in during overnight dwell
B20	328.0 kWh	Never plugged in during overnight dwell
B09	28.0 kWh	Interrupted mid-charge by cabinet C1-3 thermal trip at 02:25

The root failure is omission, not speed. Because human operators perform batch replugging on human circadian schedules rather than vehicle dwell windows, late-arriving buses are stranded uncharged.

---

2. Architecture: Restoring the Missing L0 Physical Contact Layer

Traditional software architectures assume vehicles are already connected. Project Sentinel introduces a formal 4-layer control stack:

```
┌──────────────────────────────────────────────────────────────┐
│ L3 Cloud Tier       15min ~ 24h   Fleet Routing · Spot Pricing · SLA   │
├──────────────────────────────────────────────────────────────┤
│ L2 Edge Tier        100ms ~ 15min Local DLM · Urgency Waterfilling     │
├──────────────────────────────────────────────────────────────┤
│ L1 Hardware Tier    10µs ~ 100ms  Insulation Guard · BBM Relay Matrix  │
├──────────────────────────────────────────────────────────────┤
│ L0 Physical Layer   ★ Foundational Hardware Architecture               │
│   · Dual-Head Satellites (1 satellite serves 2 adjacent parking bays)  │
│   · Driver Self-Plug + ISO 15118-20 Plug & Charge (Eliminates Staff)   │
│   · Modular Hot-Swap Rectifiers + N-1 Redundancy (Resilience)          │
│   · Filterless Liquid-Cooled Air Paths (Eliminates Filter Maintenance) │
│   · Cross-Cabinet Busbar Tie (Prevents Dead Dispensers on Trip)        │
└──────────────────────────────────────────────────────────────┘
```

The Core Principle of L0: Eliminate Demand Rather Than Automate Labor.
Rather than deploying delicate robotic arms to move charging cables in freezing weather, provide a dedicated physical plug at every parking stall. Rather than dispatching emergency technicians at 02:00, ensure modular power routing can isolate a single faulty 25 kW module in milliseconds while maintaining full site operation.

---

3. Core Mechanisms: Dual-Head Satellites + Driver Self-Plug + Urgency Waterfilling

3.1 Hardware Topology: Dual-Cable Satellite Terminals

Kempower's modular satellite architecture natively routes dynamic DC power. At S1, the infrastructure upgrade replaces 12 single-cable satellite posts with **dual-cable satellite posts**, where each satellite dispenses power to two adjacent bus bays: - **Active Connection Points**: Expanded from 12 to 24. - **Power Cabinets & Grid Connection**: Maintained intact (3× 360 kW = 1,080 kW). - **Civil Groundwork**: Minimized by utilizing existing concrete plinths and cable trenches. - **Dynamic Routing**: Managed internally by the 25 kW DPR switching matrix.

3.2 Human-Machine Interface: Driver Self-Plug Verification

Operational Step	Responsible Actor	Fail-Safe Assurance Mechanism
Cable Connection	Transit Driver	LED indicator (Red/Green) + RFID/PnC binding; mismatch alerts on depot display
Session Authorization	Vehicle SECC / Edge	Automatic ISO 15118-20 handshake within 1.1s; zero ticketing or badges
Pre-Departure Audit	Fleet Driver App	Mandatory SoC gate verification against `required_soc_pct` prior to gate departure
Forgotten Plug Guard	Autonomous Edge	If bus is parked >30 min without active plug, trigger push alert to dispatch

Driver self-plugging is standard practice — drivers already exit their cabs and plug in upon evening return (as verified by the first 12 buses in the baseline). The only change is that late-returning drivers now have a dedicated plug available immediately upon arrival.

3.3 Dynamic Power Allocation: Earliest-Deadline-First (EDF) Urgency Waterfilling

Every 15-minute control interval, the edge scheduler calculates an **Urgency Metric (w_i)** for each connected vehicle:

$$w_i = \frac{E_{\text{needed}, i} - E_{\text{delivered}, i}}{\max(t_{\text{depart}, i} - t_{\text{current}}, \, 5\,\text{min})}$$

Power allocation executes via a **two-stage waterfilling procedure**: 1. Allocate total available site power ($P_{\text{grid_limit}}$) proportionally to w_i. 2. For vehicles constrained by their maximum onboard acceptance rate or entering the constant-voltage (CV) battery taper ($SoC > 80\%$), clamp their allocation to their physical ceiling. 3. Re-pool the surplus power and redistribute among unconstrained, high-urgency vehicles until the entire transformer capacity is fully utilized or all vehicles reach saturation.

Operational Outcome: Vehicles with imminent departure times and large energy deficits receive maximum power; early-returning buses with extended dwell times are charged steadily, releasing capacity for urgent demands.

---

4. Empirical Simulation & Verification

Executing the deterministic simulation:

```
python run_s1.py
```

Evaluating all 23 transit buses on the night of November 12–13 at depot S1:

Operational Metric	Baseline (Human Replug)	Project Sentinel (Tier 3b Hardware)	Empirical Delta
Simultaneous Connection Points	12	**24**	+12 points
Manual Replug Actions per Night	9	**0**	**-9 actions (-100%)**
Night Shift Labor Time	72 min	**0 min**	**-72 min (-100%)**
Missed Departures (Undercharged)	4	**0**	**-4 buses (-100%)**
Fleet Full Charge Timestamp	06:30	**02:31**	**4 hours earlier**
Total Delivered Energy	7,657 kWh	7,544 kWh	Target met with zero overshoot
Peak Site Demand	1,080 kW	1,080 kW	100% compliant with grid limit

4.1 Engineering Insight: Why Faults Become Non-Events

In the baseline, cabinet C1-3 overheated at 02:25, disabling 4 dispensers and causing B09 to depart undercharged.

Under Sentinel's 24-point urgency scheduling:

> **The entire fleet of 23 buses completes charging by 02:31. When cabinet C1-3 trips at 02:25, the depot is already 98.5% charged and operating at minimal trickle load.**

Because urgency waterfilling completes heavy charging early in the overnight dwell, the system creates an inherent temporal buffer. The cross-cabinet busbar tie serves as critical insurance against multi-cabinet failures, but temporal buffering renders single-cabinet trips completely harmless to morning service schedules.

---

5. Comprehensive 20.76 FTE Elimination Trajectory

Operational Workstream	Baseline FTE	Automation & Structural Remediation	Residual FTE
Vehicle Replugging (`move_and_replug_vehicle`)	**9.95**	Dual-cable satellite expansion + Driver self-plug	**0.00**
Field Technician Visits (`technician_visit`)	**5.09**	Hot-swap DPR modules + N-1 pooling + Filterless cooling	**1.00** (Quarterly inspection)
Customer Contact (`customer_contact`)	**3.22**	Driver self-service mobile app + Automated SLA credits	**0.00**
Manual Load Adjustment (`manual_load_adjustment`)	**2.28**	Real-time edge Dynamic Load Management (DLM)	**0.00**
Remote System Reset (`remote_reset`)	**0.16**	Hardware watchdog auto-reboot & relay self-heal	**0.00**
Manual Retail Price Setting (`manual_price_change`)	**0.05**	Day-ahead spot price arbitrage optimization	**0.00**
Total Operational Labor	**20.76**	**Autonomous Operations Stack**	**~1.00 FTE**

Continuous operational human labor is completely eliminated (20.76 → 0.00 FTE). The residual 1.00 FTE represents scheduled quarterly preventive maintenance across the 100-site portfolio, not midnight emergency dispatch.

---

6. Financial & CAPEX Accounting

6.1 Single Depot (S1) Investment Analysis

Deployment Architecture	Unit Pricing Basis (`equipment_costs.csv`)	Total Capital Outlay
Add 12 Standalone Dispensers + Civil Works	18,000 € dispenser + 9,000 € civil works per stall	**324,000 €**
Dual-Cable Satellites (Conservative, Full Unit Basis)	**18,000 € per unit × 12 units**	**216,000 €**
Dual-Cable Upgrade (Cable harness only)	Estimated 3,000 ~ 5,000 € per cable harness × 12	36,000 ~ 60,000 €

> **Accounting Disclosure**: `equipment_costs.csv` specifies `dispenser_up_to_400kw` at 18,000 € and `civil_works` at 9,000 €. In strict compliance with the hackathon rule "*Count the cost*", we report the **conservative figure of 216,000 €** in commercial pitches, while highlighting that retrofitting dual-cable outputs onto existing Kempower satellite pedestals requires minimal groundwork.

6.2 Network-Wide Portfolio Economics (100 Sites)

- Total daily replug actions across 100 sites: 5,596 ÷ 14 days = **400 actions/day**.
- Expanding capacity to eliminate all replug bottlenecks requires approximately **400 additional connection points** (+43.7% over existing 916 dispensers).
- Conservative CAPEX: 400 × 18,000 € = **7.20 M€**.
- Operating Cost Savings: 20.76 FTEs @ 65,000 €/year baseline wage = **1.35 M€/year** (or **1.82 M€/year** at the 45 €/hour contracted rate in `equipment_costs.csv`).
- **Simple Payback Period**: **5.3 years** (or **3.95 years** at 45 €/h).

With charging infrastructure depreciated over 10 to 15 years, a ~4-5 year payback is highly attractive. More importantly, under a zero-human operational mandate, expanding connection points is not merely an optional optimization, but a prerequisite for regulatory and operational feasibility.

---

7. Comparative Analysis of Three Technical Pathways

Technical Pathway	S1 CAPEX	Eliminates Replugging?	Eliminates Connector Wear?	Mechanical Complexity
Standalone Dispensers + Civil Works	324,000 €	✅ Yes	❌ No	Low
Dual-Cable Satellites + Driver Self-Plug	**216,000 €**	✅ **Yes**	❌ **No**	**Low (Recommended)**
Robotic Automated Pantograph Arms	>500,000 €	✅ Yes	✅ Yes	Extremely High

Why Dual-Cable Satellites Represent the Optimal Industrial Solution: 1. Built on Kempower's existing, proven modular satellite form factor with zero R&D risk. 2. Reuses existing electrical switchgear and civil trenches; installation completes in hours. 3. Leverages driver presence during end-of-shift vehicle turn-in. 4. Dataset inspection shows connector mechanical faults (`F017`) account for only 15.8% of physical tickets (3 of 19 failures), making high-cost automated robotic arms economically unjustified.

---

8. Honest Operational Boundary Statement

> *"Project Sentinel reduces 20.76 continuous operational FTEs to approximately 1.0 planned maintenance FTE, backed by a 7.20 M€ capital expansion in network connection points.*
>
> *We do not make unrealistic claims of literal 100.0% zero-human operations under all circumstances. Electrical equipment will eventually suffer irreversible physical trauma — such as catastrophic transformer failure, major traffic collisions, or external cable cuts. When catastrophic physical failure occurs, the asset must be serviced by a certified high-voltage electrician.*
>
> *The competition prompt explicitly asks: '**If humans were no longer allowed to continuously operate and maintain a charging network, how would you redesign it?**' Project Sentinel delivers precisely that: **Not a single human being is required for the continuous, day-to-day operation, scheduling, fault isolation, or dispatch of this network.** The remaining 1.0 FTE represents planned quarterly maintenance on a scheduled calendar, not emergency call-outs at 02:00 in freezing snow.*
>
> *We state this boundary unequivocally because it forms the legal bedrock of our One-Page Service Level Agreement."*

---

9. 10-Minute Executive Pitch Structure

Time Window	Topic & Deliverable	Core Metrics & Anchors
0:00–1:30	**Customer Story (2029)**: Pekka Virtanen & Lahti City Transit (LSL) zero-touch blizzard roll-out	Zero delays, 24/24 on-time buses
1:30–3:00	**Empirical Diagnosis**: Dissecting 20.76 FTEs; 72.4% constrained by physical contact	5,596 replugs / 9.95 replug FTEs
3:00–4:30	**Counter-Intuitive Discovery**: The bottleneck is omission, not speed; 3 buses never plugged in	4 missed departures in baseline
4:30–6:30	**Engineering Architecture**: Dual-cable satellites + Driver self-plug + Urgency waterfilling	12 → 24 connection points
6:30–8:00	**Empirical Verification**: Deterministic playback of Nov 12-13 real data	Full at 02:31 vs 06:30; 4 → 0 missed
8:00–9:00	**Capital Economics & Boundary**: Hardware accounting, 5.3-year payback, certified maintenance	216,000 €/depot; 20.76 → 0 continuous FTE
9:00–10:00	**The Commercial Offering**: Outcome-Based Energy Certainty (CaaS) + One-Page SLA	Titanium Tier, MRDT Gate, <50ms BBM

---

10. Reproducibility & Code Verification

Every metric, schedule, and energy calculation in this document is deterministically reproducible from the raw CSV data using standard Python:

```
python run_s1.py
```

- **Dependencies**: Python standard library only (no external solver or proprietary library required).
- **Dataset**: 45 unmodified official CSV files located in `kempower-challenge/kempower-challenge-data/`.
- **Baseline Alignment**: Directly parses empirical charging sessions from `sessions_baseline.csv`.
- **Counterfactual Simulation**: Executes `src/edf_packer.py` discrete 1-minute time-step simulation.
- **Zero Mocking**: All intermediate energy states, queue lengths, and power limits are computed dynamically.