

This page contains the following errors:

error on line 276 at column 72: xmlParseEntityRef: no name

Below is a rendering of the page up to the first error.

KALASIN ENGINEERING xCIP-1545 SYSTEM (PROJECT REF: x2608003)
CHASSIS C1 - C8 TO DESTINATION JUNCTION BOX ARCHITECTURE & INTERCONNECTION DIAGRAM

CHASSIS C1: MAIN CONTROLLER RACK

LOC: CA1 Main Cabinet (Control Room)

SLOT 00	1756-L90TSPXT	[CPU]	-> CA1 (1p)
SLOT 01	1756-EN4TR	[ETH]	-> CA1 (1p)
SLOT 02	1756-EN4TR	[ETH]	-> CA1 (1p)
SLOT 03	1756-EN4TR	[ETH]	-> CA1 (1p)
SLOT 04	1756-IB32	[DI]	-> CA1 (16p), JB-401 (16p)
SLOT 05	1756-IB32	[DI]	-> JB-401 (32p)
SLOT 06	1756-IB32	[DI]	-> JB-401 (16p), JB-601 (16p)
SLOT 07	1756-IB32	[DI]	-> JB-601 (32p)
SLOT 08	1756-OB32	[DO]	-> CA1 (16p), JB-401 (16p)
SLOT 09	1756-OB32	[DO]	-> JB-401 (16p), JB-601 (16p)
SLOT 10	1756-IF16	[AI]	-> JB-401 (16p)
SLOT 11	1756-IF16	[AI]	-> JB-601 (16p)

CHASSIS C2: MAIN EXPANSION RACK

LOC: CA1 Main Cabinet (Control Room)

SLOT 00	1756-EN4TR	[ETH]	-> CA1 (1p)
SLOT 01	1756-IB32	[DI]	-> JB-402 (32p)
SLOT 02	1756-IB32	[DI]	-> JB-602 (32p)
SLOT 03	1756-IB32	[DI]	-> JB-602 (28p)
SLOT 04	1756-IB32	[DI]	-> JB-607 (32p)
SLOT 05	1756-IB32	[DI]	-> JB-607 (32p)
SLOT 06	1756-OB32	[DO]	-> JB-402 (16p), JB-602 (16p)
SLOT 07	1756-OB32	[DO]	-> JB-607 (32p)
SLOT 08	1756-OB32	[DO]	-> JB-607 (32p)
SLOT 09	1756-IF16	[AI]	-> JB-402 (16p)
SLOT 10	1756-IF16	[AI]	-> JB-602 (16p)

CHASSIS C3: REMOTE I/O RACK 1

LOC: Spray Drying Cabinet (Dryer 3/4/70/FB)

SLOT 00	1756-EN4TR	[ETH]	-> CA1 (1p)
SLOT 01	1756-IB32	[DI]	-> JB-618 (1p)
SLOT 02	1756-IB32	[DI]	-> JB-618 (3p)
SLOT 03	1756-OB32	[DO]	-> JB-618 (32p)
SLOT 05	1756-IF16	[AI]	-> JB-618 (4p)
SLOT 06	1756-IF16/RTD	[AI]	-> JB-602 (16p)
SLOT 07	1756-IF16/RTD	[AI]	-> JB-602 (16p)
SLOT 08	1756-IF16/RTD	[AI]	-> JB-602 (16p)
SLOT 11	1756-QPS	[AO]	-> JB-402 (2p), JB-602 (2p), ...

CHASSIS C4: REMOTE I/O RACK 2

LOC: Spray Drying Cabinet (Dryer 80/BB/FB)

SLOT 00	1756-EN4TR	[ETH]	-> CA1 (1p)
SLOT 01	1756-IB32	[DI]	-> JB-606 (16p)
SLOT 02	1756-IB32	[DI]	-> JB-612 (32p)
SLOT 04	1756-OB32	[DO]	-> JB-606 (8p), JB-612 (16p)
SLOT 05	1756-IF16	[AI]	-> JB-606 (2p), JB-608 (8p), ...

CHASSIS C5: RIO-200 SLURRY PROCESS

LOC: Slurry Dewatering and Filter

SLOT 00	1756-EN4TR	[ETH]	-> CA1 (1p)
SLOT 01	1756-IB32	[DI]	-> RIO-200 (32p)
SLOT 02	1756-IB32	[DI]	-> RIO-200 (32p)
SLOT 03	1756-OB32	[DO]	-> RIO-200 (32p)
SLOT 04	1756-IF16	[AI]	-> RIO-200 (16p)

CHASSIS C6: MOTOR CONTROL INTERFACE

LOC: MCC Room (Control Room)

SLOT 05	1756-OB16	[DO]	-> MCC (8p)
SLOT 06	1756-IB16	[DI]	-> MCC (16p)

