

2.3 引脚配置及功能 PINMUX

HPM6E00 系列的引脚配置及功能如下:

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
K4	G2	PA00	GPIO_A_00(ALT0) GPTMR1_COMP_0(ALT1) UART0_TXD(ALT2) MCAN0_TXD(ALT7) PWM0_P_0(ALT16) TRGM_P_00(ALT17) SYSCTL_CLK_OBS_0(ALT 24)	-	B01
K5	G3	PA01	GPIO_A_01(ALT0) GPTMR1_CAPT_0(ALT1) UART0_RXD(ALT2) MCAN0_RXD(ALT7) PWM0_P_1(ALT16) TRGM_P_01(ALT17) SYSCTL_CLK_OBS_2(ALT 24)	-	B01
J4	G4	PA02	GPIO_A_02(ALT0) GPTMR1_COMP_1(ALT1) UART0_DE(ALT2) UART0_RTS(ALT3) I2C2_SCL(ALT4) MCAN0_STBY(ALT7) PWM0_P_2(ALT16) TRGM_P_02(ALT17) SYSCTL_CLK_OBS_1(ALT 24)	-	B01
J5	G5	PA03	GPIO_A_03(ALT0) GPTMR1_CAPT_1(ALT1) UART0_CTS(ALT3) I2C2_SDA(ALT4) SPI0_CS_3(ALT5) MCAN1_STBY(ALT7) PWM0_P_3(ALT16) TRGM_P_03(ALT17) SYSCTL_CLK_OBS_3(ALT 24)	-	B01

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
H3	F2	PA04	GPIO_A_04(ALT0) UART1_CTS(ALT3) SPI1_SCLK(ALT5) MCAN1_RXD(ALT7) PWM0_P_4(ALT16) TRGM_P_04(ALT17) JTAG_TDO(ALT24)	-	B01
H4	F3	PA05	GPIO_A_05(ALT0) GPTMR1_COMP_2(ALT1) UART1_DE(ALT2) UART1_RTS(ALT3) SPI1_CS_0(ALT5) MCAN1_TXD(ALT7) PWM0_P_5(ALT16) TRGM_P_05(ALT17) JTAG_TDI(ALT24)	-	B01
H5	F4	PA06	GPIO_A_06(ALT0) GPTMR0_CAPT_0(ALT1) UART1_RXD(ALT2) I2C3_SDA(ALT4) SPI1_MISO(ALT5) PWM0_P_6(ALT16) TRGM_P_06(ALT17) JTAG_TCK(ALT24)	-	B01
G5	F5	PA07	GPIO_A_07(ALT0) GPTMR0_COMP_0(ALT1) UART1_TXD(ALT2) I2C3_SCL(ALT4) SPI1_MOSI(ALT5) PDM0_D_3(ALT9) PWM0_P_7(ALT16) TRGM_P_07(ALT17) JTAG_TMS(ALT24)	-	B01

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
K1	G1	PA08	GPIO_A_08(ALT0) GPTMR0_COMP_1(ALT1) UART2_TXD(ALT2) I2C0_SCL(ALT4) SPI0_CS_2(ALT5) MCAN2_TXD(ALT7) PWM1_P_0(ALT16) TRGM_P_08(ALT17) RDC0_PWM_N(ALT20) QEO2_B(ALT21) SEI2_TX(ALT22) SDM1_DAT_0(ALT23) JTAG_TRST(ALT24)	-	B01
K2	F1	PA09	GPIO_A_09(ALT0) GPTMR0_CAPT_1(ALT1) UART2_RXD(ALT2) I2C0_SDA(ALT4) SPI0_CS_1(ALT5) MCAN2_RXD(ALT7) ESC0_REFCK(ALT11) PWM1_P_1(ALT16) TRGM_P_09(ALT17) RDC0_PWM_P(ALT20) QEO2_A(ALT21) SEI2_RX(ALT22) SDM1_CLK_0(ALT23) TSW0_EVTO_2(ALT26)	-	B01

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
K3	-	PA10	GPIO_A_10(ALT0) GPTMR0_COMP_2(ALT1) UART2_DE(ALT2) UART2_RTS(ALT3) SPI0_SCLK(ALT5) MCAN2_STBY(ALT7) ESC0_CTR_1(ALT11) PWM1_P_2(ALT16) TRGM_P_10(ALT17) QEI3_F(ALT20) QE02_Z(ALT21) SEI2_DE(ALT22) SDM1_DAT_1(ALT23) ETH0_EVTI_0(ALT25) TSW0_EVTI_0(ALT26) ESC0_EVTI_0(ALT27)	-	B01
J1	-	PA11	GPIO_A_11(ALT0) UART2_CTS(ALT3) SPI0_CS_0(ALT5) PDM0_CLK(ALT9) ESC0_CTR_0(ALT11) PWM1_P_3(ALT16) TRGM_P_11(ALT17) QEI3_H1(ALT20) RDC1_PWM_N(ALT21) SEI2_CK(ALT22) SDM1_CLK_1(ALT23) ETH0_EVTO_0(ALT25) TSW0_EVTO_0(ALT26) ESC0_EVTO_0(ALT27)	-	B01

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
J2	-	PA12	GPIO_A_12(ALT0) UART3_CTS(ALT3) I2C1_SDA(ALT4) SPI0_MISO(ALT5) PDM0_D_0(ALT9) ESC0_SDA(ALT11) PWM1_P_4(ALT16) TRGM_P_12(ALT17) QEI3_H0(ALT20) RDC1_PWM_P(ALT21) SEI3_CK(ALT22) SDM1_DAT_2(ALT23) ETH0_EVTI_1(ALT25) TSW0_EVTI_1(ALT26) ESC0_EVTI_1(ALT27)	-	B01
J3	-	PA13	GPIO_A_13(ALT0) GPTMR1_COMP_3(ALT1) UART3_DE(ALT2) UART3_RTS(ALT3) I2C1_SCL(ALT4) SPI0_MOSI(ALT5) MCAN3_STBY(ALT7) PDM0_CLK(ALT9) ESC0_SCL(ALT11) PWM1_P_5(ALT16) TRGM_P_13(ALT17) QEI3_Z(ALT20) QEO3_Z(ALT21) SEI3_DE(ALT22) SDM1_CLK_2(ALT23) ETH0_EVTO_1(ALT25) TSW0_EVTO_1(ALT26) ESC0_EVTO_1(ALT27)	-	B01

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
H1	-	PA14	GPIO_A_14(ALT0) UART3_RXD(ALT2) SPI0_DAT2(ALT5) MCAN3_RXD(ALT7) PDM0_D_2(ALT9) ESC0_CTR_2(ALT11) PWM1_P_6(ALT16) TRGM_P_14(ALT17) QEI3_B(ALT20) QEO3_B(ALT21) SEI3_RX(ALT22) SDM1_CLK_3(ALT23) TSW0_EVTO_3(ALT26)	-	B01
H2	-	PA15	GPIO_A_15(ALT0) GPTMR0_COMP_3(ALT1) UART3_TXD(ALT2) SPI0_DAT3(ALT5) MCAN3_TXD(ALT7) PDM0_D_1(ALT9) ESC0_CTR_3(ALT11) PWM1_P_7(ALT16) TRGM_P_15(ALT17) QEI3_A(ALT20) QEO3_A(ALT21) SEI3_TX(ALT22) SDM1_DAT_3(ALT23)	-	B01
P1	L1	PA16	GPIO_A_16(ALT0) GPTMR3_COMP_0(ALT1) UART4_TXD(ALT2) MCAN4_TXD(ALT7) TSW0_P1_RXDV(ALT10) ESC0_P0_RXDV(ALT11) PWM2_P_0(ALT16) TRGM_P_16(ALT17) QEO1_A(ALT21) SEI1_TX(ALT22) SDM0_DAT_3(ALT23)	-	B01

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
P2	L2	PA17	GPIO_A_17(ALT0) GPTMR3_CAPT_0(ALT1) UART4_RXD(ALT2) MCAN4_RXD(ALT7) TSW0_P1_RXD_0(ALT10) ESC0_P0_RXD_0(ALT11) PWM2_P_1(ALT16) TRGM_P_17(ALT17) QEO1_B(ALT21) SEI1_RX(ALT22) SDM0_CLK_3(ALT23)	-	B01
N1	K1	PA18	GPIO_A_18(ALT0) GPTMR3_COMP_1(ALT1) UART4_DE(ALT2) UART4_RTS(ALT3) I2C6_SCL(ALT4) MCAN4_STBY(ALT7) TSW0_P1_RXD_1(ALT10) ESC0_P0_RXD_1(ALT11) PWM2_P_2(ALT16) TRGM_P_18(ALT17) QE12_H1(ALT20) QEO1_Z(ALT21) SEI1_DE(ALT22) SDM0_DAT_2(ALT23)	-	B01
N2	K2	PA19	GPIO_A_19(ALT0) GPTMR3_CAPT_1(ALT1) UART4_CTS(ALT3) I2C6_SDA(ALT4) SPI3_CS_3(ALT5) MCAN5_STBY(ALT7) TSW0_P1_RXD_2(ALT10) ESC0_P0_RXD_2(ALT11) PWM2_P_3(ALT16) TRGM_P_19(ALT17) QE12_F(ALT20) SEI1_CK(ALT22) SDM0_CLK_2(ALT23)	-	B01

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
M1	J1	PA20	GPIO_A_20(ALT0) UART5_CTS(ALT3) SPI2_SCLK(ALT5) MCAN5_RXD(ALT7) TSW0_P1_RXD_3(ALT10) ESC0_P0_RXD_3(ALT11) PWM2_P_4(ALT16) TRGM_P_20(ALT17) QEI2_H0(ALT20) SEI0_CK(ALT22) SDM0_DAT_1(ALT23)	-	B01
M2	J2	PA21	GPIO_A_21(ALT0) GPTMR3_COMP_2(ALT1) UART5_DE(ALT2) UART5_RTS(ALT3) SPI2_CS_0(ALT5) MCAN5_TXD(ALT7) TSW0_P1_RXCK(ALT10) ESC0_P0_RXCK(ALT11) PWM2_P_5(ALT16) TRGM_P_21(ALT17) QEI2_Z(ALT20) QEO0_Z(ALT21) SEI0_DE(ALT22) SDM0_CLK_1(ALT23)	-	B01
L1	H1	PA22	GPIO_A_22(ALT0) GPTMR2_CAPT_0(ALT1) UART5_RXD(ALT2) I2C7_SDA(ALT4) SPI2_MISO(ALT5) TSW0_P2_RXER(ALT10) ESC0_P1_RXER(ALT11) PWM2_P_6(ALT16) TRGM_P_22(ALT17) ETH0_TXER(ALT18) QEI2_B(ALT20) QEO0_B(ALT21) SEI0_RX(ALT22) SDM0_DAT_0(ALT23)	-	B01

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
L2	H2	PA23	GPIO_A_23(ALT0) GPTMR2_COMP_0(ALT1) UART5_TXD(ALT2) I2C7_SCL(ALT4) SPI2_MOSI(ALT5) TSW0_P1_RXER(ALT10) ESC0_P0_RXER(ALT11) PWM2_P_7(ALT16) TRGM_P_23(ALT17) ETH0_RXER(ALT18) QEI2_A(ALT20) QEO0_A(ALT21) SEI0_TX(ALT22) SDM0_CLK_0(ALT23)	-	B01
P3	K3	PA24	GPIO_A_24(ALT0) GPTMR2_COMP_1(ALT1) UART6_TXD(ALT2) I2C4_SCL(ALT4) SPI3_CS_2(ALT5) MCAN6_TXD(ALT7) TSW0_P1_TXCK(ALT10) ESC0_P0_TXCK(ALT11) PWM3_P_0(ALT16) TRGM_P_24(ALT17) QEO2_A(ALT21) SEI2_TX(ALT22)	-	B01
N3	K4	PA25	GPIO_A_25(ALT0) GPTMR2_CAPT_1(ALT1) UART6_RXD(ALT2) I2C4_SDA(ALT4) SPI3_CS_1(ALT5) MCAN6_RXD(ALT7) TSW0_P1_TXD_0(ALT10) ESC0_P0_TXD_0(ALT11) PWM3_P_1(ALT16) TRGM_P_25(ALT17) ESC0_CTR_0(ALT18) QEO2_B(ALT21) SEI2_RX(ALT22)	-	B01

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
N4	J3	PA26	GPIO_A_26(ALT0) GPTMR2_COMP_2(ALT1) UART6_DE(ALT2) UART6_RTS(ALT3) SPI3_SCLK(ALT5) MCAN6_STBY(ALT7) TSW0_P1_TXD_1(ALT10) ESC0_P0_TXD_1(ALT11) PWM3_P_2(ALT16) TRGM_P_26(ALT17) QE11_H1(ALT20) QEO2_Z(ALT21) SEI2_DE(ALT22)	-	B01
M3	J4	PA27	GPIO_A_27(ALT0) UART6_CTS(ALT3) SPI3_CS_0(ALT5) TSW0_P1_TXD_2(ALT10) ESC0_P0_TXD_2(ALT11) PWM3_P_3(ALT16) TRGM_P_27(ALT17) QE11_F(ALT20) SEI2_CK(ALT22)	-	B01
M4	J5	PA28	GPIO_A_28(ALT0) UART7_CTS(ALT3) I2C5_SDA(ALT4) SPI3_MISO(ALT5) TSW0_P1_TXD_3(ALT10) ESC0_P0_TXD_3(ALT11) PWM3_P_4(ALT16) TRGM_P_28(ALT17) ESC0_CTR_1(ALT18) QE11_H0(ALT20) SEI3_CK(ALT22)	-	B01

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
M5	H3	PA29	GPIO_A_29(ALT0) GPTMR3_COMP_3(ALT1) UART7_DE(ALT2) UART7_RTS(ALT3) I2C5_SCL(ALT4) SPI3_MOSI(ALT5) MCAN7_STBY(ALT7) TSW0_P1_TXEN(ALT10) ESC0_P0_TXEN(ALT11) PWM3_P_5(ALT16) TRGM_P_29(ALT17) QEI1_Z(ALT20) QEO3_Z(ALT21) SEI3_DE(ALT22)	-	B01
L4	H4	PA30	GPIO_A_30(ALT0) UART7_RXD(ALT2) SPI3_DAT2(ALT5) MCAN7_RXD(ALT7) TSW0_P1_MDC(ALT10) ESC0_MDIO(ALT11) PWM3_P_6(ALT16) TRGM_P_30(ALT17) ETH0_MDIO(ALT18) QEI1_A(ALT20) QEO3_B(ALT21) SEI3_RX(ALT22)	-	B01
L5	H5	PA31	GPIO_A_31(ALT0) GPTMR2_COMP_3(ALT1) UART7_TXD(ALT2) SPI3_DAT3(ALT5) MCAN7_TXD(ALT7) TSW0_P1_MDIO(ALT10) ESC0_MDC(ALT11) PWM3_P_7(ALT16) TRGM_P_31(ALT17) ETH0_MDC(ALT18) QEI1_B(ALT20) QEO3_A(ALT21) SEI3_TX(ALT22)	-	B01

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
G1	E1	PB00	GPIO_B_00(ALT0) GPTMR5_COMP_0(ALT1) UART8_TXD(ALT2) MCAN0_TXD(ALT7) I2S0_TXD_0(ALT8) PDM0_CLK(ALT9) TSW0_P1_RXDV(ALT10) ESC0_P0_RXDV(ALT11) PWM0_P_0(ALT16) TRGM_P_00(ALT17) ETH0_RXDV(ALT18) QEO1_A(ALT21) SEI1_TX(ALT22)	-	B02
G2	E2	PB01	GPIO_B_01(ALT0) GPTMR5_CAPT_0(ALT1) UART8_RXD(ALT2) MCAN0_RXD(ALT7) I2S0_BCLK(ALT8) PDM0_D_2(ALT9) TSW0_P1_RXD_0(ALT10) ESC0_P0_RXD_0(ALT11) PWM0_P_1(ALT16) TRGM_P_01(ALT17) ETH0_RXD_0(ALT18) QEO1_B(ALT21) SEI1_RX(ALT22) SDM1_DAT_3(ALT23)	-	B02

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
F1	D1	PB02	GPIO_B_02(ALT0) GPTMR5_COMP_1(ALT1) UART8_DE(ALT2) UART8_RTS(ALT3) I2C2_SCL(ALT4) MCAN0_STBY(ALT7) I2S0_TXD_3(ALT8) PDM0_CLK(ALT9) TSW0_P1_RXD_1(ALT10) ESC0_P0_RXD_1(ALT11) PWM0_P_2(ALT16) TRGM_P_02(ALT17) ETH0_RXD_1(ALT18) QEIO_H1(ALT20) QEO1_Z(ALT21) SEI1_DE(ALT22) SDM1_CLK_3(ALT23)	-	B02
F2	D2	PB03	GPIO_B_03(ALT0) GPTMR5_CAPT_1(ALT1) UART8_CTS(ALT3) I2C2_SDA(ALT4) SPI4_CS_3(ALT5) MCAN1_STBY(ALT7) I2S0_TXD_1(ALT8) PDM0_D_0(ALT9) TSW0_P1_RXD_2(ALT10) ESC0_P0_RXD_2(ALT11) PWM0_P_3(ALT16) TRGM_P_03(ALT17) ETH0_RXD_2(ALT18) QEIO_F(ALT20) SEI1_CK(ALT22)	-	B02

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
E1	C1	PB04	GPIO_B_04(ALT0) UART9_CTS(ALT3) SPI5_SCLK(ALT5) MCAN1_RXD(ALT7) I2S0_MCLK(ALT8) PDM0_D_1(ALT9) TSW0_P1_RXD_3(ALT10) ESC0_P0_RXD_3(ALT11) PWM0_P_4(ALT16) TRGM_P_04(ALT17) ETH0_RXD_3(ALT18) QEIO_H0(ALT20) SEIO_CK(ALT22) SDM1_DAT_2(ALT23)	-	B02
E2	C2	PB05	GPIO_B_05(ALT0) GPTMR5_COMP_2(ALT1) UART9_DE(ALT2) UART9_RTS(ALT3) SPI5_CS_0(ALT5) MCAN1_TXD(ALT7) I2S0_TXD_2(ALT8) PDM0_D_3(ALT9) TSW0_P1_RXCK(ALT10) ESC0_P0_RXCK(ALT11) PWM0_P_5(ALT16) TRGM_P_05(ALT17) ETH0_RXCK(ALT18) QEIO_Z(ALT20) QEO0_Z(ALT21) SEIO_DE(ALT22) SDM1_CLK_2(ALT23)	-	B02

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
D1	E3	PB06	GPIO_B_06(ALT0) GPTMR4_CAPT_0(ALT1) UART9_RXD(ALT2) I2C3_SDA(ALT4) SPI5_MISO(ALT5) I2S0_RXD_1(ALT8) TSW0_P1_TXCK(ALT10) ESC0_P0_TXCK(ALT11) PWM0_P_6(ALT16) TRGM_P_06(ALT17) ETH0_TXCK(ALT18) QEIO_B(ALT20) QEO0_B(ALT21) SEIO_RX(ALT22) SDM1_DAT_1(ALT23)	-	B02
D2	E4	PB07	GPIO_B_07(ALT0) GPTMR4_COMP_0(ALT1) UART9_TXD(ALT2) I2C3_SCL(ALT4) SPI5_MOSI(ALT5) I2S0_RXD_3(ALT8) TSW0_P1_TXD_0(ALT10) ESC0_P0_TXD_0(ALT11) PWM0_P_7(ALT16) TRGM_P_07(ALT17) ETH0_TXD_0(ALT18) QEIO_A(ALT20) QEO0_A(ALT21) SEIO_TX(ALT22) SDM1_CLK_1(ALT23)	-	B02

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
C1	D3	PB08	GPIO_B_08(ALT0) GPTMR4_COMP_1(ALT1) UART10_TXD(ALT2) I2C0_SCL(ALT4) SPI4_CS_2(ALT5) MCAN2_TXD(ALT7) I2S0_RXD_0(ALT8) TSW0_P1_TXD_1(ALT10) ESC0_P0_TXD_1(ALT11) PWM1_P_0(ALT16) TRGM_P_08(ALT17) ETH0_TXD_1(ALT18) QEO2_B(ALT21) SEI2_TX(ALT22) SDM1_DAT_0(ALT23)	-	B02
C2	D4	PB09	GPIO_B_09(ALT0) GPTMR4_CAPT_1(ALT1) UART10_RXD(ALT2) I2C0_SDA(ALT4) SPI4_CS_1(ALT5) MCAN2_RXD(ALT7) I2S0_RXD_2(ALT8) TSW0_P1_TXD_2(ALT10) ESC0_P0_TXD_2(ALT11) PWM1_P_1(ALT16) TRGM_P_09(ALT17) ETH0_TXD_2(ALT18) QEO2_A(ALT21) SEI2_RX(ALT22) SDM1_CLK_0(ALT23)	-	B02

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
B1	C3	PB10	GPIO_B_10(ALT0) GPTMR4_COMP_2(ALT1) UART10_DE(ALT2) UART10_RTS(ALT3) SPI4_SCLK(ALT5) MCAN2_STBY(ALT7) I2S0_FCLK(ALT8) TSW0_P1_TXD_3(ALT10) ESC0_P0_TXD_3(ALT11) PWM1_P_2(ALT16) TRGM_P_10(ALT17) ETH0_TXD_3(ALT18) QEI3_F(ALT20) QEO2_Z(ALT21) SEI2_DE(ALT22)	-	B02
C3	C4	PB11	GPIO_B_11(ALT0) UART10_CTS(ALT3) SPI4_CS_0(ALT5) I2S0_MCLK(ALT8) TSW0_P1_TXEN(ALT10) ESC0_P0_TXEN(ALT11) PWM1_P_3(ALT16) TRGM_P_11(ALT17) ETH0_TXEN(ALT18) QEI3_H1(ALT20) SEI2_CK(ALT22)	-	B02
G4	-	PB12	GPIO_B_12(ALT0) UART11_CTS(ALT3) I2C1_SDA(ALT4) SPI4_MISO(ALT5) TSW0_P2_RXDV(ALT10) ESC0_P1_RXDV(ALT11) PWM1_P_4(ALT16) TRGM_P_12(ALT17) QEI3_H0(ALT20) SEI3_CK(ALT22) SDM0_DAT_3(ALT23)	-	B03

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
F3	-	PB13	GPIO_B_13(ALT0) GPTMR5_COMP_3(ALT1) UART11_DE(ALT2) UART11_RTS(ALT3) I2C1_SCL(ALT4) SPI4_MOSI(ALT5) MCAN3_STBY(ALT7) TSW0_P2_RXD_0(ALT10) ESC0_P1_RXD_0(ALT11) PWM1_P_5(ALT16) TRGM_P_13(ALT17) QEI3_Z(ALT20) QEO3_Z(ALT21) SEI3_DE(ALT22) SDM0_CLK_3(ALT23)	-	B03
F4	-	PB14	GPIO_B_14(ALT0) UART11_RXD(ALT2) SPI4_DAT2(ALT5) MCAN3_RXD(ALT7) TSW0_P2_RXD_1(ALT10) ESC0_P1_RXD_1(ALT11) PWM1_P_6(ALT16) TRGM_P_14(ALT17) QEI3_B(ALT20) QEO3_B(ALT21) SEI3_RX(ALT22) SDM0_DAT_2(ALT23)	-	B03

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
E3	-	PB15	GPIO_B_15(ALT0) GPTMR4_COMP_3(ALT1) UART11_TXD(ALT2) SPI4_DAT3(ALT5) MCAN3_TXD(ALT7) TSW0_P2_RXD_2(ALT10) ESC0_P1_RXD_2(ALT11) PWM1_P_7(ALT16) TRGM_P_15(ALT17) QEI3_A(ALT20) QEO3_A(ALT21) SEI3_TX(ALT22) SDM0_CLK_2(ALT23)	-	B03
E4	-	PB16	GPIO_B_16(ALT0) GPTMR7_COMP_0(ALT1) UART12_TXD(ALT2) MCAN4_TXD(ALT7) TSW0_P2_RXD_3(ALT10) ESC0_P1_RXD_3(ALT11) PWM2_P_0(ALT16) TRGM_P_16(ALT17) RDC0_PWM_N(ALT20) QEO1_A(ALT21) SEI1_TX(ALT22)	-	B03
D3	-	PB17	GPIO_B_17(ALT0) GPTMR7_CAPT_0(ALT1) UART12_RXD(ALT2) MCAN4_RXD(ALT7) TSW0_P2_RXCK(ALT10) ESC0_P1_RXCK(ALT11) PWM2_P_1(ALT16) TRGM_P_17(ALT17) RDC0_PWM_P(ALT20) QEO1_B(ALT21) SEI1_RX(ALT22) SDM0_DAT_1(ALT23)	-	B03

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
F5	-	PB18	GPIO_B_18(ALT0) GPTMR7_COMP_1(ALT1) UART12_DE(ALT2) UART12_RTS(ALT3) I2C6_SCL(ALT4) MCAN4_STBY(ALT7) TSW0_P2_TXCK(ALT10) ESC0_P1_TXCK(ALT11) PWM2_P_2(ALT16) TRGM_P_18(ALT17) QEI2_H1(ALT20) QEO1_Z(ALT21) SEI1_DE(ALT22) SDM0_CLK_1(ALT23)	-	B03
E5	-	PB19	GPIO_B_19(ALT0) GPTMR7_CAPT_1(ALT1) UART12_CTS(ALT3) I2C6_SDA(ALT4) SPI7_CS_3(ALT5) MCAN5_STBY(ALT7) TSW0_P2_TXD_0(ALT10) ESC0_P1_TXD_0(ALT11) PWM2_P_3(ALT16) TRGM_P_19(ALT17) QEI2_F(ALT20) RDC1_PWM_N(ALT21) SEI1_CK(ALT22) SDM0_DAT_0(ALT23)	-	B03

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
E6	-	PB20	GPIO_B_20(ALT0) UART13_CTS(ALT3) SPI6_SCLK(ALT5) MCAN5_RXD(ALT7) DAO_RP(ALT9) TSW0_P2_TXD_1(ALT10) ESC0_P1_TXD_1(ALT11) PWM2_P_4(ALT16) TRGM_P_20(ALT17) QEI2_H0(ALT20) RDC1_PWM_P(ALT21) SEI0_CK(ALT22) SDM0_CLK_0(ALT23)	-	B03
D5	-	PB21	GPIO_B_21(ALT0) GPTMR7_COMP_2(ALT1) UART13_DE(ALT2) UART13_RTS(ALT3) SPI6_CS_0(ALT5) MCAN5_TXD(ALT7) DAO_LN(ALT9) TSW0_P2_TXD_2(ALT10) ESC0_P1_TXD_2(ALT11) PWM2_P_5(ALT16) TRGM_P_21(ALT17) QEI2_Z(ALT20) QEO0_Z(ALT21) SEI0_DE(ALT22)	-	B03

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
C4	-	PB22	GPIO_B_22(ALT0) GPTMR6_CAPT_0(ALT1) UART13_RXD(ALT2) I2C7_SDA(ALT4) SPI6_MISO(ALT5) DAO_RN(ALT9) TSW0_P2_TXD_3(ALT10) ESC0_P1_TXD_3(ALT11) PWM2_P_6(ALT16) TRGM_P_22(ALT17) QEI2_B(ALT20) QEO0_B(ALT21) SEI0_RX(ALT22)	-	B03
C5	-	PB23	GPIO_B_23(ALT0) GPTMR6_COMP_0(ALT1) UART13_TXD(ALT2) I2C7_SCL(ALT4) SPI6_MOSI(ALT5) DAO_LP(ALT9) TSW0_P2_TXEN(ALT10) ESC0_P1_TXEN(ALT11) PWM2_P_7(ALT16) TRGM_P_23(ALT17) QEI2_A(ALT20) QEO0_A(ALT21) SEI0_TX(ALT22)	-	B03

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
A2	A2	PB24	GPIO_B_24(ALT0) GPTMR6_COMP_1(ALT1) UART14_TXD(ALT2) I2C4_SCL(ALT4) SPI7_CS_2(ALT5) MCAN6_TXD(ALT7) ESC0_CTR_4(ALT11) XPI0_CA_CS1(ALT14) PWM3_P_0(ALT16) TRGM_P_24(ALT17) RDC0_PWM_N(ALT21) SDM0_CLK_3(ALT23) ETH0_EVTI_0(ALT25) TSW0_EVTI_0(ALT26) ESC0_EVTI_0(ALT27)	-	B04
B2	B1	PB25	GPIO_B_25(ALT0) GPTMR6_CAPT_1(ALT1) UART14_RXD(ALT2) I2C4_SDA(ALT4) SPI7_CS_1(ALT5) MCAN6_RXD(ALT7) ESC0_CTR_5(ALT11) XPI0_CA_DQS(ALT14) PWM3_P_1(ALT16) TRGM_P_25(ALT17) RDC0_PWM_P(ALT21) SDM0_DAT_3(ALT23) ETH0_EVTO_0(ALT25) TSW0_EVTO_0(ALT26) ESC0_EVTO_0(ALT27)	-	B04

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
A3	A3	PB26	GPIO_B_26(ALT0) GPTMR6_COMP_2(ALT1) UART14_DE(ALT2) UART14_RTS(ALT3) SPI7_SCLK(ALT5) MCAN6_STBY(ALT7) ESC0_CTR_6(ALT11) XPI0_CA_D_2(ALT14) PWM3_P_2(ALT16) TRGM_P_26(ALT17) QE11_H1(ALT20) RDC1_PWM_N(ALT21) SDM0_CLK_2(ALT23) ETH0_EVTI_1(ALT25) TSW0_EVTI_1(ALT26) ESC0_EVTI_1(ALT27)	-	B04
B3	B2	PB27	GPIO_B_27(ALT0) UART14_CTS(ALT3) SPI7_CS_0(ALT5) ESC0_CTR_7(ALT11) XPI0_CA_D_0(ALT14) PWM3_P_3(ALT16) TRGM_P_27(ALT17) QE11_F(ALT20) RDC1_PWM_P(ALT21) SDM0_DAT_2(ALT23) TSW0_EVTO_2(ALT26)	-	B04
A4	A4	PB28	GPIO_B_28(ALT0) UART15_CTS(ALT3) I2C5_SDA(ALT4) SPI7_MISO(ALT5) ESC0_CTR_8(ALT11) XPI0_CA_D_1(ALT14) PWM3_P_4(ALT16) TRGM_P_28(ALT17) QE11_H0(ALT20) RDC0_PWM_N(ALT21) SDM0_CLK_1(ALT23)	-	B04

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
B4	B3	PB29	GPIO_B_29(ALT0) GPTMR7_COMP_3(ALT1) UART15_DE(ALT2) UART15_RTS(ALT3) I2C5_SCL(ALT4) SPI7_MOSI(ALT5) MCAN7_STBY(ALT7) XPI0_CA_SCLK(ALT14) PWM3_P_5(ALT16) TRGM_P_29(ALT17) QE11_Z(ALT20) RDC0_PWM_P(ALT21) SDM0_DAT_1(ALT23) ETH0_EVTO_1(ALT25) TSW0_EVTO_1(ALT26) ESC0_EVTO_1(ALT27)	-	B04
A5	A5	PB30	GPIO_B_30(ALT0) UART15_RXD(ALT2) SPI7_DAT2(ALT5) MCAN7_RXD(ALT7) ESC0_CTR_7(ALT11) XPI0_CA_CS0(ALT14) PWM3_P_6(ALT16) TRGM_P_30(ALT17) QE11_A(ALT20) RDC1_PWM_N(ALT21) SDM0_CLK_0(ALT23)	-	B04

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
B5	B4	PB31	GPIO_B_31(ALT0) GPTMR6_COMP_3(ALT1) UART15_TXD(ALT2) SPI7_DAT3(ALT5) MCAN7_TXD(ALT7) ESC0_CTR_8(ALT11) XPI0_CA_D_3(ALT14) PWM3_P_7(ALT16) TRGM_P_31(ALT17) QE11_B(ALT20) RDC1_PWM_P(ALT21) SDM0_DAT_0(ALT23) TSW0_EVTO_3(ALT26)	-	B04
A6	B5	PC00	GPIO_C_00(ALT0) GPTMR1_COMP_0(ALT1) UART0_TXD(ALT2) MCAN0_TXD(ALT7) ESC0_GPI_63(ALT10) ESC0_GPO_00(ALT11) FEMC_DQ_24(ALT12) PPI0_DQ_24(ALT13) XPI0_CB_CS0(ALT14) PWM0_P_0(ALT16) TRGM_P_00(ALT17) ESC0_GPI_15(ALT18)	-	B05
B6	A6	PC01	GPIO_C_01(ALT0) GPTMR1_CAPT_0(ALT1) UART0_RXD(ALT2) MCAN0_RXD(ALT7) ESC0_GPI_62(ALT10) ESC0_GPO_01(ALT11) FEMC_DQ_25(ALT12) PPI0_DQ_25(ALT13) XPI0_CB_D_1(ALT14) PWM0_P_1(ALT16) TRGM_P_01(ALT17) ESC0_GPI_14(ALT18)	-	B05

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
C6	B6	PC02	GPIO_C_02(ALT0) GPTMR1_COMP_1(ALT1) UART0_DE(ALT2) UART0_RTS(ALT3) I2C2_SCL(ALT4) MCAN0_STBY(ALT7) ESC0_GPI_61(ALT10) ESC0_GPO_02(ALT11) FEMC_DQ_22(ALT12) PPI0_DQ_22(ALT13) XPI0_CB_D_2(ALT14) PWM0_P_2(ALT16) TRGM_P_02(ALT17) ESC0_GPI_13(ALT18) QEIO_H1(ALT20) SDM1_CLK_0(ALT23)	-	B05
A7	A7	PC03	GPIO_C_03(ALT0) GPTMR1_CAPT_1(ALT1) UART0_CTS(ALT3) I2C2_SDA(ALT4) SPI1_CS_3(ALT5) MCAN1_STBY(ALT7) ESC0_GPI_60(ALT10) ESC0_GPO_03(ALT11) FEMC_DQ_26(ALT12) PPI0_DQ_26(ALT13) XPI0_CB_D_3(ALT14) PWM0_P_3(ALT16) TRGM_P_03(ALT17) ESC0_GPI_12(ALT18) QEIO_F(ALT20)	-	B05

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
B7	B7	PC04	GPIO_C_04(ALT0) UART1_CTS(ALT3) SPI0_SCLK(ALT5) MCAN1_RXD(ALT7) ESC0_GPI_59(ALT10) ESC0_GPO_04(ALT11) FEMC_DQ_27(ALT12) PPI0_DQ_27(ALT13) XPI0_CB_SCLK(ALT14) PWM0_P_4(ALT16) TRGM_P_04(ALT17) ESC0_GPI_11(ALT18) QEIO_H0(ALT20) SEIO_CK(ALT22)	-	B05
A8	A8	PC05	GPIO_C_05(ALT0) GPTMR1_COMP_2(ALT1) UART1_DE(ALT2) UART1_RTS(ALT3) SPI0_CS_0(ALT5) MCAN1_TXD(ALT7) ESC0_GPI_58(ALT10) ESC0_GPO_05(ALT11) FEMC_DQ_28(ALT12) PPI0_DQ_28(ALT13) XPI0_CA_CS0(ALT14) PWM0_P_5(ALT16) TRGM_P_05(ALT17) ESC0_GPI_10(ALT18) QEIO_Z(ALT20) QEIO_Z(ALT21) SEIO_DE(ALT22)	-	B05

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
B8	B8	PC06	GPIO_C_06(ALT0) GPTMR0_CAPT_0(ALT1) UART1_RXD(ALT2) I2C3_SDA(ALT4) SPI0_MISO(ALT5) ESC0_GPI_57(ALT10) ESC0_GPO_06(ALT11) FEMC_DQ_29(ALT12) PPI0_DQ_29(ALT13) XPI0_CA_D_1(ALT14) PWM0_P_6(ALT16) TRGM_P_06(ALT17) ESC0_GPI_09(ALT18) QEIO_B(ALT20) QEO0_B(ALT21) SEIO_RX(ALT22)	-	B05
A9	A9	PC07	GPIO_C_07(ALT0) GPTMR0_COMP_0(ALT1) UART1_TXD(ALT2) I2C3_SCL(ALT4) SPI0_MOSI(ALT5) ESC0_GPI_56(ALT10) ESC0_GPO_07(ALT11) FEMC_DQ_30(ALT12) PPI0_DQ_30(ALT13) XPI0_CA_D_3(ALT14) PWM0_P_7(ALT16) TRGM_P_07(ALT17) ESC0_GPI_08(ALT18) QEIO_A(ALT20) QEO0_A(ALT21) SEIO_TX(ALT22)	-	B05

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
B9	B9	PC08	GPIO_C_08(ALT0) GPTMR0_COMP_1(ALT1) UART2_TXD(ALT2) I2C0_SCL(ALT4) SPI1_CS_2(ALT5) MCAN2_TXD(ALT7) ESC0_GPI_55(ALT10) ESC0_GPO_08(ALT11) FEMC_DQ_31(ALT12) PPIO_DQ_31(ALT13) XPIO_CA_SCLK(ALT14) PWM1_P_0(ALT16) TRGM_P_08(ALT17) ESC0_GPI_07(ALT18)	-	B05
D6	C5	PC09	GPIO_C_09(ALT0) GPTMR0_CAPT_1(ALT1) UART2_RXD(ALT2) I2C0_SDA(ALT4) SPI1_CS_1(ALT5) MCAN2_RXD(ALT7) ESC0_GPI_54(ALT10) ESC0_GPO_09(ALT11) FEMC_DQ_23(ALT12) PPIO_DQ_23(ALT13) XPIO_CB_CS1(ALT14) PWM1_P_1(ALT16) TRGM_P_09(ALT17) ESC0_GPI_06(ALT18) SDM1_DAT_0(ALT23)	-	B05

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
D7	D5	PC10	GPIO_C_10(ALT0) GPTMR0_COMP_2(ALT1) UART2_DE(ALT2) UART2_RTS(ALT3) SPI1_SCLK(ALT5) MCAN2_STBY(ALT7) ESC0_GPI_53(ALT10) ESC0_GPO_10(ALT11) FEMC_DQ_20(ALT12) PPIO_DQ_20(ALT13) XPIO_CB_D_0(ALT14) PWM1_P_2(ALT16) TRGM_P_10(ALT17) ESC0_GPI_05(ALT18) QEI3_F(ALT20) SDM1_CLK_1(ALT23)	-	B05
E7	C6	PC11	GPIO_C_11(ALT0) UART2_CTS(ALT3) SPI1_CS_0(ALT5) ESC0_GPI_52(ALT10) ESC0_GPO_11(ALT11) FEMC_DQ_21(ALT12) PPIO_DQ_21(ALT13) XPIO_CB_DQS(ALT14) PWM1_P_3(ALT16) TRGM_P_11(ALT17) ESC0_GPI_04(ALT18) QEI3_H1(ALT20) SDM1_DAT_1(ALT23)	-	B05

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
C8	D6	PC12	GPIO_C_12(ALT0) UART3_CTS(ALT3) I2C1_SDA(ALT4) SPI1_MISO(ALT5) ESC0_GPI_51(ALT10) ESC0_GPO_12(ALT11) FEMC_DM_2(ALT12) PPIO_DM_2(ALT13) XPIO_CA_D_2(ALT14) PWM1_P_4(ALT16) TRGM_P_12(ALT17) ESC0_GPI_03(ALT18) QEI3_H0(ALT20) SEI2_CK(ALT22)	-	B05
D8	C7	PC13	GPIO_C_13(ALT0) GPTMR1_COMP_3(ALT1) UART3_DE(ALT2) UART3_RTS(ALT3) I2C1_SCL(ALT4) SPI1_MOSI(ALT5) MCAN3_STBY(ALT7) ESC0_GPI_50(ALT10) ESC0_GPO_13(ALT11) FEMC_DQ_18(ALT12) PPIO_DQ_18(ALT13) XPIO_CA_CS1(ALT14) PWM1_P_5(ALT16) TRGM_P_13(ALT17) ESC0_GPI_02(ALT18) QEI3_Z(ALT20) QEO2_Z(ALT21) SEI2_DE(ALT22) SDM1_CLK_2(ALT23)	-	B05

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
E8	D7	PC14	GPIO_C_14(ALT0) UART3_RXD(ALT2) SPI1_DAT2(ALT5) MCAN3_RXD(ALT7) ESC0_GPI_49(ALT10) ESC0_GPO_14(ALT11) FEMC_DQ_19(ALT12) PPI0_DQ_19(ALT13) PWM1_P_6(ALT16) TRGM_P_14(ALT17) ESC0_GPI_01(ALT18) QEI3_B(ALT20) QEO2_B(ALT21) SEI2_RX(ALT22) SDM1_DAT_2(ALT23)	-	B05
C9	C8	PC15	GPIO_C_15(ALT0) GPTMR0_COMP_3(ALT1) UART3_TXD(ALT2) SPI1_DAT3(ALT5) MCAN3_TXD(ALT7) ESC0_GPI_48(ALT10) ESC0_GPO_15(ALT11) FEMC_DM_3(ALT12) PPI0_DM_3(ALT13) XPI0_CA_D_0(ALT14) PWM1_P_7(ALT16) TRGM_P_15(ALT17) ESC0_GPI_00(ALT18) QEI3_A(ALT20) QEO2_A(ALT21) SEI2_TX(ALT22)	-	B05

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
D9	D8	PC16	GPIO_C_16(ALT0) GPTMR3_COMP_0(ALT1) UART4_TXD(ALT2) MCAN4_TXD(ALT7) ESC0_GPI_47(ALT10) ESC0_GPO_16(ALT11) FEMC_DQ_16(ALT12) PPI0_DQ_16(ALT13) XPI0_CA_DQS(ALT14) PWM2_P_0(ALT16) TRGM_P_16(ALT17) SDM1_CLK_3(ALT23)	-	B05
E9	C9	PC17	GPIO_C_17(ALT0) GPTMR3_CAPT_0(ALT1) UART4_RXD(ALT2) MCAN4_RXD(ALT7) ESC0_GPI_46(ALT10) ESC0_GPO_17(ALT11) FEMC_DQ_17(ALT12) PPI0_DQ_17(ALT13) PWM2_P_1(ALT16) TRGM_P_17(ALT17) SDM1_DAT_3(ALT23)	-	B05
A10	A10	PC18	GPIO_C_18(ALT0) GPTMR3_COMP_1(ALT1) UART4_DE(ALT2) UART4_RTS(ALT3) I2C6_SCL(ALT4) MCAN4_STBY(ALT7) ESC0_GPI_45(ALT10) ESC0_GPO_18(ALT11) FEMC_A_04(ALT12) PPI0_DQ_04(ALT13) PWM2_P_2(ALT16) TRGM_P_18(ALT17) ESC0_CTR_0(ALT18) QEI2_H1(ALT20)	-	B06

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
B10	B10	PC19	GPIO_C_19(ALT0) GPTMR3_CAPT_1(ALT1) UART4_CTS(ALT3) I2C6_SDA(ALT4) SPI2_CS_3(ALT5) MCAN5_STBY(ALT7) ESC0_GPI_44(ALT10) ESC0_GPO_19(ALT11) FEMC_A_05(ALT12) PPIO_DQ_05(ALT13) PWM2_P_3(ALT16) TRGM_P_19(ALT17) ESC0_CTR_1(ALT18) QEI2_F(ALT20)	-	B06
A11	A11	PC20	GPIO_C_20(ALT0) UART5_CTS(ALT3) SPI3_SCLK(ALT5) MCAN5_RXD(ALT7) ESC0_GPI_43(ALT10) ESC0_GPO_20(ALT11) FEMC_A_06(ALT12) PPIO_DQ_06(ALT13) PWM2_P_4(ALT16) TRGM_P_20(ALT17) ESC0_CTR_2(ALT18) QEI2_H0(ALT20) SEI1_CK(ALT22)	-	B06

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
B11	B11	PC21	GPIO_C_21(ALT0) GPTMR3_COMP_2(ALT1) UART5_DE(ALT2) UART5_RTS(ALT3) SPI3_CS_0(ALT5) MCAN5_TXD(ALT7) ESC0_GPI_42(ALT10) ESC0_GPO_21(ALT11) FEMC_A_07(ALT12) PPIO_DQ_07(ALT13) PWM2_P_5(ALT16) TRGM_P_21(ALT17) ESC0_CTR_3(ALT18) QEI2_Z(ALT20) QEO1_Z(ALT21) SEI1_DE(ALT22)	-	B06
A12	A12	PC22	GPIO_C_22(ALT0) GPTMR2_CAPT_0(ALT1) UART5_RXD(ALT2) I2C7_SDA(ALT4) SPI3_MISO(ALT5) ESC0_GPI_41(ALT10) ESC0_GPO_22(ALT11) FEMC_SRDY(ALT12) PPIO_CTR_2(ALT13) PWM2_P_6(ALT16) TRGM_P_22(ALT17) QEI2_B(ALT20) QEO1_B(ALT21) SEI1_RX(ALT22)	-	B06

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
B12	A13	PC23	GPIO_C_23(ALT0) GPTMR2_COMP_0(ALT1) UART5_TXD(ALT2) I2C7_SCL(ALT4) SPI3_MOSI(ALT5) ESC0_GPI_40(ALT10) ESC0_GPO_23(ALT11) FEMC_A_08(ALT12) PPIO_DQ_08(ALT13) PWM2_P_7(ALT16) TRGM_P_23(ALT17) QEI2_A(ALT20) QEO1_A(ALT21) SEI1_TX(ALT22)	-	B06
A13	B14	PC24	GPIO_C_24(ALT0) GPTMR2_COMP_1(ALT1) UART6_TXD(ALT2) I2C4_SCL(ALT4) SPI2_CS_2(ALT5) MCAN6_TXD(ALT7) ESC0_GPI_39(ALT10) ESC0_GPO_24(ALT11) FEMC_A_09(ALT12) PPIO_DQ_09(ALT13) PWM3_P_0(ALT16) TRGM_P_24(ALT17)	-	B06
B13	C14	PC25	GPIO_C_25(ALT0) GPTMR2_CAPT_1(ALT1) UART6_RXD(ALT2) I2C4_SDA(ALT4) SPI2_CS_1(ALT5) MCAN6_RXD(ALT7) ESC0_GPI_38(ALT10) ESC0_GPO_25(ALT11) FEMC_A_11(ALT12) PPIO_DQ_11(ALT13) PWM3_P_1(ALT16) TRGM_P_25(ALT17)	-	B06

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
A14	D14	PC26	GPIO_C_26(ALT0) GPTMR2_COMP_2(ALT1) UART6_DE(ALT2) UART6_RTS(ALT3) SPI2_SCLK(ALT5) MCAN6_STBY(ALT7) ESC0_GPI_37(ALT10) ESC0_GPO_26(ALT11) FEMC_A_12(ALT12) PPIO_DQ_12(ALT13) PWM3_P_2(ALT16) TRGM_P_26(ALT17) QE11_H1(ALT20)	-	B06
B14	D13	PC27	GPIO_C_27(ALT0) UART6_CTS(ALT3) SPI2_CS_0(ALT5) ESC0_GPI_36(ALT10) ESC0_GPO_27(ALT11) FEMC_CLK_0(ALT12) PPIO_CTR_0(ALT13) PWM3_P_3(ALT16) TRGM_P_27(ALT17) ESC0_CTR_4(ALT18) QE11_F(ALT20)	-	B06
A15	E14	PC28	GPIO_C_28(ALT0) UART7_CTS(ALT3) I2C5_SDA(ALT4) SPI2_MISO(ALT5) ESC0_GPI_35(ALT10) ESC0_GPO_28(ALT11) FEMC_CKE(ALT12) PPIO_DM_0(ALT13) PWM3_P_4(ALT16) TRGM_P_28(ALT17) ESC0_CTR_5(ALT18) QE11_H0(ALT20) SEI3_CK(ALT22)	-	B06

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
B15	E13	PC29	GPIO_C_29(ALT0) GPTMR3_COMP_3(ALT1) UART7_DE(ALT2) UART7_RTS(ALT3) I2C5_SCL(ALT4) SPI2_MOSI(ALT5) MCAN7_STBY(ALT7) ESC0_GPI_34(ALT10) ESC0_GPO_29(ALT11) FEMC_SCLK_0(ALT12) PPI0_CLK(ALT13) PWM3_P_5(ALT16) TRGM_P_29(ALT17) ESC0_CTR_6(ALT18) QEI1_Z(ALT20) QEO3_Z(ALT21) SEI3_DE(ALT22) SOC_REF0(ALT24)	-	B06
A16	F14	PC30	GPIO_C_30(ALT0) UART7_RXD(ALT2) SPI2_DAT2(ALT5) MCAN7_RXD(ALT7) ESC0_GPI_33(ALT10) ESC0_GPO_30(ALT11) FEMC_SCS_0(ALT12) PPI0_CS_0(ALT13) PWM3_P_6(ALT16) TRGM_P_30(ALT17) ESC0_CTR_7(ALT18) QEI1_A(ALT20) QEO3_B(ALT21) SEI3_RX(ALT22) SOC_REF1(ALT24)	-	B06

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
B16	F13	PC31	GPIO_C_31(ALT0) GPTMR2_COMP_3(ALT1) UART7_TXD(ALT2) SPI2_DAT3(ALT5) MCAN7_TXD(ALT7) ESC0_GPI_32(ALT10) ESC0_GPO_31(ALT11) FEMC_SCS_1(ALT12) PPI0_CS_1(ALT13) PWM3_P_7(ALT16) TRGM_P_31(ALT17) ESC0_CTR_8(ALT18) QE11_B(ALT20) QEO3_A(ALT21) SEI3_TX(ALT22)	-	B06
C10	D9	PD00	GPIO_D_00(ALT0) GPTMR5_COMP_0(ALT1) UART8_TXD(ALT2) MCAN0_TXD(ALT7) ESC0_GPI_31(ALT10) ESC0_GPO_32(ALT11) FEMC_A_02(ALT12) PPI0_DQ_02(ALT13) PWM0_P_0(ALT16) TRGM_P_00(ALT17) ESC0_REFCK(ALT18)	-	B06
D10	C10	PD01	GPIO_D_01(ALT0) GPTMR5_CAPT_0(ALT1) UART8_RXD(ALT2) MCAN0_RXD(ALT7) ESC0_GPI_30(ALT10) ESC0_GPO_33(ALT11) FEMC_A_03(ALT12) PPI0_DQ_03(ALT13) PWM0_P_1(ALT16) TRGM_P_01(ALT17) ESC0_REFCK(ALT18)	-	B06

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
E10	D10	PD02	GPIO_D_02(ALT0) GPTMR5_COMP_1(ALT1) UART8_DE(ALT2) UART8_RTS(ALT3) I2C2_SCL(ALT4) MCAN0_STBY(ALT7) ESC0_GPI_29(ALT10) ESC0_GPO_34(ALT11) FEMC_A_00(ALT12) PPIO_DQ_00(ALT13) PWM0_P_2(ALT16) TRGM_P_02(ALT17) ESC0_SCL(ALT18) QEIO_H1(ALT20)	-	B06
D11	C11	PD03	GPIO_D_03(ALT0) GPTMR5_CAPT_1(ALT1) UART8_CTS(ALT3) I2C2_SDA(ALT4) SPI5_CS_3(ALT5) MCAN1_STBY(ALT7) ESC0_GPI_28(ALT10) ESC0_GPO_35(ALT11) FEMC_A_01(ALT12) PPIO_DQ_01(ALT13) PWM0_P_3(ALT16) TRGM_P_03(ALT17) ESC0_SDA(ALT18) QEIO_F(ALT20)	-	B06

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
E11	D11	PD04	GPIO_D_04(ALT0) UART9_CTS(ALT3) SPI4_SCLK(ALT5) MCAN1_RXD(ALT7) ESC0_GPI_27(ALT10) ESC0_GPO_36(ALT11) FEMC_A_10(ALT12) PPI0_DQ_10(ALT13) PWM0_P_4(ALT16) TRGM_P_04(ALT17) QEIO_H0(ALT20) SEIO_CK(ALT22)	-	B06
C12	B12	PD05	GPIO_D_05(ALT0) GPTMR5_COMP_2(ALT1) UART9_DE(ALT2) UART9_RTS(ALT3) SPI4_CS_0(ALT5) MCAN1_TXD(ALT7) ESC0_GPI_26(ALT10) ESC0_GPO_37(ALT11) FEMC_BA0(ALT12) PPI0_DQ_13(ALT13) PWM0_P_5(ALT16) TRGM_P_05(ALT17) QEIO_Z(ALT20) QEO0_Z(ALT21) SEIO_DE(ALT22)	-	B06

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
D12	C12	PD06	GPIO_D_06(ALT0) GPTMR4_CAPT_0(ALT1) UART9_RXD(ALT2) I2C3_SDA(ALT4) SPI4_MISO(ALT5) ESC0_GPI_25(ALT10) ESC0_GPO_38(ALT11) FEMC_BA1(ALT12) PPIO_DQ_14(ALT13) PWM0_P_6(ALT16) TRGM_P_06(ALT17) QEIO_B(ALT20) QEO0_B(ALT21) SEIO_RX(ALT22)	-	B06
E12	B13	PD07	GPIO_D_07(ALT0) GPTMR4_COMP_0(ALT1) UART9_TXD(ALT2) I2C3_SCL(ALT4) SPI4_MOSI(ALT5) ESC0_GPI_24(ALT10) ESC0_GPO_39(ALT11) FEMC_SCLK_1(ALT12) PPIO_CTR_3(ALT13) PWM0_P_7(ALT16) TRGM_P_07(ALT17) QEIO_A(ALT20) QEO0_A(ALT21) SEIO_TX(ALT22)	-	B06

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
C13	C13	PD08	GPIO_D_08(ALT0) GPTMR4_COMP_1(ALT1) UART10_TXD(ALT2) I2C0_SCL(ALT4) SPI5_CS_2(ALT5) MCAN2_TXD(ALT7) ESC0_GPI_23(ALT10) ESC0_GPO_40(ALT11) FEMC_CS_1(ALT12) PPI0_CS_3(ALT13) PWM1_P_0(ALT16) TRGM_P_08(ALT17)	-	B06
D13	D12	PD09	GPIO_D_09(ALT0) GPTMR4_CAPT_1(ALT1) UART10_RXD(ALT2) I2C0_SDA(ALT4) SPI5_CS_1(ALT5) MCAN2_RXD(ALT7) ESC0_GPI_22(ALT10) ESC0_GPO_41(ALT11) FEMC_DQS(ALT12) PWM1_P_1(ALT16) TRGM_P_09(ALT17)	-	B06
E13	E12	PD10	GPIO_D_10(ALT0) GPTMR4_COMP_2(ALT1) UART10_DE(ALT2) UART10_RTS(ALT3) SPI5_SCLK(ALT5) MCAN2_STBY(ALT7) ESC0_GPI_21(ALT10) ESC0_GPO_42(ALT11) FEMC_RAS(ALT12) PPI0_CTR_1(ALT13) PWM1_P_2(ALT16) TRGM_P_10(ALT17) QEI3_F(ALT20)	-	B06

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
C14	E11	PD11	GPIO_D_11(ALT0) UART10_CTS(ALT3) SPI5_CS_0(ALT5) ESC0_GPI_20(ALT10) ESC0_GPO_43(ALT11) FEMC_CS_0(ALT12) PPI0_CS_2(ALT13) PWM1_P_3(ALT16) TRGM_P_11(ALT17) QEI3_H1(ALT20)	-	B06
D15	F12	PD12	GPIO_D_12(ALT0) UART11_CTS(ALT3) I2C1_SDA(ALT4) SPI5_MISO(ALT5) ESC0_GPI_19(ALT10) ESC0_GPO_44(ALT11) FEMC_WE(ALT12) PPI0_DQ_15(ALT13) PWM1_P_4(ALT16) TRGM_P_12(ALT17) QEI3_H0(ALT20) SEI2_CK(ALT22)	-	B06
C15	F11	PD13	GPIO_D_13(ALT0) GPTMR5_COMP_3(ALT1) UART11_DE(ALT2) UART11_RTS(ALT3) I2C1_SCL(ALT4) SPI5_MOSI(ALT5) MCAN3_STBY(ALT7) ESC0_GPI_18(ALT10) ESC0_GPO_45(ALT11) FEMC_CAS(ALT12) PPI0_DM_1(ALT13) PWM1_P_5(ALT16) TRGM_P_13(ALT17) QEI3_Z(ALT20) QEO2_Z(ALT21) SEI2_DE(ALT22)	-	B06

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
B17	G14	PD14	GPIO_D_14(ALT0) UART11_RXD(ALT2) SPI5_DAT2(ALT5) MCAN3_RXD(ALT7) ESC0_GPI_17(ALT10) ESC0_GPO_46(ALT11) FEMC_DQ_08(ALT12) PPI0_DQ_08(ALT13) PWM1_P_6(ALT16) TRGM_P_14(ALT17) ESC0_REFCK(ALT18) QEI3_B(ALT20) QEO2_B(ALT21) SEI2_RX(ALT22) SYSCTL_CLK_OBS_3(ALT 24)	-	B07
C16	G13	PD15	GPIO_D_15(ALT0) GPTMR4_COMP_3(ALT1) UART11_TXD(ALT2) SPI5_DAT3(ALT5) MCAN3_TXD(ALT7) ESC0_GPI_16(ALT10) ESC0_GPO_47(ALT11) FEMC_DM_1(ALT12) PPI0_DM_1(ALT13) PWM1_P_7(ALT16) TRGM_P_15(ALT17) ESC0_REFCK(ALT18) QEI3_A(ALT20) QEO2_A(ALT21) SEI2_TX(ALT22) SYSCTL_CLK_OBS_2(ALT 24)	-	B07

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
C17	G12	PD16	GPIO_D_16(ALT0) GPTMR7_COMP_0(ALT1) UART12_TXD(ALT2) MCAN4_TXD(ALT7) ESC0_GPI_15(ALT10) ESC0_GPO_48(ALT11) FEMC_DQ_10(ALT12) PPI0_DQ_10(ALT13) PWM2_P_0(ALT16) TRGM_P_16(ALT17) ESC0_GPO_00(ALT18) SYSCTL_CLK_OBS_0(ALT 24)	-	B07
D16	H14	PD17	GPIO_D_17(ALT0) GPTMR7_CAPT_0(ALT1) UART12_RXD(ALT2) MCAN4_RXD(ALT7) ESC0_GPI_14(ALT10) ESC0_GPO_49(ALT11) FEMC_DQ_09(ALT12) PPI0_DQ_09(ALT13) PWM2_P_1(ALT16) TRGM_P_17(ALT17) ESC0_GPO_01(ALT18) SYSCTL_CLK_OBS_1(ALT 24)	-	B07

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
D17	H13	PD18	GPIO_D_18(ALT0) GPTMR7_COMP_1(ALT1) UART12_DE(ALT2) UART12_RTS(ALT3) I2C6_SCL(ALT4) MCAN4_STBY(ALT7) ESC0_GPI_13(ALT10) ESC0_GPO_50(ALT11) FEMC_DQ_12(ALT12) PPI0_DQ_12(ALT13) PWM2_P_2(ALT16) TRGM_P_18(ALT17) ESC0_GPO_02(ALT18) QEI2_H1(ALT20)	-	B07
E16	H12	PD19	GPIO_D_19(ALT0) GPTMR7_CAPT_1(ALT1) UART12_CTS(ALT3) I2C6_SDA(ALT4) SPI6_CS_3(ALT5) MCAN5_STBY(ALT7) ESC0_GPI_12(ALT10) ESC0_GPO_51(ALT11) FEMC_DQ_11(ALT12) PPI0_DQ_11(ALT13) PWM2_P_3(ALT16) TRGM_P_19(ALT17) ESC0_GPO_03(ALT18) QEI2_F(ALT20)	-	B07

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
E17	J14	PD20	GPIO_D_20(ALT0) UART13_CTS(ALT3) SPI7_SCLK(ALT5) MCAN5_RXD(ALT7) ESC0_GPI_11(ALT10) ESC0_GPO_52(ALT11) FEMC_DQ_14(ALT12) PPI0_DQ_14(ALT13) PWM2_P_4(ALT16) TRGM_P_20(ALT17) ESC0_GPO_04(ALT18) QEI2_H0(ALT20) SEI1_CK(ALT22)	-	B07
F16	J13	PD21	GPIO_D_21(ALT0) GPTMR7_COMP_2(ALT1) UART13_DE(ALT2) UART13_RTS(ALT3) SPI7_CS_0(ALT5) MCAN5_TXD(ALT7) ESC0_GPI_10(ALT10) ESC0_GPO_53(ALT11) FEMC_DQ_13(ALT12) PPI0_DQ_13(ALT13) PWM2_P_5(ALT16) TRGM_P_21(ALT17) ESC0_GPO_05(ALT18) QEI2_Z(ALT20) QEO1_Z(ALT21) SEI1_DE(ALT22)	-	B07

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
F17	J12	PD22	GPIO_D_22(ALT0) GPTMR6_CAPT_0(ALT1) UART13_RXD(ALT2) I2C7_SDA(ALT4) SPI7_MISO(ALT5) ESC0_GPI_09(ALT10) ESC0_GPO_54(ALT11) FEMC_DQ_15(ALT12) PPIO_DQ_15(ALT13) PWM2_P_6(ALT16) TRGM_P_22(ALT17) ESC0_GPO_06(ALT18) QEI2_B(ALT20) QEO1_B(ALT21) SEI1_RX(ALT22)	-	B07
E15	F10	PD23	GPIO_D_23(ALT0) GPTMR6_COMP_0(ALT1) UART13_TXD(ALT2) I2C7_SCL(ALT4) SPI7_MOSI(ALT5) ESC0_GPI_08(ALT10) ESC0_GPO_55(ALT11) FEMC_DM_0(ALT12) PPIO_DM_0(ALT13) PWM2_P_7(ALT16) TRGM_P_23(ALT17) ESC0_GPO_07(ALT18) QEI2_A(ALT20) QEO1_A(ALT21) SEI1_TX(ALT22)	-	B07

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
E14	G11	PD24	GPIO_D_24(ALT0) GPTMR6_COMP_1(ALT1) UART14_TXD(ALT2) I2C4_SCL(ALT4) SPI6_CS_2(ALT5) MCAN6_TXD(ALT7) ESC0_GPI_07(ALT10) ESC0_GPO_56(ALT11) FEMC_DQ_06(ALT12) PPIO_DQ_06(ALT13) PWM3_P_0(ALT16) TRGM_P_24(ALT17) ESC0_GPO_08(ALT18) SDM0_DAT_3(ALT23)	-	B07
F15	G10	PD25	GPIO_D_25(ALT0) GPTMR6_CAPT_1(ALT1) UART14_RXD(ALT2) I2C4_SDA(ALT4) SPI6_CS_1(ALT5) MCAN6_RXD(ALT7) ESC0_GPI_06(ALT10) ESC0_GPO_57(ALT11) FEMC_DQ_07(ALT12) PPIO_DQ_07(ALT13) PWM3_P_1(ALT16) TRGM_P_25(ALT17) ESC0_GPO_09(ALT18) SDM0_CLK_3(ALT23)	-	B07

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
F14	H11	PD26	GPIO_D_26(ALT0) GPTMR6_COMP_2(ALT1) UART14_DE(ALT2) UART14_RTS(ALT3) SPI6_SCLK(ALT5) MCAN6_STBY(ALT7) ESC0_GPI_05(ALT10) ESC0_GPO_58(ALT11) FEMC_DQ_05(ALT12) PPIO_DQ_05(ALT13) PWM3_P_2(ALT16) TRGM_P_26(ALT17) ESC0_GPO_10(ALT18) QE11_H1(ALT20) SDM0_CLK_2(ALT23)	-	B07
F13	H10	PD27	GPIO_D_27(ALT0) UART14_CTS(ALT3) SPI6_CS_0(ALT5) ESC0_GPI_04(ALT10) ESC0_GPO_59(ALT11) FEMC_DQ_04(ALT12) PPIO_DQ_04(ALT13) PWM3_P_3(ALT16) TRGM_P_27(ALT17) ESC0_GPO_11(ALT18) QE11_F(ALT20) SDM0_DAT_2(ALT23)	-	B07

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
G14	J11	PD28	GPIO_D_28(ALT0) UART15_CTS(ALT3) I2C5_SDA(ALT4) SPI6_MISO(ALT5) ESC0_GPI_03(ALT10) ESC0_GPO_60(ALT11) FEMC_DQ_03(ALT12) PPIO_DQ_03(ALT13) PWM3_P_4(ALT16) TRGM_P_28(ALT17) ESC0_GPO_12(ALT18) QE11_H0(ALT20) SEI3_CK(ALT22) SDM0_CLK_1(ALT23)	-	B07
G13	J10	PD29	GPIO_D_29(ALT0) GPTMR7_COMP_3(ALT1) UART15_DE(ALT2) UART15_RTS(ALT3) I2C5_SCL(ALT4) SPI6_MOSI(ALT5) MCAN7_STBY(ALT7) ESC0_GPI_02(ALT10) ESC0_GPO_61(ALT11) FEMC_DQ_02(ALT12) PPIO_DQ_02(ALT13) PWM3_P_5(ALT16) TRGM_P_29(ALT17) ESC0_GPO_13(ALT18) QE11_Z(ALT20) QEO3_Z(ALT21) SEI3_DE(ALT22) SDM0_DAT_1(ALT23)	-	B07

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
H15	K12	PD30	GPIO_D_30(ALT0) UART15_RXD(ALT2) SPI6_DAT2(ALT5) MCAN7_RXD(ALT7) ESC0_GPI_01(ALT10) ESC0_GPO_62(ALT11) FEMC_DQ_01(ALT12) PPI0_DQ_01(ALT13) PWM3_P_6(ALT16) TRGM_P_30(ALT17) ESC0_GPO_14(ALT18) QEI1_A(ALT20) QEO3_B(ALT21) SEI3_RX(ALT22) SDM0_CLK_0(ALT23)	-	B07
H14	K11	PD31	GPIO_D_31(ALT0) GPTMR6_COMP_3(ALT1) UART15_TXD(ALT2) SPI6_DAT3(ALT5) MCAN7_TXD(ALT7) ESC0_GPI_00(ALT10) ESC0_GPO_63(ALT11) FEMC_DQ_00(ALT12) PPI0_DQ_00(ALT13) PWM3_P_7(ALT16) TRGM_P_31(ALT17) ESC0_GPO_15(ALT18) QEI1_B(ALT20) QEO3_A(ALT21) SEI3_TX(ALT22) SDM0_DAT_0(ALT23)	-	B07

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
G17	M14	PE00	GPIO_E_00(ALT0) GPTMR1_COMP_0(ALT1) UART0_TXD(ALT2) MCAN0_TXD(ALT7) TSW0_P1_MDC(ALT10) ESC0_CTR_4(ALT11) PPIO_CTR_4(ALT13) PWM0_P_0(ALT16) TRGM_P_00(ALT17) RDC0_PWM_N(ALT20) QEO1_A(ALT21) SEI1_TX(ALT22) SDM1_DAT_2(ALT23) USB0_ID(ALT24) ETH0_EVTO_1(ALT25) TSW0_EVTO_1(ALT26) ESC0_EVTO_1(ALT27)	-	B08
G16	M13	PE01	GPIO_E_01(ALT0) GPTMR1_CAPT_0(ALT1) UART0_RXD(ALT2) MCAN0_RXD(ALT7) DAO_RP(ALT9) TSW0_P1_MDIO(ALT10) ESC0_CTR_5(ALT11) PPIO_CTR_5(ALT13) PWM0_P_1(ALT16) TRGM_P_01(ALT17) RDC0_PWM_P(ALT20) QEO1_B(ALT21) SEI1_RX(ALT22) SDM1_CLK_2(ALT23)	-	B08

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
H17	M12	PE02	GPIO_E_02(ALT0) GPTMR1_COMP_1(ALT1) UART0_DE(ALT2) UART0_RTS(ALT3) I2C2_SCL(ALT4) MCAN0_STBY(ALT7) DAO_LP(ALT9) ESC0_CTR_6(ALT11) PPIO_CTR_6(ALT13) PWM0_P_2(ALT16) TRGM_P_02(ALT17) QEIO_H1(ALT20) QEO1_Z(ALT21) SEI1_DE(ALT22) SDM1_DAT_3(ALT23)	-	B08
H16	N14	PE03	GPIO_E_03(ALT0) GPTMR1_CAPT_1(ALT1) UART0_CTS(ALT3) I2C2_SDA(ALT4) SPI0_CS_3(ALT5) MCAN1_STBY(ALT7) TSW0_P2_MDC(ALT10) ESC0_CTR_1(ALT11) PPIO_CTR_7(ALT13) PWM0_P_3(ALT16) TRGM_P_03(ALT17) QEIO_F(ALT20) RDC1_PWM_N(ALT21) SEI1_CK(ALT22) SDM1_DAT_1(ALT23) USB0_OC(ALT24) TSW0_EVTO_2(ALT26)	-	B08

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
J17	N13	PE04	GPIO_E_04(ALT0) UART1_CTS(ALT3) SPI1_SCLK(ALT5) MCAN1_RXD(ALT7) DAO_RN(ALT9) TSW0_P2_MDIO(ALT10) ESC0_CTR_2(ALT11) PWM0_P_4(ALT16) TRGM_P_04(ALT17) QEIO_H0(ALT20) RDC1_PWM_P(ALT21) SEIO_CK(ALT22) SDM1_CLK_1(ALT23) ETH0_EVTI_1(ALT25) TSW0_EVTI_1(ALT26) ESC0_EVTI_1(ALT27)	-	B08
J16	P13	PE05	GPIO_E_05(ALT0) GPTMR1_COMP_2(ALT1) UART1_DE(ALT2) UART1_RTS(ALT3) SPI1_CS_0(ALT5) MCAN1_TXD(ALT7) DAO_LN(ALT9) ESC0_CTR_3(ALT11) PWM0_P_5(ALT16) TRGM_P_05(ALT17) QEIO_Z(ALT20) QEO0_Z(ALT21) SEIO_DE(ALT22) SDM1_CLK_3(ALT23) TSW0_EVTO_3(ALT26)	-	B08

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
K17	-	PE06	GPIO_E_06(ALT0) GPTMR0_CAPT_0(ALT1) UART1_RXD(ALT2) I2C3_SDA(ALT4) SPI1_MISO(ALT5) TSW0_P3_MDC(ALT10) ESC0_REFCK(ALT11) PWM0_P_6(ALT16) TRGM_P_06(ALT17) ETH0_CRS(ALT18) QEIO_B(ALT20) QEO0_B(ALT21) SEIO_RX(ALT22) SDM1_DAT_0(ALT23) USB0_PWR(ALT24) ETH0_EVTO_0(ALT25) TSW0_EVTO_0(ALT26) ESC0_EVTO_0(ALT27)	-	B08
K16	-	PE07	GPIO_E_07(ALT0) GPTMR0_COMP_0(ALT1) UART1_TXD(ALT2) I2C3_SCL(ALT4) SPI1_MOSI(ALT5) TSW0_P3_MDIO(ALT10) ESC0_CTR_0(ALT11) PWM0_P_7(ALT16) TRGM_P_07(ALT17) ETH0_COL(ALT18) QEIO_A(ALT20) QEO0_A(ALT21) SEIO_TX(ALT22) SDM1_CLK_0(ALT23) ETH0_EVTI_0(ALT25) TSW0_EVTI_0(ALT26) ESC0_EVTI_0(ALT27)	-	B08

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
J15	-	PE08	GPIO_E_08(ALT0) GPTMR0_COMP_1(ALT1) UART2_TXD(ALT2) I2C0_SCL(ALT4) SPI0_CS_2(ALT5) MCAN2_TXD(ALT7) TSW0_P1_RXDV(ALT10) ESC0_P2_RXDV(ALT11) PWM1_P_0(ALT16) TRGM_P_08(ALT17) RDC0_PWM_N(ALT20) QEO2_B(ALT21) SEI2_TX(ALT22)	-	B09
J14	-	PE09	GPIO_E_09(ALT0) GPTMR0_CAPT_1(ALT1) UART2_RXD(ALT2) I2C0_SDA(ALT4) SPI0_CS_1(ALT5) MCAN2_RXD(ALT7) TSW0_P1_RXD_0(ALT10) ESC0_P2_RXD_0(ALT11) PWM1_P_1(ALT16) TRGM_P_09(ALT17) RDC0_PWM_P(ALT20) QEO2_A(ALT21) SEI2_RX(ALT22)	-	B09
H13	-	PE10	GPIO_E_10(ALT0) GPTMR0_COMP_2(ALT1) UART2_DE(ALT2) UART2_RTS(ALT3) SPI0_SCLK(ALT5) MCAN2_STBY(ALT7) TSW0_P1_RXD_1(ALT10) ESC0_P2_RXD_1(ALT11) PWM1_P_2(ALT16) TRGM_P_10(ALT17) QEI3_F(ALT20) QEO2_Z(ALT21) SEI2_DE(ALT22)	-	B09

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
K15	-	PE11	GPIO_E_11(ALT0) UART2_CTS(ALT3) SPI0_CS_0(ALT5) TSW0_P1_RXD_2(ALT10) ESC0_P2_RXD_2(ALT11) PWM1_P_3(ALT16) TRGM_P_11(ALT17) QEI3_H1(ALT20) RDC1_PWM_N(ALT21) SEI2_CK(ALT22)	-	B09
K14	-	PE12	GPIO_E_12(ALT0) UART3_CTS(ALT3) I2C1_SDA(ALT4) SPI0_MISO(ALT5) TSW0_P1_RXD_3(ALT10) ESC0_P2_RXD_3(ALT11) PWM1_P_4(ALT16) TRGM_P_12(ALT17) QEI3_H0(ALT20) RDC1_PWM_P(ALT21) SEI3_CK(ALT22)	-	B09
J13	-	PE13	GPIO_E_13(ALT0) GPTMR1_COMP_3(ALT1) UART3_DE(ALT2) UART3_RTS(ALT3) I2C1_SCL(ALT4) SPI0_MOSI(ALT5) MCAN3_STBY(ALT7) TSW0_P1_RXCK(ALT10) ESC0_P2_RXCK(ALT11) PWM1_P_5(ALT16) TRGM_P_13(ALT17) QEI3_Z(ALT20) QEO3_Z(ALT21) SEI3_DE(ALT22)	-	B09

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
L14	-	PE14	GPIO_E_14(ALT0) UART3_RXD(ALT2) SPI0_DAT2(ALT5) MCAN3_RXD(ALT7) TSW0_P1_TXCK(ALT10) ESC0_P2_TXCK(ALT11) PWM1_P_6(ALT16) TRGM_P_14(ALT17) QEI3_B(ALT20) QEO3_B(ALT21) SEI3_RX(ALT22)	-	B09
L13	-	PE15	GPIO_E_15(ALT0) GPTMR0_COMP_3(ALT1) UART3_TXD(ALT2) SPI0_DAT3(ALT5) MCAN3_TXD(ALT7) TSW0_P1_TXD_0(ALT10) ESC0_P2_TXD_0(ALT11) PWM1_P_7(ALT16) TRGM_P_15(ALT17) QEI3_A(ALT20) QEO3_A(ALT21) SEI3_TX(ALT22)	-	B09
K13	-	PE16	GPIO_E_16(ALT0) GPTMR3_COMP_0(ALT1) UART4_TXD(ALT2) MCAN4_TXD(ALT7) TSW0_P1_TXD_1(ALT10) ESC0_P2_TXD_1(ALT11) PWM2_P_0(ALT16) TRGM_P_16(ALT17) RDC0_PWM_N(ALT20) QEO1_A(ALT21) SEI1_TX(ALT22)	-	B09

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
M15	-	PE17	GPIO_E_17(ALT0) GPTMR3_CAPT_0(ALT1) UART4_RXD(ALT2) MCAN4_RXD(ALT7) TSW0_P1_TXD_2(ALT10) ESC0_P2_TXD_2(ALT11) PWM2_P_1(ALT16) TRGM_P_17(ALT17) RDC0_PWM_P(ALT20) QEO1_B(ALT21) SEI1_RX(ALT22)	-	B09
M14	-	PE18	GPIO_E_18(ALT0) GPTMR3_COMP_1(ALT1) UART4_DE(ALT2) UART4_RTS(ALT3) I2C6_SCL(ALT4) MCAN4_STBY(ALT7) TSW0_P1_TXD_3(ALT10) ESC0_P2_TXD_3(ALT11) PWM2_P_2(ALT16) TRGM_P_18(ALT17) QE12_H1(ALT20) QEO1_Z(ALT21) SEI1_DE(ALT22)	-	B09
M13	-	PE19	GPIO_E_19(ALT0) GPTMR3_CAPT_1(ALT1) UART4_CTS(ALT3) I2C6_SDA(ALT4) SPI3_CS_3(ALT5) MCAN5_STBY(ALT7) TSW0_P1_TXEN(ALT10) ESC0_P2_TXEN(ALT11) PWM2_P_3(ALT16) TRGM_P_19(ALT17) QE12_F(ALT20) RDC1_PWM_N(ALT21) SEI1_CK(ALT22)	-	B09

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
R17	-	PE20	GPIO_E_20(ALT0) UART5_CTS(ALT3) SPI2_SCLK(ALT5) MCAN5_RXD(ALT7) I2S1_FCLK(ALT8) TSW0_P3_RXDV(ALT10) ESC0_P2_RXDV(ALT11) PWM2_P_4(ALT16) TRGM_P_20(ALT17) ETH0_RXDV(ALT18) QEI2_H0(ALT20) RDC1_PWM_P(ALT21) SEI0_CK(ALT22)	-	B10
R16	-	PE21	GPIO_E_21(ALT0) GPTMR3_COMP_2(ALT1) UART5_DE(ALT2) UART5_RTS(ALT3) SPI2_CS_0(ALT5) MCAN5_TXD(ALT7) I2S1_RXD_2(ALT8) TSW0_P3_RXD_0(ALT10) ESC0_P2_RXD_0(ALT11) PWM2_P_5(ALT16) TRGM_P_21(ALT17) ETH0_RXD_0(ALT18) QEI2_Z(ALT20) QEO0_Z(ALT21) SEI0_DE(ALT22)	-	B10

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
R15	-	PE22	GPIO_E_22(ALT0) GPTMR2_CAPT_0(ALT1) UART5_RXD(ALT2) I2C7_SDA(ALT4) SPI2_MISO(ALT5) I2S1_RXD_0(ALT8) TSW0_P3_RXD_1(ALT10) ESC0_P2_RXD_1(ALT11) PWM2_P_6(ALT16) TRGM_P_22(ALT17) ETH0_RXD_1(ALT18) QEI2_B(ALT20) QEO0_B(ALT21) SEI0_RX(ALT22)	-	B10
T17	-	PE23	GPIO_E_23(ALT0) GPTMR2_COMP_0(ALT1) UART5_TXD(ALT2) I2C7_SCL(ALT4) SPI2_MOSI(ALT5) I2S1_MCLK(ALT8) TSW0_P3_RXD_2(ALT10) ESC0_P2_RXD_2(ALT11) PWM2_P_7(ALT16) TRGM_P_23(ALT17) ETH0_RXD_2(ALT18) QEI2_A(ALT20) QEO0_A(ALT21) SEI0_TX(ALT22)	-	B10

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
T16	-	PE24	GPIO_E_24(ALT0) GPTMR2_COMP_1(ALT1) UART6_TXD(ALT2) I2C4_SCL(ALT4) SPI3_CS_2(ALT5) MCAN6_TXD(ALT7) I2S1_RXD_3(ALT8) TSW0_P3_RXD_3(ALT10) ESC0_P2_RXD_3(ALT11) PWM3_P_0(ALT16) TRGM_P_24(ALT17) ETH0_RXD_3(ALT18) RDC0_PWM_N(ALT20) QEO2_A(ALT21) SEI2_TX(ALT22)	-	B10
U16	-	PE25	GPIO_E_25(ALT0) GPTMR2_CAPT_1(ALT1) UART6_RXD(ALT2) I2C4_SDA(ALT4) SPI3_CS_1(ALT5) MCAN6_RXD(ALT7) I2S1_RXD_1(ALT8) TSW0_P3_RXCK(ALT10) ESC0_P2_RXCK(ALT11) PWM3_P_1(ALT16) TRGM_P_25(ALT17) ETH0_RXCK(ALT18) RDC0_PWM_P(ALT20) QEO2_B(ALT21) SEI2_RX(ALT22)	-	B10

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
N17	-	PE26	GPIO_E_26(ALT0) GPTMR2_COMP_2(ALT1) UART6_DE(ALT2) UART6_RTS(ALT3) SPI3_SCLK(ALT5) MCAN6_STBY(ALT7) I2S1_MCLK(ALT8) TSW0_P3_TXCK(ALT10) ESC0_P2_TXCK(ALT11) PWM3_P_2(ALT16) TRGM_P_26(ALT17) ETH0_TXCK(ALT18) QE11_H1(ALT20) QEO2_Z(ALT21) SEI2_DE(ALT22)	-	B10
N16	-	PE27	GPIO_E_27(ALT0) UART6_CTS(ALT3) SPI3_CS_0(ALT5) I2S1_TXD_1(ALT8) TSW0_P3_TXD_0(ALT10) ESC0_P2_TXD_0(ALT11) PWM3_P_3(ALT16) TRGM_P_27(ALT17) ETH0_TXD_0(ALT18) QE11_F(ALT20) RDC1_PWM_N(ALT21) SEI2_CK(ALT22)	-	B10

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
N15	-	PE28	GPIO_E_28(ALT0) UART7_CTS(ALT3) I2C5_SDA(ALT4) SPI3_MISO(ALT5) I2S1_TXD_2(ALT8) TSW0_P3_TXD_1(ALT10) ESC0_P2_TXD_1(ALT11) PWM3_P_4(ALT16) TRGM_P_28(ALT17) ETH0_TXD_1(ALT18) QE11_H0(ALT20) RDC1_PWM_P(ALT21) SEI3_CK(ALT22)	-	B10
P17	-	PE29	GPIO_E_29(ALT0) GPTMR3_COMP_3(ALT1) UART7_DE(ALT2) UART7_RTS(ALT3) I2C5_SCL(ALT4) SPI3_MOSI(ALT5) MCAN7_STBY(ALT7) I2S1_TXD_0(ALT8) TSW0_P3_TXD_2(ALT10) ESC0_P2_TXD_2(ALT11) PWM3_P_5(ALT16) TRGM_P_29(ALT17) ETH0_TXD_2(ALT18) QE11_Z(ALT20) QEO3_Z(ALT21) SEI3_DE(ALT22)	-	B10

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
P16	-	PE30	GPIO_E_30(ALT0) UART7_RXD(ALT2) SPI3_DAT2(ALT5) MCAN7_RXD(ALT7) I2S1_TXD_3(ALT8) TSW0_P3_TXD_3(ALT10) ESC0_P2_TXD_3(ALT11) PWM3_P_6(ALT16) TRGM_P_30(ALT17) ETH0_TXD_3(ALT18) QE11_A(ALT20) QEO3_B(ALT21) SEI3_RX(ALT22)	-	B10
P15	-	PE31	GPIO_E_31(ALT0) GPTMR2_COMP_3(ALT1) UART7_TXD(ALT2) SPI3_DAT3(ALT5) MCAN7_TXD(ALT7) I2S1_BCLK(ALT8) TSW0_P3_TXEN(ALT10) ESC0_P2_TXEN(ALT11) PWM3_P_7(ALT16) TRGM_P_31(ALT17) ETH0_TXEN(ALT18) QE11_B(ALT20) QEO3_A(ALT21) SEI3_TX(ALT22)	-	B10
T13	N10	PF00	GPIO_F_00(ALT0) GPTMR5_COMP_0(ALT1) UART8_TXD(ALT2) MCAN0_TXD(ALT7) DAO_LN(ALT9) TSW0_P3_MDC(ALT10) ESC0_MDC(ALT11) PWM0_P_0(ALT16) TRGM_P_00(ALT17) ETH0_MDC(ALT18) QEO1_A(ALT21) SEI1_TX(ALT22)	ADC0_IN08 ADC1_IN08 ACMP0_CH0_I NN7 ACMP1_CH0_I NN7	B11

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
N12	L10	PF01	GPIO_F_01(ALT0) GPTMR5_CAPT_0(ALT1) UART8_RXD(ALT2) MCAN0_RXD(ALT7) DAO_LP(ALT9) TSW0_P3_MDIO(ALT10) ESC0_MDIO(ALT11) PWM0_P_1(ALT16) TRGM_P_01(ALT17) ETH0_MDIO(ALT18) QEO1_B(ALT21) SEI1_RX(ALT22)	ADC0_IN12 ADC1_IN12 ACMP0_CH1_I NN7 ACMP1_CH1_I NN7	B11
U12	P11	PF02	GPIO_F_02(ALT0) GPTMR5_COMP_1(ALT1) UART8_DE(ALT2) UART8_RTS(ALT3) I2C2_SCL(ALT4) MCAN0_STBY(ALT7) TSW0_P3_TXCK(ALT10) ESC0_P1_TXCK(ALT11) PWM0_P_2(ALT16) TRGM_P_02(ALT17) ETH0_TXCK(ALT18) QEIO_H1(ALT20) QEO1_Z(ALT21) SEI1_DE(ALT22)	ADC0_IN11 ADC1_IN11 ACMP0_CH1_I NP7 ACMP1_CH1_I NP7	B11

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
N13	M9	PF03	GPIO_F_03(ALT0) GPTMR5_CAPT_1(ALT1) UART8_CTS(ALT3) I2C2_SDA(ALT4) SPI4_CS_3(ALT5) MCAN1_STBY(ALT7) DAO_RN(ALT9) TSW0_P3_TXD_0(ALT10) ESC0_P1_TXD_0(ALT11) PWM0_P_3(ALT16) TRGM_P_03(ALT17) ETH0_TXD_0(ALT18) QEIO_F(ALT20) SEI1_CK(ALT22)	ADC0_IN13 ADC1_IN13 ACMP0_CH0_I NP7 ACMP1_CH0_I NP7	B11
N14	M8	PF04	GPIO_F_04(ALT0) UART9_CTS(ALT3) SPI5_SCLK(ALT5) MCAN1_RXD(ALT7) DAO_RP(ALT9) TSW0_P3_TXD_1(ALT10) ESC0_P1_TXD_1(ALT11) PWM0_P_4(ALT16) TRGM_P_04(ALT17) ETH0_TXD_1(ALT18) QEIO_H0(ALT20) SEIO_CK(ALT22)	ADC0_IN03 ADC1_IN03 ACMP0_CH0_I NP4 ACMP0_CH1_I NP4 ACMP1_CH0_I NP4 ACMP1_CH1_I NP4	B11

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
R14	L8	PF05	GPIO_F_05(ALT0) GPTMR5_COMP_2(ALT1) UART9_DE(ALT2) UART9_RTS(ALT3) SPI5_CS_0(ALT5) MCAN1_TXD(ALT7) TSW0_P3_TXD_2(ALT10) ESC0_P1_TXD_2(ALT11) PWM0_P_5(ALT16) TRGM_P_05(ALT17) ETH0_TXD_2(ALT18) QEIO_Z(ALT20) QEO0_Z(ALT21) SEIO_DE(ALT22)	ADC0_IN02 ADC1_IN02 ACMP0_CH0_I NN4 ACMP0_CH1_I NN4 ACMP1_CH0_I NN4 ACMP1_CH1_I NN4	B11
U11	P12	PF06	GPIO_F_06(ALT0) GPTMR4_CAPT_0(ALT1) UART9_RXD(ALT2) I2C3_SDA(ALT4) SPI5_MISO(ALT5) TSW0_P3_TXD_3(ALT10) ESC0_P1_TXD_3(ALT11) PWM0_P_6(ALT16) TRGM_P_06(ALT17) ETH0_TXD_3(ALT18) QEIO_B(ALT20) QEO0_B(ALT21) SEIO_RX(ALT22)	ADC0_IN14 ADC1_IN14 ACMP0_CH0_I NN5 ACMP0_CH1_I NN5 ACMP1_CH0_I NN5 ACMP1_CH1_I NN5	B11

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
R13	M11	PF07	GPIO_F_07(ALT0) GPTMR4_COMP_0(ALT1) UART9_TXD(ALT2) I2C3_SCL(ALT4) SPI5_MOSI(ALT5) TSW0_P3_TXEN(ALT10) ESC0_P1_TXEN(ALT11) PWM0_P_7(ALT16) TRGM_P_07(ALT17) ETH0_TXEN(ALT18) QEIO_A(ALT20) QEO0_A(ALT21) SEIO_TX(ALT22)	ADC0_IN15 ADC1_IN15 ACMP0_CH0_I NN3 ACMP0_CH1_I NN3 ACMP1_CH0_I NN3 ACMP1_CH1_I NN3	B11
R12	L11	PF08	GPIO_F_08(ALT0) GPTMR4_COMP_1(ALT1) UART10_TXD(ALT2) I2C0_SCL(ALT4) SPI4_CS_2(ALT5) MCAN2_TXD(ALT7) TSW0_P3_RXDV(ALT10) ESC0_P1_RXDV(ALT11) PWM1_P_0(ALT16) TRGM_P_08(ALT17) ETH0_RXDV(ALT18) QEO2_B(ALT21) SEI2_TX(ALT22)	ADC0_IN10 ADC1_IN10 ACMP0_CH0_I NP5 ACMP0_CH1_I NP5 ACMP1_CH0_I NP5 ACMP1_CH1_I NP5	B11
P13	M10	PF09	GPIO_F_09(ALT0) GPTMR4_CAPT_1(ALT1) UART10_RXD(ALT2) I2C0_SDA(ALT4) SPI4_CS_1(ALT5) MCAN2_RXD(ALT7) TSW0_P3_RXD_0(ALT10) ESC0_P1_RXD_0(ALT11) PWM1_P_1(ALT16) TRGM_P_09(ALT17) ETH0_RXD_0(ALT18) QEO2_A(ALT21) SEI2_RX(ALT22)	ADC0_IN09 ADC1_IN09 ACMP0_CH0_I NP3 ACMP0_CH1_I NP3 ACMP1_CH0_I NP3 ACMP1_CH1_I NP3	B11

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
U13	P10	PF10	GPIO_F_10(ALT0) GPTMR4_COMP_2(ALT1) UART10_DE(ALT2) UART10_RTS(ALT3) SPI4_SCLK(ALT5) MCAN2_STBY(ALT7) TSW0_P3_RXD_1(ALT10) ESC0_P1_RXD_1(ALT11) PWM1_P_2(ALT16) TRGM_P_10(ALT17) ETH0_RXD_1(ALT18) QEI3_F(ALT20) QEO2_Z(ALT21) SEI2_DE(ALT22)	ADC0_IN01 ADC1_IN01 ACMP0_CH0_I NN6 ACMP0_CH1_I NN6 ACMP1_CH0_I NN6 ACMP1_CH1_I NN6	B11
P12	L9	PF11	GPIO_F_11(ALT0) UART10_CTS(ALT3) SPI4_CS_0(ALT5) TSW0_P3_RXD_2(ALT10) ESC0_P1_RXD_2(ALT11) PWM1_P_3(ALT16) TRGM_P_11(ALT17) ETH0_RXD_2(ALT18) QEI3_H1(ALT20) SEI2_CK(ALT22)	ADC0_IN00 ADC1_IN00 ACMP0_CH0_I NP6 ACMP0_CH1_I NP6 ACMP1_CH0_I NP6 ACMP1_CH1_I NP6	B11
T14	N11	PF12	GPIO_F_12(ALT0) UART11_CTS(ALT3) I2C1_SDA(ALT4) SPI4_MISO(ALT5) TSW0_P3_RXD_3(ALT10) ESC0_P1_RXD_3(ALT11) PWM1_P_4(ALT16) TRGM_P_12(ALT17) ETH0_RXD_3(ALT18) QEI3_H0(ALT20) SEI3_CK(ALT22)	ADC0_IN05 ADC1_IN05 ACMP0_CH0_I NN2 ACMP0_CH1_I NN2 ACMP1_CH0_I NN2 ACMP1_CH1_I NN2	B11

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
U14	N12	PF13	GPIO_F_13(ALT0) GPTMR5_COMP_3(ALT1) UART11_DE(ALT2) UART11_RTS(ALT3) I2C1_SCL(ALT4) SPI4_MOSI(ALT5) MCAN3_STBY(ALT7) TSW0_P3_RXCK(ALT10) ESC0_P1_RXCK(ALT11) PWM1_P_5(ALT16) TRGM_P_13(ALT17) ETH0_RXCK(ALT18) QEI3_Z(ALT20) QEO3_Z(ALT21) SEI3_DE(ALT22)	ADC0_IN04 ADC1_IN04 ACMP0_CH0_I NP2 ACMP0_CH1_I NP2 ACMP1_CH0_I NP2 ACMP1_CH1_I NP2	B11
U15	N9	PF14	GPIO_F_14(ALT0) UART11_RXD(ALT2) SPI4_DAT2(ALT5) MCAN3_RXD(ALT7) TSW0_P3_RXER(ALT10) ESC0_P1_RXER(ALT11) PWM1_P_6(ALT16) TRGM_P_14(ALT17) ETH0_RXER(ALT18) QEI3_B(ALT20) QEO3_B(ALT21) SEI3_RX(ALT22)	ADC0_IN06 ADC1_IN06 ACMP0_CH0_I NN1 ACMP0_CH1_I NN1 ACMP1_CH0_I NN1 ACMP1_CH1_I NN1	B11

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
T15	P9	PF15	GPIO_F_15(ALT0) GPTMR4_COMP_3(ALT1) UART11_TXD(ALT2) SPI4_DAT3(ALT5) MCAN3_TXD(ALT7) TSW0_P1_RXER(ALT10) ESC0_P2_RXER(ALT11) PWM1_P_7(ALT16) TRGM_P_15(ALT17) ETH0_TXER(ALT18) QEI3_A(ALT20) QEO3_A(ALT21) SEI3_TX(ALT22)	ADC0_IN07 ADC1_IN07 ACMP0_CH0_I NP1 ACMP0_CH1_I NP1 ACMP1_CH0_I NP1 ACMP1_CH1_I NP1	B11
U9	N7	PF16	GPIO_F_16(ALT0) GPTMR7_COMP_0(ALT1) UART12_TXD(ALT2) MCAN4_TXD(ALT7) PWM2_P_0(ALT16) TRGM_P_16(ALT17) SDM0_DAT_0(ALT23)	ADC2_IN08 ADC3_IN08 ACMP2_CH0_I NN7 ACMP3_CH0_I NN7	B12
U10	P7	PF17	GPIO_F_17(ALT0) GPTMR7_CAPT_0(ALT1) UART12_RXD(ALT2) MCAN4_RXD(ALT7) PWM2_P_1(ALT16) TRGM_P_17(ALT17) SDM0_CLK_0(ALT23)	ADC2_IN12 ADC3_IN12 ACMP2_CH1_I NN7 ACMP3_CH1_I NN7	B12

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
T10	P8	PF18	GPIO_F_18(ALT0) GPTMR7_COMP_1(ALT1) UART12_DE(ALT2) UART12_RTS(ALT3) I2C6_SCL(ALT4) MCAN4_STBY(ALT7) PWM2_P_2(ALT16) TRGM_P_18(ALT17) SDM0_DAT_1(ALT23) USB0_PWR(ALT24) ETH0_EVTO_0(ALT25) TSW0_EVTO_0(ALT26) ESC0_EVTO_0(ALT27)	ADC2_IN13 ADC3_IN13 ACMP2_CH0_I NP7 ACMP3_CH0_I NP7	B12
T8	M5	PF19	GPIO_F_19(ALT0) GPTMR7_CAPT_1(ALT1) UART12_CTS(ALT3) I2C6_SDA(ALT4) SPI7_CS_3(ALT5) MCAN5_STBY(ALT7) PWM2_P_3(ALT16) TRGM_P_19(ALT17) SDM0_CLK_1(ALT23) USB0_PWR(ALT24) TSW0_EVTO_2(ALT26)	ADC2_IN11 ADC3_IN11 ACMP2_CH1_I NP7 ACMP3_CH1_I NP7	B12
T11	N6	PF20	GPIO_F_20(ALT0) UART13_CTS(ALT3) SPI6_SCLK(ALT5) MCAN5_RXD(ALT7) PWM2_P_4(ALT16) TRGM_P_20(ALT17) SDM0_DAT_3(ALT23) USB0_OC(ALT24) ETH0_EVTO_1(ALT25) TSW0_EVTO_1(ALT26) ESC0_EVTO_1(ALT27)	ADC2_IN03 ADC3_IN03 ACMP2_CH0_I NP4 ACMP2_CH1_I NP4 ACMP3_CH0_I NP4 ACMP3_CH1_I NP4	B12

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
N11	L6	PF21	GPIO_F_21(ALT0) GPTMR7_COMP_2(ALT1) UART13_DE(ALT2) UART13_RTS(ALT3) SPI6_CS_0(ALT5) MCAN5_TXD(ALT7) PWM2_P_5(ALT16) TRGM_P_21(ALT17) SDM0_DAT_2(ALT23) USB0_ID(ALT24) ETH0_EVTI_0(ALT25) TSW0_EVTI_0(ALT26) ESC0_EVTI_0(ALT27)	ADC2_IN02 ADC3_IN02 ACMP2_CH0_I NN4 ACMP2_CH1_I NN4 ACMP3_CH0_I NN4 ACMP3_CH1_I NN4	B12
T9	N8	PF22	GPIO_F_22(ALT0) GPTMR6_CAPT_0(ALT1) UART13_RXD(ALT2) I2C7_SDA(ALT4) SPI6_MISO(ALT5) PWM2_P_6(ALT16) TRGM_P_22(ALT17) SDM0_CLK_2(ALT23) USB0_ID(ALT24) ETH0_EVTI_1(ALT25) TSW0_EVTI_1(ALT26) ESC0_EVTI_1(ALT27)	ADC2_IN14 ADC3_IN14 ACMP2_CH0_I NN5 ACMP2_CH1_I NN5 ACMP3_CH0_I NN5 ACMP3_CH1_I NN5	B12
R8	L5	PF23	GPIO_F_23(ALT0) GPTMR6_COMP_0(ALT1) UART13_TXD(ALT2) I2C7_SCL(ALT4) SPI6_MOSI(ALT5) PWM2_P_7(ALT16) TRGM_P_23(ALT17) SDM0_CLK_3(ALT23) USB0_OC(ALT24)	ADC2_IN15 ADC3_IN15 ACMP2_CH0_I NN3 ACMP2_CH1_I NN3 ACMP3_CH0_I NN3 ACMP3_CH1_I NN3	B12

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
P9	M6	PF24	GPIO_F_24(ALT0) GPTMR6_COMP_1(ALT1) UART14_TXD(ALT2) I2C4_SCL(ALT4) SPI7_CS_2(ALT5) MCAN6_TXD(ALT7) PWM3_P_0(ALT16) TRGM_P_24(ALT17) SDM1_DAT_0(ALT23)	ADC2_IN10 ADC3_IN10 ACMP2_CH0_I NP5 ACMP2_CH1_I NP5 ACMP3_CH0_I NP5 ACMP3_CH1_I NP5	B12
P10	L7	PF25	GPIO_F_25(ALT0) GPTMR6_CAPT_1(ALT1) UART14_RXD(ALT2) I2C4_SDA(ALT4) SPI7_CS_1(ALT5) MCAN6_RXD(ALT7) PWM3_P_1(ALT16) TRGM_P_25(ALT17) SDM1_CLK_0(ALT23)	ADC2_IN09 ADC3_IN09 ACMP2_CH0_I NP3 ACMP2_CH1_I NP3 ACMP3_CH0_I NP3 ACMP3_CH1_I NP3	B12
T12	P6	PF26	GPIO_F_26(ALT0) GPTMR6_COMP_2(ALT1) UART14_DE(ALT2) UART14_RTS(ALT3) SPI7_SCLK(ALT5) MCAN6_STBY(ALT7) PWM3_P_2(ALT16) TRGM_P_26(ALT17) SDM1_DAT_1(ALT23) TSW0_EVTO_3(ALT26)	ADC2_IN01 ADC3_IN01 ACMP2_CH0_I NN6 ACMP2_CH1_I NN6 ACMP3_CH0_I NN6 ACMP3_CH1_I NN6	B12

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
P11	M7	PF27	GPIO_F_27(ALT0) UART14_CTS(ALT3) SPI7_CS_0(ALT5) PWM3_P_3(ALT16) TRGM_P_27(ALT17) SDM1_CLK_1(ALT23)	ADC2_IN00 ADC3_IN00 ACMP2_CH0_I NP6 ACMP2_CH1_I NP6 ACMP3_CH0_I NP6 ACMP3_CH1_I NP6	B12
R10	P5	PF28	GPIO_F_28(ALT0) UART15_CTS(ALT3) I2C5_SDA(ALT4) SPI7_MISO(ALT5) PWM3_P_4(ALT16) TRGM_P_28(ALT17) SDM1_DAT_2(ALT23)	ADC2_IN05 ADC3_IN05 ACMP2_CH0_I NN2 ACMP2_CH1_I NN2 ACMP3_CH0_I NN2 ACMP3_CH1_I NN2	B12
N10	M4	PF29	GPIO_F_29(ALT0) GPTMR7_COMP_3(ALT1) UART15_DE(ALT2) UART15_RTS(ALT3) I2C5_SCL(ALT4) SPI7_MOSI(ALT5) MCAN7_STBY(ALT7) PWM3_P_5(ALT16) TRGM_P_29(ALT17) SDM1_CLK_2(ALT23)	ADC2_IN04 ADC3_IN04 ACMP2_CH0_I NP2 ACMP2_CH1_I NP2 ACMP3_CH0_I NP2 ACMP3_CH1_I NP2	B12

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
N9	L4	PF30	GPIO_F_30(ALT0) UART15_RXD(ALT2) SPI7_DAT2(ALT5) MCAN7_RXD(ALT7) PWM3_P_6(ALT16) TRGM_P_30(ALT17) SDM1_CLK_3(ALT23)	ADC2_IN06 ADC3_IN06 ACMP2_CH0_I NN1 ACMP2_CH1_I NN1 ACMP3_CH0_I NN1 ACMP3_CH1_I NN1	B12
R9	N5	PF31	GPIO_F_31(ALT0) GPTMR6_COMP_3(ALT1) UART15_TXD(ALT2) SPI7_DAT3(ALT5) MCAN7_TXD(ALT7) PWM3_P_7(ALT16) TRGM_P_31(ALT17) SDM1_DAT_3(ALT23)	ADC2_IN07 ADC3_IN07 ACMP2_CH0_I NP1 ACMP2_CH1_I NP1 ACMP3_CH0_I NP1 ACMP3_CH1_I NP1	B12
-	-	PV00	GPIO_V_00(ALT0) GPTMR1_COMP_0(ALT1) UART0_TXD(ALT2) MCAN0_TXD(ALT7) TSW0_P1_RXDV(ALT10) ESC0_P0_RXDV(ALT11)	-	B01
-	-	PV01	GPIO_V_01(ALT0) GPTMR1_CAPT_0(ALT1) UART0_RXD(ALT2) MCAN0_RXD(ALT7) TSW0_P1_RXD_0(ALT10) ESC0_P0_RXD_0(ALT11)	-	B01

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
-	-	PV02	GPIO_V_02(ALT0) GPTMR1_COMP_1(ALT1) UART0_DE(ALT2) UART0_RTS(ALT3) I2C2_SCL(ALT4) MCAN0_STBY(ALT7) TSW0_P1_RXD_1(ALT10) ESC0_P0_RXD_1(ALT11)	-	B01
-	-	PV03	GPIO_V_03(ALT0) GPTMR1_CAPT_1(ALT1) UART0_CTS(ALT3) I2C2_SDA(ALT4) SPI1_CS_3(ALT5) MCAN1_STBY(ALT7) TSW0_P1_RXD_2(ALT10) ESC0_P0_RXD_2(ALT11)	-	B01
-	-	PV04	GPIO_V_04(ALT0) UART1_CTS(ALT3) SPI0_SCLK(ALT5) MCAN1_RXD(ALT7) TSW0_P1_RXD_3(ALT10) ESC0_P0_RXD_3(ALT11)	-	B01
-	-	PV05	GPIO_V_05(ALT0) GPTMR1_COMP_2(ALT1) UART1_DE(ALT2) UART1_RTS(ALT3) SPI0_CS_0(ALT5) MCAN1_TXD(ALT7) TSW0_P1_RXCK(ALT10) ESC0_P0_RXCK(ALT11)	-	B01
-	-	PV06	GPIO_V_06(ALT0) GPTMR0_CAPT_0(ALT1) UART1_RXD(ALT2) I2C3_SDA(ALT4) SPI0_MISO(ALT5) TSW0_P1_TXCK(ALT10) ESC0_P0_TXCK(ALT11)	-	B01

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
-	-	PV07	GPIO_V_07(ALT0) GPTMR0_COMP_0(ALT1) UART1_TXD(ALT2) I2C3_SCL(ALT4) SPI0_MOSI(ALT5) TSW0_P1_TXD_0(ALT10) ESC0_P0_TXD_0(ALT11)	-	B01
-	-	PV08	GPIO_V_08(ALT0) GPTMR0_COMP_1(ALT1) UART2_TXD(ALT2) I2C0_SCL(ALT4) SPI1_CS_2(ALT5) MCAN2_TXD(ALT7) TSW0_P1_TXD_1(ALT10) ESC0_P0_TXD_1(ALT11)	-	B01
-	-	PV09	GPIO_V_09(ALT0) GPTMR0_CAPT_1(ALT1) UART2_RXD(ALT2) I2C0_SDA(ALT4) SPI1_CS_1(ALT5) MCAN2_RXD(ALT7) TSW0_P1_TXD_2(ALT10) ESC0_P0_TXD_2(ALT11)	-	B01
-	-	PV10	GPIO_V_10(ALT0) GPTMR0_COMP_2(ALT1) UART2_DE(ALT2) UART2_RTS(ALT3) SPI1_SCLK(ALT5) MCAN2_STBY(ALT7) TSW0_P1_TXD_3(ALT10) ESC0_P0_TXD_3(ALT11)	-	B01
-	-	PV11	GPIO_V_11(ALT0) UART2_CTS(ALT3) SPI1_CS_0(ALT5) TSW0_P1_TXEN(ALT10) ESC0_P0_TXEN(ALT11)	-	B01

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
-	-	PV12	GPIO_V_12(ALT0) UART3_CTS(ALT3) I2C1_SDA(ALT4) SPI1_MISO(ALT5) TSW0_P1_RXER(ALT10) ESC0_CTR_0(ALT11)	-	B01
-	-	PV13	GPIO_V_13(ALT0) GPTMR1_COMP_3(ALT1) UART3_DE(ALT2) UART3_RTS(ALT3) I2C1_SCL(ALT4) SPI1_MOSI(ALT5) MCAN3_STBY(ALT7) ESC0_CTR_2(ALT11)	-	B01
-	-	PV14	GPIO_V_14(ALT0) UART3_RXD(ALT2) SPI1_DAT2(ALT5) MCAN3_RXD(ALT7) ESC0_CTR_4(ALT11)	-	B01
-	-	PV15	GPIO_V_15(ALT0) GPTMR0_COMP_3(ALT1) UART3_TXD(ALT2) SPI1_DAT3(ALT5) MCAN3_TXD(ALT7) ESC0_P0_RXER(ALT11)	-	B01
-	-	PW00	GPIO_W_00(ALT0) GPTMR5_COMP_0(ALT1) UART8_TXD(ALT2) MCAN0_TXD(ALT7) TSW0_P2_RXDV(ALT10) ESC0_P1_RXDV(ALT11) ETH0_RXDV(ALT18)	-	B01
-	-	PW01	GPIO_W_01(ALT0) GPTMR5_CAPT_0(ALT1) UART8_RXD(ALT2) MCAN0_RXD(ALT7) TSW0_P2_RXD_0(ALT10) ESC0_P1_RXD_0(ALT11) ETH0_RXD_0(ALT18)	-	B01

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
-	-	PW02	GPIO_W_02(ALT0) GPTMR5_COMP_1(ALT1) UART8_DE(ALT2) UART8_RTS(ALT3) MCAN0_STBY(ALT7) TSW0_P2_RXD_1(ALT10) ESC0_P1_RXD_1(ALT11) ETH0_RXD_1(ALT18)	-	B01
-	-	PW03	GPIO_W_03(ALT0) GPTMR5_CAPT_1(ALT1) UART8_CTS(ALT3) SPI5_CS_3(ALT5) MCAN1_STBY(ALT7) TSW0_P2_RXD_2(ALT10) ESC0_P1_RXD_2(ALT11) ETH0_RXD_2(ALT18)	-	B01
-	-	PW04	GPIO_W_04(ALT0) UART9_CTS(ALT3) SPI4_SCLK(ALT5) MCAN1_RXD(ALT7) TSW0_P2_RXD_3(ALT10) ESC0_P1_RXD_3(ALT11) ETH0_RXD_3(ALT18)	-	B01
-	-	PW05	GPIO_W_05(ALT0) GPTMR5_COMP_2(ALT1) UART9_DE(ALT2) UART9_RTS(ALT3) SPI4_CS_0(ALT5) MCAN1_TXD(ALT7) TSW0_P2_RXCK(ALT10) ESC0_P1_RXCK(ALT11) ETH0_RXCK(ALT18)	-	B01
-	-	PW06	GPIO_W_06(ALT0) GPTMR4_CAPT_0(ALT1) UART9_RXD(ALT2) SPI4_MISO(ALT5) TSW0_P2_TXCK(ALT10) ESC0_P1_TXCK(ALT11) ETH0_TXCK(ALT18)	-	B01

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
-	-	PW07	GPIO_W_07(ALT0) GPTMR4_COMP_0(ALT1) UART9_TXD(ALT2) SPI4_MOSI(ALT5) TSW0_P2_TXD_0(ALT10) ESC0_P1_TXD_0(ALT11) ETH0_TXD_0(ALT18)	-	B01
-	-	PW08	GPIO_W_08(ALT0) GPTMR4_COMP_1(ALT1) UART10_TXD(ALT2) I2C4_SCL(ALT4) SPI5_CS_2(ALT5) MCAN2_TXD(ALT7) TSW0_P2_TXD_1(ALT10) ESC0_P1_TXD_1(ALT11) ETH0_TXD_1(ALT18)	-	B01
-	-	PW09	GPIO_W_09(ALT0) GPTMR4_CAPT_1(ALT1) UART10_RXD(ALT2) I2C4_SDA(ALT4) SPI5_CS_1(ALT5) MCAN2_RXD(ALT7) TSW0_P2_TXD_2(ALT10) ESC0_P1_TXD_2(ALT11) ETH0_TXD_2(ALT18)	-	B01
-	-	PW10	GPIO_W_10(ALT0) GPTMR4_COMP_2(ALT1) UART10_DE(ALT2) UART10_RTS(ALT3) SPI5_SCLK(ALT5) MCAN2_STBY(ALT7) TSW0_P2_TXD_3(ALT10) ESC0_P1_TXD_3(ALT11) ETH0_TXD_3(ALT18)	-	B01

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
-	-	PW11	GPIO_W_11(ALT0) UART10_CTS(ALT3) SPI5_CS_0(ALT5) TSW0_P2_TXEN(ALT10) ESC0_P1_TXEN(ALT11) ETH0_TXEN(ALT18)	-	B01
-	-	PW12	GPIO_W_12(ALT0) UART11_CTS(ALT3) I2C5_SDA(ALT4) SPI5_MISO(ALT5) TSW0_P2_RXER(ALT10) ESC0_CTR_1(ALT11) ETH0_RXER(ALT18)	-	B01
-	-	PW13	GPIO_W_13(ALT0) GPTMR5_COMP_3(ALT1) UART11_DE(ALT2) UART11_RTS(ALT3) I2C5_SCL(ALT4) SPI5_MOSI(ALT5) MCAN3_STBY(ALT7) ESC0_CTR_3(ALT11) ETH0_TXER(ALT18)	-	B01
-	-	PW14	GPIO_W_14(ALT0) UART11_RXD(ALT2) SPI5_DAT2(ALT5) MCAN3_RXD(ALT7) ESC0_CTR_5(ALT11) ETH0_COL(ALT18)	-	B01
-	-	PW15	GPIO_W_15(ALT0) GPTMR4_COMP_3(ALT1) UART11_TXD(ALT2) SPI5_DAT3(ALT5) MCAN3_TXD(ALT7) ESC0_P1_RXER(ALT11) ETH0_CRS(ALT18)	-	B01

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
-	-	PW16	GPIO_W_16(ALT0) GPTMR7_COMP_0(ALT1) UART12_TXD(ALT2) MCAN4_TXD(ALT7) TSW0_P1_MDIO(ALT10) ESC0_CTR_6(ALT11) ETH0_MDIO(ALT18)	-	B01
-	-	PW17	GPIO_W_17(ALT0) GPTMR7_CAPT_0(ALT1) UART12_RXD(ALT2) MCAN4_RXD(ALT7) TSW0_P1_MDC(ALT10) ESC0_CTR_7(ALT11) ETH0_MDC(ALT18)	-	B01
-	-	PW18	GPIO_W_18(ALT0) GPTMR7_COMP_1(ALT1) UART12_DE(ALT2) UART12_RTS(ALT3) MCAN4_STBY(ALT7) TSW0_P2_MDIO(ALT10) ESC0_MDIO(ALT11)	-	B01
-	-	PW19	GPIO_W_19(ALT0) GPTMR7_CAPT_1(ALT1) UART12_CTS(ALT3) SPI6_CS_3(ALT5) MCAN5_STBY(ALT7) TSW0_P2_MDC(ALT10) ESC0_MDC(ALT11)	-	B01
-	-	PW20	GPIO_W_20(ALT0) UART13_CTS(ALT3) SPI7_SCLK(ALT5) MCAN5_RXD(ALT7) ESC0_REFCK(ALT11) SOC_REF0(ALT24)	-	B01

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
-	-	PW21	GPIO_W_21(ALT0) GPTMR7_COMP_2(ALT1) UART13_DE(ALT2) UART13_RTS(ALT3) SPI7_CS_0(ALT5) MCAN5_TXD(ALT7) ESC0_REFCK(ALT11) SOC_REF1(ALT24)	-	B01
-	-	PW22	GPIO_W_22(ALT0) GPTMR6_CAPT_0(ALT1) UART13_RXD(ALT2) SPI7_MISO(ALT5) ESC0_CTR_8(ALT11)	-	B01
-	-	PW23	GPIO_W_23(ALT0) GPTMR6_COMP_0(ALT1) UART13_TXD(ALT2) SPI7_MOSI(ALT5)	-	B01
-	-	PX00	GPIO_X_00(ALT0) GPTMR3_COMP_0(ALT1) UART4_TXD(ALT2) MCAN4_TXD(ALT7) XPI0_CB_DQS(ALT14)	-	B04
-	-	PX01	GPIO_X_01(ALT0) GPTMR3_CAPT_0(ALT1) UART4_RXD(ALT2) MCAN4_RXD(ALT7) XPI0_CA_D_0(ALT14)	-	B04
-	-	PX02	GPIO_X_02(ALT0) GPTMR3_COMP_1(ALT1) UART4_DE(ALT2) UART4_RTS(ALT3) I2C4_SCL(ALT4) MCAN4_STBY(ALT7) XPI0_CA_SCLK(ALT14)	-	B04

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
-	-	PX03	GPIO_X_03(ALT0) GPTMR3_CAPT_1(ALT1) UART4_CTS(ALT3) I2C4_SDA(ALT4) SPI2_CS_3(ALT5) MCAN5_STBY(ALT7) XPI0_CA_D_3(ALT14)	-	B04
-	-	PX04	GPIO_X_04(ALT0) UART5_CTS(ALT3) SPI3_SCLK(ALT5) MCAN5_RXD(ALT7) XPI0_CA_DQS(ALT14)	-	B04
-	-	PX05	GPIO_X_05(ALT0) GPTMR3_COMP_2(ALT1) UART5_DE(ALT2) UART5_RTS(ALT3) SPI3_CS_0(ALT5) MCAN5_TXD(ALT7) XPI0_CA_CS0(ALT14)	-	B04
-	-	PX06	GPIO_X_06(ALT0) GPTMR2_CAPT_0(ALT1) UART5_RXD(ALT2) I2C5_SDA(ALT4) SPI3_MISO(ALT5) XPI0_CA_D_1(ALT14)	-	B04
-	-	PX07	GPIO_X_07(ALT0) GPTMR2_COMP_0(ALT1) UART5_TXD(ALT2) I2C5_SCL(ALT4) SPI3_MOSI(ALT5) FEMC_DQS(ALT12) XPI0_CA_D_2(ALT14)	-	B04
U6	-	PY00	GPIO_Y_00(ALT0) GPTMR1_COMP_0(ALT1) UART0_TXD(ALT2) MCAN0_TXD(ALT7)	-	VPMC

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
T6	-	PY01	GPIO_Y_01(ALT0) GPTMR1_CAPT_0(ALT1) UART0_RXD(ALT2) MCAN0_RXD(ALT7)	-	VPMC
U5	-	PY02	GPIO_Y_02(ALT0) GPTMR1_COMP_1(ALT1) UART0_DE(ALT2) UART0_RTS(ALT3) I2C0_SCL(ALT4) MCAN0_STBY(ALT7) PDM0_CLK(ALT9)	-	VPMC
T5	-	PY03	GPIO_Y_03(ALT0) GPTMR1_CAPT_1(ALT1) UART0_CTS(ALT3) I2C0_SDA(ALT4) MCAN1_STBY(ALT7) PDM0_D_3(ALT9)	-	VPMC
R6	-	PY04	GPIO_Y_04(ALT0) UART1_CTS(ALT3) SPI1_SCLK(ALT5) MCAN1_RXD(ALT7) PDM0_D_2(ALT9)	-	VPMC
R5	-	PY05	GPIO_Y_05(ALT0) GPTMR1_COMP_2(ALT1) UART1_DE(ALT2) UART1_RTS(ALT3) SPI1_CS_0(ALT5) MCAN1_TXD(ALT7) PDM0_D_1(ALT9)	-	VPMC
P5	-	PY06	GPIO_Y_06(ALT0) GPTMR0_CAPT_0(ALT1) UART1_RXD(ALT2) I2C1_SDA(ALT4) SPI1_MISO(ALT5) PDM0_CLK(ALT9)	-	VPMC

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
N5	-	PY07	GPIO_Y_07(ALT0) GPTMR0_COMP_0(ALT1) UART1_TXD(ALT2) I2C1_SCL(ALT4) SPI1_MOSI(ALT5) PDM0_D_0(ALT9)	-	VPMC
P8	-	PZ00	GPIO_Z_00(ALT0) GPTMR3_COMP_0(ALT1) UART4_TXD(ALT2) MCAN4_TXD(ALT7)	-	VBAT
N8	-	PZ01	GPIO_Z_01(ALT0) GPTMR3_CAPT_0(ALT1) UART4_RXD(ALT2) MCAN4_RXD(ALT7)	-	VBAT
P7	-	PZ02	GPIO_Z_02(ALT0) GPTMR3_COMP_1(ALT1) UART4_DE(ALT2) UART4_RTS(ALT3) I2C0_SCL(ALT4) MCAN4_STBY(ALT7)	-	VBAT
N7	-	PZ03	GPIO_Z_03(ALT0) GPTMR3_CAPT_1(ALT1) UART4_CTS(ALT3) I2C0_SDA(ALT4) MCAN5_STBY(ALT7)	-	VBAT
P6	-	PZ04	GPIO_Z_04(ALT0) UART5_CTS(ALT3) SPI2_SCLK(ALT5) MCAN5_RXD(ALT7)	-	VBAT
N6	-	PZ05	GPIO_Z_05(ALT0) GPTMR3_COMP_2(ALT1) UART5_DE(ALT2) UART5_RTS(ALT3) SPI2_CS_0(ALT5) MCAN5_TXD(ALT7)	-	VBAT

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
-	-	PZ06	GPIO_Z_06(ALT0) GPTMR2_CAPT_0(ALT1) UART5_RXD(ALT2) I2C1_SDA(ALT4) SPI2_MISO(ALT5)	-	VBAT
-	-	PZ07	GPIO_Z_07(ALT0) GPTMR2_COMP_0(ALT1) UART5_TXD(ALT2) I2C1_SCL(ALT4) SPI2_MOSI(ALT5)	-	VBAT
A1,U 1,G3, L3,D 4,P4, C7,H 7,J7, K7,R 7,G8, J8,L8 ,G9, H9,K 9,G1 0,J10 ,C11, H11, J11,K 11,R 11,D 14,P 14,G 15,L1 5,A1 7,U1 7	A1,P 1,N3, E5,K 5,F7, G7,H 7,J7, F8,G 8,E1 0,K1 0,A1 4,P1 4	VSS	-	-	-
R1,T 1	M1,M 2	DCDC_IN	-	-	-
R2,T 2,U2	N1,P 2	DCDC_GND	-	-	-

HPM6E00 系列

基于 RISC-V 内核的 32 位高性能微控制器数据手册 Rev0.10

2 引脚及功能描述

封装		PIN 名称	数字功能	模拟功能	供电分组
BGA _289	BGA _196				
R3,T 3,U3	N2,P 3	DCDC_LP	-	-	-
R4	L3	WKUP	-	-	-
T4	M3	RSTN	-	-	-
U4	P4	VPMC	-	-	-
F6,G 7,L7, H8,K 8,J9, H10, K10, G11, L11,F 12	F6,G 6,F9, G9,H 9	VDD_SOC	-	-	-
G6	-	VIO_B04	-	-	-
H6	-	VIO_B03	-	-	-
J6	-	VIO_B02	-	-	-
K6	E6,K 6,E7, E8	VIO_B01	-	-	-
L6	H6	VDD_PHY1CAP	-	-	-
M6	-	DCDC_SNS	-	-	-
F7	-	VIO_B05	-	-	-
M7	J6	VDD_PHY0CAP	-	-	-
T7	-	RTC_XO	-	-	-
U7	-	RTC_XI	-	-	-
F8	-	VIO_B06	-	-	-
M8	K7	VDD_OTPCAP	-	-	-
U8	N4	VBAT	-	-	-
F9	-	VIO_B07	-	-	-
L9	J8	VREFL	-	-	-
M9	K8	VDD_PMCCAP	-	-	-
F10	-	VIO_B08	-	-	-
L10	H8	VSSA	-	-	-