Why complex numbers arise

Real rotation matrix

$$R_\theta = \begin{bmatrix} \cos\theta & -\sin\theta \\ \sin\theta & \cos\theta \end{bmatrix}$$

has no nonzero real eigenvector when $\theta \not\equiv 0 \pmod{\pi}$. Its eigenvalues are

$$\lambda = e^{\pm i\theta}.$$

Complex eigenvectors describe oscillations, roots of unity, and periodic signals. A real matrix has conjugate-paired nonreal eigenvalues. Nonreal modes must be paired with conjugate coefficients to construct real solutions; real eigenvector modes can appear on their own.

We use $i^2 = -1$. Electrical engineering often writes j for the same imaginary unit.

Lin Cing
https://github.com/xinhi6716/computer-science-self-study

Arithmetic in the complex field

Write $z = a + bi$ with real a, b. Add and subtract components.

$$(a + bi) + (c + di) = (a + c) + (b + d)i.$$

Multiplication gives

$$(a + bi)(c + di) = (ac - bd) + (ad + bc)i.$$

The complex numbers form a field. For nonzero $a + bi$,

$$\frac{1}{a + bi} = \frac{a - bi}{a^2 + b^2}.$$

Multiplication commutes, and the positive squared modulus of a nonzero number supplies the reciprocal denominator. Standard basis vectors also work in $\mathbb{C}^n$, with complex coefficients.

Lin Cing
https://github.com/xinhi6716/computer-science-self-study

Conjugation, modulus, and dimension

Conjugate:

$$\overline{a+bi} = a - bi.$$

Modulus:

$$|z| = \sqrt{z\overline{z}} = \sqrt{a^2+b^2}.$$

Conjugation preserves sums and products.

$$\overline{z+w} = \overline{z} + \overline{w}, \qquad \overline{zw} = \overline{z}\,\overline{w}.$$

Also $|zw| = |z||w|$, and the triangle inequality holds.

The complex dimension of $\mathbb{C}^n$ is n. Its real dimension is $2n$, because every component has a real and imaginary part. Specify the scalar field when counting dimensions or ranks.

Polar form and Euler's formula

A nonzero complex number

$$z = a + bi$$

has

$$r = |z|, \qquad \theta = \operatorname{atan2}(b, a),$$
$$z = re^{i\theta} = r(\cos\theta + i\sin\theta).$$

Euler formula:

$$e^{i\theta} = \cos\theta + i\sin\theta.$$

Multiplication multiplies moduli and adds arguments.

$$(re^{i\theta})(se^{i\phi}) = rse^{i(\theta+\phi)}.$$

Powers:

$$(re^{i\theta})^k = r^k e^{ik\theta}.$$

For example,

$$1 + i = \sqrt{2}e^{i\pi/4},$$
$$(1+i)^8 = 16e^{2\pi i} = 16.$$

Arguments differing by 2π represent the same number. A branch choice matters for multivalued operations such as the complex logarithm.

Roots of unity

Solve

$$z^n = 1.$$

Set

$$\omega = e^{2\pi i/n}.$$

The roots are

$$1, \omega, \omega^2, \ldots, \omega^{n-1}.$$

They are equally spaced on the unit circle, forming a regular polygon for $n \geq 3$.

If $z = re^{i\theta}$ and $z^n = 1$, then


$$r = 1, \qquad n\theta = 2\pi k.$$

For $n = 4$, the roots are $1, i, -1, -i$. They also generate Fourier vectors and eigenvectors of cyclic shifts.

Lin Cing
https://github.com/xinhi6716/computer-science-self-study

Roots of unity (continued)

Eighth roots of unity: equally spaced on the unit circle



ω=e^(2πi/8)

roots：1,ω,…,ω⁷

$F_8 F_8^H = 8I$

Orthogonal columns; Fourier basis

Lin Cing
https://github.com/xinhi6716/computer-science-self-study

The complex inner product

Our convention is

$$\langle u, v \rangle = u^H v = \sum_j \overline{u_j} v_j,$$

where

$$u^H = \overline{u^T}.$$

For $u = (1, i)^T$,

$$\|u\|^2 = u^H u = |1|^2 + |i|^2 = 2,$$

rather than the bilinear expression $1^2 + i^2 = 0$.

Inner product properties:

$$\langle u, v \rangle = \overline{\langle v, u \rangle},$$
$$\langle u, v + w \rangle = \langle u, v \rangle + \langle u, w \rangle,$$
$$\langle u, \alpha v \rangle = \alpha \langle u, v \rangle,$$
$$\langle \alpha u, v \rangle = \overline{\alpha}\, \langle u, v \rangle.$$

Conjugation belongs to the first argument throughout. A different convention requires consistent changes in every formula.


The adjoint moves a map across an inner product

With this chapter's convention $\langle x, y \rangle = x^H y$, the adjoint of $A \in \mathbb{C}^{m \times n}$ is $A^H \in \mathbb{C}^{n \times m}$, since for all $x \in \mathbb{C}^n$, $y \in \mathbb{C}^m$,

$$\langle Ax, y \rangle = (Ax)^H y = x^H A^H y = \langle x, A^H y \rangle.$$

These are standard orthonormal coordinates: a plain transpose omits the necessary conjugation. For a convention linear in the first argument, formulate and derive the adjoint identity consistently with that convention.

Check both sides on the same complex vectors



Let $A = \begin{bmatrix} 2i & 3 \\ 1 & -1 \end{bmatrix}$, so $A^H = \begin{bmatrix} -2i & 1 \\ 3 & -1 \end{bmatrix}$. For $x = (1, i)^T$, $y = (2, 1 + i)^T$, obtain $Ax = (5i, 1 - i)^T$ and $A^H y = (1 - 3i, 5 - i)^T$.

Term by term, $\langle Ax, y \rangle = (-5i)2 + (1 + i)(1 + i) = -8i$, while $\langle x, A^H y \rangle = (1, -i)(1 - 3i, 5 - i)^T = -8i$. Conjugating the wrong factor can change either result.

Orthogonality and the four subspaces

Orthogonality means

$$u^H v = 0.$$

For example,

$$u = (1, i)^T, \qquad v = (1, -i)^T,$$
$$u^H v = (1, -i)(1, -i)^T = 1 + (-i)(-i) = 1 - 1 = 0.$$

The complex four-subspace relations use the conjugate transpose.

$$C(A) \perp N(A^H), \qquad C(A^H) \perp N(A).$$

Ordinary A^T does not generally give the Hermitian orthogonal complements. For instance, $(A^H y)^H x = y^H A x$, which vanishes when $Ax = 0$.

Dimensions:

$$\dim C(A) = \dim C(A^H) = r,$$
$$\dim N(A) = n - r, \qquad \dim N(A^H) = m - r.$$

Hermitian matrices

A square matrix is Hermitian if

$$S^H = S.$$

Entrywise:

$$s_{ji} = \overline{s_{ij}}.$$

Its diagonal entries are real. For every z,

$$(z^H S z)^H = z^H S^H z = z^H S z.$$

The scalar equals its own conjugate, so

$$z^H S z \in \mathbb{R}.$$

For example,

$$S = \begin{bmatrix} 2 & 1+i \\ 1-i & 3 \end{bmatrix}$$

is Hermitian.

Lin Cing
https://github.com/xinhi6716/computer-science-self-study

Hermitian eigenvalues and eigenvectors

If nonzero z satisfies

$$Sz = \lambda z,$$

multiply on the left by z^H.

$$z^H S z = \lambda z^H z.$$

The left side is real and $z^H z > 0$, proving λ real.

If

$$Su = \lambda u, \qquad Sv = \mu v,$$

then, using reality of λ,

$$\lambda u^H v = (Su)^H v = u^H S v = \mu u^H v.$$

For distinct eigenvalues,

$$(\lambda - \mu) u^H v = 0,$$

so the eigenvectors are orthogonal.

Lin Cing
https://github.com/xinhi6716/computer-science-self-study

The spectral theorem: a complete orthonormal eigenbasis

For completeness of the eigenbasis, maximize the real-valued quadratic form $z^H S z$ on the complex unit sphere. Stationarity in real and imaginary directions gives $Sq = \lambda q$. The complement $q^\perp$ is invariant because $q^H S v = (Sq)^H v = 0$. Restriction remains Hermitian, so induction yields a complete orthonormal eigenbasis. Gram-Schmidt can be applied within repeated eigenspaces. Thus

$$S = Q \Lambda Q^H,$$

where $Q^H Q = I$ and Λ is real diagonal.

Lin Cing
https://github.com/xinhi6716/computer-science-self-study

Unitary matrices

A square matrix $Q \in \mathbb{C}^{n \times n}$ is unitary if

$$Q^H Q = I.$$

It also satisfies $QQ^H = I$, so

$$Q^{-1} = Q^H.$$

It preserves inner products.

$$\langle Qu, Qv \rangle = (Qu)^H (Qv) = u^H v.$$

Thus $\|Qu\| = \|u\|$.

If $Qu = \lambda u$,

$$\|u\| = \|Qu\| = |\lambda| \|u\|,$$

so

$$|\lambda| = 1.$$

The determinant also records length preservation.

$$1 = \det(Q^H Q) = (\det Q)^H \det Q = |\det Q|^2,$$

Hence $|\det Q| = 1$. Real orthogonal matrices are the real special case of unitary matrices.

Lin Cing
https://github.com/xinhi6716/computer-science-self-study

Normal matrices

A square matrix is normal if

$$AA^H = A^H A.$$

A complex square matrix is unitarily diagonalizable exactly when it is normal. For sufficiency, take a unit eigenvector and extend it to a unitary basis, producing $\begin{bmatrix} \lambda & b^H \\ 0 & C \end{bmatrix}$. Equality of the $(1,1)$ entries of AA^H and $A^H A$ gives $|\lambda|^2 + \|b\|^2 = |\lambda|^2$, so $b = 0$. The remaining block is normal, and induction proves the result. Necessity follows by multiplying $A = Q\Lambda Q^H$ and its adjoint. Important classes include

- Hermitian:eigenvalues real;
- skew-Hermitian $K^H = -K$:eigenvalues pure imaginary;
- unitary:eigenvalues modulus 1.

Ordinary diagonalizability requires an eigenbasis. Unitary diagonalizability requires an orthonormal eigenbasis, a stronger condition.

A Hermitian diagonalization example

$$S = \begin{bmatrix} 2 & i \\ -i & 2 \end{bmatrix} = S^H.$$

Characteristic polynomial:

$$\det(S - \lambda I) = (2-\lambda)^2 - |i|^2 = (\lambda - 1)(\lambda - 3).$$

Eigenvalues 1,3.

For $\lambda = 3$,

$$\begin{bmatrix} -1 & i \\ -i & -1 \end{bmatrix} z = 0$$

gives $z_1 = iz_2$. Choose

$$q_1 = (i, 1)^T / \sqrt{2}.$$

For $\lambda = 1$, choose

$$q_2 = (-i, 1)^T / \sqrt{2}.$$

Both vectors have unit norm and $q_1^H q_2 = 0$. Therefore

$$S = Q \begin{bmatrix} 3 & 0 \\ 0 & 1 \end{bmatrix} Q^H,$$

$$Q = \frac{1}{\sqrt{2}} \begin{bmatrix} i & -i \\ 1 & 1 \end{bmatrix}.$$

The Fourier matrix

Let

$$\omega = e^{2\pi i/n}.$$

Forward Fourier matrix:

$$(F_n)_{jk} = \omega^{jk}, \qquad 0 \le j, k < n.$$

Forward transform:

$$y = F_n c.$$

The Fourier matrix is symmetric. It is generally not Hermitian for $n > 2$; sizes 1 and 2 are real symmetric exceptions. Its columns are orthogonal because

$$\sum_{j=0}^{n-1} (\omega^{jk})^H \omega^{j\ell} = \sum_{j} \omega^{j(\ell-k)} = n\delta_{k\ell}.$$

Therefore

$$F_n F_n^H = nI, \qquad F_n^{-1} = F_n^H / n.$$

Inverse DFT and Parseval

Inverse:

$$c_j = \frac{1}{n} \sum_{k=0}^{n-1} \omega^{-jk} y_k.$$

Software using

$$\omega = e^{-2\pi i/n},$$

interchanges the forward and inverse sign conventions.

Parseval:

$$\|y\|^2 = (F_n c)^H (F_n c) = n\|c\|^2.$$

Normalized unitary Fourier matrix:

$$Q = F_n / \sqrt{n}$$

satisfies $Q^H Q = I$, preserving the norm. Normalization changes scale constants without changing which information the transform represents.

DFT and cyclic convolution

Define cyclic convolution by $h_j = \sum_{k=0}^{n-1} a_k b_{(j-k) \bmod n}$. Its Fourier transform is

$$F_n h = (F_n a) \odot (F_n b)$$

Substitute this definition into $\sum_j \omega^{\ell j} h_j$ and set $s = (j-k) \bmod n$. The sum factors into $(\sum_k a_k \omega^{\ell k})(\sum_s b_s \omega^{\ell s})$. This identity uses the unnormalized forward transform. A forward transform divided by $\sqrt{n}$ requires an extra factor $\sqrt{n}$ on the right.

Two FFTs, pointwise multiplication, and an inverse FFT take $O(n \log n)$ arithmetic operations, compared with $O(n^2)$ for general direct cyclic convolution. Sequences of lengths p, q have linear convolution length $p + q - 1$; pad to at least that length to avoid wraparound.

Coefficient order, sign, and normalization must match the convolution definition. Record these conventions in FFT or finite-field transform implementations.

Even–odd decomposition in radix-2 FFT

Let $n = 2m$, $0 \le j < m$, and split the sequence into

$$c' = (c_0, c_2, \ldots, c_{2m-2}),$$
$$c'' = (c_1, c_3, \ldots, c_{2m-1}).$$

Separate $y_j = \sum_{k=0}^{n-1} c_k \omega_n^{jk}$ into even indices $k = 2s$ and odd indices $k = 2s+1$. Since $\omega_n^2 = \omega_m$, $\omega_n^m = -1$,

$$y_j = y'_j + \omega_n^j y''_j,$$
$$y_{j+m} = y'_j - \omega_n^j y''_j.$$

where y', y'' are DFTs of size $m = n/2$.

This butterfly operation combines two half-sized problems with m twiddle multiplications. One split works for any positive even n; recursively using radix-2 down to size 1 additionally requires $n = 2^\ell$, $\ell \ge 0$.

For $n = 4$, $c = (1, 2, 0, -1)^T$, bit reversal first gives

$$(c_0, c_2, c_1, c_3) = (1, 0, 2, -1).$$

The first stage performs two two-point butterflies.

$$(1, 0) \mapsto (1, 1), \qquad (2, -1) \mapsto (1, 3).$$

The second stage uses $\omega_4^0 = 1, \omega_4^1 = i$.

Even–odd decomposition in radix-2 FFT (continued)


$$(1,1) \mapsto (2,0), \qquad (1,3) \mapsto (1+3i, 1-3i).$$

Consequently,

$$y = F_4 c = (2, 1+3i, 0, 1-3i)^T.$$

Direct evaluation gives $y_1 = 1 + 2i + (-1)(-i) = 1 + 3i$, $y_3 = 1 - 2i + (-1)i = 1 - 3i$. The plus and minus branches share the same twiddle product.

Four-point FFT stage 1: even and odd two-point DFTs




Upper branch adds; lower subtracts green from blue. Next, pair matching E_j and O_j.

Which intermediate values combine in a four-point FFT?

The first-stage array is $(E_0, E_1, O_0, O_1) = (1, 1, 1, 3)$. The second stage pairs positions $(0, 2)$ and $(1, 3)$. Only matching E_j, O_j produce y_j, y_{j+2}. The diagram separates the two butterflies to keep those pairings visible.

Four-point FFT stage 2: combine matching E_j and O_j



Blue $u=E_j$; green $\omega v=\omega_4^j O_j$. Upper: $u+\omega v$; lower: $u-\omega v$. Output order y_0, y_1, y_2, y_3.

The first three intermediate values happen to agree in this example, concealing a wrong pairing. Instead take $c = (2, 5, 7, -1)$. The first stage is $(9, -5, 4, 6)$, and the correct output is $(13, -5+6i, 5, -5-6i)$. Pairing E_0, E_1 incorrectly would give $9 + (-5) = 4$ instead of 13. Pairing indices are part of the algorithm.

Recursion and arithmetic cost

$n = 2^{\ell}$:

$$T(n) = 2T(n/2) + \Theta(n).$$

There are $\log_2 n$ levels with linear work at each level, giving

$$T(n) = \Theta(n \log n).$$

Naive Fourier matrix multiplication:

$$n^2$$

multiplications in the direct matrix formula.

For $n = 1024 = 2^{10}$,

$$n^2 = 1,048,576,$$
$$\frac{n}{2} \log_2 n = 5,120.$$

The theoretical multiplication-count ratio is 204.8 in this model. This is not a measured runtime speedup. Additions, memory access, parallel execution, and root generation affect actual runtime.

Iterative FFT and bit reversal

The recursion can be implemented bottom-up. A radix-2 decimation-in-time arrangement for $n = 8$ begins with bit-reversed input order

$$0, 4, 2, 6, 1, 5, 3, 7.$$

and applies butterflies of lengths 2, 4, and 8.

$$(a, b) \mapsto (a + \omega b, a - \omega b).$$

An inverse transform can conjugate the input, apply the forward transform, conjugate the output, and divide by n.

Other sizes can use mixed-radix methods or Bluestein's algorithm. A real-input FFT can exploit conjugate symmetry, but a generic complex interface need not do so automatically.

Numerical interpretation

Practical issues include the following.

- Compute or store twiddle factors accurately.
- Control accumulated phase error.
- Specify the forward scale and inverse sign.
- Zero-padding changes the frequency grid but creates no new observations.
- Windowing changes the signal while reducing some leakage.
- Bin frequency is $k/(n\Delta t)$; bins above Nyquist may instead be represented as $(k - n)/(n\Delta t)$ under a signed-frequency convention. For even n, specify the sign convention for the Nyquist bin.

A spectral peak can combine signal, leakage, and noise. A nonzero numerical bin alone does not establish an exact physical frequency.

Chapter review

- The first inner-product argument is conjugated; adjoints use the conjugate transpose.
- Hermitian eigenvalues are real; unitary matrices preserve norm, under different conditions.
- State DFT sign and normalization; Parseval scaling depends on the latter.
- Full radix-2 recursion requires a power-of-two length; butterflies pair matching indices.

References and attribution

Lin Cing, handwritten linear algebra notes. Gilbert Strang, Introduction to Linear Algebra, 5th ed., Chapter 9.

Original educational synthesis by Lin Cing, licensed under CC BY 4.0.

https://github.com/xinhi6716/computer-science-self-study