

XR/17032 Processor Specification

Draft 14

April 1, 2023

SPECIFICATION COPYRIGHT

BSD 3-Clause License

Copyright (c) 2023, TomAwezome

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

1. Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
2. Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
3. Neither the name of the copyright holder nor the names of its contributors may be used to endorse or promote products derived from this software without specific prior written permission.

THIS SOFTWARE IS PROVIDED BY THE COPYRIGHT HOLDERS AND CONTRIBUTORS “AS IS” AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE COPYRIGHT HOLDER OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

REGISTERS

The XR/17032 processor architecture contains 32 GPRs (general-purpose registers), and 16 CRs (control registers).

Control Registers

For control registers, there are 2 instructions, **MTCR** and **MFCR**, that alter the control registers, and for these 2 instructions the control registers are encoded in 4 bits of the opcode. The **TBL0** and **TBINDEX** control registers specifically are modified by the **TBRD** and **TBFN** instructions.

Name	Encoding	Description
RS	0000	Processor Status
TBL0	0010	TLB Entry
EPC	0011	Exception Program Counter
EVEC	0100	Exception Vector
PGTB	0101	Page Table Base
TBINDEX	0110	TLB Index
EBADADDR	0111	Bad Address
TBVEC	1000	TLB Miss Handler
FWVEC	1001	Firmware Call Vector
TBSCRATCH	1010	TLB Miss Scratch
TBHI	1011	ASID & TLB Miss Address
K0	1100	
K1	1101	
K2	1110	
K3	1111	

General Purpose Registers

General purpose registers are encoded with 5 bits in instruction opcodes using registers.

Name	Encoding	Description
ZERO	00000	Zero Register: always reads zero, ignores writes.
T0	00001	
T1	00010	
T2	00011	
T3	00100	
T4	00101	
T5	00110	
A0	00111	
A1	01000	
A2	01001	
A3	01010	
S0	01011	
S1	01100	
S2	01101	
S3	01110	
S4	01111	
S5	10000	

Name	Encoding	Description
S6	10001	
S7	10010	
S8	10011	
S9	10100	
S10	10101	
S11	10110	
S12	10111	
S13	11000	
S14	11001	
S15	11010	
S16	11011	
S17	11100	
S18 / TP	11101	AISIX: Scratch register 18. MINTIA: Thread Local Storage Pointer
SP	11110	Stack Pointer
LR	11111	Link Register

MEMORY

The memory layout of the address space of the XR/17032 architecture are discussed here.

TODO:

- finish writing this section

OPCODES

Move From Control Register - MFCR Rd, Cs

Encoding

1111 0000 0000 ssss 0000 Oddd dd10 1001

Description

Sets the value of a general purpose register to the value stored in a control register.

Implementation

```
rd = (ir >> 6) & 31;
rb = (ir >> 16) & 15;

if (rd == 0)
    break;

Reg[rd] = ControlReg[rb];
```

Move To Control Register - MTCR Cs, Ra

Encoding

1110 0000 0000 ssss aaaa a000 0010 1001

Description

Sets the value of a control register to the value stored in a general purpose register.

Implementation

```
ra = (ir >> 11) & 31;
rb = (ir >> 16) & 15;

ControlReg[rb] = Reg[ra];
```