GS Meter

User Manual

Michael Dungan

GS Meter Manual



Figure 1: GS Meter interface

What is GS Meter?

GS Meter is a lightweight loudness meter with an integrated gain utility, purpose-built for clip-to-zero workflows. It is designed to replace dpMeter5 in projects where you need a meter on every track, bus, and master – 50+ instances without killing your CPU or eating your RAM.

If you're not doing clip-to-zero, this plugin is probably not for you. It has no visual meters, no bar graphs, no loudness history. It shows numbers and lets you set gain from them. That's it.

Why does this exist?

dpMeter5 is the standard meter for clip-to-zero, but running 50+ instances of any full-featured meter adds up. GS Meter is built from the ground up for density:

- **CPU rendering** – no OpenGL, no GPU driver loaded. Zero memory overhead when the GUI is closed.
- **SIMD metering** – peak detection and RMS accumulation use f32x16 SIMD, true peak FIR uses SIMD dot products.
- **50 instances: ~16% CPU, 48 MB total memory** (measured at 48 kHz / 1024 samples, GUI closed).

Installation

Build from source (requires nightly Rust):

```
cargo nih-plug bundle gs-meter --release
```

Plugins are installed to `~/.vst3/` and `~/.clap/`.

Controls

Gain

Output gain applied to the audio signal. Range: -40 to +40 dB. Default: 0 dB.

This is the gain you adjust to match your reference level. The "-> Gain" buttons next to each reading auto-set this value.

Reference

Your target level. Range: -60 to 0 dB. Default: 0 dB.

When you click a "-> Gain" button, the gain is set to: `reference - meter_reading`. For example, if your reference is -14 dB and the integrated RMS reads -18 dB, clicking "-> Gain" sets gain to +4 dB.

RMS Window

The sliding window size for momentary RMS measurement. Range: 50 to 3000 ms. Default: 600 ms.

This matches dpMeter5's RMS Window setting. Changing it resets the momentary max.

Channel Mode

- **Stereo** – readings sum both channels' power (matches dpMeter5 SUM mode)
- **Left** – readings from the left channel only
- **Right** – readings from the right channel only

Scaling

Use the **-** / **+** buttons in the upper right corner, or **Ctrl+=** / **Ctrl+-** on the keyboard. Range: 75% to 300%.

Readings

Peak Max

Highest absolute sample value since reset, in dBFS.

True Peak

Highest inter-sample peak since reset, in dBTP. Uses 4x polyphase oversampling with the exact ITU-R BS.1770-4 Annex 2 reference filter coefficients (48-tap, 4-phase FIR). At sample rates >=96 kHz, uses 2x oversampling. At >=192 kHz, true peak equals sample peak (no interpolation needed).

True peak may read slightly different from dpMeter5 (typically within 0.1-0.2 dB). This is due to filter design differences – both implementations comply with the ITU standard.

RMS (Int)

Integrated RMS since reset. Accumulates the mean-square of all samples processed and reports the square root. Uses f64 accumulation for precision over long measurement periods.

In Stereo mode, this is `sqrt(ms_L + ms_R)` – the sum of both channels' mean-square power, matching dpMeter5's SUM mode.

RMS (Mom)

Momentary RMS over the current sliding window (set by RMS Window). Updates continuously.

RMS Max

Highest momentary RMS value observed since reset. Updated once per audio buffer.

Crest

Crest factor: `Peak Max (dB) - RMS Integrated (dB)`. Shows the dynamic range of the signal – higher values mean more transient peaks relative to average loudness. This is a live value that settles as the integrated RMS accumulates.

In Stereo mode, crest factor uses the stereo peak (max of L/R) and stereo RMS (sum of power). This matches dpMeter5's convention but gives values ~3 dB lower than a per-channel crest factor for balanced stereo content.

-> Gain Buttons

Each reading (except Crest) has a "-> Gain" button that sets: `Gain = Reference - Reading`.

Use this after letting the meter accumulate for a representative section of audio. The integrated RMS button is the most useful for clip-to-zero – it tells you how much gain to add to hit your reference level.

Reset

Clears all accumulated values: peak max, true peak, integrated RMS, momentary max, and crest factor. Momentary RMS continues from the current window contents.

Double-click any slider or the channel selector to reset it to its default value.

Clip-to-Zero Workflow

1. Insert GS Meter on every track and bus (it's cheap – 50 instances use 16% CPU)
2. Set your reference level to 0 dB (the default)
3. Play a representative section of the song
4. Click the "-> Gain" button next to Peak Max to auto-set the gain
5. Reset and repeat if needed

Technical Notes

- **No audio-thread allocations** – the process() callback never allocates heap memory
- **Pre-allocated RMS ring buffer** – sized for 3000 ms at 192 kHz (worst case), no resize on the audio thread
- **CPU rendering** – uses tiny-skia (software rasterizer) + fontdue (glyph cache) + softbuffer (pixel buffer). No OpenGL context, no GPU drivers loaded
- **SIMD** – uses Rust's portable SIMD (`std::simd::f32x16`) for peak detection, sum-of-squares, and true peak FIR convolution
- **Embedded font** – DejaVu Sans, compiled into the binary. No runtime font loading

Formats

- CLAP
- VST3
- Standalone (JACK or ALSA backend)

License

GPL-3.0-or-later