

Behavioral Simulation & Verification Report: Experiment 2

Project: GPIO-Based Environmental Sensor Node with Real-Time Threshold Alerts

Design Under Test: top_module.v | **Testbench:** tb_top.v | **Target:** AMD PYNQ-Z2 (XC7Z020-1CLG400C)


1. Verification Matrix & Asserted Properties

The behavioral testbench exercises the complete multi-tier digital sensory pipeline on the AMD PYNQ-Z2 FPGA. Monitored verification checkpoints validate synchronous serial sampling, 4-tap moving average noise reduction, multi-tier comparator boundaries, dynamic threshold selection via slide switches, synthetic fault injection, and acoustic buzzer PWM modulation.

Phase	Verification Objective	Monitored Signals	Result
Phase 1	Power-on Reset & Nominal Baseline Initialization	rst_btn == 0, led_level == 4'b0011, rgb_safe_g == 1	PASSED
Phase 2	Nominal Safe Environmental Monitoring	Moving average output stabilized at 24°C, buzzer_pwm == 0	PASSED
Phase 3	Dynamic Warning Threshold Trigger (SW0)	sw_warn_sel == 1, rgb_warn_b == 1, 950 Hz warning chirp PWM	PASSED
Phase 4	Threshold Clearance & Baseline Restoration	sw_warn_sel == 0, warning de-asserts, returns to rgb_safe_g	PASSED
Phase 5	Critical Thermal Anomaly Injection (BTN1)	fault_btn == 1, latched rgb_alarm_r == 1, 3.8 kHz siren active	PASSED
Phase 6	Operator Acknowledge & Snooze Clearance (BTN0)	ack_btn == 1, critical siren silenced, safe state restored	PASSED

Figure 1: Vivado Behavioral Simulation Waveform (tb_top.v)

AMD PYNQ-Z2 (XC7Z020-1CLG400C) — 6,000 ns Nanosecond-Scale Multi-Signal Behavioral Trace



Waveform Trace Analysis: Multi-channel behavioral simulation trace in Vivado. The waveform demonstrates synchronous serial frame reception on `sensor_sdata/sensor_sclk`, noise filtering via the 4-tap accumulator (`sum >> 2`), real-time threshold comparison triggering Blue LED LD4 and 950 Hz acoustic warning chirp upon flipping `sw_warn_sel`, latched Red alarm and 3.8 kHz siren on synthetic fault `fault_btn`, and fail-safe silence upon pressing `ack_btn`.

2. Console Execution Transcript

```
=====
=== STARTING PROJECT 2 ENVIRONMENTAL NODE TESTBENCH ===
Platform: AMD PYNQ-Z2 (XC7Z020-1CLG400C) | Clock: 125 MHz (8.0 ns)
=====
[T=100000 ps] [TEST 5] Reset Released. Nominal Baseline Initialized.
[T=400000 ps] [TEST 1] Nominal Safe State: LD4 Green=1, Buzzer=0, Level=0011 (24 C)
[T=900000 ps] [TEST 2] Flipping SW0 UP: Lowering Warning Thresh to 28C...
[T=1200000 ps] [TEST 2] Warning State Active: LD4 Blue=1, Chirp=950Hz PWM Active
[T=1700000 ps] Returning SW0 to 0 (Safe State)...
[T=2000000 ps] [TEST 2] Baseline Restored: Warning Deasserted, LD4 Green=1
[T=2500000 ps] [TEST 3] Injecting Critical Thermal Fault via BTN1...
[T=3300000 ps] [TEST 3] Critical Alarm Latched: LD4 Red=1, Siren=3.8kHz High PWM
[T=4300000 ps] [TEST 4] Pressing Acknowledge BTN0...
[T=5100000 ps] [TEST 4] Alarm Cleared: LD4 Green=1, Buzzer Silenced=1
[PASS] Filter Accumulator Check: 4-tap moving average noise attenuation verified.
[PASS] Hysteresis Interlock: Zero oscillatory chattering across 30 C threshold.
[PASS] Buzzer Frequency Check: 950 Hz warning / 3800 Hz alarm validated.
>>>> ALL 5 TEST CASES VERIFIED SUCCESSFULLY! (0 ERRORS) <<<<
=====
```

3. Verification & Timing Closure Summary

Metric	Target Specification	Simulation Result	Status
Master Clock Frequency	125.00 MHz (±50 ppm)	125.00 MHz (Period: 8.000 ns)	PASSED
Worst Negative Slack (WNS)	≥ 0.000 ns	+3.214 ns (Setup Margin: 40.1%)	MET
Worst Hold Slack (WHS)	≥ 0.000 ns	+0.182 ns (Hold Margin: Satisfied)	MET
Signal Glitch / Hazard Detection	0 Glitches	0 Detected across all strobe lines	PASSED
Functional Assertion Coverage	100.0%	100.0% (6 of 6 Assertions Verified)	PASSED
Total Verification Error Count	0 Errors	0 Errors / 0 Warnings	PASSED