



Name: Yaseen Reyad Hassan

ID : 1320221531

Course: communications and digital consulting devices

Instructor: Dr. Mohamed Kamal Naeem

Real-World Signal Analysis and Simulation Using MATLAB

Part 1 – General Theoretical Overview

1. Signal Classifications

1. Signal Classifications

Signals are representations of information. They can be classified in several ways based on their characteristics:

- **Continuous vs. Discrete:**
 - **Continuous-time signals** are defined for all values of time, changing smoothly and continuously. An example is a sound wave or an electrocardiogram (ECG) signal. They can be denoted by $x(t)$.
 - **Discrete-time signals** are defined only at specific, distinct time intervals. They can be obtained by sampling a continuous signal. An example is a sequence of hourly temperature readings. They are denoted by $x[n]$.
- **Periodic vs. Aperiodic:**
 - **Periodic signals** repeat their pattern over a fixed time interval, called the **period (T)**. They satisfy the condition $x(t)=x(t+T)$. A sine wave is a classic example.
 - **Aperiodic signals** never repeat. A single pulse or a random sound is aperiodic.
- **Energy vs. Power Signals**
 - **Energy Signals:** Have finite total energy but zero average power.
 - **Total Energy (E):**
$$E = \int_{-\infty}^{\infty} |x(t)|^2 dt$$
 - **Example:** A square pulse.

➔ **Power Signals:** Have finite average power but infinite total energy.

- **Average Power (P):**

$$P = \lim_{T \rightarrow \infty} \frac{1}{2T} \int_{-T}^T |x(t)|^2 dt$$

- **Example:** A sine wave.

- **Even vs. Odd:**

- An **even signal** is symmetric about the vertical axis, satisfying the condition $x(t) = x(-t)$. A cosine wave is an example.
- An **odd signal** is anti-symmetric about the origin, satisfying the condition $x(t) = -x(-t)$. A sine wave is an example.
- Any signal can be decomposed into its even and odd parts.

- **Causal vs. Non-causal:**

- A **causal signal** is a signal that is zero for all negative time ($t < 0$). In other words, the signal does not exist before a specific moment (usually $t = 0$). These signals represent real-world systems that cannot respond to an input before it occurs.
- **Equation:** $x(t) = 0$ for $t < 0$.
- **Example:** A step function that starts at $t = 0$ and remains non-zero thereafter.
- A **non-causal signal** is a signal that has non-zero values for some negative time ($t < 0$). These signals depend on future values, which is impossible for physical systems operating in real time. However, they are useful in mathematical modeling and analysis.
- **Equation:** $x(t) \neq 0$ for some $t < 0$.
- **Example:** An ideal sine wave that extends from $-\infty$ to $+\infty$.

2. Fourier Analysis Summary

Fourier analysis is a mathematical tool that allows us to decompose a signal into its constituent frequencies. It helps us understand the frequency content of a signal, which is often more insightful than its time-domain representation.

Purpose of Fourier Series:

The **Fourier Series** is used to represent periodic signals as a sum of harmonically related sinusoids (sines and cosines). The series allows us to express a complex periodic signal in the **frequency domain**, revealing which frequencies are present and their respective amplitudes and phase shifts. This decomposition is crucial for analyzing and synthesizing periodic signals.

Importance of Time-to-Frequency Domain Conversion:

Converting a signal from the **time domain** to the **frequency domain** provides a different perspective on its characteristics.

- **Time-Domain:** Shows how the signal's amplitude changes over time. It's useful for observing instantaneous values and signal duration.
- **Frequency-Domain:** Reveals the signal's spectral content—which frequencies are present and how strong they are. This is essential for applications like filter design, where we need to isolate or remove specific frequencies, and for understanding the bandwidth of a signal in communication systems.

Part 2 – Applied Research and Case Study: ECG Signal

1. What is the ECG Signal?

The **electrocardiogram (ECG)** is a medical signal that measures the electrical activity of the heart. Electrical impulses generated by the heart cause the heart muscle to contract and pump blood. An ECG device records these impulses using electrodes placed on the body's surface, translating them into a time-varying waveform.

In an engineering context, the ECG signal is a **bio-potential signal**. It's a low-frequency, low-amplitude signal (typically in the millivolt range) that reflects the depolarization and repolarization of the heart's atria and ventricles.

The ECG is a cornerstone of **cardiology**. It's used to diagnose various heart conditions, including arrhythmias (irregular heartbeats), myocardial infarction

(heart attack), and cardiac hypertrophy (enlargement of the heart). It is a routine diagnostic tool in hospitals, clinics, and emergency medical services.

2. Mathematical Modeling and Characteristics

A single cycle of a healthy ECG waveform is characterized by three main components: the P wave, the QRS complex, and the T wave.

- **P wave:** Represents atrial depolarization.
- **QRS complex:** Represents ventricular depolarization.
- **T wave:** Represents ventricular repolarization.

While a healthy ECG is quasi-periodic, it's not perfectly periodic due to variations in heart rate and physiological noise. A simplified mathematical model of a single ECG cycle can be represented as a sum of Gaussian-like functions and sinusoids. For example, a basic model might look like:

$$x(t) = A_p e^{-\frac{(t - t_p)^2}{2\sigma_p^2}} + A_{qrs} e^{-\frac{(t - t_{qrs})^2}{2\sigma_{qrs}^2}} \cos(2\pi f_{qrs}(t - t_{qrs})) + A_t e^{-\frac{(t - t_t)^2}{2\sigma_t^2}}$$

- **Periodicity:** The ECG is **quasi-periodic**, as the time between successive heartbeats is not perfectly constant. However, for analysis over short durations, it can be treated as a periodic signal.
- **Energy/Power:** A single ECG beat is an **energy signal** as it has a finite duration. However, the continuous recording of a person's ECG over a long period can be considered a **power signal** because the average power over time is constant and finite.
- **Even/Odd:** The ECG signal is neither an even nor an odd signal. It has no symmetry about the y-axis.
- **Causality:** The ECG signal is a **non-causal** signal in a theoretical sense, as it exists for all time. However, in practice, a recorded ECG signal starts at a specific time, making the recorded segment causal from the perspective of the measurement system.
- **Fourier Series:** Because the ECG is quasi-periodic, it can be decomposed using a Fourier Series, especially when analyzing a single, repeating cardiac cycle. For non-periodic segments or aperiodic signals, the **Fourier Transform** is the more appropriate tool.

3. Fourier Series Analysis

The Fourier Series decomposes the ECG into a sum of sinusoids at different frequencies. Each frequency component corresponds to a specific aspect of the heart's electrical activity.

Derivation/Explanation: The Fourier Series coefficients C_k for a periodic signal $x(t)$ with period T_0 are calculated as:

$$C_k = \frac{1}{T_0} \int_{T_0} x(t) \cdot e^{-j2\pi kt/T_0} dt$$

These coefficients represent the magnitude and phase of each frequency component ($k\omega_0$), where $\omega_0 = 2\pi/T_0$ is the fundamental frequency.

The Spectrum: The frequency spectrum of an ECG signal is dominated by low-frequency components, primarily below 40 Hz. The bulk of the signal's energy is concentrated in this range. The spectrum would show a few prominent peaks corresponding to the fundamental heart rate and its harmonics.

What the Spectrum Tells Us: The spectrum provides critical diagnostic information:

- **Dominant Frequency:** The fundamental frequency (the first peak in the spectrum) corresponds to the heart rate.
- **Harmonic Content:** The presence and amplitude of higher harmonics can indicate abnormalities. For instance, a broadened spectrum or specific harmonic peaks might suggest certain arrhythmias or other pathologies.
- **Noise Identification:** The frequency domain makes it easy to identify and filter out unwanted noise, such as 60 Hz power line interference or high-frequency muscle artifacts.

4. Application and Impact

The ECG signal is paramount in modern medicine. Its importance stems from its ability to provide a non-invasive, real-time window into the heart's function.

Processing and Analysis: In practice, ECG signals are processed to remove noise and extract key features. This often involves:

1. **Filtering:** Low-pass or band-pass filters are applied to remove high-frequency noise and DC offset.
2. **QRS Detection:** Algorithms are used to precisely locate the QRS complex, which is the most prominent feature. This is crucial for calculating heart rate.
3. **Feature Extraction:** Specific features like the duration of the P-R interval, QRS duration, and S-T segment elevation are measured. These values are compared to established norms to identify potential issues.

Part 3 – MATLAB Simulation

This section uses MATLAB to simulate a simplified, periodic ECG-like signal and analyze it in both the time and frequency domains.

1. MATLAB Code


→ Simulated ECG Signal in Time Domain

```
Fs = 1000; % Sampling frequency (Hz)
T = 1/Fs; % Sampling period
L = 2000; % Number of samples
t = (0:L-1)*T; % Time vector
t_beat = t(1:500);
P_wave = 0.1*exp(-100*(t_beat - 0.05).^2);
QRS_complex = -0.5*exp(-100*(t_beat - 0.1).^2) + 1.2*exp(-100*(t_beat - 0.12).^2);
T_wave = 0.3*exp(-100*(t_beat - 0.25).^2);
single_beat = P_wave + QRS_complex + T_wave;

% Repeat the beat to create a periodic signal
ECG = repmat(single_beat, 1, 4);
ECG = [ECG, zeros(1, L - length(ECG))]; % Pad with zeros to fit L samples

% Time-domain plotting
figure;
plot(t, ECG);
title('Simulated ECG Signal in Time Domain');
xlabel('Time (s)');
ylabel('Amplitude (mV)');
grid on;
```

Output → →




→ Single-Sided Amplitude Spectrum of ECG Signal

```
% Fourier Analysis using FFT
Y = fft(ECG);
P2 = abs(Y/L);
P1 = P2(1:L/2+1);
P1(2:end-1) = 2*P1(2:end-1);
f = Fs*(0:(L/2))/L;

% Visualize the spectrum
figure;
plot(f, P1);
title('Single-Sided Amplitude Spectrum of ECG Signal');
xlabel('Frequency (Hz)');
ylabel('|P1(f)|');
xlim([0 50]); % Focus on the relevant frequency range
grid on;
```

Output → →



2. Plot Outputs

Time-Domain Plot

The first plot shows the simulated ECG signal over time. The signal is clearly periodic, with distinct P, QRS, and T-wave-like components repeating at regular intervals. This visualization helps confirm the signal's periodicity and allows us to observe its morphology.

Frequency-Domain Plot

The second plot shows the signal's frequency spectrum obtained using the Fast Fourier Transform (FFT).

The plot displays the magnitude of the frequency components.

This spectrum reveals several key features:

- A dominant peak at a low frequency, which corresponds to the fundamental heart rate.
- Smaller peaks at integer multiples of the fundamental frequency (harmonics).
- The signal's energy is concentrated in the low-frequency range, as expected for a typical ECG signal. The frequency spectrum effectively transforms the signal into a representation of its constituent frequencies, which is invaluable for analysis, especially when a more nuanced view is needed beyond just the time-domain plot.

This simulation demonstrates how MATLAB can be used to model, visualize, and analyze a real-world signal like the ECG, providing a powerful tool for understanding its properties and applications.